Rockchip Solutions DDR SDRAM Approved List

Ver 3.03

2026/4/28

Do not download or use this document (“Document”) unless carefully reviewed and accepted the following notice (“Notice”). By downloading or using this Document, customers acknowledge that they have read and agreed to be bound by the Notice. If customers don’t agree to all of the Notice, please do NOT download or use this Document, and destroy any downloaded or saved copies.

NOTICE

THIS DOCUMENT IS PROVIDED “AS IS”. AND ROCKCHIP ELECTRONICS CO., LTD. (“ROCKCHIP”) DOES NOT PROVIDE ANYWARRANTY OF ANY KIND, WHETHER EXPRESSED, IMPLIED OR OTHERWISE, WITH RESPECT TO THE ACCURACY, RELIABILITY,COMPLETENESS,MERCHANTABILITY, FITNESS FOR ANY PARTICULAR PURPOSE OR NON-INFRINGEMENT OF ANYREPRESENTATION, INFORMATION AND CONTENT IN THIS DOCUMENT. THIS DOCUMENT IS FOR REFERENCE ONLY, AND ROCKHIP DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THIS DOCUMENT. THIS DOCUMENT MAY BE UPDATED OR CHANGED WITHOUT ANY NOTICE AT ANY TIME FOR SOME REASONS.

GUIDANCE

Symbol	Description
√	**Fully Tested and Mass production**
T/A	**Sample Tested and Applicable, and requires mass production verification.**
S/A	**Sample Tested and Applicable, but there is a risk of small margins or others that require mass production to validation.**
N/A	**Not Applicable**
Empty	**Not be evaluated**

- Rockchip only validates limited pieces of each sample from vendors and has no mass production experience with the DDR products on this list, so we do not guarantee any DDR quality provided to customers by vendors. Customers are solely responsible for the validating and testing DDR products ensure such product meets applicable standards and any safety, security or other reguirements.
- Please copy the Rockchip reference design model of DRAM area PCB Layout directly without any modification and follow the PCB layout rules from Rockchip. Contact information: fae@rock-chips.com
- The DRAM Part Number usually consists of two parts divided by '-', the first part contains memory type, density, orgainization, package, and the second part usually means data rate. It should be noticed that some vendors like ESMT, RAYSON, CXMT, BIWIN, Kingston, Foresee, Goldkey,the second part contains other important information. We don't care about the part represented of data rate.
- Rockchip platform can support all the chips that match the first part of Part Number which marks '√', 'T/A' or 'S/A', and do not need to care the second part. If you want your system running more effective, you may need to find out the exact data rate in DRAM datasheet and config in kernel menuconfig.
- Every times update will be highlighted by yellow.
- For DDR products on this list, except for specific products marked with application note, they can be used without any software modification.
- For DDR products on this list, each platform corresponds to each testing separately and the test results of different platforms CANNOT BE REFERENCED.

◆Application Note:

[1] Because lack of Address pin A15 in package, following SoCs do not support the 512M*8 DDR3: RK2906-6, RK2906-8, RK3066.
[2] Only support for RK3128.
[3] The DRAM's VDD and VDDQ should powered by 1.5V when it used on these SoCs.
[4] It can work stably on RK3399 with loader version rk3399_ddr_XXXMHz_v1.22.bin and trust version rk3399_bl31_v1.28.elf, or the later version than all above. On RK3399pro, loader should be updated to rk3399pro_ddr_XXXMHz_v1.22.bin, trust version should be updated to rk3399pro_bl31_v1.28.elf. Or the later version than all above.
[5] Only after week code 1937 (means 2019, week 37th) can be used, the product with early week code may cause system crash or unstable.

week code 

[6] The DDR must be boot from 400MHz, please use XXXX_ddr_400MHz_vX.XX.bin to merge loader.
[7] On RK3568/RK3566, loader should be updated to rk3568_ddr_xxxMHz_v1.09.bin / rk3566_ddr_xxxMHz_v1.09.bin or later version.
[8] Only after week code 2101 (means 2021, week 01th) can be used, the product with early week code may cause system crash or unstable.

week code 

[9] Only after week code 2118 (the third row, first four numbers means 2021, week 18th) can be used, the product with early week code may cause system crash or unstable.

week code 

[10] Only after week code 022 (the fourth row, first three numbers means 2020, week 22th) can be used, the product with early week code may cause system crash or unstable.

week code 

[11] For LPDDR4 and LPDDR4X unified product, platform only approve LPDDR4 mode, not guarantee LPDDR4X mode can work stably. So VDDQ must provide 1.1V not 0.6V.
[12] For LPDDR4X mode, the DDR bin need update to V1.13 or later version on RK3568 and RK3566.
[13] Only after week code 201 (the fourth row, first three numbers means 2022, week 2nd) can be used, the product with early week code may cause crash.

week code 

[14]At the speed of 4266Mbps, it exists unfixable issues.The maximum frequency of this product is limited to 3733.
[15] On RV1126/RV1109, the performance of LPDDR4/LPDDR4X is not enough, please use it after evaluation.
[16] It can't work normally between 400MHz-625MHz and DTS cannot use this frequency band.
[17] On RK3588, the DDR bin should be updated to rk3588_ddr_lp4_2112MHz_lp5_2736MHz_v1.10.bin or later version, the bl31 should be updated to rk3588_bl31_v1.37.elf or later version.
[18] We tested samples like below, the left picture below may showed a boot error and the right picture below passes the test.

FAIL 

PASS 

[19] The DDR bin need update to V1.04 or later version on RK3576.

[20] Products produced only after week code 2328(picture below the third row, the last four numbers means 2024, week 11th) are marked as S/A. Products produced before week code 2328 are marked as N/A. There

is a problem with using the product before the 28th week in the year 2023 in the client application, and it cannot be worked.

week code 

[21] Please use the template which DDR3_A15 has a link to the DDR chip.

[22] The auto self-refresh function, frequency conversion feature, and standby wake-up function need to be disabled before use.See https://redmine.rock-chips.com/boards/6/topics/274

[23] Products produced with week code 2333, 2409, 2417, 2419, 2427, 2431(picture below the third row, the first four numbers means 2023, week 33rd) are non-compliant with requirements.

week code 

[24] Please update the ddr.bin to v1.23 or the later version, the CA_ODT pin of the DDR component must be pulled up to VDD2, which need modify PCB layout.

[25] On RK3588, the DDR bin should be updated to rk3588_ddr_lp4_2112MHz_lp5_2736MHz_v1.18.bin or later version, on RK3576 the DDR bin should be updated to rk3576_ddr_lp4_2112MHz_lp5_2736MHz_v1.06.bin or later version.

[26]For some DDR products whose frequencies are lower than the maximum frequency of the platform, it is necessary to modify the frequency to a matching one by yourself.Refer to "修改DDR bin文件" in the "Rockchip_Developer_Guide_DDR_CN" or "Modify the DDR bin file" in "Rockchip_Developer_Guide_DDR_EN".

[27]If use K3PE0E000A-XGC2, RZQ needs to be changed to NC.

[28]If use K3PE0E000M-XGC2, RZQ needs to be changed to 150ohm.

[29]For 256M16 DRAM on RK3066 and RK31xx platforms, fixed-frequency related patches must be applied. Additionally, strict adherence to our PCB layout requirements is mandatory due to high demands on reference plane integrity in the PCB design.

[30] NT5AD512M16C4-JR (Specific Version) has been validated and passed all tests. However, legacy production lots exhibit known issues. For distinguishing Validated Lots(Specifies the version has passed qualification tests), please contact Nanya Technology directly.

[31]On RK3576, the DDR bin should be updated to rk3576_ddr_lp4_2112MHz_lp5_2736MHz_v1.10.bin or later version.

[32] BWMYAX32P8A-64G produced only after week code 2514 are marked as S/A(picture below the third row, the first four numbers means 2025, week 4th). Products produced before week code 2514 are marked as N/A. There is a problem with using the product before the 14th week in the year 2025 in the client application, and it cannot be worked. BWMYAX32P8A-32G produced only after week code 2502 are marked as S/A. Products produced before week code 2502 are marked as N/A. There is a problem with using the product before the 2nd week in the year 2025 in the client application, and it cannot be worked.



[33]W66DP2RQQA*J produced only after week code 2533 are marked as S/A(picture below the fourth row, the first three numbers means 2024, week 50th). Products produced before week code 2533 are marked as N/A.



[34]This sample only passed at a speed of 4800Mbps，and reboot fail at 5500Mbps.

[35]It can only be used with a special hardware template and the corresponding DDR Bin file, as detailed below:
Hardware Template: Refer to https://redmine.rock-chips.com/documents/116 -> 对外发布版本DDR模板列表_VX.XX.pdf". Versions marked with "WDQS 支持" are applicable. As shown in the figure below.



平台	DDR类型	颗粒类型	模板名称	备注
RK3562	LPDDR4/4X	196ball	RK3562_Template_LP4XD196P132SD6R_34R0X25R0_1333MHz	
RK3562	LPDDR4/4X	200ball	RK3562_Template_LP4D200P132SD4_31R5x25R1_1333MHz_H1R0	1，板厚：1.0mm（模块区域内bottom面仅放置0201封装的器件）； 2，WDQS支持：[redacted]；

DDR Bin File: Use the corresponding version of the DDR bin as described in rkbin/specific/Rockchip_Specific_PCB_Template_and_DDR_bin_Configuration_Table.md. **This information must be notified to the software team.**If the file cannot be found in rkbin, please update the rkbin repository or refer to the Patch Report at https://redmine.rock-chips.com/issues/601354.

[36]This product has not been tested yet. Costmer must perform compatibility testing and assume all risks by their own. Additionally, as it uses Hynix or Nanya LP4/LP4X wafers, when used on platforms such as RK3568, RK3566, RK3528, and RK3562, it can only be used with a specific hardware template and the corresponding DDR Bin file, as shown below:
Hardware Template: refer to https://redmine.rock-chips.com/documents/116 -> 对外发布版本DDR模板列表_VX.XX.pdf". Versions marked with "WDQS 支持" are applicable. As shown in the figure below.



平台	DDR类型	颗粒类型	模板名称	备注
RK3562	LPDDR4/4X	196ball	RK3562_Template_LP4XD196P132SD6R_34R0X25R0_1333MHz	
RK3562	LPDDR4/4X	200ball	RK3562_Template_LP4D200P132SD4_31R5x25R1_1333MHz_H1R0	1，板厚：1.0mm（模块区域内bottom面仅放置0201封装的器件）； 2，WDQS支持：[redacted]；

DDR Bin File: Use the corresponding version of the DDR bin as described in rkbin/specific/Rockchip_Specific_PCB_Template_and_DDR_bin_Configuration_Table.md. **This information must be notified to the software team**.If the file cannot be found in rkbin, please update the rkbin repository or refer to the Patch Report at https://redmine.rock-chips.com/issues/601354.
Testing Guidance： refer to "Chapter-3 DDR 颗粒验证流程说明" in the Rockchip_Developer_Guide_DDR_CN.pdf document available at https://redmine.rock-chips.com/documents/49.

◆ Revision History

Revision No.	History	Date
2.00	ORG.	2012.12.24
2.42	Add some supporting messages, switch column order of product name.	2020.03.30
2.43	Add some supporting messages	2020.06.16
2.44	Add some supporting messages, modify H9HCNNNBPUMLHR, H9CCNNN8JTMLAR, H9CKNNNBPTMRLR, H9CKNNNCPTMRPR to N/A. Add "Product Status".	2020.09.02
2.45	Add some supporting messages, change the order of manufacture.	2020.11.17
2.49	Modify T/A of K4U8E3S4AD-MG**, NT6AP256T32AV, NT6AP512T32AV to N/A on RV1126/RV1109, fill Samsung and Nanya LPDDR4X on RV1126/RV1109 with N/A.	2021.07.23
2.50	Add some supporting messages, add note [8][9][10][11].	2021.10.22
2.51	Add some supporting messages	2022.01.17
2.52	Add some supporting messages, change note [12][13].	2022.04.01
2.53	Add some supporting messages, add note [14], modify T/A of K4U6E3S4AA-MG**, K4UHE3D4AB-MG**, K4UBE3D4AA-MG** to N/A on RK3588, modify T/A of NCLDXC1MJ512M32, FLXC2002G-N2, RS512M32LM4D2BDS-53BT to N/A on RK3399, modify T/A of FLXC4004G-26, GE8062666ND to N/A on RK3568.	2022.05.30
2.54	Add note [15][16], change note [4], modify T/A of M15T1G1664A-DEBG2C to N/A on RV1126/RV1109, T/A of RS2G32LF4D4BDT-53BT to N/A on RK3588.	2022.08.18
2.55	Change T/A of H9HCNNNBKUMLXR to N/A on RK3399, T/A of EM6HC16EWBH-09H to N/A on all platforms. Delete parts of verison history.	2022.12.05
2.56	Change T/A of NCLDXC1MG256M32 to N/A on all platforms. Add note [17].	2023.04.07
2.57	Add some supporting messages, modify note[14] and part of HYNIX NANYA KINGSTON product to S/A, change T/A of BWSR8X32H2A-32G-X to N/A.	2023.11.22
2.58	Add some supporting messages	2023.12.05
2.59	Add some supporting messages,modify S/A of NT6AN512T32AV, T/A of RS1G32LF4D2BDS-53BT,K3LKCKC0BM-MG** to N/A.	2024.04.23
2.60	Add some supporting messages,modify N/A of K3LKCKC0BM-MG** to T/A.	2024.04.30
2.62	Add some supporting messages	2024.09.03
2.63	Modify T/A of NT6AP512T32BL on RK3568/3562/3566 to N/A.	2024.09.05
2.64	Add some supporting messages, modify T/A of CXDQ3BFAM-CQ-A,CXDQ3BFAM-CJ-A,CXDQ3BFAM-IJ-A to S/A.	2024.11.28
2.65	Add some supporting messages, modify T/A of IS43QR16256B-083RBLI,NT5AD512M16C4,A3F8GH40BBF-MC,N2AD8G16C4-JR,D5116AN9CXGXN to N/A.	2025.03.17
3.00	Add some supporting messages, delete RK290x RK2918, modify T/A of W66DP2RQQA*J to N/A.	2025.08.08
3.01	Add some supporting messages	2025.10.20
3.02	Add some supporting messages	2026.02.28
3.03	Add some supporting messages	2026.04.28

See Infocenter, https://redmine.rock-chips.com/documents/49, for access to the latest support list.

Consumer

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S/	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO CPU_RAM	RK3399PRO NPU_RAM	RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK2928/RK3028A/RK3128/PX3-SE	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
Micron	MT47H64M16HR-25	EOL	1G bit	64M×16	DDR2	84ball																												
	MT41J128M8JP-15E:G (D9MNL)		1G bit	128M×8	DDR3	78ball																												
	MT41K128M8DA-107:J (D9RDJ)		1G bit	128M×8	DDR3L	78ball																												T/A
	MT41K64M16TW-107:J (D9SFT)		1G bit	64M×16	DDR3L	96ball					T/A	T/A	T/A								T/A													
	MT41J128M16HA-15E:D (D9LGQ)		2G bit	128M×16	DDR3	96ball																												
	MT41J256M8HX-15E:D (D9LGK)		2G bit	256M×8	DDR3	78ball																								T/A		T/A	T/A	T/A
	MT41K256M8DA-125:K (D9PSH)		2G bit	256M×8	DDR3L	78ball																								T/A		T/A	T/A	T/A
	MT41K256M8DA-125:M (D9PFJ)		2G bit	256M×8	DDR3L	78ball																								T/A		T/A	T/A	T/A
	MT41K128M16HA-15E:D (D9LJM)		2G bit	128M×16	DDR3L	96ball																												
	MT41K128M16JT-125:K (D9PTK)		2G bit	128M×16	DDR3L	96ball							T/A							T/A	T/A									T/A	T/A	T/A	T/A	T/A
	MT41K128M16JT-107:K (D9PSZ)		2G bit	128M×16	DDR3L	96ball					T/A	T/A								T/A							T/A		T/A					
	MT41K512M8RH-125:E (D9QBJ)		4G bit	512M×8	DDR3L	78ball																								T/A		T/A	T/A	T/A [1]
	MT41K512M8RG-107:N (D9RVX)		4G bit	512M×8	DDR3L	78ball																												T/A
	MT41K512M8DA-107:P (D9SGQ)		4G bit	512M×8	DDR3L	78ball																												T/A
	MT41K256M16RE-15E:D (D9PBF)		4G bit	256M×16	DDR3L	96ball																												
	MT41K256M16HA-125:E (D9PXV)		4G bit	256M×16	DDR3L	96ball																								T/A		T/A	T/A	T/A
	MT41K256M16LY-107:N (D9SDD)		4G bit	256M×16	DDR3L	96ball														T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A		T/A	T/A	T/A	T/A	T/A
	MT41K256M16TW-107:P (D9SHD)		4G bit	256M×16	DDR3L	96ball					T/A	T/A	T/A			T/A		T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A			T/A
	MT41K256M16TW-107 IT:P (D9SHG)		4G bit	256M×16	DDR3L	96ball																	T/A					T/A						
	MT41K512M16HA-125:A (D9STQ)	EOL	8G bit	512M×16	DDR3L	96ball																	√					T/A						
	MT41K512M16HA-107:A (D9SDQ)	EOL	8G bit	512M×16	DDR3L	96ball																								T/A				T/A
	MT40A256M16GE-083E:B (D9TGQ)	EOL	4G bit	256M×16	DDR4	96ball																T/A		T/A			T/A		T/A					
	MT40A256M16GE-075E:B (D9TGS)	EOL	4G bit	256M×16	DDR4	96ball														T/A					T/A	T/A	T/A		T/A					
	MT40A512M16TB-062E:J (D9WWP)	EOL	8G bit	512M×16	DDR4	96ball									T/A		T/A	T/A	T/A	T/A							T/A		T/A					
	MT40A512M16JY-083E:B (D9TBK)		8G bit	512M×16	DDR4	96ball									T/A		T/A	T/A	T/A			T/A		T/A										
	MT40A512M16TB-062E:R (D8BPK)		8G bit	512M×16	DDR4	96ball				T/A	T/A	T/A		T/A	T/A		T/A	T/A	T/A	T/A					T/A									
	MT40A512M16LY-062E:E (D9WFJ)	EOL	8G bit	512M×16	DDR4	96ball									T/A		T/A	T/A	T/A	T/A														
	MT40A1G16WBU-083E:B (D9TPH)	EOL	16G bit	1024M×16	DDR4	96ball																T/A		T/A			T/A		T/A					
	MT40A1G16KD-062E:E (D9ZFW)	EOL	16G bit	1024M×16	DDR4	96ball									T/A		T/A	T/A	T/A	T/A					T/A	T/A								
	MT40A1G16TB-062E:F (D8CJX)		16G bit	1024M×16	DDR4	96ball				T/A	T/A	T/A		T/A	T/A		T/A	T/A	T/A	T/A					T/A									
	MT40A2G16SKL-062E:B (D9XQF)		32G bit	2048M×16	DDR4	96ball									T/A		T/A	T/A	T/A															
	MT42L128M32D1GU-25 WT:A (Z9QHG)		4G bit	128M×32	LPDDR2	134ball																								T/A				T/A
	MT42L256M16D1GU-18 WT:A (D9RLT)		4G bit	256M×16	LPDDR2	134ball															T/A													
	MT42L128M64D2LL-25 WT:A (D9QQG)		8G bit	128M×32×2Ch	LPDDR2	216ball																								T/A				N/A
	MT52L256M32D1PF-107 WT:B (D9SRZ)		8G bit	256M×32	LPDDR3	178ball														T/A		T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A				
	MT52L512M32D2PF-107 WT:B (D9SSF)		16G bit	512M×32	LPDDR3	178ball														T/A		T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A			
	MT52L256M32D1PF-093 WT:B (D9SVR)		8G bit	256M×32	LPDDR3	178ball					T/A	T/A																						
	MT52L512M32D2PF-093 WT:B (D9SVT)		16G bit	512M×32	LPDDR3	178ball					T/A	T/A																						
	MT53E128M16D1DS-046 WT:A (D9WXT)		2G bit	128M×16	LPDDR4/LPDDR4X	200ball														S/A [11][15]													
	MT53E128M32D2DS- 046 WT:A (D9WXR)		4G bit	128M×32	LPDDR4/LPDDR4X	200ball					T/A				T/A					S/A [11][15]													
	MT53B256M32D1NP-062 WT:C (D9TFT)	EOL	8G bit	256M×32	LPDDR4	200ball																	T/A					T/A						
	MT53E256M32D2DS-053 WT:B (D9WRB)	EOL	8G bit	256M×32	LPDDR4/LPDDR4X	200ball													T/A [11]	S/A [11][15]			T/A [4][11]					T/A [4][11]						
	MT53E256M32D2FW-046 WT:B (D9ZKT)		8G bit	256M×32	LPDDR4/LPDDR4X	200ball								T/A	T/A	T/A [7][11]	T/A	T/A [7][11]	T/A [7][11]	S/A [11][15]					T/A									
	MT53E256M32D1KS-046 WT:L (D8FCW)		8G bit	256M×32	LPDDR4/LPDDR4X	200ball					T/A			T/A	T/A	T/A	T/A	T/A	T/A						T/A									
	MT53E384M32D2DS-053 WT:E (D9WRN)		12G bit	384M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A	S/A [15]														
	MT53E384M32D2FW -046 WT:E (D8BBR)		12G bit	384M×32	LPDDR4/LPDDR4X	200ball								T/A	T/A	T/A [7][11]	T/A	T/A [7][11]	T/A [7][11]						T/A [11]									
	MT53B512M32D2NP-062 WT:C (D9TFW)	EOL	16G bit	512M×32	LPDDR4	200ball																	T/A					T/A						
	MT53D512M32D2DS-053 WT:D (D9WHZ)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball									T/A [11]	T/A		T/A	T/A	S/A [15]				T/A [11]				T/A						
	MT53E512M32D2NP-046 WT:E (D9WGB)	EOL	16G bit	512M×32	LPDDR4/LPDDR4X	200ball										T/A [7][11]	T/A [11]	T/A [7][11]	T/A [7][11]	S/A [11][15]				T/A [11]				T/A [11]						
	MT53E512M32D2NP-046 WT:F (D9XRR)	EOL	16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A								T/A [11]									
	MT53E512M32D2FW-046 WT:D (D9ZZL)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A	T/A	T/A [7]	T/A	T/A [7]	T/A [7]						T/A									
	MT53E512M32D1NP-046 WT:B (D8BQM)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A	T/A	T/A [11]	T/A	T/A [11]	T/A [11]				T/A		T/A [11]			T/A						
	MT53E512M32D4NQ-053 RS WT:F (D9ZBD)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball													T/A [11]															
	MT53E512M32D1ZW-046 WT:B (D8CSC)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball					T/A				T/A	T/A		T/A	T/A				T/A					T/A						
	MT53E512M32D1ZW-046 B WT:B (D8FLP)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A	T/A	T/A	T/A	T/A	T/A						T/A									
	MT53E768M32D4DT-046 WT:E (D9WRP)		24G bit	768M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A						T/A									
	MT53E768M32D2ZW-046 WT:C (D8DTV)		24G bit	768M×32	LPDDR4/LPDDR4X	200ball					T/A			T/A	T/A	T/A	T/A	T/A	T/A	N/A					N/A									
	MT53D1024M32D4DT-053 WT:D (D9WHV)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball									T/A	T/A [11]		T/A [7][11]	T/A [11]	S/A [11][15]														
	MT53D1024M32D4DT-046 WT:D (D9WQG)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball											T/A [11]								T/A [11]								
	MT53E1G32D2FW-046 WT:B (D8CJG)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball					T/A			T/A		T/A	T/A	T/A	T/A						T/A [11]									
	MT53E1G32D2FW-046 WT:C (D8DVT)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A					T/A	T/A	T/A	T/A	T/A	T/A															
	MT53E1G32D4NQ-046 WT:E (D9WLQ)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A															
	MT53E1536M32D4DE-046 WT:B (D8BDQ)	EOL	48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
	MT53E1536M32DDNQ-046 WT:A(D8BWF)		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
	MT53E1536M32D4DE-046 WT:C(D8DDB)		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
	MT53E2G32D4DE-046 WT:A (D9ZRD)		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A [7][11]	T/A	T/A [7][11]	T/A [7][11]															
	MT53E2G32D4DE-046 WT:C (D8CJN)		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A					T/A		T/A	T/A	T/A	T/A															
	MT53E2G32D4NQ-046 WT:C (D8BQX)		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																	
	MT53E4G32D8CY-046 WT:C (D8CBG)		128G bit	4G×32	LPDDR4/LPDDR4X	200ball								T/A			T/A [17]																	
	MT53E4G32D8GS-046 WT:C (D8DPM)		128G bit	4G×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																	
	MT53B512M64D4NK-053 WT:C (D9TGF)	EOL	32G bit	512M×64	LPDDR4	366ball																	T/A					T/A						
	MT53E512M64D4NK-046 WT:D (D9XPK)	EOL	32G bit	512M×64	LPDDR4	366ball																	T/A					T/A						
	MT62F512M32D2DS-031 WT:B (D8BCN)		16G bit	512M×32	LPDDR5	315ball								T/A			T/A																	
	MT62F512M32D1DS-020 WT:E (D8GSM)		16G bit	512M×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F768M32D2DS-020B WT:D (D8HHC)		24G bit	768M×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F1G32D4DS-031 WT:B (D8BFH)	EOL	32G bit	1024M×32	LPDDR5	315ball								T/A			T/A																	
	MT62F1G32D2DS-026 WT:B (D8CTX)		32G bit	1G×32	LPDDR5/LPDDR5X	315ball											T/A																	
	MT62F1G32D2DS-026 WT:C (D8DHC)		32G bit	1G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F1G32D2DS-020 WT:F(D8FQT)		32G bit	1G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F1G32D2DS-020 WT:D (D8GPW)		32G bit	1G×32	LPDDR5/LPDDR5X	315ball			T/A					T/A			T/A																	
	MT62F1536M32D4DS-026 WT:B(D8CNS)		48G bit	1536M×32	LPDDR5/LPDDR5X	315ball								T/A																				
	MT62F1536M32D4DS-020B WT:D(D8HPL)		48G bit	1536M×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F2G32D4DS-026 WT:B (D8CTP)	EOL	64G bit	2G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F2G32D4DS-026 WT:C (D8DNF)		64G bit	2G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F2G32D4DS-020 WT:F(D8GBN)		64G bit	2G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F2G32D4DS-020 WT:D D8GPC		64G bit	2G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F3G32D8DV-026 WT:B (D8CPV)		96G bit	3G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A [17]																	
	MT62F3G32D8DV-023 WT:C (D8FMF)		96G bit	3G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F4G32D8DV-026 WT:B (D8CWL)	EOL	128G bit	4G×32	LPDDR5/LPDDR5X	315ball											T/A [17]																	
	MT62F4G32D8DV-026 WT:C (D8DVL)		128G bit	4G×32	LPDDR5/LPDDR5X	315ball								T/A [15]			T/A [25]																	
	MT62F4G32D8DV-020 WT:F(D8GDJ)		128G bit	4G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F4G32D8DV-020 WT:D(D8HRF)		128G bit	4G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																	
	MT62F768M64D4ZU-026 WT:B (D8CCJ)		48G bit	768M×64	LPDDR5/LPDDR5X	496ball											T/A																	
	MT62F1G64D4ZX-023 WT:C (D8DRK)		64G bit	1024M×64	LPDDR5/LPDDR5X	496ball											T/A																	
	MT62F1536M64D8CL-026 WT:B (D8CCN)		96G bit	1536M×64	LPDDR5/LPDDR5X	496ball											T/A																	
	MT62F2G64D8ZA-023 WT:C (D8DQK)		128G bit	2048M×64	LPDDR5/LPDDR5X	496ball											T/A																	

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO CPU_RAM	RK3399PRO NPU_RAM	RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK2928/RK3028A/RK3128/PX3-SE	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
Samsung	K4T1G164QE		1G bit	64M×16	DDR2	84ball																												
	K4B1G0846G		1G bit	128M×8	DDR3	78ball																								T/A				T/A
	K4B1G1646I-*C**		1G bit	64M×16	DDR3	96ball														T/A	T/A													
	K4B1G1646I-*Y**		1G bit	64M×16	DDR3L	96ball														T/A	T/A													
	K4B2G0846C		2G bit	256M×8	DDR3	78ball																												
	K4B2G0846F-*Y**		2G bit	256M×8	DDR3L	78ball																								T/A				T/A
	K4B2G1646C		2G bit	128M×16	DDR3	96ball																												
	K4B2G1646E		2G bit	128M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	K4B2G1646Q		2G bit	128M×16	DDR3	96ball															T/A	T/A		T/A	T/A	T/A				T/A	T/A	T/A	T/A	T/A
	K4B2G1646F-*Y**		2G bit	128M×16	DDR3L	96ball	T/A	T/A												T/A	T/A	T/A		T/A	T/A	T/A	T/A		T/A	T/A	T/A	T/A	T/A	T/A	T/A
	K4B4G0846E-*C**		4G bit	512M×8	DDR3	78ball															T/A	T/A		T/A	T/A	T/A					T/A			
	K4B4G1646B-*C**		4G bit	256M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	K4B4G1646Q-*Y**	EOL	4G bit	256M×16	DDR3L	96ball															T/A	T/A		√	T/A	T/A				T/A	T/A	T/A	T/A	T/A
	K4B4G1646D-*Y**	EOL	4G bit	256M×16	DDR3L	96ball															T/A	T/A		√	T/A	T/A				T/A	T/A	T/A	T/A	T/A
	K4B4G1646D-*C**	EOL	4G bit	256M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	K4W4G1646Q-*C**		4G bit	256M×16	DDR3	96ball																								T/A				T/A
	K4B4G1646E-*Y**		4G bit	256M×16	DDR3L	96ball					T/A					T/A		T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A			T/A		T/A		T/A	T/A	T/A
	K4B4G1646E-*C**		4G bit	256M×16	DDR3	96ball				T/A	T/A	T/A			T/A	T/A		T/A	T/A	T/A	T/A	T/A		T/A	T/A	T/A	T/A	T/A	T/A		T/A	T/A	T/A	T/A
	K4B8G1646D-*Y**	EOL	8G bit	512M×16	DDR3L	96ball																	T/A	√	T/A	T/A		√		T/A				
	K4A4G165WE-BC**	EOL	4G bit	256M×16	DDR4	96ball													T/A				T/A		T/A	T/A	T/A		T/A					
	K4A4G165WF-BC**	EOL	4G bit	256M×16	DDR4	96ball										T/A		T/A	T/A	T/A			T/A		√	T/A	T/A								
	K4A4G165WG-BC**		4G bit	256M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A	T/A						T/A	T/A								
	K4A8G085WC-BC**		8G bit	1024M×8	DDR4	78ball										T/A		T/A	T/A																
	K4A8G165WB-BC**	EOL	8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A	T/A			T/A				T/A		T/A						
	K4A8G165WC-BC**	EOL	8G bit	512M×16	DDR4	96ball				T/A	T/A	T/A			T/A	T/A		T/A	T/A	T/A					S/A [16]	S/A [16]	T/A		T/A						
	K4A8G165WG-BC**		8G bit	512M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A	T/A					T/A	T/A									
	K4AAG165WA-BC**	EOL	16G bit	1024Mx16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A	T/A							T/A		T/A						
	K4AAG165WB-MC**	EOL	16G bit	1024Mx16	DDR4	96ball				T/A					T/A			T/A	T/A																
	K4AAG165WB-BC**	EOL	16G bit	1024Mx16	DDR4	96ball										T/A		T/A	T/A																
	K4AAG165WC-BC**		16G bit	1024Mx16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A	T/A					T/A										
	K4ABG165WA-MC**		32G bit	2048M×16	DDR4	96ball										T/A		T/A	T/A																
	K3PE0E000A-XGC2	EOL	16Gb/2Channel	256M×32×2Ch	LPDDR2	220ball																								T/A [27]				N/A
	K3PE0E000M-XGC2	EOL	16Gb/2Channel	256M×32×2Ch	LPDDR2	216ball																								T/A [28]				N/A
	K4E8E304ED-EGCC	EOL	8G bit	256M×32	LPDDR3	178ball																					T/A		T/A	T/A	T/A				
	K4E8E304EE-EGCE	EOL	8G bit	256M×32	LPDDR3	178ball																		T/A				T/A		T/A					
	K4E8E324EB-AGCF	EOL	8G bit	256M×32	LPDDR3	168ball																									T/A				
	K4E8E324EB-EGCF	EOL	8G bit	256M×32	LPDDR3	178ball																T/A	T/A	T/A	T/A	T/A		T/A		T/A	T/A				
	K4E8E324ED-EGCG	EOL	8G bit	256M×32	LPDDR3	178ball																	T/A				T/A	T/A	T/A						
	K3QF1F10DM-AGCE	EOL	8Gb/2Channel	128M×32×2Ch	LPDDR3	253ball																								T/A					
	K3QF1F10EM-BGCF	EOL	8G bit	128M×32×2Ch	LPDDR3	216ball																								T/A					
	K4E6E304EE-EGCE	EOL	16G bit	512M×32	LPDDR3	178ball																T/A		T/A	T/A	T/A				T/A	T/A				
	K4E6E304EB-EGCF	EOL	16G bit	512M×32	LPDDR3	178ball																T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A				
	K4E6E304EC-EG**	EOL	16G bit	512M×32	LPDDR3	178ball										T/A		T/A	T/A			T/A	T/A	T/A	T/A	T/A				T/A					
	K4E6E304ED-EG**	EOL	16G bit	512M×32	LPDDR3	178ball														T/A			T/A		T/A	T/A	T/A	T/A	T/A	T/A					
	K4EBE304EC-EGC**	EOL	32G bit	1024M×32	LPDDR3	178ball														T/A		T/A		T/A	T/A	T/A									
	K3QF3F30BM-QGCF	EOL	16G bit	256M×32×2Ch	LPDDR3	216ball																								T/A					
	K3QF3F30BM-BGCF	EOL	16G bit	256M×32×2Ch	LPDDR3	216ball																								T/A					
	K4F4E3S4HF-MG**		4G bit	128M×32	LPDDR4	200ball									T/A					S/A [15]														
	K4F8E304HB-MG**	EOL	8G bit	256M×32	LPDDR4	200ball					T/A	T/A				T/A		T/A	T/A	S/A [15]			T/A					T/A							
	K4F8E3S4HD-MG**		8G bit	256M×32	LPDDR4	200ball								T/A	T/A	T/A [7]	T/A	T/A [7]	T/A [7]	S/A [15]			T/A		T/A			T/A							
	K4F2E3S4HM-MG**		12G bit	384M×32	LPDDR4	200ball													T/A [7]															
	K4F6E3S4HM-MG**		16G bit	512M×32	LPDDR4	200ball										T/A		T/A	T/A	S/A [15]			T/A		T/A			T/A							
	K4F6E3S4HM-SG**		16G bit	512M×32	LPDDR4	200ball								T/A		T/A	T/A	T/A	T/A																
	K4F6E3S4HB-MG**		16G bit	512M×32	LPDDR4	200ball					T/A	T/A		T/A	T/A	T/A	T/A	T/A	T/A				T/A		T/A			T/A							
	K4FHE3D4HM-MG**	EOL	24G bit	768M×32	LPDDR4	200ball													T/A [7]															
	K4FBE3D4HM-MG**		32G bit	1024M×32	LPDDR4	200ball										N/A	N/A	N/A	N/A																
	K4FBE3D4HB-MG**		32G bit	1024M×32	LPDDR4	200ball					T/A	T/A		T/A	T/A	T/A	T/A	T/A	T/A						T/A										
	K4U8E3S4AD-MG**		8G bit	256M×32	LPDDR4X	200ball					T/A			T/A		T/A [7]	T/A	T/A [7]	T/A [7]	N/A															
	K4U6E3S4AM-MG**		16G bit	512M×32	LPDDR4X	200ball										T/A		T/A	T/A																
	K4U6E3S4AA-MG**	EOL	16G bit	512M×32	LPDDR4X	200ball					T/A					T/A	S/A	T/A	T/A	N/A															
	K4U6E3S4AB-MG**		16G bit	512M×32	LPDDR4X	200ball					T/A			T/A	T/A	T/A	T/A	T/A	T/A																
	K4UHE3S4AA-MG**		24G bit	768M×32	LPDDR4X	200ball								T/A	T/A	T/A	T/A	T/A	T/A	N/A					N/A										
	K4UHE3D4AB-MG**	EOL	24G bit	768M×32	LPDDR4X	200ball										T/A	S/A	T/A	T/A																
	K4UBE3S4AM-MG**		32G bit	1024M×32	LPDDR4X	200ball								T/A	T/A	T/A	T/A	T/A	T/A																
	K4UBE3D4AA-MG**	EOL	32G bit	1024M×32	LPDDR4X	200ball									T/A	T/A [7]	S/A	T/A [7]	T/A [7]	N/A															
	K4UBE3D4AB-MG**		32G bit	1024M×32	LPDDR4X	200ball			T/A		T/A			T/A	T/A	T/A	T/A	T/A	T/A																
	K4UJE3D4AA-MG**		48G bit	1536M×32	LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	K4UCE3Q4AA-MG**	EOL	64G bit	2048M×32	LPDDR4X	200ball										T/A	S/A	T/A	T/A																
	K4UCE3Q4AB-MGCL		64G bit	2048M×32	LPDDR4X	200ball								S/A [14]		S/A	S/A [14]	S/A	S/A																
	K4UKE3Q4AA-MG**		96G bit	3072M×32	LPDDR4X	200ball								T/A			T/A																	
	K3RG2G20CM-MGCJ	EOL	32G bit	512M×64	LPDDR4	366ball																		T/A [4]				T/A [4]						
	K3KLDLD0EM-TG**		48G bit	1536M×32	LPDDR5X	245ball								T/A			T/A																	
	K3KL9L90DM-TG**		64G bit	2048M×32	LPDDR5X	245ball								T/A																				
	K3KLNLN0DM-TG**		96G bit	3072M×32	LPDDR5X	245ball								T/A			T/A																	
	K3KLTLT0DM-TG**		128G bit	4096M×32	LPDDR5X	245ball								T/A			T/A																	
	K3KL6L60GM-MG**		16G bit	512M×32	LPDDR5X	315ball											T/A																	
	K3LKBKB0BM-MG**		32G bit	1024M×32	LPDDR5	315ball								T/A			T/A																	
	K3LKCKC0BM-MG**		64G bit	2048M×32	LPDDR5	315ball								S/A			T/A																	
	K3KL8L80QM-MG**		32G bit	1024M×32	LPDDR5X	315ball								T/A			T/A																	
	K3KL8L80EM-MG**		32G bit	1024M×32	LPDDR5X	315ball								T/A			T/A																	
	K3KL9L90QM-MG**		64G bit	2048M×32	LPDDR5X	315ball								T/A			T/A																	
	K3KL9L90EM-MG**		64G bit	2048M×32	LPDDR5X	315ball								T/A			T/A																	
	K3KLALA0EM-MG**		128G bit	4096M×32	LPDDR5X	315ball								T/A			T/A																	
	K3KL3L30CM-BG**		64G bit	1024M×64	LPDDR5	496ball											T/A																	
	K3LK7K70BM-BG**		64G bit	1024M×64	LPDDR5	496ball											T/A																	
	K3LK4K40CM-BG**		96G bit	1536M×64	LPDDR5	496ball											T/A																	
	K3LK6K60BM-BG**		128G bit	2048M×64	LPDDR5	496ball											T/A																	

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO CPU_RAM	RK3399PRO NPU_RAM	RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK2928/RK3028A/RK3128/PX3-SE	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
Hynix	H5PS1G63CFP	EOL	1G bit	64M×16	DDR2	84ball																													
	H5PS1G63EFR	EOL	1G bit	64M×16	DDR2	84ball																													
	H5TQ1G83DFR	EOL	1G bit	128M×8	DDR3	78ball																								T/A					T/A
	H5TQ1G83TFR	EOL	1G bit	128M×8	DDR3	78ball																													
	H5TQ2G83CFR	EOL	2G bit	256M×8	DDR3	78ball																								√			√	√	√
	H5TQ2G83BFR	EOL	2G bit	256M×8	DDR3	78ball																								√			T/A	T/A	√
	H5TQ2G83EFR	EOL	2G bit	256M×8	DDR3	78ball																								T/A			T/A	T/A	T/A
	H5TQ2G83FFR	EOL	2G bit	256M×8	DDR3	78ball																											T/A	T/A	
	H5TQ2G83GFR	EOL	2G bit	256M×8	DDR3	78ball																								T/A					T/A
	H5TQ2G63BFR	EOL	2G bit	128M×16	DDR3	96ball																													
	H5TQ2G63FFR	EOL	2G bit	128M×16	DDR3	96ball																											T/A	T/A	
	H5TQ2G63GFR	EOL	2G bit	128M×16	DDR3	96ball															T/A	T/A		T/A	T/A	T/A				T/A	T/A		T/A	T/A	T/A
	H5TC2G63GFR	EOL	2G bit	128M×16	DDR3L	96ball															T/A						T/A		T/A		T/A				
	H5TQ2G63DFR	EOL	2G bit	128M×16	DDR3	96ball																								T/A					T/A
	H5TQ4G83AFR	EOL	4G bit	512M×8	DDR3	78ball																								T/A			T/A	T/A	T/A [1]
	H5TC4G83AFR	EOL	4G bit	512M×8	DDR3L	78ball																								T/A					T/A [1]
	H5TQ4G83MFR	EOL	4G bit	512M×8	DDR3	78ball																								T/A			T/A	T/A	T/A [1]
	H5TC4G83BFR	EOL	4G bit	512M×8	DDR3L	78ball																											T/A	T/A	
	H5TQ4G63MFR	EOL	4G bit	256M×16	DDR3	96ball																								T/A			T/A	T/A	T/A
	H5TQ4G63AFR	EOL	4G bit	256M×16	DDR3	96ball															T/A	T/A	T/A	T/A	T/A	T/A		T/A		T/A	T/A		T/A	T/A	T/A
	H5TC4G63AFR	EOL	4G bit	256M×16	DDR3L	96ball																								T/A			T/A	T/A	T/A
	H5TC4G63CFR	EOL	4G bit	256M×16	DDR3L	96ball															T/A	T/A		T/A	T/A	T/A				T/A	T/A				T/A
	H5TC4G63EFR		4G bit	256M×16	DDR3L	96ball														T/A	T/A	T/A	T/A	T/A	T/A	T/A		T/A		T/A	T/A				T/A
	H5TQ4G63EFR		4G bit	256M×16	DDR3	96ball														T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A				
	H5TQ4G63CFR	EOL	4G bit	256M×16	DDR3	96ball															T/A	T/A	T/A	T/A	T/A	T/A		T/A		T/A	T/A		T/A	T/A	T/A
	H5TC8G63AMR	EOL	8G bit	512M×16	DDR3L	96ball																T/A						T/A							
	H5TC8G63CMR	EOL	8G bit	512M×16	DDR3L	96ball																								T/A					
	H5AN4G6NAFR	EOL	4G bit	256M×16	DDR4	96ball															T/A		T/A			T/A		T/A							
	H5AN4G6NBJR		4G bit	256M×16	DDR4	96ball				T/A	T/A	T/A			T/A				T/A	T/A	T/A		T/A	T/A	T/A		T/A		T/A						
	H5AN8G6NAFR	EOL	8G bit	512M×16	DDR4	96ball															T/A		T/A	T/A	T/A	T/A		T/A							
	H5AN8G6NCJR	EOL	8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A	T/A				T/A	T/A	T/A		T/A							
	H5AN8G6NDJR		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A	T/A	T/A			T/A	T/A	T/A									
	H5AG36EXNJX017N		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A	T/A															
	H5ANAG6NAMR	EOL	16G bit	1024M×16	DDR4	96ball										T/A		T/A	T/A	T/A					T/A	T/A	T/A		T/A						
	H5ANAG6NCMR	EOL	16G bit	1024M×16	DDR4	96ball				T/A					T/A	T/A		T/A	T/A	T/A															
	H5ANAG6NCJR		16G bit	1024M×16	DDR4	96ball										T/A		T/A	T/A	T/A		T/A			T/A										
	H5AG36EXNDX017N		8G bit	512M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A	T/A						T/A	T/A								
	H5AG46DXNDX117N		16G bit	1024M×16	DDR4	96ball										T/A		T/A	T/A	T/A						T/A	T/A								
	H9TCNNN8JDMMPR		8Gb/2CS	256M×32	LPDDR2	134ball																								T/A					T/A
	H8TJR00X0MLR		8Gb/2CS	256M×32	LPDDR2	168ball																								T/A					T/A
	H9TKNNN8KDMPQR		8Gb/2Channel	128M×32×2Ch	LPDDR2	216ball																											T/A [2]		
	H9TKNNNBPDMRAR		16Gb/2Channel	256M×32×2Ch	LPDDR2	220ball																								T/A					N/A
	H9CCNNN8JTALAR	EOL	8G bit	256M×32	LPDDR3	178ball																								T/A					
	H9CCNNN8GTMLAR	EOL	8G bit	256M×32	LPDDR3	178ball																	T/A	T/A	T/A	T/A	T/A		T/A		T/A				
	H9CCNNN8JTMLAR	EOL	8G bit	256M×32	LPDDR3	178ball																	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	H9CCNNNBJTALAR	EOL	16G bit	512M×32	LPDDR3	178ball																	T/A	T/A	T/A	T/A	T/A		T/A						
	H9CCNNNBLTALAR	EOL	16G bit	512M×32	LPDDR3	178ball																	T/A		T/A	T/A	T/A				T/A				
	H9CCNNNBJTMLAR	EOL	16G bit	512M×32	LPDDR3	178ball																	N/A	N/A	N/A				N/A		T/A	N/A	N/A	N/A	N/A
	H9CKNNNBPTMRLR	EOL	16G bit	512M×32	LPDDR3	216ball																	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	H9CKNNNDATMUPR		24G bit	786M×32	LPDDR3	256ball										N/A		N/A	N/A															
	H9CKNNNCPTMRPR	EOL	32G bit	1024M×32	LPDDR3	256ball																	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	H9HCNNN8KUMLHR	EOL	8G bit	256M×32	LPDDR4	200ball					T/A	T/A			[26]	[26]		[26]	[26]	N/A				N/A				N/A							
	H9HCNNNBPUMLHR	EOL	16G bit	512M×32	LPDDR4	200ball									[26]	[26]		[26]	[26]	N/A				N/A				N/A							
	H9HCNNNBKUMLHR	EOL	16G bit	512M×32	LPDDR4	200ball									[26]	[26]		[26]	[26]	S/A [15]				S/A				S/A							
	H9HCNNNBKUMLXR	EOL	16G bit	512M×32	LPDDR4	200ball								T/A	[26]	[26]	T/A	[26]	S/A [25]	N/A				N/A				N/A							
	H9HCNNNCPUMLXR		32G bit	1024M×32	LPDDR4	200ball					T/A	T/A		T/A	[26]	[26]	T/A	[26]	[26]	S/A [15]															
	H9HCNNNBKMMLHR	EOL	16G bit	512M×32	LPDDR4X	200ball									[26]	[26]		[26]	S/A [25]	S/A [15]															
	H9HCNNNBKMMLXR		16G bit	512M×32	LPDDR4X	200ball								T/A	[26]	[26]	T/A	[26]	[26]																
	H9HCNNNCPMMLXR		32G bit/2cs	1024M×32	LPDDR4X	200ball					T/A			T/A	[26]	[26]	T/A	S/A [7][15]	S/A [7][25]	S/A [15]															
	H54GE6CYRBX262N		48G bit	1536M×32	LPDDR4X	200ball								N/A	N/A	N/A	N/A	N/A	N/A	N/A			N/A		N/A			N/A						
	H9HKNNNECMMUJR		48G bit	1536M×32	LPDDR4X	200ball								N/A	N/A	N/A	N/A	N/A	N/A	N/A			N/A		N/A			N/A						
	H9HCNNNFAMMLXR		64G bit	2048M×32	LPDDR4X	200ball								T/A		[26]	T/A	S/A [25]	S/A [25]															
	H54G38AYRBX259N		8G bit	256M×32	LPDDR4/LPDDR4X	200ball								T/A	[26]	[26]	T/A	[26]	[26]	N/A			N/A		N/A			N/A						
	H54G38AYRBX259		8G bit	256M×32	LPDDR4/LPDDR4X	200ball								T/A	[26]	[26]	T/A	[26]	[26]	N/A			N/A		N/A			N/A						
	H54G46CYRBX267N		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A	[26]	[26]	T/A	S/A [25]	S/A [25]				S/A		S/A			S/A						
	H54G56CYRBX247N		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball									[26]	[26]		[26]	[26]	N/A			N/A		N/A			N/A						
	H54G38AYRBX247		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball									[26]	[26]		[26]	[26]	N/A			N/A		N/A			N/A						
	H9HKNNNDBUMUBR	EOL	24G bit	384M×64	LPDDR4	366ball									[26]	[26]		[26]	[26]				N/A					N/A						
	H9HKNNNCUUMUBR	EOL	32G bit	512M×64	LPDDR4	366ball									[26]	[26]		[26]	[26]				N/A					N/A						
	H9HKNNNCTUMUBR	EOL	32G bit	512M×64	LPDDR4	366ball									[26]	[26]		[26]	[26]				S/A					S/A						
	H9JCNNNBK3MLYR		16G bit	512M×32	LPDDR5	315ball								T/A			T/A																	
	H9JCNNNCP3MLYR		32G bit	1024M×32	LPDDR5	315ball								S/A			T/A																	
	H9JCNNNFA5MLYR		64G bit	2048M×32	LPDDR5	315ball			T/A					T/A			T/A																	
	H58G56CK8BX146N		32G bit	1024M×32	LPDDR5X	315ball								T/A			T/A																	
	H58G66CK8BX147N		64G bit	2048M×32	LPDDR5X	315ball								T/A			T/A																	
	H58G78CK8BX185		128G bit	4096M×32	LPDDR5X	315ball								T/A			T/A																	

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK2928/RK3028A/RK3128/PX3-SE	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
																												CPU_RAM	NPU_RAM					
Nanya	NT5TU32M16CG-3C		512M bit	32M×16	DDR2	84ball																											
	NT5TU32M16FG		512M bit	32M×16	DDR2	84ball															T/A												
	NT5TU64M16HG		1G bit	64M×16	DDR2	84ball															T/A												
	NT5CB64M16GP		1G bit	64M×16	DDR3	96ball	T/A	T/A		T/A	T/A	T/A	T/A		T/A						T/A										T/A		T/A	
	NT5CC64M16GP		1G bit	64M×16	DDR3L	96ball							T/A								T/A												
	NT5CB128M8DN		1G bit	128M×8	DDR3	96ball																											
	NT5CC128M8DN		1G bit	128M×8	DDR3L	78ball																								T/A			T/A
	NT5CB128M8FN		1G bit	128M×8	DDR3	78ball																								T/A			T/A
	NT5CC128M8GN		1G bit	128M×8	DDR3L	78ball																											T/A
	NT5CB256M8GN		2G bit	256M×8	DDR3	78ball																								T/A		T/A	T/A	T/A
	NT5CB256M8BN		2G bit	256M×8	DDR3	78ball																								T/A		T/A	T/A	T/A
	NT5CB256M8FN		2G bit	256M×8	DDR3	78ball																								T/A		T/A	T/A	T/A
	NT5CB256M8IN		2G bit	256M×8	DDR3	78ball															T/A	T/A		T/A	T/A	T/A					T/A			
	NT5CC256M8IN		2G bit	256M×8	DDR3L	78ball															T/A	T/A		T/A	T/A	T/A					T/A			T/A
	NT5CB128M16BP		2G bit	128M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	NT5CB128M16HP		2G bit	128M×16	DDR3	96ball																								T/A				T/A
	NT5CC128M16BP		2G bit	128M×16	DDR3L	96ball																												
	NT5CB128M16FP		2G bit	128M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	NT5CC128M16IP	EOL	2G bit	128M×16	DDR3L	96ball															T/A									T/A	T/A	T/A	T/A	T/A
	NT5CB128M16IP	EOL	2G bit	128M×16	DDR3	96ball															T/A				T/A	T/A				T/A	T/A	T/A	T/A	T/A
	NT5CB128M16JR		2G bit	128M×16	DDR3	96ball				T/A					T/A					T/A	T/A													
	NT5CC128M16JR		2G bit	128M×16	DDR3L	96ball							T/A							T/A	T/A	T/A		T/A	T/A	T/A	T/A		T/A	T/A	T/A			
	NT5CB512M8DN		4G bit	512M×8	DDR3	78ball															T/A	T/A		T/A	T/A	T/A					T/A			
	NT5CB512M8BN		4G bit	512M×8	DDR3	78ball																								T/A		T/A	T/A	T/A [1]
	NT5CC512M8CN		4G bit	512M×8	DDR3L	78ball																								T/A		T/A	T/A	T/A [1]
	NT5CC512M8DN		4G bit	512M×8	DDR3L	78ball															T/A	T/A		T/A	T/A	T/A					T/A			T/A
	NT5CC512M8EN		4G bit	512M×8	DDR3L	78ball															T/A										T/A			
	NT5CB256M16BP		4G bit	256M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	NT5CB256M16CP	EOL	4G bit	256M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	NT5CB256M16DP	EOL	4G bit	256M×16	DDR3	96ball																								T/A				
	NT5CB256M16EP		4G bit	256M×16	DDR3	96ball														T/A	T/A	T/A	T/A	T/A	T/A	T/A		T/A			T/A			
	NT5CC256M16CP	EOL	4G bit	256M×16	DDR3L	96ball																								T/A		T/A	T/A	T/A
	NT5CC256M16DP	EOL	4G bit	256M×16	DDR3L	96ball															T/A	T/A	T/A	T/A	T/A	T/A		T/A		T/A	T/A	T/A	T/A	T/A
	NT5CC256M16EP		4G bit	256M×16	DDR3L	96ball															T/A	T/A	T/A	T/A	T/A	T/A		T/A		T/A	T/A	T/A		T/A
	NT5CC256M16ER		4G bit	256M×16	DDR3L	96ball					T/A	T/A	T/A			T/A		T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A			T/A		T/A	T/A			
	NT5CB256M16ER		4G bit	256M×16	DDR3	96ball				T/A	T/A	T/A	T/A		T/A	T/A		T/A	T/A						T/A									
	NT5CC512M16EH		8G bit	512M×16	DDR3L	96ball										T/A		T/A	T/A														
	NT5AD256M16B2	EOL	4G bit	256M×16	DDR4	96ball																T/A		T/A			T/A		T/A				
	NT5AD256M16D4	EOL	4G bit	256M×16	DDR4	96ball													T/A	T/A		T/A		T/A	T/A	T/A	T/A		T/A				
	NT5AD256M16E4		4G bit	256M×16	DDR4	96ball				T/A	T/A	T/A			T/A	T/A		T/A	T/A	T/A					T/A	T/A								
	NT5AD512M16A4	EOL	8G bit	512M×16	DDR4	96ball																					T/A		T/A				
	NT5AD512M16C4		8G bit	512M×16	DDR4	96ball					N/A	N/A			N/A	N/A [39]		N/A [39]	N/A [39]	N/A		N/A		N/A	N/A	N/A	N/A		N/A				
	NT5AD512M16G4	EOL	8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A						T/A	T/A							
	NT5AD512M16H4		8G bit	512M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A	T/A													
	NT6TL128M32AQ		4G bit	128M×32	LPDDR2	168ball																								T/A				T/A
	NT6TL256F32AI		8G bit	256M×32	LPDDR2	134ball																								T/A				T/A
	NT6TL256T32AI		8G bit	256M×32	LPDDR2	134ball																								T/A				T/A
	NT6TL256T32AQ		8G bit	256M×32	LPDDR2	168ball																								T/A				T/A
	NT6CL128M32BM		4G bit	128M×32	LPDDR3	178ball																								T/A				
	NT6CL128M32CM		4G bit	128M×32	LPDDR3	178ball																	T/A				T/A	T/A	T/A					
	NT6CL128M32DM		4G bit	128M×32	LPDDR3	178ball					T/A	T/A								T/A			T/A				T/A	T/A	T/A					
	NT6CL256T32CM		8G bit	256M×32	LPDDR3	178ball																T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A					
	NT6CL256T32BM		8G bit	256M×32	LPDDR3	178ball																T/A	T/A	T/A	T/A	T/A		T/A	T/A		T/A	T/A			
	NT6CL256M32AM		8G bit	256M×32	LPDDR3	178ball					T/A	T/A								T/A		T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A			
	NT6CL512T32AM		16G bit	512M×32	LPDDR3	178ball														T/A		T/A [5]	T/A	T/A [5]	T/A	T/A		T/A		T/A [5]	T/A				
	NT6CL1024F32AP		32G bit	1024M×32	LPDDR3	178ball					T/A	T/A																						
	NT6CL256T32AQ		8G bit	256M×32	LPDDR3	168ball																									T/A			
	NT6AN256T32AV		8G bit	256M×32	LPDDR4	200ball									[36]	[36]		[36]	[36]				N/A						N/A					
	NT6AN512T32AV		16G bit	512M×32	LPDDR4	200ball					T/A	T/A			[36]	S/A [35]		S/A [35]	S/A [35]	N/A			N/A		N/A				N/A					
	NT6AN1024T32AV		32G bit	1024M×32	LPDDR4	200ball									[36]	[36]	N/A	S/A [35]	S/A [35]															
	NT6AP128M16BV		4G bit	128M×16	LPDDR4X	200ball					T/A																							
	NT6AP256M16BV		8G bit	256M×16	LPDDR4X	200ball					T/A																							
	NT6AP256T32AV		8G bit	256M×32	LPDDR4X	200ball								T/A	[36]	[36]	T/A	[36]	[36]	N/A														
	NT6AP256T32BV		8G bit	256M×32	LPDDR4X	200ball					T/A				[36]	[36]	N/A	[36]	[36]															
	NT6AP512T32BV		16G bit	512M×32	LPDDR4X	200ball								T/A	[36]	[36]	T/A	[36]	[36]															
	NT6AP512T32AV		16G bit	512M×32	LPDDR4X	200ball									[36]	[36]	T/A	[36]	[36]	N/A														
	NT6AP512T32BL		16G bit	512M×32	LPDDR4X	200ball					T/A	T/A		S/A	[36]	S/A [35]	S/A	S/A [35]	S/A [35]															
	NT6AP1024F32BV		32G bit	1024M×32	LPDDR4X	200ball									[36]	[36]	N/A	[36]	[36]															

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106 B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228 B/RK3229 /PX5	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3
																												CPU_RAM	NPU_RAM					
CXMT	CXDQ2BFAMCG	EOL	4G bit	256M×16	DDR4	96ball													T/A	T/A		T/A [5]		T/A [5]										
	CXDQ2BFAM-CE-B		4G bit	256M×16	DDR4	96ball																				T/A									
	CXDQ3BFAMCG	EOL	8G bit	512M×16	DDR4	96ball													T/A	T/A		T/A [5]		T/A [5]										
	CXDQ3BFAM-CQ-A	EOL	8G bit	512M×16	DDR4	96ball				S/A [123]					S/A [22]	N/A		N/A	S/A [22]	N/A		N/A		N/A	S/A [22]	N/A	N/A		N/A					
	CXDQ3BFAM-CJ-A	EOL	8G bit	512M×16	DDR4	96ball									N/A	S/A [22]		S/A [22]	S/A [22]	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	CXDQ4BFAM-CJ-M		16G bit	1024M×16	DDR4	96ball										S/A [16]		S/A [16]	S/A [16]															
	CXDB3ABAM-MK		8G bit	256M×32	LPDDR4/LPDDR4X	200ball										T/A [7][12]		T/A [7][12]	T/A [7][12]	S/A [15]			T/A		T/A			T/A						
	CXDB3ABAM-MK-A		8G bit	256M×32	LPDDR4/LPDDR4X	200ball								T/A [26]	T/A	T/A	T/A [26]	T/A	T/A	S/A [11][15]														
	CXDB3CBAM-MA-A		8G bit	256M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A															
	CXDB4ABAM-MK		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		T/A [7][12]	T/A [26]	T/A [7][12]	T/A [7][12]	S/A [15]			T/A		T/A			T/A						
	CXDB4CBAM-MK-A		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A [26]	T/A	T/A	T/A [17][26]	T/A	T/A				T/A		T/A			T/A						
	CXDB4CBAM-ML-A		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A [17]																	
	CXDB4CCAM-MJ		16G bit	512M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A															
	CXDB4CBAM-MA-B		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A		T/A			T/A			T/A																	
	CXDBBCCBM-MK-B		24G bit	768M×32	LPDDR4/LPDDR4X	200ball								T/A [26]	T/A	T/A	T/A [26]	T/A	T/A						T/A									
	CXDB5CCAM-MK		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		T/A [12]	T/A	T/A [12]	T/A [12]															
	CXDB5CCAM-ML		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball											N/A																	
	CXDB5CCBM-M*-A		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball					T/A			T/A	T/A	S/A	T/A [17]	S/A	S/A						T/A									
	CXDB5CBAM-MA-B		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball					T/A			T/A	T/A	T/A	T/A	T/A	T/A	N/A					N/A									
	CXDBCCCDM-MA-M		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
	CXDB6CCDM-MA-M		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A [21]		T/A	T/A [17]	T/A	T/A															
	CXDB6CCBM-MA-A		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A					T/A		T/A	T/A	T/A	T/A															
	CXDBDCCCM-MA-M		96G bit	3G×32	LPDDR4/LPDDR4X	200ball								T/A [25]			T/A [25]																	
	CXDB7CCDM-MA-M		128G bit	4G×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																	
	CXDD5DBAM-MC-M		32G bit	1024M×32	LPDDR5X	315ball								T/A			T/A																	
	CXDD6DCBM-MC-M		64G bit	2048M×32	LPDDR5X	315ball								T/A			T/A																	
	CXDCCDCBM-MT-M		48G bit	1536M×32	LPDDR5	315ball								T/A			T/A																	
	CXDCDJEDM-MT-M		96G bit	1536M×64	LPDDR5	496ball											N/A																	
GigaDevice/XCMemory	GDP1BFLM-CB		2G bit	128M×16	DDR3L	96ball				T/A					T/A						T/A	T/A								T/A				
	GDP1BFLM-CA		2G bit	128M×16	DDR3L	96ball										T/A		T/A	T/A															
	GDP1BFLA-C*		2G bit	128M×16	DDR3L	96ball							T/A		N/A	T/A		T/A	T/A		T/A													
	GDP2BFLM-C*		4G bit	256M×16	DDR3L	96ball				T/A	T/A	T/A	T/A		T/A	T/A		T/A	T/A	T/A	T/A	T/A		T/A		T/A				T/A				
	GDP2BFLM-WA		4G bit	256M×16	DDR3L	96ball					T/A	T/A																						
	GDP3BELM-CB		8G bit	512M×16	DDR3L	96ball							T/A			N/A		N/A	N/A											T/A				
	GDQ2BFAA-CE		4G bit	256M×16	DDR4	96ball									N/A				T/A	T/A					T/A	T/A	N/A		N/A					
	GDQ2BFAA-CQ		4G bit	256M×16	DDR4	96ball									N/A	S/A [29]		S/A [20]	S/A [20]	S/A [20]		N/A		N/A	S/A [20]	S/A [20]	N/A		N/A					
	GDQ2BFAA-CJ		4G bit	256M×16	DDR4	96ball									N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	GDQ2BFAC-CJ		4G bit	256M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A						T/A	T/A								
	GDQ3BFAM-CJ		8G bit	512M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A	T/A					T/A	T/A								
	GDB4CBQM-MK		16G bit	512M×32	LPDDR4/LPDDR4X	200ball									T/A	T/A		T/A	T/A						T/A									
	GDB4CBQN-M*		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A	T/A	T/A	T/A	T/A	T/A				T/A		N/A			N/A						
	GDB4CBQM-ML		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																	
	GDB5CCQN-ML		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A	T/A	T/A	T/A	T/A	T/A						N/A									
	GDB5CBQN-ML		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
JHICC	CA4S4G16V-F9**C		4G bit	256M×16	DDR4	96ball					T/A	T/A				T/A [8]		T/A [8]	T/A [8]	T/A					T/A									
	CA4S8G16V-F9**C		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A	T/A					T/A									
	CB4S8G16V-F9**C		8G bit	512M×16	DDR4	96ball				T/A	T/A	T/A			T/A	T/A		T/A	T/A						T/A									
ESMT	M14D1G1664A-1.8BG2S		1G bit	64M×16	DDR2	84ball															T/A												
	M15T1G1664A-DEBG2C		1G bit	64M×16	DDR3L	96ball														N/A	T/A												
	M15T1G1664A-DEBG2CS		1G bit	64M×16	DDR3L	96ball														T/A													T/A	
	M15T1G1664A-EFBG2S		1G bit	64M×16	DDR3L	96ball														T/A														
	M15T1G1664A-DEBG2S		1G bit	64M×16	DDR3L	96ball							T/A								T/A													
	M15T2G16128A-DEBG2L	EOL	2G bit	128M×16	DDR3L	96ball															T/A				N/A	N/A					T/A			
	M15T2G16128A-DEBG2LS	EOL	2G bit	128M×16	DDR3L	96ball														T/A	T/A				T/A	T/A	T/A		T/A	T/A	T/A			
	M15T2G16128A--DEBG2R		2G bit	128M×16	DDR3L	96ball														T/A					T/A	T/A								
	M15T2G16128A-DEBG2D		2G bit	128M×16	DDR3L	96ball					T/A	T/A	T/A								T/A													
	M15T4G16256A-DEBG2L	EOL	4G bit	256M×16	DDR3L	96ball																T/A		T/A	T/A	T/A								
	M15F4G16256A-DEBG2L	EOL	4G bit	256M×16	DDR3	96ball															N/A	N/A		N/A	N/A	N/A						N/A		
	M15T4G16256A-DEBG2R	EOL	4G bit	256M×16	DDR3L	96ball																			T/A	T/A								
	M15T4G16256A-DEBG2G	EOL	4G bit	256M×16	DDR3L	96ball														T/A					T/A	T/A								
	M15T4G16256A--DEBG2S		4G bit	256M×16	DDR3L	96ball										T/A		T/A	T/A	T/A														
	M15T4G16256A-DEBG2P		4G bit	256M×16	DDR3L	96ball					T/A	T/A	T/A								T/A					T/A								
	M16U4G16256A-KJBG		4G bit	256M×16	DDR4	96ball				T/A					T/A					T/A				T/A	T/A								
	M16U4G16256A-QLBG		4G bit	256M×16	DDR4	96ball													T/A					T/A	T/A								
	M16U4G16256A-QLBG2Z		4G bit	256M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A	T/A		T/A		T/A	S/A								
	M16U8G16512A-NLBG2W		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A	T/A													
	M16U8G16512A-NLBG2C		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A						T/A	T/A								
	M56Z8G32256A-SMBIG		8G bit	256M×32	LPDDR4	200ball														S/A [15]					T/A									
	M56Z8G32256A-SMBYIG		8G bit	256M×32	LPDDR4/LPDDR4X	200ball									N/A	N/A		N/A	N/A															
	M56Z16G32512A-TNBYG2D		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A						T/A									
UniIC	SCB15H1G160CF-13K		1G bit	64M×16	DDR3	96ball															T/A												
	SCB15H1G160AF-13K		1G bit	64M×16	DDR3	96ball															T/A												
	SCB13H1G160EF-11M		1G bit	64M×16	DDR3L	96ball															T/A												
	SCN13H2G160AF-13K		2G bit	128M×16	DDR3	96ball																										T/A		
	SCB13H2G160AF-11M		2G bit	128M×16	DDR3L	96ball															T/A										T/A			
	SCB15H2G160AF-13K	EOL	2G bit	128M×16	DDR3	96ball																			T/A	T/A								
	SCB13H2G160AF-13K		2G bit	128M×16	DDR3L	96ball							N/A		N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A		N/A	N/A	N/A
	SCB13H2G160EF-09N		2G bit	128M×16	DDR3L	96ball				T/A			T/A		T/A					T/A	T/A				T/A	T/A	T/A		T/A	T/A				
	SCB13H2G160GF-09N		2G bit	128M×16	DDR3L	96ball										T/A		T/A	T/A															
	SCB13H4G160AF-11M		4G bit	256M×16	DDR3L	96ball							T/A								T/A	T/A	T/A	T/A	T/A	T/A		T/A		T/A				
	SCB13H4G160BF-11M		4G bit	256M×16	DDR3L	96ball					T/A	T/A	T/A									T/A												
	HXB15H4G800AF-13K		4G bit	512M×8	DDR3	78ball															T/A										T/A			
	HXB13H4G160AF-13KT		4G bit	256M×16	DDR3	96ball															T/A										T/A	T/A	T/A	T/A
	HX115H4G160AF-13K		4G bit	256M×16	DDR3	96ball																	T/A					T/A						
	SCB13H8G162BF-11M		8G bit	512M×16	DDR3L	96ball															T/A		T/A	T/A	T/A	T/A	T/A	T/A			T/A			
	SCB12Q4G160AF-07Q		4G bit	256M×16	DDR4	96ball									N/A	T/A		T/A	T/A	T/A														
	SCB12Q4G160BF-07Q		4G bit	256M×16	DDR4	96ball														T/A														
	SCB12Q4G160BF-06S		4G bit	256M×16	DDR4	96ball				T/A					T/A	T/A		T/A	T/A						T/A	T/A								
	SCB12Q4G160CF-06S		4G bit	256M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A															
	SCB12Q8G160BF-06S		8G bit	512M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A															
	SCE11N8G322BF-04Z		8G bit	256M×32	LPDDR4	200ball					T/A	T/A																						

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO CPU_RAM	RK3399PRO NPU_RAM	RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK2928/RK3028A/RK3128/PX3-SE	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
SCSemicon	HXB18T1G160AF-25D		1G bit	64M×16	DDR2	84ball																												
	HXB18T2G160AF-25D		2G bit	128M×16	DDR2	84ball																												
	HXB15H2G800BF-15H		2G bit	256M×8	DDR3	78ball																								T/A		T/A	N/A	T/A
	HXB15H2G160CF-13K		2G bit	128M×16	DDR3	96ball																										T/A		
	HXB15H4G800BF-15H		4G bit	512M×8	DDR3	78ball																								T/A		T/A	N/A	T/A [1]
	HXB15H4G160BF-15H		4G bit	256M×16	DDR3	96ball																								T/A				T/A [25]
Winbond	W9751G6KB-25		512M bit	32M×16	DDR2	84ball															T/A													
	W9751G6NB-25		512M bit	32M×16	DDR2	84ball															T/A													
	W971GG6SB-18		1G bit	64M×16	DDR2	84ball															T/A													
	W631GG6KB-12		1G bit	64M×16	DDR3	96ball															T/A										T/A			
	W631GG6MB-12	EOL	1G bit	64M×16	DDR3	96ball															T/A													
	W631GU6NB-12		1G bit	64M×16	DDR3L	96ball															T/A [10]													
	W631GU6RB-11		1G bit	64M×16	DDR3L	96ball							T/A																					
	W632GG6KB-15		2G bit	128M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	W632GG6NB-12		2G bit	128M×16	DDR3	96ball									N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	W632GU6NB-11		2G bit	128M×16	DDR3L	96ball				S/A																								
	W632GU6NB-09		2G bit	128M×16	DDR3L	96ball														T/A														
	W632GU6QB-09		2G bit	128M×16	DDR3L	96ball					T/A	T/A				T/A		T/A	T/A	T/A														
	W632GU6RB-**		2G bit	128M×16	DDR3L	96ball				T/A	T/A	T/A	T/A		T/A						T/A												T/A	
	W634GU8RB-09		4G bit	512M×8	DDR3L	78ball				T/A																								
	W634GU6QB-11		4G bit	256M×16	DDR3L	96ball																	T/A [13]					T/A [13]						
	W634GU6QB-09		4G bit	256M×16	DDR3L	96ball										T/A		T/A	T/A						T/A	T/A								
	W634GU6RB-**		4G bit	256M×16	DDR3L	96ball					T/A	T/A	T/A			T/A		T/A	T/A	T/A	T/A					T/A								
	W638GU6QB-11I		8G bit	512M×16	DDR3L	96ball																								T/A				
	W638GU6QB-09		8G bit	512M×16	DDR3L	96ball							T/A			N/A		N/A	N/A															
	W664GG6RB-06		4G bit	256M×16	DDR4	96ball				T/A					T/A	T/A		T/A	T/A	T/A					S/A									
	W66BL6NBUAFI		2G bit	128M×16	LPDDR4	200ball														S/A [15]													
	W66DP2RQQAGJ		8G bit	256M×32	LPDDR4/LPDDR4X	200ball					N/A	N/A		N/A	N/A	S/A [33]	N/A	S/A [33]	S/A [33]	N/A			N/A		N/A			N/A						
	W66DP2RQQAHJ		8G bit	256M×32	LPDDR4/LPDDR4X	200ball					T/A			T/A	T/A		T/A																	
	W66DP2RQTAHJE		8G bit	256M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																	
Etron Tech	EM68B16CWPA-25H		512M bit	32M×16	DDR2	84ball																												
	EM68B16CWQK-18H		512M bit	32M×16	DDR2	84ball															T/A													
	EM68B16CWQH-18H		512M bit	32M×16	DDR2	84ball															T/A													
	EM6GC16EWKG-12H		1G bit	64M×16	DDR3	96ball														T/A	T/A										T/A			
	EM6HC16EWBJ-10H		1G bit	64M×16	DDR3L	96ball							T/A																					
	EM6GC16EWKE-12H	EOL	2G bit	128M×16	DDR3	96ball															T/A													
	EM6GC16EWXD-12H	EOL	2G bit	128M×16	DDR3	96ball															T/A													
	EM6GD16EWKG-12H	EOL	2G bit	128M×16	DDR3	96ball															T/A				T/A	T/A					T/A			
	EM6GD16EWXF-12H	EOL	EOL	128M×16	DDR3	96ball															T/A				T/A	T/A					T/A			
	EM6GD16EWBH-12H		2G bit	128M×16	DDR3	96ball																					T/A		T/A			T/A		
	EM6HC16EWBH-09H		2G bit	128M×16	DDR3L	96ball									N/A	N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	EM6GE16EW5B-15H		4G bit	256M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	EM6GE08EWSC-12H		4G bit	512M×8	DDR3	96ball																										T/A	T/A	
	EM6GE16EWXC-12H		4G bit	256M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	EM6HE16EWXD-12H	EOL	4G bit	256M×16	DDR3L	96ball															T/A	T/A		T/A	T/A	T/A	T/A		T/A					
	EM6GE16EWXD-10H	EOL	4G bit	256M×16	DDR3	96ball															T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A
	EM6GE16EW5F-12H	EOL	4G bit	256M×16	DDR3	96ball																T/A		T/A	T/A	T/A								
	EM6HE16EW5F-12H	EOL	4G bit	256M×16	DDR3L	96ball																T/A		T/A	T/A	T/A								
	EM6HE16EWAKG-10H		4G bit	256M×16	DDR3L	96ball							T/A			T/A		T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A			
	EM6HE16EWAKG-09H		4G bit	256M×16	DDR3L	96ball									N/A																			
	EM6GE16EWAKG-10H		4G bit	256M×16	DDR3	96ball							T/A			T/A		T/A	T/A	T/A			T/A					T/A						
	EM6HF16EBXB-10SH		8G bit	512M×16	DDR3L	96ball							T/A													T/A								
	EM6HF16EBXB-10ESH		8G bit	512M×16	DDR3L	96ball																												
	EM6HF16EBXB-09SH		8G bit	512M×16	DDR3L	96ball				T/A [23]	T/A	T/A			T/A [21]	T/A		T/A	T/A																
	EM6OE16NWAKA-08H		4G bit	256M×16	DDR4	96ball										T/A		T/A	T/A	T/A														
	EM6OE16NWBB-62H		4G bit	256M×16	DDR4	96ball										T/A		T/A	T/A															
	EM6OE16NWBB-07H		4G bit	256M×16	DDR4	96ball				T/A					T/A				T/A	T/A					T/A									
	EM6OF16NWBD-62H		8G bit	512M×16	DDR4	96ball									N/A	N/A		N/A	N/A	N/A			N/A		N/A	N/A	N/A	N/A		N/A				
	EM6OF16NWBE-62H		8G bit	512M×16	DDR4	96ball				T/A	T/A	T/A			T/A	T/A		T/A	T/A						T/A									
	EM6OG16NWBB-62H		16G bit	1024M×16	DDR4	96ball										T/A		T/A	T/A															
	EM6LG32MVAPD-46SH		16G bit	512M×32	LPDDR4	200ball									[24]	S/A [35]		S/A [35]	S/A [35]	N/A			N/A		N/A			N/A						
	EM6PH32MVAJA-46SH		32G bit	1024M×32	LPDDR4	200ball								T/A		T/A	T/A	T/A	T/A															
Zentel	A3R12E40DBF-AH		512M bit	32M×16	DDR2	84ball															T/A													
	A3T1GF40CBF-HP		1G bit	64M×16	DDR3	96ball									N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	A3T1GF40CBF-GM		1G bit	64M×16	DDR3	96ball									N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	A3T2GF40BBF-GM		2G bit	128M×16	DDR3	96ball															N/A											T/A		
	A3T2GF40CBF-HP		2G bit	128M×16	DDR3	96ball															T/A													
	A3T4GF40BBF-HP		4G bit	256M×16	DDR3	96ball															T/A													
	A3T4GF40AABF-GM		4G bit	256M×16	DDR3	96ball																T/A		T/A	T/A	T/A								
	A3T8GF33BBF-GM**		8G bit	1G×8	DDR3	78ball																			N/A	N/A								
	A3T8GF33BBF-HP**		8G bit	1G×8	DDR3	78ball																			N/A	N/A								
	A3F4GH40CBF-WD		4G bit	256M×16	DDR4	96ball													T/A						T/A									
	A3F8GH40BBF-KD		8G bit	512M×16	DDR4	96ball													T/A						T/A									
	A3F4GH40ABF-WD		4G bit	256M×16	DDR4	96ball													T/A							T/A								
	A3F8GH40BBF-MC		8G bit	512M×16	DDR4	96ball									N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	A8XAGH50BBA-PM		16G bit	512M×32	LPDDR4X	200ball										T/A		T/A	T/A															
	A8XAGH50ABA-PM		16G bit	512M×32	LPDDR4X	200ball								T/A [26]	[26]	[26]	T/A [26]	[26]	[26]															
	A8XBGH52ABA-PM		32G bit	1024M×32	LPDDR4X	200ball								T/A [26]	[26]	[26]	T/A [26]	[26]	[26]															
	A8XBGH52BBA-PM		32G bit	1024M×32	LPDDR4X	200ball										T/A		T/A	T/A															
	A8XBGH50BBA-CM		32G bit	1024M×32	LPDDR4X	200ball								T/A			T/A																	

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO CPU_RAM	RK3399PRO NPU_RAM	RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK2928/RK3028A/RK3128/PX3-SE	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
ΣPM	PME810816CBR-G8DN		1G bit	64M×16	DDR2	84ball															T/A													
	PMF510816ABR-G8DN		1G bit	64M×16	DDR3	96ball																												
	PMF410816EBR-MBDN		1G bit	64M×16	DDR3L	96ball														T/A														
	PMF511816ABR-G8DN		2G bit	128M×16	DDR3	96ball																												
	PMF511816DBR-KADN		2G bit	128M×16	DDR3	96ball																								T/A				T/A
	PMF411816HBR-NCDN		2G bit	128M×16	DDR3L	96ball														T/A														
	PMF412816HBR-KADN		4G bit	256M×16	DDR3L	96ball																			T/A	T/A								
	PMF512816BBR-KADN		4G bit	256M×16	DDR3	96ball																								T/A				T/A
	PMF512816DBR-KADN		4G bit	256M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	PMF512816HBR-KADN		4G bit	256M×16	DDR3	96ball																								T/A [9]				
	PMF512816HBR-NCDN		4G bit	256M×16	DDR3	96ball														T/A														
	PMF412816FBR-KADN		4G bit	256M×16	DDR3L	96ball																								T/A				
τ Memory	TMF41G66EBR-MBDN		1G bit	64M×16	DDR3L	96ball							T/A								T/A													
	TMF42G66HBR-MBDN		2G bit	128M×16	DDR3L	96ball							T/A																					
	TMF42G66HBR-NCDN		2G bit	128M×16	DDR3L	96ball										T/A		T/A	T/A	T/A					T/A	T/A								
	TMF54G6HBR-KADN		4G bit	256M×16	DDR3	96ball																								T/A [9]				
	TMF54G66HBR-NCDN		4G bit	256M×16	DDR3	96ball										T/A		T/A	T/A	T/A														
	TDG64G6DB-KCNN		4G bit	256M×16	DDR4	96ball					T/A					T/A		T/A	T/A						N/A									
	TDG68G6CB-KCNN		8G bit	512M×16	DDR4	96ball					T/A					T/A		T/A	T/A															
ISSI	IS43TR16640B-125KBL		1G bit	64M×16	DDR3	96ball															T/A													
	IS43TR16128C-125KBL		2G bit	128M×16	DDR3	96ball															T/A				T/A	T/A	T/A		T/A		T/A			
	IS43TR16512BL-125KBLI		8G bit	512M×16	DDR3L	96ball																	T/A					T/A		T/A				
Essencore	I5TQ4G63EFR		4G bit	256M×16	DDR3	96ball																T/A		T/A	T/A	T/A								
	EL38NMAAA1-PBER		8G bit	256M×32	LPDDR3	178ball																	T/A					T/A						
	EL4BPMBBB1-S4ER		16G bit	512M×32	LPDDR4	200ball									N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
SPECTEK	PE918-15E (PRN256M8V79DG8GQF-15E)		2G bit	256M×8	DDR3	78ball																								T/A		T/A	T/A	T/A
	PE936-15E(PRN256M8V89CG8GQF-15E)		2G bit	256M×8	DDR3	78ball																								N/A		T/A	T/A	N/A
	PEB08-15E(PRN512M8V80AG8RHF-15E)		4G bit	512M×8	DDR3	78ball																								T/A			T/A	T/A [1]
	PEB15-15E(PRN256M16V80AG8GPF-15E)		4G bit	256M×16	DDR3	96ball																								T/A		T/A	T/A	T/A
	PEB16-15E(PRM256M16V80AG8GPF-15E)		4G bit	256M×16	DDR3	96ball																								T/A			T/A	T/A
	PE017(SUU256M16V90BG8LY-125TP)		4G bit	256M×16	DDR3	96ball																											N/A	
	PE039(SUU256M16V90BG8LY-125TP)		4G bit	256M×16	DDR3	96ball															T/A										T/A			
	PE029(PRN256M16V00HG8GNF-125)		4G bit	256M×16	DDR3	96ball														T/A					T/A	T/A								
	Z9QHG(SM128MX32U80MD1LGU-25FT)		4G bit	128M×32	LPDDR2	96ball																								T/A				T/A
	PB047(SS256M32V01MD1LPF-107BT)		8G bit	256M×32	LPDDR3	178ball																N/A	N/A	N/A	N/A	N/A								
	PB008(SM512M322E0FD4LHL)		16G bit	512M×32	LPDDR3	178ball																	T/A					T/A						
	PS006(SU256M32Z01MD1BNP)		8G bit	256M×32	LPDDR4	200ball																	N/A					N/A						
	PS007(SU512M32Z01MD2BNP)		16G bit	512M×32	LPDDR4	200ball																	T/A					T/A						
	(PS086)SU256M64Z00MD4DKN)		16G bit	256M×64	LPDDR4	366ball																	T/A					T/A						
	PS004(SM512M64Z91MD4BNK)		32G bit	512M×64	LPDDR4	366ball																	T/A					T/A						
	PS035(SU512M64Z01MD4BNK)		32G bit	512M×64	LPDDR4	366ball																	T/A					T/A						
	PS013(SM512M64Z01MD4BNK)		32G bit	512M×64	LPDDR4	366ball																	T/A					T/A						
	PU031(SM768M64Y4BMD4FZU-UT)		48G bit	768M×64	LPDDR5/LPDDR5X	496ball											T/A																	
	PU055(SM1G64Y42MD4FZV-UT)		64G bit	1G×64	LPDDR5/LPDDR5X	496ball											T/A																	
	PU032(SM1536M64Y4BMD8FCL-UT)		96G bit	1536M×64	LPDDR5/LPDDR5X	496ball											T/A																	
	PU054(SM2G64Y42MD8FCL-UT)		128G bit	2G×64	LPDDR5/LPDDR5X	496ball											T/A [10]																	

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK290x/RK2918	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
																												CPU_RAM	NPU_RAM					
elixir	N2CB2G16JR-FL		2G bit	128M×16	DDR3	96ball										T/A		T/A	T/A															
	N2CB4G16ER-FL		4G bit	256M×16	DDR3	96ball										T/A		T/A	T/A															
	N2AD4G16E4-JR		4G bit	256M×16	DDR4	96ball									S/A	T/A		T/A	T/A	T/A				T/A										
	N2AD8G16C4-JR		8G bit	512M×16	DDR4	96ball									N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
MIRA	P3R1GE4CFF-G8E		1G bit	64M×16	DDR2	84ball																										√		
	P3R1GE3FGF-G8E		1G bit	128M×8	DDR2	84ball																										√		
	P2P2GF4ALF-GGN		2G bit	128M×16	DDR3	96ball															T/A										T/A			
	P2P2GF4ALF-GJS		2G bit	128M×16	DDR3	96ball															T/A	T/A		T/A	T/A	T/A								
	P3P4GF3BLF-GGN		4G bit	512M×8	DDR3	78ball																								N/A			N/A	N/A
	P3P4GF4BLF-GGN		4G bit	256M×16	DDR3	96ball									N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	P3P4GF4BLF-GJS		4G bit	256M×16	DDR3	96ball									N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	P3P4GF4DMF-GJS		4G bit	256M×16	DDR3	96ball														T/A		T/A		T/A	T/A	T/A								
	P5M4GK4CMF-GMX		4G bit	256M×16	DDR4	96ball																					T/A		T/A					
Kingston	D1216ECMDXGJD		2G bit	128M×16	DDR3L	96ball														T/A					T/A	T/A								
	D5128EETBPGGBU		4G bit	512M×8	DDR3	78ball																								T/A			T/A	T/A [29]
	D2516EC4BXGGB	EOL	4G bit	256M×16	DDR3L	96ball															T/A [5]									T/A [5]	T/A [5]		T/A [5]	T/A [5][29]
	D2516ECMDXGJD		4G bit	256M×16	DDR3L	96ball				T/A					T/A					T/A	T/A	T/A		T/A	T/A	T/A	T/A			T/A	T/A			
	D2516JC4BXGJD		4G bit	256M×16	DDR3	96ball																								T/A				
	B5116ECMDXGJD		8G bit	512M×16	DDR3L	96ball																	T/A					T/A		T/A				
	D2516ACPCXGRK	EOL	4G bit	256M×16	DDR4	96ball										T/A		T/A	T/A	T/A					T/A	T/A								
	D2516AN9EXGXN		4G bit	256M×16	DDR4	96ball									S/A	T/A		T/A	T/A	T/A					T/A									
	D5116AH8CXGUM		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A	T/A		T/A		T/A										
	D5116AN9CXGXN		8G bit	512M×16	DDR4	96ball									N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	D2532LA3WLGJA		8G bit	256M×32	LPDDR3	178ball																					T/A		T/A		T/A			
	D2532LA6MLGJA		8G bit	256M×32	LPDDR3	178ball																T/A		T/A	T/A	T/A	T/A		T/A					
	D0811LN2ALGJA		8G bit	256M×32	LPDDR3	178ball														T/A										T/A				
	KB23AADL3E08G		8G bit	512M×16	LPDDR3	178ball																								T/A				
	C1612LN2ALGJA		8G bit	512M×16	LPDDR3	178ball																								T/A				
	D2516PC1CDGPLR	EOL	8G bit	256M×32	LPDDR4	200ball																	T/A				T/A							
	B1621PC6FDGUKR	EOL	16G bit	512M×32	LPDDR4	200ball										T/A [7]	N/A	T/A [7]	T/A [7]	S/A [15]					N/A										
	Q5116PH1MDGPAR	EOL	16G bit	512M×32	LPDDR4	200ball										N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	B5116PH3MDGPAR	EOL	16G bit	512M×32	LPDDR4	200ball									[26]	[26]		[26]	[26]	S/A [15]			T/A					T/A						
	B1621XH5ADGTKR	EOL	16G bit	512M×32	LPDDR4X	200ball									[26]	[26]		S/A [7][15]	S/A [7][15]	S/A [15]														
	B1621XH6BDGTAR	EOL	16G bit	512M×32	LPDDR4X	200ball									[26]	[26]		S/A [25]	S/A [25]															
	B1621XH7CDGUAR		16G bit	512M×32	LPDDR4X	200ball								T/A [26]	[26]	[26]	T/A [26]	[26]	[26]															
	B2421XC4FDGTKR	EOL	24G bit	768M×32	LPDDR4X	200ball										T/A		T/A	T/A	N/A					N/A									
	B3221XC5GDGTKR	EOL	32G bit	1024M×32	LPDDR4X	200ball										T/A [7]		T/A [7]	T/A [7]	N/A					N/A									
	Q3222XH6BDGUAR	EOL	32G bit	1024M×32	LPDDR4X	200ball								T/A [26]	[26]	[26]	T/A [26]	S/A [25]	S/A [25]															

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK290x/RK2918	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
																												CPU_RAM	NPU_RAM					
FORESEE	F60C1A0002-M6		2G bit	128M×16	DDR3L	96ball							T/A							T/A	T/A				T/A	T/A	T/A			T/A	T/A		T/A	
	F60C1A0004-M79R		4G bit	256M×16	DDR3L	96ball				T/A			T/A		T/A					T/A	T/A		T/A		T/A	T/A		T/A		T/A	T/A			
	F62C1A0004-M59R		4G bit	256M×16	DDR4	96ball										T/A		T/A	T/A	T/A														
	FD4V10004-22		4G bit	256M×16	DDR4	96ball																			T/A	T/A								
	FD45116ZSA062C		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A						T/A									
	MD4C10004-N93R		4G bit	256M×16	DDR4	96ball				T/A					T/A	T/A		T/A	T/A	T/A					T/A									
	MD4C1001G-N43R		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A	T/A					T/A	T/A								
	MD4C1002G-W43R		16G bit	1024M×16	DDR4	96ball				T/A					T/A	T/A		T/A	T/A	T/A					T/A									
	NCLD3B1128M32		4G bit	128M×32	LPDDR3	178ball																			T/A	T/A								
	NCLD3B2256M32		8G bit/ 2cs	256M×32	LPDDR3	178ball																	T/A					T/A		T/A				
	NCLD4C1MA256M32	EOL	8G bit	256M×32	LPDDR4	200ball																	T/A					T/A						
	NCLDXC1MG256M32		8G bit	256M×32	LPDDR4/LPDDR4X	200ball										N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A
	FL4C2001G-D9		8G bit	256M×32	LPDDR4	200ball														S/A [15]														
	FLXC2002G-N2		16G bit	512M×32	LPDDR4/LPDDR4X	200ball										T/A [11]		T/A [11]	T/A [11]	S/A [11][15]			N/A					N/A						
	FLXC2002G-26		16G bit	512M×32	LPDDR4/LPDDR4X	200ball										T/A [11]		T/A [11]	T/A [11]	S/A [11][15]					T/A									
	FLXC2002G-C4		16G bit	512M×32	LPDDR4X	200ball										T/A		T/A	T/A															
	NCLD4C2MA512M32	EOL	16G bit	512M×32	LPDDR4	200ball																	T/A					T/A						
	NCLDXC1MC512M32	EOL	16G bit	512M×32	LPDDR4/LPDDR4X	200ball																	T/A [11]					T/A [11]						
	NCLDXC1MJ512M32		16G bit	512M×32	LPDDR4/LPDDR4X	200ball										N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A
	FLXC1002G-N1		16G bit	512M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A				T/A [11]					T/A [11]						
	FLXC2002G-W6		16G bit	512M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A															
	FLXC2003G-49		24G bit	768M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A	N/A					N/A									
	FLXC4003G-W7		24G bit	768M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		N/A	T/A [26]	N/A	N/A															
	FLXC4004G-26		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball										N/A		N/A	N/A															
	FLXC2004G-N1		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
	FLXW2004G-P1		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
	FLXC4004G-W6		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		N/A	T/A [26]	N/A	N/A						T/A									
	FLXC4004G-61		32G bit	1024M×32	LPDDR4X	200ball								T/A	[26]	[26]	T/A	[26]	[26]															
	FLXC2004G-30		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								S/A [26]			S/A [26]																	
	FLXC4006G-20		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								T/A		N/A	T/A	N/A	N/A															
	FLXC4006G-63		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball											N/A																	
	FLXCE006G-61		48G bit	1536M×32	LPDDR4X	200ball								N/A	N/A	N/A	N/A	N/A	N/A	N/A			N/A		N/A				N/A					
	FLXC4006G-49		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
	FLXC8008G-61		64G bit	2048M×32	LPDDR4X	200ball								T/A		[26]	T/A	[26]	[26]															
	FLXC4008G-30		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
	FLXW4008G-P1		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A															
	FX5K2004G-60		32G bit	1024M×32	LPDDR5/LPDDR5X	245ball								T/A			T/A																	
	FX5K4008G-60		64G bit	2048M×32	LPDDR5/LPDDR5X	245ball								T/A			T/A																	
	FL5P4004G-N5		32G bit	1024M×32	LPDDR5	315ball											N/A																	
	FL5P2004G-60		32G bit	1024M×32	LPDDR5	315ball								T/A			T/A																	
	FX5P2004G-60		32G bit	1024M×32	LPDDR5X	315ball								T/A			T/A																	
	FL5P4006G-62		48G bit	1536M×32	LPDDR5	315ball								N/A																				
	FL5P4008G-60		64G bit	2048M×32	LPDDR5	315ball								S/A			S/A																	
	FX5P4008G-60		64G bit	2048M×32	LPDDR5X	315ball								T/A			T/A																	
	FX5S8016G-60		128G bit	2044M×64	LPDDR5X	496ball											T/A																	

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK290x RK2918	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
																													CPU_RAM	NPU_RAM					
BIWIN	BWPDD3X16A9B-04Gb		4G bit	256M×16	DDR3L	96ball												T/A	N/A		T/A					T/A									
	BWSD3X16N8B-04Gb		4G bit	256M×16	DDR3L	96ball														T/A															
	BWND3X16J8B-04Gb		4G bit	256M×16	DDR3L	96ball																				T/A									
	BWSDD4X16A9B-04Gb		4G bit	256M×16	DDR4	96ball												T/A	T/A	T/A					T/A										
	TDDR4004JA		4G bit	256M×16	DDR4	96ball					T/A	T/A				N/A		N/A	N/A																
	TDDR4008JA		8G bit	512M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A																
	BW52L256M32D1PF		8G bit	256M×32	LPDDR3	178ball																	T/A						T/A						
	BW52L512M32D2PF		16G bit	512M×32	LPDDR3	178ball																					T/A			T/A		T/A			
	BWMD4X32H2A-08Gb	EOL	8G bit	256M×32	LPDDR4	200ball																	N/A					N/A							
	BWMECX32H2A-08Gb	EOL	8G bit	256M×32	LPDDR4	200ball														S/A [15]			N/A					N/A							
	BWMD4X32H2A-16Gb	EOL	16G bit	512M×32	LPDDR4	200ball																	T/A					T/A							
	BWME9X32H2A-16Gb		16G bit	512M×32	LPDDR4	200ball													T/A				T/A					T/A							
	BWMEYX32H2A-16Gb		16G bit	512M×32	LPDDR4	200ball																	N/A					N/A							
	BWME9X32H2A-16Gb-X		16G bit	512M×32	LPDDR4X	200ball										T/A		T/A	T/A	S/A [15]															
	BWMZAX32H2A-16G-X		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		S/A	T/A [26]	S/A	S/A				T/A					T/A							
	BWMZEX32H2A-16G-X		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		T/A	T/A [26]	T/A	T/A				N/A					N/A							
	BWSR8X32H2A-16G-X		16G bit	512M×32	LPDDR4X	200ball								S/A [26]		T/A	S/A [26]	T/A	T/A																
	BWSRSX32H2A-16G-X		16G bit	512M×32	LPDDR4X	200ball										T/A		T/A	T/A																
	BWCC2X32N2A-16G-X		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A [26]	T/A	T/A	T/A [26]	T/A	T/A				N/A		N/A			N/A							
	BWCC1X32N2A-16G-X		16G bit	512M×32	LPDDR4/LPDDR4X	200ball									T/A	T/A		T/A	T/A																
	BWME4X32H2A-24Gb-X		24G bit	768M×32	LPDDR4X	200ball										T/A		T/A	T/A	N/A					N/A										
	BWMEXX32H2A-24Gb-X		24G bit	768M×32	LPDDR4X	200ball								S/A [26]		N/A	S/A [26]	N/A	N/A	N/A					N/A										
	BWMEIX32H2A-24G-X		24G bit	768M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A	N/A					N/A										
	BWCC4X32N2A-24G-X		24G bit	768M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A																
	BWSRGX32H2A-24G-X		24G bit	768M×32	LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	BWMEDX32H2A-32Gb-X		32G bit	1024M×32	LPDDR4X	200ball								T/A		T/A [7]	T/A	T/A [7]	T/A [7]	N/A					N/A										
	BWSR8X32H2A-32G-X	EOL	32G bit	1024M×32	LPDDR4X	200ball									N/A	N/A	T/A [26]	N/A	N/A	N/A			N/A		N/A			N/A							
	BWSRSX32H2A-32G-X		32G bit	1024M×32	LPDDR4X	200ball										T/A		T/A	T/A																
	BWMZAX32H2A-32Gb-X		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		T/A	T/A [26]	T/A	T/A																
	BWMZCX32H2A-32G-X		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		T/A	T/A [26]	T/A	T/A	N/A					N/A										
	BWCC2X32N2A-32G-X		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A	T/A	T/A	T/A	T/A	T/A																
	BWCGBX32N2A-32G-X		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A	S/A	T/A	T/A	T/A	T/A																
	BWMEIX32H2A-48G-X		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	BWMEXX32H2A-48Gb-X		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball										N/A		N/A	N/A																
	BWMZCX32H2A-64G-X		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A		S/A	T/A [26]	S/A	S/A																
	BWMEDX32H2A-64Gb-X		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A		N/A	T/A	N/A	N/A																
	BWCGBX32N2A-64G-X		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	BWMYAX32U9A-32G		32G bit	1024M×32	LPDDR5/LPDDR5X	245ball								T/A			T/A [24]																		
	BWMYAX32U9A-64G		64G bit	2048M×32	LPDDR5/LPDDR5X	245ball											T/A [24]																		
	BWMZGX32P8A-24G		24G bit	768M×32	LPDDR5	315ball											N/A																		
	BWSR9X98P8A-24Gb		24G bit	768M×32	LPDDR5	315ball											N/A																		
	BWMZJX32P8A-32G		32G bit	1024M×32	LPDDR5	315ball											N/A																		
	BWMYAX32P8A-32G		32G bit	1024M×32	LPDDR5	315ball								S/A [22]			S/A [22]																		
	BWMZGX32P8A-48G		48G bit	1536M×32	LPDDR5	315ball								T/A			T/A																		
	BWMEJX32P8A-48G		48G bit	1536M×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																		
	BWMYAX32P8A-64G		64G bit	2048M×32	LPDDR5/LPDDR5X	315ball								S/A [22]			S/A [22]																		
	BWMZJX32P8A-64G		64G bit	2048M×32	LPDDR5	315ball								T/A			S/A [25]																		
	BWMYAX32P8A-128G		128G bit	4G×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																		
	BWMYAX64F9B-128G		128G bit	2G×64	LPDDR5/LPDDR5X	496ball											T/A																		

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126B	RV1126B-P	RK3506/RK2118	RK3576	RK3528	RK3562	RK3588/RK3588S	RK3568	RK3566	RV1126/RV1109	RV1108/RK3308/RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/PX30S	RK3326/PX30	RK1808/RK1806	RK3399PRO CPU_RAM	RK3399PRO NPU_RAM	RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK290x/RK2918	RK2926/RK3026/RK3036/RK3036G/RK3126	RK3066/RK3066A/PX2/RK3168/RK3188/PX3
RAYSON	RS128M16VRDK-93BT	EOL	2G bit	128M×16	DDR3	96ball										T/A		T/A	T/A						T/A	T/A									
	RS128M16VRDB-107AT		2G bit	128M×16	DDR3	96ball							T/A			T/A		T/A	T/A		T/A														
	RS256M16V0DB-107AT		4G bit	256M×16	DDR3	96ball							T/A			T/A		T/A	T/A		T/A				T/A										
	RS256M16VRDK-93BT	EOL	4G bit	256M×16	DDR3	96ball										T/A		T/A	T/A																
	RS256M16VNDG-107AT		4G bit	256M×16	DDR3L	96ball																								T/A					
	RS256M16ZADD-75DT		4G bit	256M×16	DDR4	96ball													T/A																
	RS256M16Z0DC-75DT	EOL	4G bit	256M×16	DDR4	96ball													T/A	T/A					T/A										
	RS512M16Z2DD-62DT		8G bit	512M×16	DDR4	96ball				T/A					T/A	T/A		T/A	T/A						T/A										
	RS1G16Z3DK-75DT		16G bit	1024M×16	DDR4	96ball									N/A	T/A		T/A	T/A																
	RS1G16Z3DK-62DT		16G bit	1024M×16	DDR4	96ball										T/A		T/A	T/A																
	RS1G16Z4DD-62DT		16G bit	1024M×16	DDR4	96ball										T/A		T/A	T/A																
	RS128M32LD3D1LMZ-125BT	EOL	4G bit	128M×32	LPDDR3	178ball														T/A					T/A	T/A									
	RS256M32LD3D1LMZ-125BT		8G bit	256M×32	LPDDR3	178ball														T/A															
	RS512M32LD3D2LMZ-125BT		16G bit	512M×32	LPDDR3	178ball				T/A					T/A																				
	RS128M32LZ4D1ANP-75BT		4G bit	128M×32	LPDDR4/LPDDR4X	200ball					T/A				T/A					S/A [15]															
	RS256M32LZ4D1ANP-75BT	EOL	8G bit	256M×32	LPDDR4	200ball										N/A		N/A	N/A	S/A [15]			T/A					T/A							
	RS256M32LZ4D2BNP-62BT		8G bit	256M×32	LPDDR4/LPDDR4X	200ball										N/A		N/A	N/A						T/A										
	RS256M32LS4D1BNR-46BT		8G bit	256M×32	LPDDR4	200ball												T/A	T/A						T/A										
	RS256M32LS4D4BNR-53BT		8G bit	256M×32	LPDDR4X	200ball										T/A		T/A	T/A																
	RS512M32LZ4D2ANP-75BT	EOL	16G bit	512M×32	LPDDR4	200ball														S/A [15]			T/A					T/A							
	RS512M32LM4D2BDS-53BT		16G bit	512M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A				N/A					N/A							
	RS512M32LO4D1BDS-53BT		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A [26]	T/A	T/A	T/A [24]	T/A	T/A	S/A [11][15]			N/A		T/A			N/A							
	RS512M32LO4D1BDS-46BT		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																		
	RS512M32LX4D2BNR-53BT		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A [26]	T/A	T/A	T/A [24]	T/A	T/A																
	RS768M32LB4D2BDS-53BT		24G bit	768M×32	LPDDR4/LPDDR4X	200ball										T/A		T/A	T/A	N/A					N/A										
	RS768M32LP4D2BDS-53BT		24G bit	768M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		N/A	T/A [24]	N/A	N/A	N/A					N/A										
	RS1G32LF4D2BDS-53BT	EOL	32G bit	1024M×32	LPDDR4/LPDDR4X	200ball										T/A [11]	N/A	T/A [11]	T/A [11]	N/A					N/A										
	RS1G32LO4D2BDS-53BT		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		T/A	T/A [26]	T/A	T/A																
	RS1G32LO4D2BDS-46BT		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																		
	RS1G32LX4D4BNR-53BT		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		T/A	T/A [26]	T/A	T/A						T/A										
	RS1G32LR4D2BNR-46BT		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A					T/A		T/A	T/A	T/A	T/A																
	RS1G32LV4D2BDS-46BT		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																		
	RS1536M32LB4D4BDT-53BT		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		N/A	T/A [26]	N/A	N/A																
	RS2G32LV4D4BDT-53BT		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		T/A	T/A [26]	T/A	T/A																
	RS2G32LV4D4BDT-46BT		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																		
	RS2G32LF4D4BDT-53BT	EOL	64G bit	2048M×32	LPDDR4/LPDDR4X	200ball										T/A	N/A	T/A	T/A																
	RS2G32LX4D8BNR-53BT		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A [26]		T/A	T/A [24]	T/A	T/A																
	RS2G32LR4D4BNR-46BT		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																		
	RS4G32LV4D8BDT-53BT		128G bit	4G×32	LPDDR4/LPDDR4X	200ball								T/A [26]			T/A [24]																		
	RS1G32LP5D2FZB-23BT		32G bit	1024M×32	LPDDR5X	245ball								T/A			T/A																		
	RS1G32LO5D2FDB-31BT		32G bit	1024M×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																		
	RS1536M32LG5D4FDB-31BT		48G bit	1536M×32	LPDDR5/LPDDR5X	315ball								N/A			N/A																		
	RS2G32LO5D4FDB-31BT		64G bit	2G×32	LPDDR5/LPDDR5X	315ball								S/A [23]			S/A [23]																		
	RS3G32LG5D8FDB-31BT		96G bit	3G×32	LPDDR5/LPDDR5X	315ball								T/A			S/A [25]																		
	RS4G32LO5D8FDB-31BT		128G bit	4G×32	LPDDR5/LPDDR5X	315ball								S/A			S/A [25]																		
SCY	DP3B04G16BBB		4G bit	256M×16	DDR3	96ball					S/A									N/A					N/A	N/A				N/A					
	SD4D8G6-FC		8G bit	512M×16	DDR4	96ball													S/A																
	DP4D04G16FJB		4G bit	256M×16	DDR4	96ball													S/A					S/A										
	DP4D04G16HMB		4G bit	256M×16	DDR4	96ball					S/A																								
	DP4D08G16FJB		8G bit	512M×16	DDR4	96ball													S/A																
	DL4B08G32X2V-DC		8G bit	512M×32	LPDDR4	200ball										S/A [15]		S/A [15]	S/A [15]																
	D4A16G32D2V-DC	EOL	16G bit	512M×32	LPDDR4/LPDDR4X	200ball														S/A [11][15]															
	DL4A16G32K1V-DC	EOL	16G bit	512M×32	LPDDR4/LPDDR4X	200ball										S/A		S/A	S/A				N/A					N/A							
	DL4A16G32T2V-EC		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								S/A [26]	S/A	S/A	S/A [24]	S/A	S/A																
	DL4A24G32A2V-EC		24G bit	768M×32	LPDDR4/LPDDR4X	200ball								S/A			S/A																		
	DL4A24G32P4V-EC		24G bit	768M×32	LPDDR4/LPDDR4X	200ball										S/A		S/A	S/A																
	DL4A32G32N2V-EC		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball										S/A		S/A	S/A	N/A					N/A										
	DL4A32G32T4V-EC		32G bit	1024M×32	LPDDR4X	200ball								S/A [26]		S/A	S/A [26]	S/A	S/A																
	DL4A32G32S2V-EC		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball										S/A		S/A	S/A																
	DL4A32G32H4V-EC		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								S/A			S/A																		
	DL4A48G32E4V-DC		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								S/A		N/A	S/A	N/A	N/A																
	DL4A48G32A4V-EC		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball								S/A		S/A	S/A	S/A	S/A																
	DL4A64G32N4V-EC		64G bit	2G×32	LPDDR4/LPDDR4X	200ball								S/A		S/A	S/A	S/A	S/A																
	DL4A64G32S4V-EC		64G bit	2G×32	LPDDR4/LPDDR4X	200ball										S/A		S/A	S/A																
	SL5D24G32B2A-GC0		24G bit	768M×32	LPDDR5X	315ball								S/A			S/A																		
	SL5D32G32A2A-GC0		32G bit	1024M×32	LPDDR5	315ball											S/A																		
	SL5D32G32C2A-GC0		32G bit	1024M×32	LPDDR5X	315ball								S/A																					
	SL5D48G32B4A-GC0		48G bit	1536M×32	LPDDR5X	315ball								S/A			S/A																		
	SL5D64G32C4A-GC0		64G bit	2G×32	LPDDR5X	315ball								S/A			S/A																		
Hosin	HG-DR30232-62001		4G bit	256M×16	DDR3L	96ball																	S/A					S/A		S/A				
	HG512M32D2PDA1-H2		16G bit	512M×32	LPDDR4X	200ball									[26]	[26]		S/A [25]	S/A [25]	[26]															
	HG4XB02G-C2JA		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								S/A [26]		S/A	S/A [24]	S/A	S/A				N/A		N/A			N/A							
	HG768M32D4LQM1-H1		24G bit	768M×32	LPDDR4	200ball									[26]	N/A		N/A	N/A	N/A															
	HG4XD03G-C4JA		24G bit	768M×32	LPDDR4/LPDDR4X	200ball								S/A			S/A																		
	HG4XD04G-C2JA		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								S/A		S/A	S/A	S/A	S/A																
	HG4XB04G-C7JA-A		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								S/A			S/A																		
	HG4XD08G-C8JA		64G bit	2G×32	LPDDR4/LPDDR4X	200ball								S/A			S/A																		
Dosilicon	FM38E16SAB-9MGD		2G bit	128M×16	DDR3L	96ball														S/A					S/A	S/A								
	FM38F16SBB-9MGD		4G bit	256M×16	DDR3L	96ball																			S/A	S/A				S/A				

Industrial&Wide Temperature

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1106B	RV1106	RK3572	RK3538	RV1126BJ	RV1126B-P	RK3506J	RK3576J	RK3528	RK3562J	RK3588J	RK3568J	RK3566	RV1126K	RV1108K1 RK3308J	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3358J	RK1808K	RK3399PRO CPU_RAM	RK3399PRO NPU_RAM	RK3288	RK3368/RK3228A/RK3228B/RK3229 /PX5	RK290x RK2918	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3
Micron	MT41K128M16JT-107 IT:K(D9RQN)		2G bit	128M×16	DDR3L	96ball																				T/A									
	MT41K256M16TW-107 IT:P(D9SHG)		4G bit	256M×16	DDR3L	96ball					T/A	T/A											T/A					T/A								
	MT41K512M16VRP-107 IT:P(D9ZWN)		8G bit	512M×16	DDR3L	96ball										T/A		T/A	T/A											T/A					
	MT40A512M16TB-062E IT:R(D8BVB)		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A																
	MT40A1G16TD-062E AIT:F (D8CHH)		16G bit	1024M×16	DDR4	96ball										T/A		T/A	T/A																
	MT40A1G16TB-062E IT:F (D8CJZ)		16G bit	1024M×16	DDR4	96ball					T/A					T/A		T/A	T/A																
	MT53E256M32D1KS-046 IT:L (D8FCZ)		8G bit	256M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	MT53E384M32D2FW-046 IT:E (D8BXT)		12G bit	384M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	MT53E512M32D1ZW-046 BIT:B (D8FLQ)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	MT53E1G32D2FW-046 IT:C (D8DVP)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	MT62F1G32D2DS-023 IT:C（D8DGX）		32G bit	1024M×32	LPDDR5/LPDDR5X	315ball								T/A			T/A																		
	MT62F2G32D4DS-023 IT:C (D8DMN)		64G bit	2G×32	LPDDR5/LPDDR5X	315ball								T/A																					
Samsung	K4B4G1646E-BMMA		4G bit	256M×16	DDR3L	96ball																	T/A			T/A		T/A							
	K4A4G165WG-BIWE		4G bit	256M×16	DDR4	96ball					T/A																								
	K4A8G165WG-BIWE		8G bit	512M×16	DDR4	96ball					T/A																								
	K4AAG165WC-BIWE		16G bit	512M×32	DDR4	96ball					T/A					T/A		T/A	T/A																
	K4F6E3S4HM-TF**		16G bit	512M×32	LPDDR4	200ball														S/A [15]															
Nanya	NT5CC256M16ER-EKI		4G bit	256M×16	DDR3L	96ball					T/A	T/A											T/A					T/A								
	NT5AD256M16E4-JRI		4G bit	256M×16	DDR4	96ball					T/A					T/A		T/A	T/A																
	NT5AD512M16C4-JRI		8G bit	512M×16	DDR4	96ball									N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A						
	NT5AD512M16H4-JRI		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A																
	NT6AN512T32AV-J1I		16G bit	512M×32	LPDDR4	200ball									N/A	N/A	N/A	N/A	N/A	N/A			N/A		N/A			N/A							
CXMT	CXDQ3BFAM-IJ-A		8G bit	512M×16	DDR4	96ball									N/A	S/A [22]		S/A [22]	S/A [22]	N/A		N/A		N/A	N/A	S/A [22]	N/A		N/A						
JHICC	CA4S8G16V-F9JSI		8G bit	512M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A																
GigaDevice	GDP1BFLA-WB		2G bit	128M×16	DDR3L	96ball										T/A		T/A	T/A																
	GDP2BFLM-WB		4G bit	256M×16	DDR3L	96ball										T/A		T/A	T/A																
	GDQ2BFAA-WJ		4G bit	256M×16	DDR4	96ball										S/A [20]		S/A [20]	S/A [20]																
	GDQ3BFAM-WJ		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A																
UniIC	SCB13H8G162BF-13KI		8G bit	512M×16	DDR3L	96ball																	T/A					T/A							
	SCB12Q8G160BF-06SI		8G bit	512M×16	DDR4	96ball										N/A		N/A	N/A																
winbond	W632GU6NB-11K		2G bit	128M×16	DDR3L	96ball																				N/A									
	W634GU6NB-11K		4G bit	256M×16	DDR3L	96ball																				N/A									
ISSI	IS46DR16320E-25DBLA2		512M bit	32M×16	DDR2	84ball															T/A														
	IS43TR16128DL-125KBLI		2G bit	128M×16	DDR3L	96ball															T/A														
	IS43TR16128DL-107MBLI		2G bit	128M×16	DDR3L	96ball										T/A		T/A	T/A																
	IS43TR16256BL-107MBLI		4G bit	256M×16	DDR3L	96ball										T/A		T/A	T/A																
	IS43TR16512BL-107MBLI		8G bit	512M×16	DDR3L	96ball										T/A		T/A	T/A																
	IS43QR16256B-083RBLI		4G bit	256M×16	DDR4	96ball									N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A						
	IS46QR16512A-075VBLA2		8G bit	512M×16	DDR4	96ball										N/A		N/A	N/A																
	IS43QR16512A-083TBLI		8G bit	512M×16	DDR4	96ball																					N/A								
	IS43LD16128C-18BLI		2Gb bit	128M×16	LPDDR2	134ball															T/A														
	IS43LQ32256A-062BLI		8G bit	256M×32	LPDDR4/LPDDR4X	200ball												S/A [24]	S/A [24]																
	IS43LQ32256B-0**BL**		8G bit	256M×32	LPDDR4/LPDDR4X	200ball								N/A	N/A	N/A	N/A	N/A	N/A	N/A			N/A		N/A			N/A						
	IS43LQ32512A-046BLI		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A [11]	T/A	T/A [11]	T/A [11]																
Zentel	A3R12E40DBF-8EA		512M bit	32M×16	DDR2	84ball															T/A														
	A3T2GF40CBF-HPI		2G bit	128M×16	DDR3	96ball							N/A																						
BIWIN	TGDR4004JA		4G bit	256M×16	DDR4	96ball					T/A	T/A				T/A		T/A	T/A																
	TGDR4008JA		8G bit	512M×16	DDR4	96ball										T/A		T/A	T/A																
	BWMZAX32H2A-16GI-X		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	BWMZCX32H2A-32GI-X		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A		N/A	T/A	N/A	N/A																
	BWMZCX32H2A-64GI-X		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																		
FORESEE	F60C1A0004-M79W		4G bit	256M×16	DDR3L	96ball										T/A		T/A	T/A																
Artmem	ATL4X2G32M1D-46 IT		16G bit	512M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																		
	ATL4X4G32M1D-46 IT		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball								T/A		T/A	T/A	T/A	T/A																
	ATL4X8G32M2D-46 IT		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball								T/A			T/A																		
	ATL5X4G32M7E-31IT		32G bit	1024M×32	LPDDR5/LPDDR5X	315ball											T/A																		
	ATL5X8G32M7E-31IT		64G bit	2048M×32	LPDDR5/LPDDR5X	315ball								T/A																					

Automotive

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RV1126B	RK2118M	RK3576M	RK3588M	RK3568M	RK3308M	RK3358M
Micron	MT53E256M32D1KS-046 AAT:L (D8FDP)		8G bit	256M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	MT53E512M32D1ZW-046 AAT:B (D8CSG)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A		
	MT53E768M32D2ZW-046 AIT:C（D8DTX）		24G bit	768M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	MT53E1G32D2FW-046 AAT:B (D8CJB)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A		
	MT53E1536M32D4DE-046 AIT:C (D8DCZ)		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A		
	MT53E2G32D4DE-046 AAT:C（D8CJK)		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A		
	MT53E2G32D4DE-046 AAT:A (D9ZRB)		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	MT53E4G32D8GS-046 AIT:C (D8DHH)		128G bit	4G×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	MT53E1G32D2FW-046 AIT:C (D8DWK)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	MT62F1G32D2DS-020 AIT:F(D8GQF)		32G bit	1024M×32	LPDDR5/LPDDR5X	315ball				T/A			
	MT62F512M32D1DS-020 AIT:E(D8HNR)		16G bit	512M×32	LPDDR5/LPDDR5X	315ball			T/A	T/A			
	MT62F2G32D4DS-020 AIT:F (D8GQD)		64G bit	2048M×32	LPDDR5/LPDDR5X	315ball				T/A			
	MT62F4G32D8DV-020 AIT:F (D8GQV)		128G bit	4G×32	LPDDR5/LPDDR5X	315ball			T/A	T/A			
Samsung	K4F8E3S4HD-GF**		8G bit	256M×32	LPDDR4	200ball			T/A	T/A	T/A		
	K4F6E3S4HB-KH**		16G bit	512M×32	LPDDR4	200ball			T/A	T/A			
	K4FHE3S4HA-KH**		24G bit	768M×32	LPDDR4	200ball					N/A		
	K4FBE3D4HB-KH**		32G bit	1024M×32	LPDDR4	200ball			T/A	T/A	T/A		
	K4U6E3S4AB-KH**		16G bit	512M×32	LPDDR4X	200ball			T/A	T/A			
	K4UJE3Q4AA-T***		48G bit	1536M×32	LPDDR4X	200ball				N/A	N/A		
	K4UCE3Q4AB-KH**		64G bit	2048M×32	LPDDR4X	200ball				N/A	T/A		
	K3KL9L90QM-MH**		64G bit	2048M×32	LPDDR5X	315ball				T/A			
Hynix	H54G66BYYVX104		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	H54G46BYYQX085N		16G bit	512M×32	LPDDR4X	200ball			T/A	T/A			
	H54G56BYYQX089N		32G bit	1024M×32	LPDDR4X	200ball			T/A	T/A			
	H54G56BYYQX089		32G bit	1024M×32	LPDDR4X	200ball			T/A	T/A			
Nanya	NT5CC64M16GP-EKH		1G bit	64M×16	DDR3L	96ball							T/A
	NT5CC256M16ER-EKA		4G bit	256M×16	DDR3L	96ball							T/A
	NT6AN512T32AC-J2J		16G bit	512M×32	LPDDR4	200ball					N/A		
	NT6AN512T32AC-J1H		16G bit	512M×32	LPDDR4	200ball				N/A	N/A		
CXMT	CXDB4CBAM-EA-M		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A		
	CXDB4CBAM-EA-A		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	CXDB5CBM-EA-M		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball					N/A		
	CXDB5CCBM-EA-A		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	CXDB5CBAM-EA-B		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A		
	CXDBCCCDM-EA-M		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	CXDB6CCDM-EA-M		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	CXDB6CCBM-EA-A		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A		
ISSI	IS46TR16640CL-107MBLA2		1G bit	64M×16	DDR3L	96ball		T/A					
	IS46TR16128DL-125KBLA1		2G bit	128M×16	DDR3L	96ball							T/A
	IS46LQ32256B-053BLA1		8G bit	256M×32	LPDDR4	200ball				N/A			
UNIC	SCE11N4G320AF-06YA3		4G bit	128M×32	LPDDR4	200ball				N/A	N/A	N/A	N/A
	SCE11N4G320AH-06YA2		4G bit	128M×32	LPDDR4	200ball	T/A						
	SCE11N8G322AF-062YA2		8G bit	256M×32	LPDDR4	200ball				N/A	N/A	N/A	
	SCE11R8G322AF-062YA2		8G bit	256M×32	LPDDR4X	200ball				N/A	N/A	N/A	
	SCB11U32322EF-04ZIA2		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
Foresee	FLXCE004G-61		32G bit	1024M×32	LPDDR4X	200ball			T/A	T/A			
BIWIN	BWLGYA004GN6ZC		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	BWLGYA006GN6E1		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	BWLGYB008GN6ZC		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
Artmem	ATL4X4G32M1D-46 AIT		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	ATL4X6G32M2D-46 AAT		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			
	ATL4X8G32M2D-46 AAT		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A			

Conducted by the Manufacturer

NOTICE

1. This part was tested and validated only by the DRAM manufacturer,not by Rockchip.
2. If you encounter any DRAM issues during product usage, please contact the DRAM manufacturer for assistance
3. **Rockchip strongly advises conducting a comprehensive Production Verification Test (PVT) prior to mass production to ensure product conformance and reliability.**
4. The manufacturer conducted the tests in accordance with the test data and methods provided by RK and the results were reviewed by RK.

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package				RK3538	RV1126B	RV1126B-P	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3
																												CPU_RAM	NPU_RAM					