Technical, Empirical, and Procurement Audit of the KAVACH Automatic Train Protection System

1. Technical Architecture and RDSO Specifications

The indigenous Indian Railways Automatic Train Protection (IRATP) system—formally designated as KAVACH and engineered during its developmental phase between 2011 and 2020 as the Train Collision Avoidance System (TCAS)—is a continuous, closed-loop, cab-signaling and speed-supervision architecture. Originally deployed under Research Designs and Standards Organisation (RDSO) specification RDSO/SPN/196/2012 Version 3.2, the system transitioned to a mainline national standard under RDSO/SPN/196/2020 Version 4.0. While the base Functional Requirements Specification (FRS) for Version 4.0 was issued on April 11, 2022 and the System Requirement Specification (SRS) was updated on June 7, 2024, the finalized operational baseline—incorporating critical revisions to mode transitions, configurable station parameters, and network telemetry—received formal RDSO approval on July 16, 2024. Unlike legacy Auxiliary Warning Systems (AWS) that rely on intermittent magnetic track inductors to trigger simple binary alerters, Kavach operates by synthesizing absolute spatial localization from trackside Radio Frequency Identification (RFID) tags with continuous dynamic state updates broadcast from interlocking-linked stationary computers over a dedicated time-slotted radio network.

Trackside Subsystem: Mechanical, Interlocking, and Radio Layers

The physical foundation of Kavach's spatial awareness rests on passive RFID tags clamped directly onto Pre-Stressed Concrete (PSC) track sleepers along the centerline of the broad-gauge (1,676\text{ mm}) alignment. Enclosed in weatherproof IP67-rated polymeric housings certified to withstand a 5\text{-tonne} mechanical impact load, these tags require zero external wiring or battery power; they are energized inductively by the electromagnetic field emitted by the locomotive's under-chassis reader antenna even at speeds up to 160–200\text{ km/h}. Each tag is programmed with a stationary data payload containing a unique Tag Identification Number (TIN), absolute location coordinates (kilometrage), Track Identification Number (Track ID), directional linkage vectors, and relative distances to the next signal or point turnout.

Under RDSO/SPN/196/2020 and Annexure-H (KAVACH RFID Tag-TIN Layout Guidelines Amdt-5), tags are deployed in a strict topological cadence across the track bed. Normal tags are installed along block sections and station yards at a maximum spacing of 1,000\text{ meters} (1\text{ km}), with each Normal tag logically linked in the onboard database to the next two consecutive Normal tags in both the nominal and reverse directions to preserve directional continuity and tolerate single-tag damage. Signal Approach tags are placed 150\text{ m} to 250\text{ m} in rear of approaching signals and at turnouts to prepare the onboard computer for aspect verification or turnout speed supervision, while Signal Foot tags are positioned directly at the foot of every main signal so that any locomotive traversing the tag without a valid Movement

Authority (MA) from the stationary unit instantaneously transitions into Trip (TR) mode and vents the emergency brake pipe. Furthermore, Level Crossing (LC) Gate tags are positioned 600\text{ m} to 850\text{ m} on both approaches to interlocked or non-interlocked LC gates to trigger automatic locomotive horn whistling and enforce gate-open braking curves. Adjustment and Junction tags are placed at junction stations and specific block boundaries to recalibrate the onboard odometer's absolute kilometrage and correct cumulative wheel-slip drift without altering the nominal or reverse direction state, while Exit tags are installed at the boundary of a Kavach-equipped territory to command an orderly transition out of Full Supervision (FS) mode.
While RFID tags provide static ground coordinates, dynamic signaling intelligence is governed by the Stationary Station Kavach (STN-KAVACH) unit. Engineered on a fault-tolerant 2 \times 2\text{oo}2 (two-times-two-out-of-two) voting architecture, STN-KAVACH utilizes dual CPU modules, each housing two diversified microcontrollers running independent cross-checked software threads. The unit scales up to 1,024 vital inputs across isolated 32-channel Track Input (TIN) cards with double-cutting provisions, alongside isolated GTO vital output modules driving 16 outputs per card. STN-KAVACH interfaces with the station's existing interlocking layer—whether Panel Interlocking (PI), Route Relay Interlocking (RRI), or solid-state Electronic Interlocking (EI)—to continuously sample signal aspects, point lock detection relays (NWKR/RWKR), and track circuit or axle counter occupancy states.
At the station control desk, the system interfaces with the Station Master Operation-Cum-Indication Panel (SM-OCIP / GTSM-OCIP). This console incorporates a physical security interlock (SM-KEY), ensuring that manual Emergency SOS broadcasts or SOS cancellations cannot be actuated when the key is in the OUT position, alongside an audible buzzer and an LCD terminal displaying GPS synchronization, GSM health, and radio modem diagnostics. For sprawling yards, end cabins, mid-section interlocked LC gates, and Intermediate Block Signaling (IBS) huts located within the main station's radio footprint, Remote Interface Units (RIU)—built on a 2\text{oo}2 architecture supporting up to 256 vital inputs—fetch remote signaling states back to STN-KAVACH over a 6-direction bidirectional Ethernet-Optical Fibre Cable (OFC) ring switch. Where an IBS or interlocked LC gate lies outside the station tower's RF coverage, a standalone Stationary Kavach unit is commissioned. Every STN-KAVACH node also links via a dedicated E1 and Ethernet OFC interface to the centralized Network Monitoring System (NMS) and the Temporary Speed Restriction Management Server (TSRMS).
The radio infrastructure bridges the trackside and onboard domains. Along the right-of-way, 40\text{-meter} lattice telecom mast towers are erected every 2\text{ to }3\text{ km} at every station and mid-block site as required by terrain line-of-sight, connected to STN-KAVACH via an optical-fibre GTRI interface module to eliminate coaxial feeder attenuation. While legacy railway voice communications utilized VHF (160\text{ MHz}), Kavach operates on duplex Ultra-High Frequency (UHF) radio modems within the 406–470\text{ MHz} spectrum, utilizing a 25\text{ kHz} channel bandwidth and dual Tx/Rx Multiple-Input Multiple-Output (MIMO) antennas. Channel access is governed by a hybrid of Frequency Division Multiple Access (FDMA) and dynamic Time Division Multiple Access (TDMA). Within a station zone, STN-KAVACH and approaching locomotives communicate over a station-specific frequency pair; stationary units occupy fixed TDMA time slots sized to yard complexity, while mobile locomotives are allocated time slots dynamically as they enter the cell. Simultaneously, direct Loco-to-Loco peer telemetry—vital for preventing head-on and rear-end collisions in mid-block sections and propagating emergency SOS alerts—is broadcast by every locomotive on a dedicated, nationwide fixed frequency (f_0) during its GPS-synchronized time slot. Under Kavach 4.0, onboard and stationary units incorporate Long Term Evolution for Railways (LTE-R) modules

targeting the 700\text{ MHz} 4G/5G spectrum. Currently, LTE-R is utilized for cryptographic Authenticated Key Exchange between LOCO-KAVACH and the TSRMS server, while providing the high-bandwidth packet backbone required to migrate full signaling telemetry in dense suburban and multi-track corridors leading into Kavach 5.0, which is envisaged for Vande Bharat 4.0 trainsets.

Onboard Locomotive Subsystem (LOCO-KAVACH)

The onboard architecture (LOCO-KAVACH / LTCAS) is engineered to survive the harsh vibrational, thermal (-20^\circ\text{C} to +70^\circ\text{C}), and electromagnetic transients of 25\text{ kV} AC electric and diesel traction. Powered by the locomotive's 110\text{ V DC} nominal battery bank with wide-input voltage regulation from 88\text{ V} to 143\text{ V DC}, it integrates four tightly coupled assemblies into a continuous control loop. At the core of the locomotive cabinet sits the Dual Vital Computer Unit, operating on a 2 \times 2\text{oo}2 fail-safe hardware architecture with hot-swappable modules, onboard FPGAs, MIL-grade locking connectors, and 32 cab inputs with double-cutting provisions. A dedicated counter module (GTCC) maintains six non-resettable 6-digit hardware counters that permanently log every Brake Interface Unit (BIU) isolation, SOS actuation, and Trip (TR) intervention for post-incident forensic audits, while the chassis also includes hardware provisions for a Eurobalise reader to allow interoperability within European Train Control System (ETCS) territories.

Spatial localization on the move is handled by the odometry and location sensing array, wherein an under-chassis passive RFID Reader antenna continuously scans sleeper tags and streams decoded TIN payloads to the Vital Computer over a redundant serial bus. Between tags spaced up to 1,000\text{ m} apart, continuous displacement and velocity are computed by axle-mounted wheel-pulse tachometers (rotary encoders) fused with multi-beam Doppler radar or optical speed sensors to detect and compensate for wheel slip during traction and wheel slide during heavy braking.

Physical brake enforcement is executed by the Brake Interface Unit (BIU), an electro-pneumatic valve manifold integrated directly into the locomotive's air-brake piping. The BIU continuously monitors brake cylinder and Brake Pipe (BP) pressures and arbitrates between manual demands from the Loco Pilot's Automatic Brake Valve and electronic demands from the Vital Computer, strictly prioritizing the higher brake demand. When an overspeed or Signal Passed at Danger (SPAD) hazard is detected, the BIU de-energizes fail-safe solenoid valves to vent the Brake Pipe, executing either a modulated Service Brake (SB) or an un-overridable Emergency Brake (EB) application. Inside both leading and trailing driving cabs, the Driver Machine Interface (DMI)—a ruggedized Linux-based display panel compliant with CENELEC EN 50155 operating on 72\text{ V} to 110\text{ V DC}—provides the Loco Pilot with real-time cab signaling, including live reproduction of the approaching wayside signal aspect, exact target distance in meters to the next restriction or Red signal, Movement Authority (MA), permitted versus actual speed gauges, and audible buzzer and voice warnings.

SIL-4 Certification and CENELEC Standards

Kavach is certified to Safety Integrity Level 4 (SIL-4)—the most stringent safety tier in global industrial and railway electronics—verified by accredited Independent Safety Assessors (ISA) such as Italcertifer of Italy. Statistically, SIL-4 mandates that the Tolerable Hazard Rate (THR) or Probability of a Dangerous Failure per Hour (PFH_d) must satisfy:

$$10^{-9}\text{ hr}^{-1} \le PFH_d < 10^{-8}\text{ hr}^{-1}$$

At the 10^{-9}\text{ hr}^{-1} threshold, the probability of the system suffering an undetected dangerous failure—such as failing to command brakes when a Red aspect is transmitted, or corrupting a restrictive speed limit into a permissive one—is less than one occurrence per billion operating hours, equivalent to approximately 114,155\text{ years} of continuous operation. Achieving this mathematical guarantee requires strict compliance across four CENELEC European Norms alongside electromagnetic compatibility standards EN 61000 and EN 55016. Specifically, CENELEC EN 50126 (1999) defines the specification and demonstration of Reliability, Availability, Maintainability, and Safety (RAMS), governing hazard logs, Fault Tree Analysis (FTA), and Failure Mode, Effects, and Criticality Analysis (FMECA) across the entire system lifecycle. Software integrity is governed by CENELEC EN 50128 (2011), which for SIL-4 prohibits dynamic memory allocation and unverified interrupts, mandating formal mathematical methods, defensive programming, static code analysis, and strict organizational independence between the software designer, verifier, and validator. Hardware safety is enforced under CENELEC EN 50129 (2003), which mandates architectural fault tolerance realized in Kavach via the 2 \times 2\text{oo}2 dual-redundant voting matrix, where two independent microcontroller channels continuously cross-compare instruction cycles; any discrepancy between Channel A and Channel B immediately cuts power to the vital output relays, forcing the BIU into a fail-safe brake-applied state. Finally, CENELEC EN 50159 (Parts A & B) governs safety-related communication in closed and open transmission networks across UHF radio, OFC rings, and LTE-R, defending against packet repetition, deletion, insertion, corruption, delay, and masquerading via cryptographic Cyclic Redundancy Checks (CRC), sequence numbers, and GPS-locked timestamps.

Evolution from Kavach 3.2 to Kavach 4.0 (July 16, 2024 Approval)

While Version 3.2 (RDSO/SPN/196/2012) validated the core concept of radio-based ATP across 1,465\text{ route kilometers} on South Central Railway, field operations exposed severe architectural bottlenecks when scaling to high-density multi-track trunk corridors. The formal approval of Kavach Version 4.0 (RDSO/SPN/196/2020 Version 4.0) on July 16, 2024—alongside mandatory updates to Annexure-A1 (Mode Transitions, SOS & MA Handling Amdt-6), Annexure-A3 (Stationary Kavach Configurable Parameters Amdt-3), and Annexure-G (Network Monitoring System Protocol Amdt-4)—introduced five foundational engineering upgrades that transformed the platform from a regional pilot into a standardized mainline architecture.

First, Version 4.0 achieved full multi-vendor interoperability. Under Version 3.2, proprietary variations in air-gap packet framing and station-to-station handshakes created hardware dependencies across contiguous sections. Version 4.0 enforces a unified air-gap protocol, standardized RFID tag-TIN layout rules (Annexure-H Amdt-5), and uniform NMS telemetry (Annexure-G Amdt-4), ensuring that a locomotive fitted with Medha onboard hardware can seamlessly receive Movement Authority from an HBL or Kernex stationary unit without mode drops. Second, whereas Version 3.2 relied on bulky external parallel relay banks and auxiliary wiring to sample signal aspects and point detection states from station interlocking, Version 4.0 establishes direct serial and Ethernet digital integration between STN-KAVACH and major Electronic Interlocking (EI) platforms, eliminating thousands of physical relay contacts in major yards and enabling real-time ingestion of complex route tables.

Third, Version 4.0 resolves automatic route selection and dense multi-track yard supervision. In complex junctions with multiple parallel running lines and slip crossovers, Version 3.2 struggled with signal aspect processing and TIN sequence ambiguity. Version 4.0 integrates

station-to-station OFC ring networking with refined mode-transition logic in Annexure-A1 Amdt-6 governing the 13 operational modes: Standby (SB), Staff Responsible (SR), Limited Supervision (LS), Full Supervision (FS), Override (OV), On-Sight (OS), Trip (TR), Post-Trip (PT), Reverse (RV), Shunting (SH), Non-Leading (NL), System Failure (SF), and Isolation (IS). Specifically, the July 16, 2024 amendment modified transition priorities from Limited Supervision (LS) to Standby (SB) and from Override (OV) to Standby (SB) by correcting priority levels from p4 to p5, and updated Field 42 (Override Missing TIN) alongside hourly packet telemetry fields (Fields 30–35) in the NMS protocol (Annexure-G Amdt-4), allowing automatic route trace resolution across dense multi-track layouts without nuisance brake trips. Fourth, whereas Version 3.2 was certified for operational speeds up to 120–130\text{ km/h}, Version 4.0 features upgraded high-frequency odometry filtering and look-ahead braking curve algorithms engineered for semi-high-speed operations up to 160\text{ km/h}, validated on Vande Bharat trainsets in the Chipyana Buzurg–Tundla section of the Delhi–Howrah corridor. Finally, Version 4.0 pairs enhanced UHF transceivers—engineered to overcome radio shadowing in deep rock cuttings, mountain gradients, and long tunnels—with an integrated LTE-R communication interface for authenticated cryptographic key exchange with the TSRMS server and high-density packet handling.

Deliverable 1: Technical & Factual Verification Matrix

Subsystem / Parameter	Technical Specification & Operational Metric	Governing RDSO / CENELEC Standard Reference	Verification Status & Forensic Audit Notes
Core System Specification	Indigenous Automatic Train Protection (IRATP / TCAS)	RDSO/SPN/196/2012 Ver 3.2 (Legacy); RDSO/SPN/196/2020 Ver 4.0 (Current)	FRS issued April 11, 2022; SRS effective June 7, 2024; Final Kavach 4.0 baseline & Annexures approved **July 16, 2024**.
Trackside RFID Tags	Passive (inductively powered by loco reader); IP67 ingress protection; 5\text{-tonne} impact resistance.	RDSO/SPN/196/2020 Ver 4.0 & Annexure-H (RFID Tag-TIN Layout Guidelines Amdt-5)	Clamped on PSC sleepers. Normal tags max 1,000\text{ m} apart; Signal Approach (150–250\text{ m}); LC Gate (600–850\text{ m}); Signal Foot; Junction; Exit tags.
Stationary Kavach (STN-KAVACH) & RIU	2 \times 2\text{oo}2 fault-tolerant architecture; up to 1,024 isolated inputs (32/card) & 16 vital outputs/GTO card. RIU (2[span_35](start_span)[span_35](end_span)\text{oo}2, 256 inputs).	RDSO/SPN/196/2020 Ver 4.0 & Annexure-A3 (Configurable Parameters Amdt-3, July 16, 2024)	Interfaces with PI, RRI, and directly via digital link with EI in Ver 4.0. Connected via 6-direction Ethernet-OFC ring switch and SM-OCIP panel.
Radio Telemetry &	40\text{ m} towers	RDSO/SPN/196/2020	Dynamic TDMA/FDMA

Subsystem / Parameter	Technical Specification & Operational Metric	Governing RDSO / CENELEC Standard Reference	Verification Status & Forensic Audit Notes
Spectrum	every 2–3\text{ km}; Duplex UHF (40[span_59](start_span)[span_59](end_span)6–470\text{ MHz}, 25\text{ kHz} BW, MIMO) + LTE-R (700\t[span_82](start_span)[span_82](end_span)ext{ MHz}).	Ver[span_83](start_span)[span_83](end_span)4.0 & Annexure-G (NMS Protocol Amdt-4, July 16, 2024)	for Station-to-Loco link; dedicated fixed frequency (f_0) time slot for direct Loco-to-Loco collision broadcast; LTE-R for TSRMS Key Exchange.
Onboard Vital Computer (LOCO-KAVACH)	2 \times 2\text{oo}2 dual vital computer; 110\text{ V DC} nominal (88–143\text{ V DC}); -20^\circ\text{C} to +70^\circ\text{C}; 6 non-resettable counters.	RDSO/SPN/196/2020 Ver 4.0 & Annexure-A1 (Mode Transitions, SOS & MA Handling Amdt-6)	Supervises 13 operating modes (SB, SR, LS, FS, OV, OS, TR, PT, R[span_101](start_span)[span_101](end_span)[span_105](start_span)[span_105](end_span)V, SH, NL, SF, IS). Fuses RFID tags with wheel tachometers and Doppler radar.
Brake Interface Unit (BIU) & DMI	Electro-pneumatic fail-safe brake manifold; Linux-based DMI (72–110\text{ V DC}) with audio/visual cab aspects.	CENELEC EN 50155 (Rolling Stock Electronics) & RDSO/SPN/196/2020 Ver 4.0	Prioritizes highest brake demand between driver and Kavach to apply Service Brake (SB) or Emergency Brake (EB).
SIL-4 Safety Certification	Probability of Dangerous Failure per Hour (PFH_d) between 10^{-9} and 10^{-8}\text{ hr}^{-1}.	CENELEC EN 50126 (RAMS), EN 50128 (Software), EN 50129 (Hardware), EN 50159 (Telecom), EN 61000 (EMC)	Assessed by Independent Safety Assessor (ISA - Italcertifer, Italy). Enforces fail-safe de-energization upon any dual-channel voting mismatch.

---

2. Train Braking Physics and the Signal SPAD Reality

To understand why human visual observation fails on high-density railway corridors, one must audit the non-linear kinematics of steel wheel-on-rail braking alongside fluid-dynamic delays in compressed air brake pipes.

The Cold Physics of Emergency Braking Distance (EBD)

When a locomotive pilot or an Automatic Train Protection system commands an emergency stop from an initial velocity v_0 (where $v_0 = \frac{V_{\text{km/h}}}{3.6}$ in m/s), the train does not decelerate instantaneously. The total Emergency Braking Distance (EBD) is governed by a two-stage kinematic equation accounting for total system lag time ($t_{\text{eff_lag}}$) during which the train continues to travel at full initial velocity v_0, followed by the active retardation phase at net deceleration a_{net} adjusted for track gradient θ:

$$\text{EBD} = \underbrace{v_0 \cdot \left(t_{\text{reaction}} + \frac{L_{\text{train}}}{2 \cdot c_{\text{air}}} + \frac{t_{\text{buildup}}}{2} \right)}_{\text{Phase 1: Free-Run Lag Distance } (d_{\text{lag}})} + \underbrace{\frac{v_0^2}{2 \cdot \left(a_{\text{brake}} \pm g \sin\theta \right)}}_{\text{Phase 2: Active Retardation Distance } (d_{\text{brake}})}$$

In conventional locomotive-hauled twin-pipe air brake systems, venting the Brake Pipe (BP) from 5.0 kg/cm^2 at the leading locomotive initiates an acoustic pressure-depletion wave that propagates toward the rear brake van at the speed of sound in a restricted pipe ($c_{\text{air}} \approx 250\text{ to }260\text{ m/s}$). Once the pressure drop reaches each coach's distributor valve, compressed air from the auxiliary reservoir flows into the brake cylinders over a build-up ramp time (t_{buildup}) before full clamping force is achieved at the brake discs or wheel treads.

Auditing the specific passenger and freight rolling-stock regimes reveals the exact physical margins across Indian Railways. A standard 24-coach Linke Hofmann Busch (LHB) rake hauled by a WAP-7 electric locomotive measures approximately 600 meters in length ($\sim 1{,}400\text{ tonnes}$ trailing load) and utilizes axle-mounted advanced pneumatic disc brakes with Wheel Slide Protection (WSP), achieving an average emergency retardation of $a_{\text{brake}} \approx 0.90\text{ m/s}^2$. Without Electro-Pneumatic (EP) assist, the pneumatic depletion wave requires $\sim 2.3\text{ s}$ to traverse the 600 m pipe, and brake cylinder pressure builds over $\sim 3.5\text{ s}$, creating an intrinsic mechanical lag equivalent to 2.86 s of free-run travel. Adding a standard human cognitive and motor reaction time of 2.5 s yields an effective human lag of 5.36 s, whereas LOCO-KAVACH triggers the BIU solenoid in 0.2 s, reducing the effective lag to 3.06 s.

At 110 km/h (30.56 m/s), a 24-coach LHB train travels 163.7 m during the human and pneumatic lag phase and 518.7 m during active disc deceleration, yielding a total human EBD of 682.4 m, which sits comfortably within the standard $1{,}000\text{-meter}$ Distant signal warning envelope. Under Kavach auto-application at 110 km/h, free-run lag drops to 93.5 m, stopping the train in 612.1 m and saving 70.3 m. At 130 km/h (36.11 m/s), the same LHB formation covers 193.5 m during human lag and 724.5 m during retardation, totaling 917.9 m manually compared to 834.9 m under Kavach, saving 83.1 m. This kinematic calculation aligns directly with official RDSO oscillation and controllability trials (Report No. RDSO/2023/TG/MT-2049/F, MT-2327/F, and Push-Pull trials on the Mumbai–Vadodara and Agra–Palwal sections), which recorded empirical level-track EBDs of 865.14 m, 891.92 m, 993.0 m, and $1{,}031.0\text{ m}$ for 20- to 22-coach LHB rakes at 130 km/h within the $1{,}100\text{ m}$ statutory ceiling. However, at 160 km/h (44.44 m/s), because kinetic energy scales with the square of velocity ($E_k = \frac{1}{2}mv^2$), increasing speed by 23% from 130 to 160 km/h increases braking work by 51.5%. Without EP-Assist, a 24-coach LHB train at 160 km/h covers 238.1 m during the 5.36 s lag phase and $1{,}097.4\text{ m}$ during deceleration, requiring $1{,}335.5\text{ m}$ to halt manually or $1{,}233.3\text{ m}$ with Kavach (saving $102.2\text{

m}). Because this stopping distance exceeds the 1,000\text{ m} single-distant signal spacing, RDSO Generic Speed Certificates mandate Electro-Pneumatic (EP) Assist brake systems—which propagate brake commands electrically via a train-line circuit rather than pneumatically—or double-distant / 4-aspect signaling whenever EBD exceeds 1,000\text{ m}. By comparison, a 16-car Vande Bharat Express EMU trainset (384\text{ m} length, \sim 850\text{ tonnes}) employs distributed computer-controlled Electro-Pneumatic (EP) bogie-mounted wheel disc brakes blended with regenerative traction braking. Because every coach vents its brake cylinders simultaneously via an electrical command wire (t_{\text{prop}} \approx 0.2\text{ s}, t_{\text{buildup}} \approx 2.0\text{ s}), the pneumatic wave delay is virtually eliminated. With a service deceleration of 0.80\text{ m/s}^2 and an emergency deceleration of a_{\text{brake}} \approx 0.95\text{ m/s}^2, a Vande Bharat trainset at 160\text{ km/h} (44.44\text{ m/s}) travels 164.4\text{ m} during the 3.70\text{ s} human and EP lag and 1,039.6\text{ m} during retardation, yielding a total human EBD of 1,204.1\text{ m}. When LOCO-KAVACH intervenes (1.40\text{ s} total lag), the trainset halts in 1,101.9\text{ m}, saving 102.2\text{ m}. Conversely, a heavy-haul freight formation—comprising a WAG-9 electric locomotive hauling 58\text{ BOXN} wagons (\sim 700\text{ m} length, 5,000\text{ tonnes} gross trailing load)—presents an entirely different mechanical regime. Freight stock relies on single-stage tread brake blocks pressing directly against the wheel rim, yielding a much lower friction coefficient and a net retardation rate of only a_{\text{brake}} \approx 0.30\text{ m/s}^2. Furthermore, to prevent violent longitudinal buff forces that can exceed 100–200\text{ tonnes} and snap couplers or derail empty middle wagons if the front of the train brakes while the rear is still unbraked, freight distributor valves are intentionally choked to build cylinder pressure slowly over 15\text{ to }25\text{ seconds}. Consequently, at 75\text{ km/h} (20.83\text{ m/s}), the effective lag time reaches 11.39\text{ s} for a human pilot or 9.09\text{ s} under Kavach. The freight train rolls 237.3\text{ m} before full braking takes effect and requires 723.4\text{ m} of active retardation, resulting in a level-track EBD of 960.7\text{ m} manually versus 912.8\text{ m} under Kavach, saving 47.9\text{ m}. In Indian Railways Carriage and Wagon (C&W) field reference manuals, a 4,500\text{-tonne} trailing load at 65\text{ km/h} on level track is benchmarked at 632\text{ m} under optimal conditions and up to 1,097\text{ m} under degraded brake power percentages, while on a 1:100 falling gradient, the stopping distance of a 5,000\text{-tonne} train at 75\text{ km/h} expands past 1,420\text{ m}.

Deliverable 2: Physics Calculation Table (Speed vs. Stopping Distance vs. Reaction Time)

Train Formation & Mass	Speed (V)	Velocity (v_0)	Human Reaction (t_r)	Effective System Lag (Human / Kavach)	Free-Run Lag Distance (Human / Kavach)	Active Retardation Rate (a_{\text{net}})	Active Braking Distance (d_{\text{brake}})	Total EBD: Human Pilot	Total EBD: KAVACH Auto-BIU	Margin Saved by KAVACH	Empirical RDSO Benchmark / Field Notes
24-Coach LHB Passe	110\text{ km/h}	30.56\text{ m/s}	2.50\text{ s}	5.36\text{ s} / 3.06\text{ s}	163.7\text{ m} / 93.5\te	0.90\text{ m/s}^2	518.7\text{ m}	**682.4\text{ m}**	**612.1\text{ m}**	**+70.3\text{ m}**	Comfortably within 1,000\t

Train Formation & Mass	Speed (V)	Velocity (v_0)	Human Reaction (t_r)	Effective System Lag (Human / Kavach)	Free-Run Lag Distance (Human / Kavach)	Active Retardation Rate (a_{net})	Active Braking Distance (d_{brake})	Total EBD: Human Pilot	Total EBD: KAVACH Auto-BIU	Margin Saved by KAVACH	Empirical RDSO Benchmark / Field Notes
nger ($\sim$ 1,400\text{ t}, 600\text{ m})					xt{ m}						ext{ m} single-distant signal spacing.
24-Coach LHB Passenger ($\sim$ 1,400\text{ t}, 600\text{ m})	130\text{ km/h}	36.11\text{ m/s}	2.50\text{ s}	5.36\text{ s} / 3.06\text{ s}	193.5\text{ m} / 110.5\text{ m}	0.90\text{ m/s}^2	724.5\text{ m}	**917.9\text{ [span_200](start_span)[span_200](end_span) m}**	**834.9\text{ m}**	**+83.1\text{ m}**	Matches RDSO 20–22 coach trials: **865.1\text{ m}–1,031\text{ m}** (limit $\le$ 1,100\text{ m}).
24-Coach LHB Passenger ($\sim$ 1,400\text{ t}, 600\text{ m})	160\text{ km/h}	44.44\text{ m/s}	2.50\text{ s}	5.36\text{ s} / 3.06\text{ s}	238.1\text{ m} / 136.0\text{ m}	0.90\text{ m/s}^2	1,097.4\text{ m}	**1,335.5\te[span_201](start_span)[span_201](end_span)xt{ m}**	**1,233.3\text{ m}**	**+102.2\text{ m}**	Exceeds 1,000\text{ m} spacing; requires EP-Assist brakes & Kavach cab signaling.
16-Car Vande	160\text{ km/h}	44.44\text{	2.50\text{ s}	3.70\text{ s} /	164.4\text{ m}	0.95\text{	1,039.6\text{	**1,204.1\text{**	**1,101.9\text{**	**+102.2\text{**	Instantaneous

Train Formation & Mass	Speed (V)	Velocity (v_0)	Human Reaction (t_r)	Effective System Lag (Human / Kavach)	Free-Run Lag Distance (Human / Kavach)	Active Retardation Rate (a_{\text{net}})	Active Braking Distance (d_{\text{brake}})	Total EBD: Human Pilot	Total EBD: KAVACH Auto-BIU	Margin Saved by KAVACH	Empirical RDSO Benchmark / Field Notes
Bharat EMU (\sim 850\text{ t}, 384\text{ m})		m/s}		1.40\text{ s}	/ 62.2\text{ m}	m/s}^2	m}	**m}**	**m}**	**m}**	EP brake command; service decel 0.8\text{ m/s}^2, EB \sim 0.95\text{ m/s}^2.
5,000-Tonne Freight (BOXN) (58\text{ wagons}, 700\text{ m})	75\text{ km/h}	20.83\text{ m/s}	2.50\text{ s}	11.39\text{ s} / 9.09\text{ s}	237.3\text{ m} / 189.4\text{ m}	0.30\text{ m/s}^2	723.4\text{ m}	**960.7\text{ m}**	**912.8\text{ m}**	**+47.9\text{ m}**	Slow 15\text{ s} distributor valve build-up; C&W manual cites up to 1,097\text{ m} at 65\text{ km/h}.

Signal Passed at Danger (SPAD) Statistics and the Winter Fog Sensory Deficit

In Indian Railways safety classification, a Signal Passed at Danger (SPAD)—occurring when a train passes a stop signal showing a Red ("ON") aspect without valid authority—is categorized as an indicative or Non-Consequential Train Accident unless it culminates in a physical collision or derailment. However, every SPAD represents a zero-margin precursor to a catastrophic collision. According to official Commission of Railway Safety (CRS) and Railway Board multi-year audits, SPAD incidents across Indian Railways have remained stubbornly plateaued between 35 and 39 cases per year, with 35 cases recorded in FY 2020–21, 39 cases in FY

2021–22, 35 to 39 cases in FY 2022–23 (within 162 to 165 total non-consequential accidents and alongside 48 consequential train accidents), 39 cases in FY 2023–24, and 35 cases in FY 2024–25. During November 2024 alone, an acute cluster of 7 SPAD cases occurred within a single month across Eastern, North Central, Northern, East Coast, North Western, South Central, and South Eastern Railways—more than double the 3 SPAD cases recorded in November 2023—while parliamentary disclosures confirm that at least 12 consequential train collisions in recent multi-year tallies were directly triggered by SPAD violations.

Financial Year	Official CRS Annual SPAD Count	Consequential Collisions / Context	Primary Operational & Environmental Drivers
FY 2020–21	**35 Cases**	1 Consequential Collision; 21 Total Consequential Accidents.	Pandemic-restricted passenger traffic; freight crew fatigue.
FY 2021–22	**39 Cases**	2 Consequential Collisions; 34–35 Total Consequential Accidents.	Post-COVID traffic surge; restoration of mail/express services.
FY 2022–23	**35–39 Cases**	6 Consequential Collisions; 48 Consequential & 162–165 Non-Consequential Accidents.	Over 33–36% of SECR loco pilots working >12\text{-hour} shifts; winter fog.
FY 2023–24	**39 Cases**	6 Consequential Collisions.	Trunk route capacity utilization at 120–150\%; safety staff vacancies.
FY 2024–25	**35 Cases**	3 Collisions up to Nov 2024; 7 SPAD cases in Nov 2024 alone (vs. 3 in Nov 2023).	Cluster across ER, NCR, NR, ECoR, NWR, SCR, and SER at onset of winter fog.

The persistence of 35\text{ to }39 annual SPAD incidents stems from the irreconcilable conflict between train braking physics and human neuro-sensory limitations under heavy winter fog and high-speed crew fatigue. During December and January across the Indo-Gangetic plains of Northern, North Central, and Eastern Railways, dense radiation fog routinely reduces optical line-of-sight visibility to less than 30\text{ to }50\text{ meters}. As established in the kinematic audit, an LHB express traveling at 110\text{ km/h} (30.56\text{ m/s}) requires 682.4\text{ meters} to come to a stop. If a Loco Pilot relies on visual sight to detect a Red or Yellow aspect from 50\text{ meters} away, the locomotive crosses the signal foot in 1.63\text{ seconds}—before the driver's 2.5\text{ s} cognitive reaction time has even elapsed, let alone the 518.7\text{ m} required for active disc braking. Legacy countermeasures deployed by Indian Railways—such as painting retro-reflective Sigma boards on OHE masts two spans prior to a signal or issuing GPS-based Fog Safety Devices (FSD)—only inform the crew of the static distance to an approaching signal post. They do not transmit the dynamic aspect of that signal into the cab, forcing crews to either crawl at 15–30\text{ km/h} (crippling sectional capacity) or risk a blind SPAD.

Furthermore, above 140–160\text{ km/h}, peripheral visual smear and ocular saccade latency

prevent the human eye from reliably resolving wayside LED signal aspects in time to respect a 1,200\text{ m} braking curve, making in-cab signaling via the Kavach DMI a mandatory prerequisite for 160\text{ km/h} operations. Compounding this biological ceiling is chronic crew exhaustion: parliamentary and Comptroller and Auditor General (CAG) audits revealed between 1.42\text{ lakh} and 3.12\text{ lakh} vacant Group-C and safety-category posts across Indian Railways, forcing 33.26\% to 35.99\% of loco pilots in high-density freight zones like South East Central Railway to work continuous duty shifts exceeding 12\text{ hours}. While locomotives are fitted with a Vigilance Control Device (VCD) that triggers a penalty brake if the driver fails to acknowledge a check every 60 seconds, an exhausted driver can mechanically reset a VCD pedal while suffering micro-sleep or attentional tunneling right past a Distant signal. Kavach eliminates this human single-point failure by continuously computing a dynamic Service Brake (SB) and Emergency Brake (EB) target velocity parabola ($v_{\text{target}}(x) = \sqrt{2 \cdot a_{\text{brake}} \cdot (x_{\text{signal}} - x_{\text{train}})}$) from over 1,500\text{ meters} out, intervening via the BIU regardless of atmospheric visibility or crew fatigue.

3. The Rollout Bottleneck and Industrial Procurement Audit

A forensic audit of Indian Railways' deployment figures exposes a stark structural gap between the scale of the national rail network and the physical throughput of the signaling supply chain.

Network Scale vs. Current Deployment Reality

According to official Indian Railways Year Book and Ministry of Railways statistical disclosures, the physical infrastructure baseline comprises 68,584\text{ Route Kilometres (RKM)} across all gauges, of which 65,977\text{ RKM} is Broad Gauge, 1,345\text{ RKM} is Metre Gauge, and 1,262\text{ RKM} is Narrow Gauge. When accounting for double, triple, and quadruple mainlines, the network spans 1,06,493\text{ Running Track Kilometres (RTKM)} (up from 1,02,831\text{ RTKM} in 2021–22) and 1,32,310\text{ Total Track Kilometres (TTKM)} including station loop lines, marshalling yards, and sidings, with Broad Gauge electrification reaching virtually 100\% across FY 2024–26. The active traction and coaching fleet encompasses approximately 15,000\text{ to }20,000+\text{ active locomotives}—including 11,138+\text{ electric locomotives} and \sim 4,500–5,000\text{ diesel locomotives}, with the Railway Board structuring Kavach locomotive procurement across 20,000\text{ locomotives} in two 10,000\text{-unit} phases alongside 1,200+\text{ EMU/MEMU rakes} (11,664+\text{ EMU/MEMU coaches})—and over 80,000\text{ passenger coaching vehicles}, including 42,677\text{ LHB coaches} manufactured between 2014 and 2025.

Against this 68,584\text{ RKM} baseline, the empirical commissioning trajectory of Kavach has progressed through two distinct phases. During the Version 3.2 pilot plateau between its adoption as the National ATP system in July 2020 and July 2024, operational Kavach deployment remained stationary at 1,465\text{ RKM} and 144\text{ locomotives} (up from 121\text{ locomotives} in August 2023), confined entirely to the South Central Railway (SCR) zone. Throughout that window, preparatory backbone works on the 3,000\text{ RKM} Delhi–Mumbai and Delhi–Howrah trunk corridors laid 4,275\text{ km} of Optical Fibre Cable (OFC) and erected 364\text{ telecom towers} while awaiting the finalization of the Version 4.0 specification. Following RDSO's approval of Kavach 4.0 on July 16, 2024, mainline acceleration commenced with initial commissionings on the Sawai Madhopur–Kota stretch of West Central

Railway (108+\text{ km}), the Malkajgiri–Kamareddi section of SCR (108\text{ RKM}), and a 207\text{ RKM} high-speed section on North Central Railway. By December 2025, Kavach 4.0 was commissioned across 1,297\text{ RKM}. According to the Ministry of Railways audit as of July 31, 2026, Kavach Version 4.0 has been successfully commissioned across 2,633\text{ RKM}, comprising 1,423\text{ RKM} on the Delhi–Mumbai corridor and 1,210\text{ RKM} on the Delhi–Howrah corridor, including the Vadodara–Virar, Gaya–Sarmatanr, Jn Cabin–Palwal, and 260\text{ RKM} Chota Ambana–Bardhaman–Howrah sections.
Combining the 1,465\text{ RKM} of Version 3.2 on SCR (for which a ₹120 crore migration work order to Version 4.0 was sanctioned) with the 2,633\text{ RKM} of newly commissioned Version 4.0 yields a total operational network coverage of 4,098\text{ RKM} as of July 31, 2026—representing 5.98\% (\sim 6.0\%) of Indian Railways' 68,584\text{ RKM} network. Concurrently, active trackside installation work is underway across 21,794\text{ RKM} covering all Golden Quadrilateral, Golden Diagonal, and High-Density Network corridors within a broader 36,000\text{ RKM} Umbrella sanction, with sub-system progress reaching 7,726\text{ RKM} of trackside equipment and 6,290\text{ locomotives} physically equipped as of July 2026, alongside ongoing fitment on a further 7,190\text{ locomotives} and 1,200\text{ EMU/MEMU rakes}.

Deliverable 3: Procurement & Rollout Bottleneck Matrix (The 68,584 km Reality)

Rather than a software patch, commissioning Kavach across a railway division is a multi-disciplinary civil, telecom, interlocking, and rolling-stock overhaul. Tracing the 68,584\text{ RKM} national network through the five-stage industrial pipeline explains why commissioned mileage stands at 4,098\text{ RKM} (6.0\%) as of mid-2026. At the foundational track level, while 65,977\text{ RKM} consists of Broad Gauge trackage, equipping a double- or quadruple-line section requires clamping passive RFID tags every 1\text{ km} (plus signal approaches and turnouts) on every individual running track (1,06,493\text{ RTKM}) and loop line (1,32,310\text{ TTKM}). At the sanction and tendering stage, Indian Railways prioritized the Golden Quadrilateral (GQ), Golden Diagonal (GD), High-Density Network (HDN), and all Automatic Block Signaling sections (5,715\text{ RKM}), sanctioning 36,000\text{ RKM} under Umbrella works. However, large-scale trackside tendering was deliberately held back prior to July 2024 to finalize the RDSO/SPN/196/2020 Version 4.0 interoperability specification, preventing the installation of non-interoperable Version 3.2 hardware on mainline trunks.
Once bids were opened across 15,091+\text{ RKM} in late 2024 and expanded to 21,794\text{ RKM} of active works by mid-2026, field execution encountered the Interlocking and Telecom Prerequisite Bottleneck. STN-KAVACH cannot be commissioned on legacy mechanical lever frames or aged relay rooms without first commissioning centralized Electronic Interlocking (EI)—installed at 6,589\text{ stations} by mid-2024—alongside complete track circuiting (6,609\text{ stations}), trenching 2\times 24 or 4\times 48 core Optical Fibre Cable (OFC) along the track bed, and erecting 40\text{-meter} steel lattice towers every 2–3\text{ km}. Furthermore, even after OFC trenches, telecom towers, and sleeper RFID tags are physically installed (7,726\text{ RKM} completed as of July 2026) and locomotives are retrofitted inside electric loco sheds (6,290\text{ locomotives} completed out of 10,000+ ordered), a section cannot be declared operational until station-specific Application Logic (TOC / Control Tables) and RFID Tag-TIN Layout Charts are individually designed, factory-acceptance-tested (FAT) per RDSO schemes, and field-verified through Light Engine trials, Passenger Train trials without BIU cut-in,

and Passenger Train trials with active BIU braking.

Pipeline Stage	Route Kilometres (RKM)	Share of Network (%)	Associated Rolling Stock & Sub-System Status	Primary Engineering & Procurement Bottleneck
Stage 1: Total IR Physical Network	**68,584\text{ RKM}**	100.0\%	1,06,493\text{ RTKM}; 1,32,310\text{ TTKM}; \sim 20,000\text{ Locos} (Phase 1 & 2 scope).	Multi-track density requires equipping 1.06\text{ lakh km} of running tracks across diverse terrain.
Stage 2: Sanctioned Umbrella Scope	**36,000\text{ RKM}**	52.5\%	Covers GQ, GD, HDN, and 5,715\text{ RKM} of Automatic Block Signaling sections.	Tendering freeze prior to July 16, 2024 while awaiting RDSO/SPN/196/2020 Ver 4.0 standardization.
Stage 3: Active Trackside Implementation	**21,794\text{ RKM}**	31.8\%	15,091\text{ RKM} bids invited in Dec 2024; 7,190\text{ Locos} & 1,200\text{ EMU/MEMU} under fitment.	Prerequisite civil works: 40\text{ m} tower erection, 4\times 48 OFC trenching, and legacy PI/RRI replacement with EI.
Stage 4: Sub-System Hardware Installed	**7,726\text{ RKM}**	11.3\%	**6,290\text{ Locomotives}** equipped with LOCO-KAVACH; 48,000+\text{ staff} trained.	Station-specific Control Table (TOC) logic design, RDSO FAT testing, and EI interface approvals.
Stage 5: Fully Commissioned & Operational	**4,098\text{ RKM}**	**6.0\%**	**1,465\text{ RKM}** (Ver 3.2 on SCR) + **2,633\text{ RKM}** (Ver 4.0 on Delhi–Mumbai & Delhi–Howrah).	Mandatory sequential Light Engine, Passenger (w/o BIU), and Passenger (with BIU) field safety trials.

Certified Vendor Ecosystem and Manufacturing Capacity

For six years between 2018 and 2024, the entire Kavach supply chain was restricted to a triopoly of three Hyderabad-based original equipment manufacturers (OEMs) approved by RDSO for Version 3.2: Medha Servo Drives Pvt. Ltd., HBL Engineering Ltd. (formerly HBL Power Systems Ltd.), and Kernex Microsystems (India) Ltd.. Collectively, these three original

vendors possessed an initial trackside installation capacity of only \sim 1,500\text{ RKM per year}. To break this industrial bottleneck and achieve the Railway Board's deployment target of 4,000\text{ to }5,500\text{ RKM per year}, RDSO fast-tracked the qualification of new domestic and global signaling players under Version 4.0. Between 2024 and 2026, Quadrant Future Tek Ltd. (QFTL)—which secured RDSO approval for Kavach 4.0 passenger trials and locomotive supply—and GG Tronics India Pvt. Ltd. (a subsidiary of CG Power & Industrial Solutions) successfully entered commercial production. Concurrently, multinational signaling leaders and major infrastructure EPC contractors entered the ecosystem via joint ventures and RDSO developmental trials, including Siemens (executing the Chota Ambana–Howrah section on Eastern Railway in an HBL–Siemens consortium), Alstom, Bharat Heavy Electricals Limited (BHEL), KEC International (executing North Central Railway contracts in the Kernex–KEC consortium), and Ashoka Buildcon (executing East Central Railway contracts in an Ashoka Buildcon–HBL consortium).

Simultaneously, the original OEMs aggressively expanded surface-mount technology (SMT) lines; for instance, Kernex Microsystems scaled its factory manufacturing capacity to 450\text{ Kavach units per month}, or \sim 5,400\text{ units annually}. This expanded 5-vendor industrial base was immediately mobilized in December 2024, when Chittaranjan Locomotive Works (CLW) issued its landmark Phase-1 purchase order for 10,000\text{ Onboard Locomotive Kavach Ver 4.0 systems} (\sim ₹7,200\text{ crore} total program outlay, with Phase-2 slated to cover the remaining 10,000\text{ locomotives}). The 10,000\text{-locomotive} CLW order was distributed across the five certified OEMs strictly in proportion to their audited production capacities: Medha Servo Drives was awarded 3,300\text{ locomotives} (33\% share), Kernex Microsystems received 2,500\text{ locomotives} (25\% share, valued at ₹2,041.40\text{ crore} inclusive of GST, complete cab harnessing, a 4-year warranty, and an 11-year Comprehensive Annual Maintenance Contract), HBL Engineering secured 2,200\text{ locomotives} (22\% share), Quadrant Future Tek was allocated 1,200\text{ locomotives} (12\% share), and GG Tronics received 800\text{ locomotives} (8\% share).

Capital Cost Breakdown and Union Budget Audit (FY 2023–24 to FY 2026–27)

From a capital-efficiency standpoint, Kavach is the least expensive SIL-4 Automatic Train Protection system globally. According to official parliamentary disclosures by the Minister of Railways, the cost of providing trackside and station Kavach equipment—including STN-KAVACH, RIUs, 40\text{ m} radio towers, sleeper RFID tags, and OFC backbone integration—averages approximately ₹50\text{ Lakh per route kilometer}. By comparison, deploying the European Train Control System (ETCS Level 2) costs between ₹1.5\text{ Crore} and ₹3.0\text{ Crore per route kilometer}, meaning Kavach delivers equivalent SIL-4 collision and SPAD protection at one-fourth to one-sixth the trackside capital cost of imported European signaling. Equipping an individual locomotive with LOCO-KAVACH costs approximately ₹70\text{ Lakh to }₹80\text{ Lakh per locomotive}—officially cited at ₹70\text{ Lakh} in August 2023, ₹72\text{ Lakh} in mid-2024 tenders, and ₹80\text{ Lakh/loco} in February 2026 Rajya Sabha disclosures when factoring in full cab wiring, BIU electro-pneumatic valves, and long-term maintenance. Turnkey corridor contracts that bundle trackside installations, 2\times 24 fibre OFC, radio towers, and locomotive fitments—such as the North Central Railway contracts awarded to Kernex for Chipyana Buzurg–Kanpur (408.75\text{ km}, 48 stations, 139 locos for ₹255.22\text{ Cr}) and Kanpur–Pt. Deen Dayal Upadhyaya (342.47\text{ km}, 51 stations, 158


locos for ₹254.86\text{ Cr})—reflect an all-inclusive blended capital outlay of \sim ₹62\text{ Lakh to }₹74\text{ Lakh per route kilometer}.

Financial Year / Metric	Overall IR Capital Outlay (Capex)	Overall IR Safety Expenditure	Dedicated KAVACH Budget Allocation	Cumulative KAVACH Funds Utilized	Operational Coverage & Key Procurement Milestones
FY 2023–24	₹2,40,200\text{ Cr} (GBS)	\sim ₹1,00,000+\text{ Cr}	**₹710.12\text{ Cr}**	₹352\text{ Cr} (in-year by Aug 2023)	1,465\text{ RKM} & 121–139\text{ locos} operational on SCR (Ver 3.2).
FY 2024–25	₹2,62,200\text{ Cr} (₹2.52\text{L Cr} GBS)	₹1,14,022\text{ Cr}	**₹1,112.57\text{ Cr}** (₹560\text{ Cr} Interim)	**₹1,216.77\text{ Cr}** (Jul '24) / **₹1,547\text{ Cr}** (Nov '24)	**Kavach 4.0 approved July 16, 2024**; 1,465\text{ RKM} & 144\text{ locos} on SCR; CLW 10,000\text{-loco} order placed Dec 2024.
FY 2025–26	₹2,65,000\text{ Cr} (₹2.52–2.65\text{L Cr} GBS)	₹1,17,693\text{ Cr} (₹1.17\text{L Cr})	**₹1,673.19\text{ Cr}**	**₹2,573.36\text{ Cr}** (up to Dec 2025)	**1,297\text{ RKM} of Ver 4.0 commissioned** on Delhi–Mumbai & Delhi–Howrah trunks (Total: 2,762[span_294](start_span)[span_294](end_span)\text{ RKM}).
FY 2026–27	₹2,93,030\text{ Cr} (Budget Grant)	₹1,20,389\text{ Cr}	**₹2,066.00\text{ Cr}**	**₹3,875.00\text{ Cr}** (up to June 2026)	**2,633\text{ RKM} of Ver 4.0 commissioned** (+1,465\text{ RKM} Ver 3.2 = **4,098\text{ RKM}**); **6,290\text{ locos}**

Financial Year / Metric	Overall IR Capital Outlay (Capex)	Overall IR Safety Expenditure	Dedicated KAVACH Budget Allocation	Cumulative KAVACH Funds Utilized	Operational Coverage & Key Procurement Milestones
					equipped; 21,794\text{ RKM} under active work.

4. Disaster Forensics: Where Kavach Works vs. Where It Cannot

A rigorous forensic examination of Indian Railways' two highest-profile recent collisions—the June 2, 2023 Balasore triple-train disaster and the June 17, 2024 Kanchanjunga Express rear-end crash—illustrates the exact architectural boundary between Interlocking Integrity, where an Automatic Train Protection system is inherently blind, and Operational or Signal-Compliance Failures, where Kavach acts as an absolute physical shield.



1. The Balasore Crash (June 2, 2023 – Bahanaga Bazar Station, South Eastern Railway)

On the evening of June 2, 2023, Train No. 12841 Shalimar–Chennai Central Coromandel

Express was approaching Bahanaga Bazar station in the Kharagpur Division of South Eastern Railway at approximately 128\text{ km/h} on the Up Main Line. All wayside signals—the Up Distant, Up Inner Distant, Up Home, and Up Mainline Starter—displayed a clear Green ("OFF") aspect, authorizing an unrestricted run-through at the maximum permissible sectional speed of 130\text{ km/h}. However, as the locomotive reached Crossover Point 17A/17B, the physical switch blades were not aligned for the straight Up Main Line; they were mechanically locked in the Reverse position, diverting the 128\text{ km/h} passenger express across a turnout rated for 15\text{ km/h} directly into the Up Loop Line, where a heavily laden iron-ore freight train was stabled. The resulting impact and derailment fouled the adjacent Down Main Line just as Train No. 12864 SMVT Bengaluru–Howrah Superfast Express passed through, resulting in 288 to 296 fatalities.

As established by the Commission of Railway Safety (CRS) statutory inquiry, the catastrophe originated not from a Loco Pilot error or an ATP absence, but from an unauthorized physical wiring alteration inside the station's signaling circuitry. Earlier that day, Signal & Telecommunication (S&T) maintenance personnel were troubleshooting an electric lifting barrier (boom-locking) circuit fault at Level Crossing Gate No. 94 (LC-94) near Bahanaga Bazar station. Because an approved, site-specific wiring diagram for LC-94 was unavailable during the modification work, the Senior Section Engineer (SSE/Signal) attempted to rewire the location box and Relay Room termination using the circuit diagram of a different gate—LC-79 at Balasore—without obtaining a formal Disconnection Memo or making mandatory entries in the Relay Room Key Register. Furthermore, a latent five-year-old circuit discrepancy existed in the point detection wiring for Crossover 17A/17B. During the unverified wiring alterations on June 2, technicians severed the true field detection return path from Point 17A/17B and inadvertently bridged a false positive electrical feed directly into the Normal Point Detection Relay (17 NWKR) input channel feeding the station's Electronic Interlocking (EI) logic. Consequently, while the physical point machine at site had driven and locked the switch blades of Crossover 17A into the Reverse position—where only the 17 RWKR logic bit was physically true on the ground—the false electrical feed energized 17 NWKR inside the Relay Room. Blinded by this corrupted electrical input, the Electronic Interlocking CPU evaluated its boolean truth table as having an unoccupied Up Main Line, a closed LC-94 gate, and Point 17A locked in Normal (17 NWKR True), and accordingly cleared the Up Home and Starter signals to Green.

Even if the Kharagpur–Bhadrak section and every locomotive at Bahanaga Bazar had been fully equipped with SIL-4 Kavach Version 4.0, the collision would still have occurred due to the fundamental architectural division between Interlocking and Automatic Train Protection. An ATP system acts on signal status and route authority, but relies entirely on the underlying Interlocking system for ground truth regarding physical switch blade lock states. STN-KAVACH does not install redundant physical blade-proximity sensors on every switch tongue in a railway yard; instead, per RDSO/SPN/196/2020, it extracts route locking, point position (17 NWKR), and signal aspect states directly from the station's Electronic Interlocking or Relay Room vital contacts. Because the EI at Bahanaga Bazar was fooled by the false 17 NWKR relay feed into believing Point 17A was locked Normal for the Up Main Line, STN-KAVACH would have ingested that exact same corrupted truth table and broadcast a valid Full Supervision (FS) Movement Authority over the 406–470\text{ MHz} UHF radio link to the Coromandel Express, displaying a Green cab aspect and a 130\text{ km/h} permitted speed ceiling on the Loco Pilot's DMI. Moreover, direct Loco-to-Loco peer radio (f_0) between the parked iron-ore freight locomotive and the approaching Coromandel Express would not have triggered an emergency brake intervention prior to the turnout. To prevent false-positive emergency braking when trains pass each other on adjacent parallel tracks, Kavach filters collision alerts by Track Identification

Number (Track ID). Having scanned the Loop Line's sleeper RFID tags upon entry, the parked freight locomotive's LOCO-KAVACH would have broadcast its occupancy on the Up Loop Line (Track ID = Loop), whereas the approaching Coromandel Express was scanning Up Main Line (Track ID = Main) sleeper tags and holding an EI-issued route authority for the Up Main Line. The Coromandel Express's LOCO-KAVACH could only discover that it had been physically diverted onto the Up Loop Line after crossing the switch blades of Point 17A and scanning the first turnout/loop-line RFID tag, at which point—traveling at 128\text{ km/h} (35.56\text{ m/s})—it was fewer than 80\text{ to }100\text{ meters} from the parked freight rake while requiring over 835\text{ meters} to halt.

2. The Kanchanjunga Express Crash (June 17, 2024 – New Jalpaiguri / Rangapani Section, Northeast Frontier Railway)

At 08:50 hrs on June 17, 2024, Train No. 13174 Down Agartala–Sealdah Kanchanjunga Express was proceeding slowly and halting at defective signals in the automatic block signaling section between Rangapani (RNI) and Chatterhat (CAT) stations—approximately 30\text{ km}[span_177](start_span)[span_177](end_span)[span_181](start_span)[span_181](end_span) south of New Jalpaiguri in the Katihar Division of Northeast Frontier Railway—when a trailing Down GFCJ container freight train slammed into its rear end, derailing four rear coaches and killing 10 people, including the freight train's Loco Pilot. At the time of the crash, Northeast Frontier Railway had zero route kilometers of operational Kavach; deployment across Indian Railways was still concentrated on South Central Railway (1,465\text{ RKM}) and under construction on the Delhi–Mumbai and Delhi–Howrah trunk corridors, with an NFR testing and training laboratory only subsequently initiated at Guwahati.

The statutory inquiry conducted by the Commissioner of Railway Safety (CRS) identified a systemic collapse of degraded-mode operating protocols across multiple levels. Beginning at 05:50 hrs that morning, the Automatic Block Signaling system between Rangapani and Chatterhat failed completely due to optical fibre and signaling cable damage, causing all mid-section automatic stop signals to remain locked at Danger (Red / "ON") or blank. Under Indian Railways General & Subsidiary Rules (G&SR Chapter IX), when automatic signaling fails for a prolonged period across an entire block section, the Station Master is required to suspend automatic working and revert the section to the Absolute Block System, allowing only one train at a time between Rangapani and Chatterhat. Instead, the Rangapani Station Master continued dispatching multiple trains one behind another into the failed section by handing each crew an improper paper line authority—Form T/A 912 (*Authority to Pass Defective Automatic Signals*)—which listed the series of failed signal numbers they were authorized to pass at Red. Crucially, Form T/A 912 relies on the Loco Pilot's compliance with G&SR Rule 9.02 / 9.07, which mandates that when passing a defective automatic signal at Danger, the driver must stop for 1 minute by day (2 minutes by night) at the foot of each Red signal and then proceed with great caution at a speed not exceeding 15\text{ km/h} (10\text{ km/h} when visibility ahead is obstructed by fog, curves, or rain). During its forensic audit of locomotive speed recorders across the division, the CRS uncovered a widespread operational breakdown: while the Loco Pilot of the Kanchanjunga Express strictly obeyed the 15\text{ km/h} rule and halted for 1 minute at each defective Red signal, most other Loco Pilots in the division did not follow the 15\text{ km/h} restriction, mistakenly treating Form T/A 912 as an unconditional line-clear authority to pass Red signals at normal sectional speeds. Traveling far above the 15\text{ km/h} sight-stopping ceiling in monsoonal rain, the GFCJ container freight crew spotted the stationary

Kanchanjunga Express too late for their slow-building freight brake pipe to arrest the train. Had Kavach been operational on the Rangapani–Chatterhat section and aboard both locomotives, the collision would have been physically impossible, blocked by two independent SIL-4 hardware layers. First, when a Kavach-equipped train approaches a defective or Red automatic signal, the Signal Approach and Signal Foot RFID tags combined with the absence of a permissive Movement Authority (MA) from the trackside unit automatically trigger a Trip (TR) emergency brake application if the driver attempts to pass the signal at normal speed. To pass a defective Red signal under paper authority (Form T/A 912), the Loco Pilot must halt or crawl below the threshold speed and physically press the Override (OV) key on the in-cab DMI. Under RDSO/SPN/196/2020 Version 4.0 (Annexure-A1 & Annexure-A3), actuating Override transitions the onboard Vital Computer into Override (OV) mode and subsequently into Staff Responsible (SR) or On-Sight (OS) supervision, wherein the Vital Computer electronically clamps the locomotive's ceiling speed to the configured caution limit of 15\text{ km/h}. Had the GFCJ freight driver misinterpreted Form T/A 912 and notched up the throttle toward normal speed, LOCO-KAVACH would have immediately commanded a Service Brake (SB) and Emergency Brake (EB) intervention via the BIU whenever the locomotive exceeded 15\text{ km/h}, completely neutralizing human rule misinterpretation. Second, even with all wayside automatic signals and station cables dead, both the halted Kanchanjunga Express and the trailing GFCJ container train would have continued scanning the passive sleeper RFID tags underneath them, confirming that both trains occupied the exact same Track ID (Down Main Line). Every second, in their GPS-synchronized TDMA time slots, both locomotives would have broadcast their Track ID, absolute kilometrage, and velocity directly to each other over the dedicated UHF collision-avoidance frequency (f_0, 406–470\text{ MHz}), autonomously triggering an un-overridable Emergency Brake application on the trailing freight train well over 1,000\text{ meters} before impact.

Deliverable 4: Root-Cause Forensic Comparison: Balasore vs. Kanchanjunga Express

Forensic Dimension	The Balasore Crash (June 2, 2023)	The Kanchanjunga Express Crash (June 17, 2024)
Location & Railway Zone	Bahanaga Bazar Station, Kharagpur Division, South Eastern Railway (Odisha).	Between Rangapani (RNI) & Chatterhat (CAT), Katihar Division, Northeast Frontier Railway (West Bengal).
Trains Involved & Casualties	12841 Coromandel Express, parked Iron-Ore Freight Train, & 12864 SMVT Bengaluru–Howrah Express; **288–296 killed**.	13174 Down Kanchanjunga Express & Down GFCJ Container Freight Train; **10 killed** (including freight Loco Pilot).
Signaling Territory Type	Station Yard with centralized **Electronic Interlocking (EI)** and motorized point machines.	**Automatic Block Signaling (ABS)** double-line electrified mid-block section.
Primary Root Cause (CRS Inquiry Findings)	**Corrupted Interlocking Input**: Unverified S&T wiring modification for LC-94 (using LC-79 diagram) injected a false	**Degraded-Mode Operational & Speed Violation**: Total failure of automatic signals since 05:50 hrs; Station Master

Forensic Dimension	The Balasore Crash (June 2, 2023)	The Kanchanjunga Express Crash (June 17, 2024)
	positive feed into the **Point 17A Normal Detection Relay (17 NWKR)**.	issued wrong paper authority (Form T/A 912); freight pilot violated the mandatory **15\text{ km/h}** caution rule.
Physical State vs. Displayed Signal Aspect	Physical switch blades of **Point 17A were locked in Reverse** (leading into the occupied Up Loop Line), but the EI logic read 17 NWKR = True and displayed a **Green ("OFF") aspect** for a 130\text{ km/h} mainline run-through.	Automatic signals were defective (Red / blank). Kanchanjunga Express obeyed the **15\text{ km/h}** rule and halted; trailing freight train misread T/A 912 as normal-speed authority and rammed the express from behind.
Was KAVACH Present on the Section?	**No.** Only 1,465\text{ RKM} on South Central Railway had Kavach at the time.	**No.** Northeast Frontier Railway had 0\text{ RKM} of commissioned Kavach (testing/training lab later initiated at Guwahati).
Would KAVACH Have Prevented the Crash?	**NO.** Kavach cannot prevent an accident caused by a corrupted station interlocking truth table.	**YES (100%).** Kavach is specifically engineered to prevent rear-end collisions and enforce degraded-mode speed limits.
Exact Engineering Mechanism of KAVACH Response	STN-KAVACH fetches route and point status directly from the station EI. Because the EI itself believed Point 17A was Normal and the Up Main Line was clear, STN-KAVACH would have transmitted a **130\text{ km/h} Full Supervision (FS) Movement Authority** to the Coromandel Express. Peer-to-peer LOCO-KAVACH radio (f_0) would not trigger because the parked freight train was on Track ID [span_17](start_span)[span_17](end_span)[span_29](start_span)[span_29](end_span)= Up Loop while the express was registered on Track ID = Up Main until crossing the switch blades <100\text{ m} before impact.	**1. Override Speed Clamping**: Passing a defective Red signal under T/A 912 requires pressing Override (OV) on the DMI, transitioning LOCO-KAVACH to OV/SR/OS mode, which electronically clamps train speed to **15\text{ km/h}** via automatic BIU braking. **2. Direct Loco-to-Loco f_0 Telemetry**: Both trains read the same Down Main Line sleeper RFID tags; direct UHF peer broadcast (f_0) detects same-track occupancy ahead and triggers an un-overridable Emergency Brake application well over 1,000\text{ m} before impact.

5. Synthesis and Engineering Conclusions

The empirical audit of KAVACH across its RDSO Version 4.0 architecture, braking kinematics, procurement pipeline, and accident forensics establishes three foundational realities for Indian Railways. First, with the July 16, 2024 approval of RDSO/SPN/196/2020 Version 4.0, Indian Railways resolved the multi-vendor interoperability, direct Electronic Interlocking integration, and 160\text{ km/h} dense-yard supervision limitations that had constrained Version 3.2 to a regional pilot on South Central Railway. At ₹50\text{ Lakh/km} for trackside infrastructure and ₹70–80\text{ Lakh/locomotive}, Kavach delivers CENELEC SIL-4 safety (PFH_d \sim 10^{-9}\text{ hr}^{-1}) at less than one-fourth the capital cost of European ETCS Level 2. However, as of July 31, 2026, operational coverage stands at 4,098\text{ RKM} (1,465\text{ RKM} Ver 3.2 plus 2,633\text{ RKM} Ver 4.0)—representing 6.0\% of the 68,584\text{ RKM} network—with 6,290\text{ locomotives} equipped. Scaling from the current 21,794\text{ RKM} of active works to nationwide completion depends entirely on the execution velocity of the expanded 5-vendor OEM ecosystem (Medha, Kernex, HBL, Quadrant Future Tek, and GG Tronics) alongside prerequisite Electronic Interlocking and OFC trenching.

Second, kinematic braking calculations prove that at 160\text{ km/h}, both 24-coach LHB rakes (1,335.5\text{ m}) and 16-car Vande Bharat trainsets (1,204.1\text{ m}) exceed the traditional 1,000\text{ m} single-distant signal warning distance, while winter radiation fog reduces visual sighting on Northern and Eastern corridors below 50\text{ m}, which equates to just 1.63\text{ s} of travel at 110\text{ km/h}. Eliminating the 35\text{ to }39 annual SPAD incidents across Indian Railways is physically impossible through human vigilance alone; it requires the 0.2\text{ s} electronic reaction of the Kavach Brake Interface Unit—which shaves 70\text{ m} to 102\text{ m} off high-speed stopping distances—and continuous in-cab DMI supervision. Finally, while full Kavach deployment will permanently eradicate rear-end, head-on, overspeed, and degraded-mode collisions like the June 2024 Kanchanjunga Express crash through 15\text{ km/h} Override speed clamping and direct Loco-to-Loco f_0 UHF radio telemetry, the June 2023 Balasore tragedy demonstrates that an ATP system is only as truthful as the station interlocking feeding it. Technological acceleration of Kavach 4.0 must therefore be paired with uncompromising S&T maintenance discipline, dual-detection point circuitry, and strict physical and cryptographic audit logging of all Electronic Interlocking relay rooms.

Works cited

1. Train Collision Avoidance System TCAS-G620 A scalable KAVACH, https://www.ggtronics.com/tcas-g620.html 2. Kavach 4.0 Railway: First Commissioning, New Features vs 3.2, https://superkalam.com/current-affairs/articles/kavach-4-0-railway-first-commissioning 3. Kavach (train protection system) - Wikipedia, https://en.wikipedia.org/wiki/Kavach_(train_protection_system) 4. TCAS Automatic Train Protction KAVACH in Indian Railway | PDF, https://www.slideshare.net/slideshow/tcas-automatic-train-protction-kavach-in-indian-railway/283013858 5. KAVACH Functional Requirements Spec 4.0 | PDF - Scribd, https://www.scribd.com/document/900502171/Functional-Requirements-Specification-of-KAVACH-RDSO-SPN-196-2020-Version-4-0 6. Functional Requirements Specification of KAVACH RDSO-SPN-196, https://www.scribd.com/document/1054338754/Functional-Requirements-Specification-of-KAVA

CH-RDSO-SPN-196-2020-Version-4-0-1 7. KAVACH System Requirements Specification - Railway Safety - Scribd, https://www.scribd.com/document/842523899/sr5 8. Annexure-A1 - Mode Transition, SOS and MA Handling Amdt-6 16, https://www.scribd.com/document/1003089397/Annexure-A1-Mode-Transition-SOS-and-MA-handling-Amdt-6-16-07-2024-Final-Signed 9. Indian Railways 2024: Major Investments, Enhanced Safety ... - PIB, https://www.pib.gov.in/PressNoteDetails.aspx?NoteId=151988&ModuleId=3 10. Kavach Network Monitoring Protocol | PDF - Scribd, https://www.scribd.com/document/906998131/Annexure-G-Specification-of-Kavach-the-Indian-Railway-ATP-Network-Monitoring-System-Protocol-Amdt-4-16-07-2024-Final-Signed 11. Overview of RDSO in Railway Research | PDF - Scribd, https://www.scribd.com/document/435969192/Final-Handout-48-Cbrr-17-08-2017 12. Vande Bharat (trainset) - Wikipedia, https://en.wikipedia.org/wiki/Vande_Bharat_(trainset) 13. Indian Railways swiftly progressing on its transformational journey, https://www.pib.gov.in/PressReleasePage.aspx?PRID=1991568 14. Railway Accidents & Safety Guidelines | PDF | Rail Transport - Scribd, https://www.scribd.com/document/960149839/S27 15. Indian Railways spent Rs 352 crore on Kavach system so far in, https://infrastructure.newsbharati.com/Encyc/2023/8/3/Indian-Railways-spent-Rs-352-crore-on-Kavach-system-so-far-in-2023-24.html 16. How Kavach and AI Are Strengthening Railway Safety in India, https://www.pib.gov.in/PressReleseDetailm.aspx?PRID=2224380 17. Indian Railways Utilises More Than ?1.14 Lakh Crore Till July 2026, https://www.pib.gov.in/newsite/PrintRelease.aspx?relid=292764 18. HBL Power Systems LTD | PDF | Income Statement | Expense - Scribd, https://www.scribd.com/document/808398742/HBL-Power-Systems-Ltd 19. Loco Kavach Implementation Overview 2024 | PDF - Scribd, https://www.scribd.com/presentation/981465872/MR-PPT-Kavach-Review-31-12-24-ver-17-30-12-24 20. 18 Amend 03 Generic Speed Certificate For Operation 22 LHB Non, https://www.scribd.com/document/1039129336/2026-03-18-Amend-03-Generic-speed-certificate-for-operation-22-LHB-non-AC 21. c&w project work | PDF - Slideshare, https://www.slideshare.net/slideshow/cw-project-work/259837715 22. Why is the Coromandel Express (12841/12842) or the Chennai Mail, https://www.quora.com/Why-is-the-Coromandel-Express-12841-12842-or-the-Chennai-Mail-12839-12840-not-being-hauled-by-SRC-WAP-7-locos-from-HWH-Why-are-these-superfast-trains-not-being-converted-to-modern-LHB-coaches-even-in-2020 23. India's fastest train with a design Speed Of 180 Km/ ph - Facebook, https://www.facebook.com/curlytales/posts/indias-fastest-train-with-a-design-speed-of-180-km-ph/1018269529680519/ 24. 2024-25 - Commission of Railway Safety, https://crs.gov.in/wp-content/uploads/2026/05/Abstract-2024-25-Final-pdf-English-12-5-26complete.pdf 25. म य रेल पुणे मंडल, https://southernrailway.gov.in/srhqpb/home/QuestionBank/CR_PUNE/CR_PUNE_Mech_CW_2018.pdf 26. MSE MJR II C&W final book.pdf - RSKR, https://rskr.irimee.in/sites/default/files/MSE%20MJR%20II%20C%26W%20final%20book.pdf 27. LOK SABHA - Sansad, https://sansad.in/getFile/questionslist/MyFolder/07082024.pdf?source=loksabhadocs 28. When will the present Modi Government wake up to the issue of, https://www.facebook.com/DrAmeeYajnik/posts/when-will-the-present-modi-government-wake-up-to-the-issue-of-railway-safety-in-/739863811490180/ 29. Increase in train accidents worries Indian Railways - The Hindu, https://www.thehindu.com/news/national/increase-in-train-accidents-worries-indian-railways/artic

le66915585.ece 30. Railways To Initiate Measures To Prevent Signal Passed At Danger, https://www.etvbharat.com/en/bharat/railways-to-initiate-measures-to-prevent-signal-passed-at-danger-cases-enn26040804235 31. Zonal Safety Review Report 2024 | PDF | Rail Transport - Scribd, https://www.scribd.com/document/809819503/CRB-VC-Agenda-Dec24 32. UPSC 2025: Kavach ATP, 15th Finance Commission and BRSR, https://anantamias.com/kavach-15th-finance-commission-brsr-upsc-notes/ 33. Railway Safety in India - RICE IAS - Best IAS Coaching in India, https://riceias.com/railway-safety-in-india/ 34. school van collision that killed 4 people, including 3 schoolchildren, https://www.facebook.com/nationalheraldindia/posts/a-railway-gateman-held-after-a-preliminary-inquiry-points-to-his-alleged-neglige/1075154028171511/ 35. Indian Railways Year Book 2022-23 | PDF - Scribd, https://www.scribd.com/document/808598864/Year-Book-2022-23-English 36. INDIAN RAILWAYS YEAR BOOK 2022-23 - The Hindu Centre, https://www.thehinducentre.com/resources/69007872-Year-Book-2022-23-English.pdf 37. Railway Budget Highlights and Key Facts - SATHEE - IIT Kanpur, https://sathee.iitk.ac.in/sathee-railway-exams/student-corner/railway-gk/indian-railway-features/railway-budget-highlights/ 38. Budgetary Allocation for Indian Railways (FY 25-26) - StudyIQ, https://www.studyiq.com/articles/budgetary-allocation-for-indian-railways/ 39. GOVERNMENT OF INDIA MINISTRY OF RAILWAYS RAJYA SABHA, https://sansad.in/getFile/annex/270/AU1699_6aKz1W.pdf?source=pqars 40. Railway Ministry allocates Rs 1112.57 cr for Kavach in 2024-25, https://m.economictimes.com/industry/transportation/railways/railway-ministry-allocates-rs-1112-57-cr-for-kavach-in-2024-25-vaishnaw/articleshow/111993514.cms 41. Kavach Train Protection System Explained: Versions and Facts, https://c4scourses.in/scheme-yojna/kavach-the-shield-of-safety/ 42. Kernex Microsystems completes Kavach 4.0 launch on 207 km high, https://www.sahi.com/news/kernex-microsystems-completes-kavach-4-0-launch-on-207-km-high-speed-north-central-railway-section-3112-PE1_COR 43. NEWS & EVENTS | Kernex Microsystems, https://www.kernex.in/news-events/ 44. Kavach, India's Indigenous Train Protection System, Set For, https://swarajyamag.com/news-brief/kavach-indias-indigenous-train-protection-system-set-for-expansion-and-lte-upgrade-formal-launch-expected-in-12-15-months 45. Quadrant Future Tek Kavach Trial Nod; Shares Surge 10.50%, https://hdfcsky.com/news/quadrant-future-tek-gets-kavach-passenger-trial-approval-shares-surge-10-50-percent 46. India's Rs 2.9 lakh cr railway budget: 3 Small-Caps set to lead Rs, https://www.financialexpress.com/market/stock-insights/indias-rs-2-9-lakh-cr-railway-budget-3-small-caps-set-to-lead-rs-40000-cr-kavach-revolution/4130338/ 47. AK Mahanta, a Senior Section Engineer who was also a part of the, https://www.facebook.com/hindustantimes/posts/ak-mahanta-a-senior-section-engineer-who-was-also-a-part-of-the-odisha-train-cra/10160455139383580/ 48. Signal failure among lapses to blame for Kanchanjunga train mishap, https://www.tribuneindia.com/news/india/signal-failure-among-lapses-to-blame-for-kanchanjunga-train-mishap-probe-640475/ 49. Nothing focuses the nation's collective attention on the Indian, https://www.facebook.com/thehindu/posts/comment-nothing-focuses-the-nations-collective-attention-on-the-indian-railways-/563060972691958/ 50. Tragedy on tracks: 9 killed, 41 hurt in Bengal train accident, https://www.hindustantimes.com/india-news/tragedy-on-tracks-9-killed-41-hurt-in-bengal-train-accident-101718648200514.html 51. Balasore train tragedy result of human error, faults in

signalling,
https://thelivenagpur.com/2023/07/04/balasore-train-tragedy-result-of-human-error-faults-in-signalling-system-crs-report/ 52. Railway Safety and Accident Management | PDF - Scribd,
https://www.scribd.com/document/890203294/s27n-Accident-Safety 53. 'Five-year-old circuit lapse led to train crash' - The New Indian Express,
https://www.newindianexpress.com/states/odisha/2023/Jul/04/five-year-old-circuit-lapse-led-to-train-crash-2591299.html 54. Probe launched to find why goods train exceeded speed limit: NFR,
https://www.millenniumpost.in/big-stories/probe-launched-to-find-why-goods-train-exceeded-speed-limit-nfr-official-568703 55. CRS Probes Deadly Train Collision in West Bengal - Devdiscourse,
https://www.devdiscourse.com/article/business/2989092-crs-probes-deadly-train-collision-in-west-bengal-inquiries-on-speed-breach?amp 56. Probe blames lapses by goods train crew, operating dept | India News,
https://www.business-standard.com/india-news/wb-train-accident-probe-blames-lapses-by-goods-train-crew-operating-dept-124062000457_1.html 57. Railway says multiple lapses caused Kanchanjunga Express,
https://english.mathrubhumi.com/news/india/railway-blames-lapses-kanchanjunga-tragedy-bf873b98 58. KAVACH: India's Indigenous Shield for Railway Safety and Efficiency,
https://ajmaliasacademy.in/kavach-indias-indigenous-shield-for-railway-safety-and-efficiency/ 59. An 'accident-in-waiting': Kanchanjunga Express report cites multiple,
https://timesofindia.indiatimes.com/india/an-accident-in-waiting-kanchanjunga-express-report-cites-multiple-level-lapses/articleshow/111793932.cms 60. Kananjunga express collided with goods train near Rangapani,
https://www.facebook.com/YogeshParikBJPWB/photos/d41d8cd9/868552648651154/ 61. Report blames staff, faulty signals for train accident | India News,
https://www.hindustantimes.com/india-news/report-blames-staff-faulty-signals-for-train-accident-101731006866128.html 62. Kanchanjungha Express train accident June 17 highlights - The Hindu,
https://www.thehindu.com/news/national/kanchanjungha-express-train-accident-highlights-goods-train-west-bengal-new-jalpaiguri/article68299231.ece 63. #Accident at #Kanchanbagh #ps limits - Facebook,
https://www.facebook.com/Sanews2.o/posts/accident-at-kanchanbagh-ps-limits/756959696452581/