Regularized Multivariate Two-way Functional Principal Component Analysis

Mobina Pourmoshir
mobina.pourmoshir@marquette.edu

Department of Mathematical and Statistical Sciences
Marquette University

MARQUETTE UNIVERSITY

BE THE DIFFERENCE.

Outline

1. Introduction & Background
2. A SVD Approach for Regularized Multivariate FPCA
3. Two-way Regularized Multivariate FPCA
4. Conclusion & Future Work

Introduction

- **Functional data** arise when measurements vary continuously over a domain such as time or space, and are naturally viewed as curves rather than isolated points.



Introduction

- **Functional data** arise when measurements vary continuously over a domain such as time or space, and are naturally viewed as curves rather than isolated points.
- Although generated by continuous processes, they are typically observed on discrete grids in applications such as engineering, finance, environmental science, and healthcare.



Introduction

- **Functional data** arise when measurements vary continuously over a domain such as time or space, and are naturally viewed as curves rather than isolated points.
- Although generated by continuous processes, they are typically observed on discrete grids in applications such as engineering, finance, environmental science, and healthcare.
- **Functional Data Analysis (FDA)** models these observations as smooth underlying functions, improving interpretation and analysis of continuous variation.



Introduction

- **Functional data** arise when measurements vary continuously over a domain such as time or space, and are naturally viewed as curves rather than isolated points.
- Although generated by continuous processes, they are typically observed on discrete grids in applications such as engineering, finance, environmental science, and healthcare.
- **Functional Data Analysis (FDA)** models these observations as smooth underlying functions, improving interpretation and analysis of continuous variation.
- **Functional PCA (FPCA)** extends classical PCA to functional data by identifying orthogonal functional components that capture the main modes of variation for dimension reduction [@ramsay2005functional].



Functional Principal Component Analysis

- **Extensions of FPCA:**
  - Smoothed FPCA: Adds roughness penalties [Silverman, 1996, Huang et al., 2008].
  - Sparse FPCA: Enforces sparsity for interpretability [Shen and Huang, 2008, Nie and Cao, 2020].
  - Multivariate FPCA (MFPCA) [Silverman, 1996, Happ and Greven, 2018].
  - Regularized MFPCA: Penalties improve estimation & interpretability [Haghbin et al., 2025].
  - **Two-way functional data:** consist of a data matrix whose row and column domains are both structured. Huang [Jianhua Z. Huang and Buja, 2009] applied regularization to both left and right singular vectors in SVD.

- **Impact:** More adaptable, robust, and applicable across different problems.

Foundations of FPCA through Minimizing Reconstruction Error

- **Goal:** Capture the dominant functional variation in $X \in \mathbb{R}^{n \times m}$ using a low-rank representation, where n is the number of discretized functions and m is the number of grid points. The vector $v \in \mathbb{R}^m$ represents the principal component function, while $u \in \mathbb{R}^n$ gives the corresponding scores.
- **Reconstruction problem:**
$$\min_{u,v} \|X - uv^\top\|_F^2 = \min_{u,v} \operatorname{tr}\{(X - uv^\top)(X - uv^\top)^\top\}.$$
- **Extensions of FPCA via Regularization:**
$$\min_{u,v} \|X - uv^\top\|_F^2 + \mathcal{P}(u, v)$$
  - **Smooth FPCA:** adds roughness penalty on functions.
  - **Sparse FPCA:** adds sparsity penalty on loadings.
- **Algorithms:** Based on iterative **power method** and **thresholding** updates.

Smooth Functional PCA

- **Problem setup** [Huang et al., 2008]: Smooth FPCA estimates a low-rank representation of $X \in \mathbb{R}^{n \times m}$ by solving

$$\min_{u,v} \|X - uv^\top\|_F^2 + \alpha\, v^\top \Omega v,$$

where $u \in \mathbb{R}^n$ denotes the scores, $v \in \mathbb{R}^m$ the loading function, Ω the roughness penalty matrix, and α the smoothing parameter. Define $S(\alpha) = (I + \alpha\Omega)^{-1} \in \mathbb{R}^{m \times m}$.

Smooth Functional PCA

- **Problem setup** [Huang et al., 2008]: Smooth FPCA estimates a low-rank representation of $X \in \mathbb{R}^{n \times m}$ by solving

$$\min_{u,v} \|X - uv^\top\|_F^2 + \alpha\, v^\top \Omega v,$$

where $u \in \mathbb{R}^n$ denotes the scores, $v \in \mathbb{R}^m$ the loading function, Ω the roughness penalty matrix, and α the smoothing parameter. Define $S(\alpha) = (I + \alpha\Omega)^{-1} \in \mathbb{R}^{m \times m}$.

Algorithm: Penalized Power Iteration

1. Initialize v.
2. Repeat until convergence:
   1. $u \leftarrow Xv$
   2. $v \leftarrow S(\alpha) X^\top u$
   3. $v \leftarrow \frac{v}{\|v\|}$
3. Update $X \leftarrow X - \sigma\, uv^\top$ and proceed to next component.

Sparse Functional PCA

- *Standard FPCA may be difficult to interpret and unstable in high-dimensional settings*, since dense components can include noisy and uninformative regions, especially when $m \gg n$.

Sparse Functional PCA

- *Standard FPCA may be difficult to interpret and unstable in high-dimensional settings,* since dense components can include noisy and uninformative regions, especially when $m \gg n$.
- Sparse FPCA incorporates a sparsity penalty $p_\gamma(v)$ [Shen and Huang, 2008]:

$$\min_{u,v} \|X - uv^\top\|_F^2 + p_\gamma(v) \tag{1}$$

Sparse Functional PCA

- *Standard FPCA may be difficult to interpret and unstable in high-dimensional settings,* since dense components can include noisy and uninformative regions, especially when $m \gg n$.
- Sparse FPCA incorporates a sparsity penalty $p_\gamma(v)$ [Shen and Huang, 2008]:

$$\min_{u,v} \|X - uv^\top\|_F^2 + p_\gamma(v) \tag{1}$$

Algorithm: sFPCA-rSVD

1. Initialization: Compute the best rank-one approximation of X using SVD
2. Iterate until convergence:
   1. Update Left Singular Vector: $u \leftarrow Xv$
   2. Update Right Singular Vector: $v \leftarrow h_\gamma X^\top u$
   3. Normalize Right Singular Vector: $v \leftarrow \frac{v}{\|v\|}$

Cross-Validation for Sparsity Selection

- **Sparsity parameter**: Tuning parameter γ controlling number of non-zero loadings in v ($0 =$ dense, $m =$ full sparsity).

Algorithm: K-fold CV Tuning Parameter Selection - Degree of sparsity

1. Randomly group the rows of side-by-side data matrix X into K roughly equal-sized groups, denoted as $X^1, ..., X^K$.
2. For each sparse tuning parameter $j \in \{0, 1, ..., m\}$ (level of sparsity), do the following:
   1. For $k = 1, ..., K$, let X^{-k} be the data matrix X leaving out X^k. Apply Algorithm sFPCA-rSVD on X^{-k} and derive the FPC scores $u^{-k}(j)$. Then project X^k onto $u^{-k}(j)$ to obtain $v^k(j)$.
   2. Calculate the K-fold CV scores defined as: (N is the number of grid points in X^k)
$$CV_j = \sum_{k=1}^{K} \frac{\|X^k - u^{-k}(j)v^k(j)\|^2}{N}$$
3. Select the degree of sparsity as $j_0 = \arg\min\{CV(j)\}$.

Overview of Existing Approaches

- **Smooth FPCA:**
  - Pros: Produces smooth eigenfunctions.
  - Algorithm: Penalized power iteration.
  - Tuning: α (smoothness) via GCV.
- **Sparse FPCA:**
  - Pros: Feature selection $\rightarrow$ interpretable.
  - Algorithm: sFPCA-rSVD algorithm.
  - Tuning: γ (sparsity) via CV.
- **Combined Approaches:** Smooth + Sparse together.

$$\min_{u,v} \|X - uv^\top\|_F^2 + \alpha v^\top \Omega v + p_\gamma(v)$$

Regularized MFPCA

- **Context**
  - Univariate FDA → **Multivariate FDA** → joint modes of variation across functions



Regularized MFPCA

- **Context**
  - Univariate FDA $\rightarrow$ **Multivariate FDA** $\rightarrow$ joint modes of variation across functions
- **Challenges**
  - Discretization & irregular grids $\rightarrow$ noise, missing data
  - High dimensionality and limited sample size $\rightarrow$ unstable eigenfunctions
  - Cross-function correlation $\rightarrow$ requires enforcing smoothness both within and across functions
- **Proposed Solution: Penalized SVD**
  - **Smoothness penalties**: roughness on derivatives
  - **Sparsity penalties**: Soft, hard, or SCAD
  - **Block-diagonal roughness matrix** for cross-function structure
- **Impact**
  - Produces **smooth, sparse, interpretable** joint modes
  - More stable & applicable to high-dimensional multivariate FDA

Methodology: Multivariate Functional Data Framework

- A multivariate functional dataset is formed by **concatenating** p **functional data matrices**.
  - Each variable: $X_i \in \mathbb{R}^{n \times m_i}$ where n: number of observations and m_i: grid points
- **Rank-one approximation** (per variable):

$$X_i \approx u_i v_i^\top, \quad u_i \in \mathbb{R}^n, \; v_i \in \mathbb{R}^{m_i}$$

Methodology: Multivariate Functional Data Framework

- A multivariate functional dataset is formed by **concatenating** p **functional data matrices**.
  - Each variable: $X_i \in \mathbb{R}^{n \times m_i}$ where n: number of observations and m_i: grid points
- **Rank-one approximation** (per variable):

$$X_i \approx u_i v_i^\top, \quad u_i \in \mathbb{R}^n, \; v_i \in \mathbb{R}^{m_i}$$

- **Full data matrix**: $\mathbf{X} = \begin{bmatrix} X_1 & X_2 & \cdots & X_p \end{bmatrix}$

$$\mathbf{X} = \begin{bmatrix} x_{11}(t_{11}) & \cdots & x_{11}(t_{1m_1}) & \cdots & x_{1p}(t_{p1}) & \cdots & x_{1p}(t_{pm_p}) \\ \vdots & \ddots & \vdots & \ddots & \vdots & \ddots & \vdots \\ x_{n1}(t_{11}) & \cdots & x_{n1}(t_{1m_1}) & \cdots & x_{np}(t_{p1}) & \cdots & x_{np}(t_{pm_p}) \end{bmatrix}$$

Penalized Smooth MFPCA

- Standard FPCA loadings may be noisy; smoothness penalties (via block-diagonal Ω_i) improve structure and interpretability.
- Let $\boldsymbol{X} \in \mathbb{R}^{n \times M}$ denote multivariate functional data, where $M = \sum_{i=1}^{p} m_i$.
  Its best rank-one approximation is $\boldsymbol{X} \approx uv^\top$,
  with $u \in \mathbb{R}^n$ (score vector) and $v = [v_1, v_2, ..., v_p]^\top \in \mathbb{R}^M$ (loading vector).
  A smoothness penalty is imposed on v.

Penalized Smooth MFPCA

- Standard FPCA loadings may be noisy; smoothness penalties (via block-diagonal Ω_i) improve structure and interpretability.
- Let $\boldsymbol{X} \in \mathbb{R}^{n \times M}$ denote multivariate functional data, where $M = \sum_{i=1}^{p} m_i$.
  Its best rank-one approximation is $\boldsymbol{X} \approx uv^\top$,
  with $u \in \mathbb{R}^n$ (score vector) and $v = [v_1, v_2, ..., v_p]^\top \in \mathbb{R}^M$ (loading vector).
  A smoothness penalty is imposed on v.
- The block-diagonal penalty matrix is $\boldsymbol{\Omega} = \mathrm{diag}(\Omega_1, \Omega_2, \ldots, \Omega_p)$, where each $\Omega_i \in \mathbb{R}^{m_i \times m_i}$ is a univariate roughness penalty matrix.

Penalized Smooth MFPCA

- Standard FPCA loadings may be noisy; smoothness penalties (via block-diagonal Ω_i) improve structure and interpretability.
- Let $\boldsymbol{X} \in \mathbb{R}^{n \times M}$ denote multivariate functional data, where $M = \sum_{i=1}^{p} m_i$.
  Its best rank-one approximation is $\boldsymbol{X} \approx uv^\top$,
  with $u \in \mathbb{R}^n$ (score vector) and $v = [v_1, v_2, ..., v_p]^\top \in \mathbb{R}^M$ (loading vector).
  A smoothness penalty is imposed on v.
- The block-diagonal penalty matrix is $\boldsymbol{\Omega} = \mathrm{diag}(\Omega_1, \Omega_2, \ldots, \Omega_p)$, where each $\Omega_i \in \mathbb{R}^{m_i \times m_i}$ is a univariate roughness penalty matrix.
- The penalized reconstruction error is

$$\min_{u,v} \|\boldsymbol{X} - uv^\top\|_F^2 + \boldsymbol{\alpha}^\top (v^\top \boldsymbol{\Omega} v),$$

  where $\boldsymbol{\alpha} = (\alpha_1, \ldots, \alpha_p)^\top$ controls smoothness.

MFPCA Power Algorithm

Algorithm: Regularized Power Iteration for Smooth MFPCA

1. Initialize v.
2. Repeat until convergence:
   1. $u \leftarrow \mathbf{X}v$
   2. $v \leftarrow \boldsymbol{S}(\boldsymbol{\alpha})\mathbf{X}^\top u$
   3. $v \leftarrow v/\|v\|$
3. Update $\mathbf{X} \leftarrow \mathbf{X} - \sigma uv^\top$ to extract the next PC.

- The smoothing operator is $\boldsymbol{S}(\boldsymbol{\alpha}) = (I + \boldsymbol{\alpha}\boldsymbol{\Omega})^{-1} \in \mathbb{R}^{M\times M}$.

MFPCA Power Algorithm

Algorithm: Regularized Power Iteration for Smooth MFPCA

1. Initialize v.
2. Repeat until convergence:
   1. $u \leftarrow \mathbf{X}v$
   2. $v \leftarrow \boldsymbol{S}(\boldsymbol{\alpha})\mathbf{X}^\top u$
   3. $v \leftarrow v/\|v\|$
3. Update $\mathbf{X} \leftarrow \mathbf{X} - \sigma uv^\top$ to extract the next PC.

- The smoothing operator is $\boldsymbol{S}(\boldsymbol{\alpha}) = (I + \boldsymbol{\alpha}\boldsymbol{\Omega})^{-1} \in \mathbb{R}^{M\times M}$.
- The smoothing parameter $\boldsymbol{\alpha}$ is selected via generalized cross-validation (GCV), defined as

$$\mathrm{GCV}(\boldsymbol{\alpha}) = \frac{1}{M}\frac{\|(I - \boldsymbol{S}(\boldsymbol{\alpha}))(\mathbf{X}^T u)\|^2}{\left(1 - \frac{1}{M}\mathrm{tr}\{\boldsymbol{S}(\boldsymbol{\alpha})\}\right)^2}. \tag{2}$$

Penalized Sparse Multivariate FPCA

- **Goal:** Extend sparse FPCA to multivariate functional data, imposing **sparsity** (select important regions) and **smoothness** (reduce noise).
- **Sparsity penalties:** Soft, hard, or SCAD thresholding Shen and Huang [2008], Zhenhua Lin and Wang [2017], Nie and Cao [2020].

Penalized Sparse Multivariate FPCA

- **Goal:** Extend sparse FPCA to multivariate functional data, imposing **sparsity** (select important regions) and **smoothness** (reduce noise).
- **Sparsity penalties:** Soft, hard, or SCAD thresholding Shen and Huang [2008], Zhenhua Lin and Wang [2017], Nie and Cao [2020].
- Sparsity parameters: $\boldsymbol{\gamma} = (\gamma_1, \ldots, \gamma_p)$, where γ_i ranges from 0 (no sparsity) to m_i for each variable.

Algorithm: Regularized Power Iteration for Sparse MFPCA

1. Initialization: Compute rank-one SVD of $\boldsymbol{X}$, $\boldsymbol{X} \approx duv^\top$, and set $u \leftarrow du$.
2. Iterate until convergence:
   1. Update left singular vector: $u \leftarrow \boldsymbol{X}v$
   2. Update right singular vector: $v \leftarrow \boldsymbol{h}_{\boldsymbol{\gamma}} \boldsymbol{X}^\top u$
   3. Normalize right singular vector: $v \leftarrow \dfrac{v}{\|v\|}$

Smooth and Sparse Multivariate FPCA

- The combined implementation of smoothness and sparsity on the loading vector v in multivariate functional data is achieved by the following algorithm:

Algorithm: Regularized Power Iteration for Smooth MFPCA

1. Initialize unit vectors u and v using SVD of $\boldsymbol{X}$ (best rank-one approximation of $\boldsymbol{X}$)
2. Repeat till convergence
   1. $u \leftarrow \boldsymbol{X} v$
   2. $v \leftarrow \boldsymbol{S}(\alpha)\boldsymbol{h}(\gamma_{\boldsymbol{v}})\boldsymbol{X}^\top u$
   3. $v \leftarrow \frac{v}{\|v\|}$
3. Update $\boldsymbol{X} = \boldsymbol{X} - \sigma u v^\top$ and proceed to find the next principal component.

- Algorithm CV Tuning for Sparsity and equation (2) are used to tune the sparsity level via K-fold CV and the smoothing parameter via GCV, respectively.

Simulation: Estimation Performance

- **Data-generating process:** Two functional variables:

$$X_{ij}^{(1)} = u_{i1} v_{11}(t_j) + u_{i2} v_{12}(t_j) + \epsilon_{ij}^{(1)}, \quad X_{ij}^{(2)} = u_{i1} v_{21}(t_j) + u_{i2} v_{22}(t_j) + \epsilon_{ij}^{(2)},$$

  - where $u_{i1} \sim N(0, \sigma_1^2)$, $u_{i2} \sim N(0, \sigma_2^2)$, $\epsilon_{ij}^{(k)} \sim N(0, \sigma^2)$, and $n = m = 101$, $t_j \in [-1, 1]$

Simulation: Estimation Performance

- **Data-generating process:** Two functional variables:

$$X_{ij}^{(1)} = u_{i1} v_{11}(t_j) + u_{i2} v_{12}(t_j) + \epsilon_{ij}^{(1)}, \quad X_{ij}^{(2)} = u_{i1} v_{21}(t_j) + u_{i2} v_{22}(t_j) + \epsilon_{ij}^{(2)},$$

  - where $u_{i1} \sim N(0, \sigma_1^2)$, $u_{i2} \sim N(0, \sigma_2^2)$, $\epsilon_{ij}^{(k)} \sim N(0, \sigma^2)$, and $n = m = 101$, $t_j \in [-1, 1]$

- **True functional PCs:**
  - Variable 1: $v_{11}(t) = \frac{t + \sin(\pi t)}{s_1}$, $\quad v_{12}(t) = \frac{\cos(3\pi t)}{s_2}$
  - Variable 2:

$$v_{21}(t) = \begin{cases} \dfrac{\sin(3\pi t)}{s_3}, & t \in (-\frac{1}{3}, \frac{1}{3}), \\ 0, & \text{otherwise}, \end{cases} \qquad v_{22}(t) = \begin{cases} \dfrac{\sin(2\pi t)}{s_4}, & t \leq -\frac{1}{3}, \\ \dfrac{\sin(\pi t)}{s_4}, & t \geq \frac{1}{3}, \\ 0, & \text{otherwise}. \end{cases}$$

Here, s_1, s_2, s_3, s_4 are normalizing constants ensuring unit L^2 norm.

Simulation: Estimation Performance

Scenarios tested:

1. Unpenalized Multivariate SVD (baseline)
2. Smoothed Multivariate SVD (smoothness penalty)
3. Sparse Multivariate SVD (sparsity penalty)
4. Sparse + Smoothed Multivariate SVD (combined regularization)

Simulation: Estimation Performance

Scenarios tested:

1. Unpenalized Multivariate SVD (baseline)
2. Smoothed Multivariate SVD (smoothness penalty)
3. Sparse Multivariate SVD (sparsity penalty)
4. Sparse + Smoothed Multivariate SVD (combined regularization)



(a) MFPCA

Simulation: Estimation Performance

Scenarios tested:

1. Unpenalized Multivariate SVD (baseline)
2. Smoothed Multivariate SVD (smoothness penalty)
3. Sparse Multivariate SVD (sparsity penalty)
4. Sparse + Smoothed Multivariate SVD (combined regularization)



(a) MFPCA (b) Smoothed MFPCA

Simulation: Estimation Performance

Scenarios tested:

1. Unpenalized Multivariate SVD (baseline)
2. Smoothed Multivariate SVD (smoothness penalty)
3. Sparse Multivariate SVD (sparsity penalty)
4. Sparse + Smoothed Multivariate SVD (combined regularization)



Simulation: Estimation Performance

Scenarios tested:

1. Unpenalized Multivariate SVD (baseline)
2. Smoothed Multivariate SVD (smoothness penalty)
3. Sparse Multivariate SVD (sparsity penalty)
4. Sparse + Smoothed Multivariate SVD (combined regularization)



(a) MFPCA (b) Smoothed MFPCA (c) Sparse MFPCA (d) Smoothed and Sparse MFPCA

Simulation: Estimation Performance

- **Performance across four methods (SVD, Smooth, Sparse, Smooth+Sparse):**
  - Smoothness and/or sparsity **reduce MSE** compared to unregularized SVD.
  - **Smooth+Sparse** yields lowest error and most stable estimates.
  - Smooth estimator performs consistently well; sparsity alone less effective (esp. for PC2).
  - Joint regularization achieves best **bias–variance tradeoff**.



PC1: Quartiles and Mean log10(MSE)

Method	Q1	Median	Mean	Q3
SVD	-3.41	-3.35	-3.34	-3.28
Smooth	-4.07	-3.96	-3.92	-3.82
Sparse	-3.57	-3.50	-3.49	-3.43
Smooth+Sparse	**-4.38**	**-4.28**	**-4.22**	**-4.14**

PC2: Quartiles and Mean log10(MSE)

Method	Q1	Median	Mean	Q3
SVD	-2.84	-2.79	-2.79	-2.75
Smooth	-3.56	-3.48	-3.47	-3.40
Sparse	-2.83	-2.79	-2.79	-2.75
Smooth+Sparse	**-3.59**	**-3.50**	**-3.49**	**-3.42**

Application: Household Power Consumption

- **Dataset:** Bivariate functional data including active power and voltage consumption [Hebrail and Berard, 2012] for one household between December 2006 and November 2010.

- Regularization reduces noise while preserving the dominant daily consumption patterns, enhancing interpretability without losing key structure.



First 3 PCs: MFPCA (red) vs ReMFPCA (black)

Two-way Regularized MFPCA

- **Two-way functional data:** A data matrix whose row and column domains are both structured. Observations vary along these two domains, with applications in climate science, neuroscience, etc.
- **Limitation of standard FPCA [Ramsay and Silverman, 2005]:**
  - Focuses on one domain (often time).
  - Penalties applied only to loadings → ignores structure in second domain.
  - Results may be rough or overly dense along the unpenalized axis.





Two-way Regularized MFPCA

- **Two-way functional data:** A data matrix whose row and column domains are both structured. Observations vary along these two domains, with applications in climate science, neuroscience, etc.
- **Limitation of standard FPCA [Ramsay and Silverman, 2005]:**
  - Focuses on one domain (often time).
  - Penalties applied only to loadings $\rightarrow$ ignores structure in second domain.
  - Results may be rough or overly dense along the unpenalized axis.
- **Two-way FPCA [Jianhua Z. Huang and Buja, 2009]:**
  - Introduced **smoothness penalties** on both scores and loadings.
  - Produces coherent, interpretable *component surfaces* instead of jagged approximations.
- **Our contribution:**
  - Extend to **two-way multivariate functional data** (multiple functional variables).
  - Combine **smoothness + sparsity penalties** in both directions.
  - Result: Low-rank, interpretable, noise-robust PCs for high-dimensional applications.

Two-way Smoothed MFPCA: Setup & Penalty

- Two-way multivariate functional data: $\boldsymbol{X} \in \mathbb{R}^{n \times M}, \quad M = \sum_{i=1}^{p} m_i$.
- Roughness matrices: $\boldsymbol{\Omega}_u \in \mathbb{R}^{n \times n}$, $\boldsymbol{\Omega}_v \in \mathbb{R}^{M \times M}$ (symmetric, non-negative definite).
- Smoothers: $\boldsymbol{S}_u(\alpha_u) = (I + \alpha_u \boldsymbol{\Omega}_u)^{-1}, \qquad \boldsymbol{S}_v(\boldsymbol{\alpha}_v) = (I + \boldsymbol{\alpha}_v \boldsymbol{\Omega}_v)^{-1}$.

Two-way Smoothed MFPCA: Setup & Penalty

- Two-way multivariate functional data: $\boldsymbol{X} \in \mathbb{R}^{n \times M}$, $\quad M = \sum_{i=1}^{p} m_i$.
- Roughness matrices: $\boldsymbol{\Omega}_u \in \mathbb{R}^{n \times n}$, $\boldsymbol{\Omega}_v \in \mathbb{R}^{M \times M}$ (symmetric, non-negative definite).
- Smoothers: $\boldsymbol{S}_u(\alpha_u) = (I + \alpha_u \boldsymbol{\Omega}_u)^{-1}, \qquad \boldsymbol{S}_v(\boldsymbol{\alpha}_v) = (I + \boldsymbol{\alpha}_v \boldsymbol{\Omega}_v)^{-1}$.
- Penalized rank-one reconstruction:

$$\min_{u,v} \|\boldsymbol{X} - uv^\top\|_F^2 + \mathcal{P}(u, v)$$

- Penalty [Jianhua Z. Huang and Buja, 2009]:
  $\mathcal{P}(u, v; \alpha_u, \boldsymbol{\alpha}_v) = u^\top(\alpha_u \boldsymbol{\Omega}_u)u\,\|v\|^2 + \|u\|^2\, v^\top(\boldsymbol{\alpha}_v \boldsymbol{\Omega}_v)v + u^\top(\alpha_u \boldsymbol{\Omega}_u)u\; v^\top(\boldsymbol{\alpha}_v \boldsymbol{\Omega}_v)v$.
- Multivariate v: $\boldsymbol{\Omega}_v = \mathrm{diag}(\Omega_1, \ldots, \Omega_p)$.

Two-way Smooth + Sparse MFPCA

- **Goal:** Extract components that are **low-rank, smooth, and sparse**.
  - Smoothness $\rightarrow$ coherent variation across subjects & functions.
  - Sparsity $\rightarrow$ highlights key observations & time regions.
- **Novelty:** First framework to combine **both** in two-way functional data.

Two-way Smooth + Sparse MFPCA

- **Goal:** Extract components that are **low-rank, smooth, and sparse**.
  - Smoothness $\rightarrow$ coherent variation across subjects & functions.
  - Sparsity $\rightarrow$ highlights key observations & time regions.
- **Novelty:** First framework to combine **both** in two-way functional data.
- Data matrix $\boldsymbol{X}$: seek u, v solving:

$$\min_{u,v} \|\boldsymbol{X} - uv^\top\|_F^2 + \sum_{j}^{J} \mathcal{P}_j^{[\theta]}(u, v)$$

- J is the number of penalty components, and θ is the vector of all tuning parameters.
- The composite penalty $\sum_{j=1}^{J} \mathcal{P}_j^{(\theta)}(u, v)$ lets us mix regularizers, e.g., smoothness with $\theta = (\alpha_u, \boldsymbol{\alpha}_v)$ and sparsity with $\theta = (\gamma_u, \boldsymbol{\gamma}_v)$ (controlling sparsity), and can include other structures as needed.

Sequential Power Algorithm

Algorithm: Two-way Smooth + Sparse MFPCA (Sequential Power)

1. Initialization: Rank-one SVD of $\boldsymbol{X}$: $\boldsymbol{X} \approx s\, u^{(0)} v^{(0)\top}$; set $u \leftarrow s\, u^{(0)}$, $v \leftarrow v^{(0)}$.
2. Repeat until convergence:
   1. $u \leftarrow \boldsymbol{S}_u^{[\alpha_u]}\, \boldsymbol{h}_u^{[\gamma_u]}(\boldsymbol{X}\, v)$
   2. $v \leftarrow \boldsymbol{S}_v^{[\boldsymbol{\alpha}_v]}\, \boldsymbol{h}_v^{[\gamma_v]}(\boldsymbol{X}^\top u)$
   3. $v \leftarrow v / \|v\|$
3. $\boldsymbol{X} \leftarrow \boldsymbol{X} - \sigma\, u\, v^\top$ to extract the next component.

- Smoothness parameters are selected with conditional GCV, while sparsity parameters are chosen via cross-validation (CV).

Selection of Regularization Parameters

- Four sets of tuning parameters:
  - α_u: smoothness of u, γ_u: sparsity of u
  - $\boldsymbol{\alpha}_v$: smoothness of v, $\boldsymbol{\gamma}_v$: sparsity of v
- **Challenge:** Ordering of tuning (smoothness vs. sparsity) affects convergence and solutions.

Selection of Regularization Parameters

- Four sets of tuning parameters:
  - α_u: smoothness of u, γ_u: sparsity of u
  - $\boldsymbol{\alpha}_v$: smoothness of v, $\boldsymbol{\gamma}_v$: sparsity of v
- **Challenge:** Ordering of tuning (smoothness vs. sparsity) affects convergence and solutions.
- **Strategy: Conditional tuning**
  1. Initialize all penalties at 0.
  2. Tune γ_u via K-fold CV.
  3. Sequentially tune $\gamma_{v,i}$ using Algorithm:Two-way Smooth + Sparse MFPCA.
  4. With sparsity fixed, tune α_u by GCV.
  5. Tune $\alpha_{v,i}$ using two-way GCV.
  6. Iterate steps 2–5 until stable.
- This alternating scheme **isolates sparsity vs. smoothness** while ensuring accuracy + interpretability.

Chessboard

True Chessboard



Chessboard

True Chessboard



Noisy Chessboard



Chessboard

True Chessboard



PCA with SVD



First PC Scores (u) Comparison

Noisy Chessboard



First PC (v) Comparison



Chessboard

True Chessboard



PCA with SVD



First PC Scores (u) Comparison



Noisy Chessboard



PCA with Smoothness Penalty



First PC (v) Comparison



Chessboard

True Chessboard



PCA with SVD



PCA with Group Lasso Penalty



First PC Scores (u) Comparison



Noisy Chessboard



PCA with Smoothness Penalty



First PC (v) Comparison



Chessboard


True Chessboard
PCA with SVD
PCA with Group Lasso Penalty
First PC Scores (u) Comparison
SVD
Smooth
Group Lasso
Group Lasso & Smooth
Noisy Chessboard
PCA with Smoothness Penalty
PCA with Group Lasso and Smoothness Penalties
First PC (v) Comparison
SVD
Smooth
Group Lasso
Group Lasso & Smooth

Simulation Results (SVD)



Simulation Results (Smoothness and Sparsity on v)



Simulation Results (Smoothness and Sparsity on u)



Simulation Results (Two-Way Smoothness)

Simulation Results (Two-Way Sparsity)



Simulation Results (Two-way Sparsity and Smoothness)



Application: Motion Sense Data

- **Dataset:** Acceleration and pitch from 24 people, 4 activities (jogging, walking, sitting, standing), about 2–3 min each.
- **Goal:** Compare SVD vs **two-way sparse + smooth ReMFPCA** on these multivariate functional signals.
- **Rescaling [Happ and Greven, 2018]:** balance variables so each contributes equally.

$$\hat{w}_j = \left(\frac{1}{m} \sum_{i=1}^{m} \widehat{\mathrm{Var}}(X_j(t_i)) \right)^{-1}, \qquad \tilde{X}_j(t_i) = \hat{w}_j^{1/2} X_j(t_i).$$

- **Penalties used:** smoothness + sparsity on loadings v; sparsity on scores u.

Results: Functional PCs (SVD vs ReMFPCA)



- **SVD (gray):** noisy, high-frequency wiggles.
- **ReMFPCA (black):** smoother, more interpretable PCs capturing dominant structure.

Results: PC Scores and Interpretation





- Sparsity on scores: **PC1 scores for walking about 0** (partially standing too).
- Interpretation: walking contributes little to PC1; removing it **improves interpretability** without hurting fit.
- Takeaway: **Two-way smooth + sparse ReMFPCA** yields cleaner PCs and activity-informative scores.

Conclusion & Future Work

- **Unified FPCA Framework**
  - Combines **smoothness** (denoise, interpretability) + **sparsity** (variable selection).
  - Extends from **univariate** → **multivariate** → **two-way functional data**.
- **Methodology**
  - Penalized SVD with roughness + ℓ_1 penalties.
  - Two-way regularization: smoothness & sparsity on both **scores (u)** and **loadings (v)**.
  - Efficient parameter tuning: **conditional GCV** & **K-fold CV** (with 1-SE rule).
- **Results**
  - Simulations & applications (mortality, call-center, image data).
  - Outperforms one-way or single-penalty methods.
  - Produces **low-rank, denoised, interpretable components**.

Accessible Implementation: R Package & Future Work

- Implemented in **R package `ReMPCA` (GitHub)**
  - Univariate & multivariate FPCA with penalties.
  - Two-way MFPCA for matrix-valued functions.
  - Automated tuning (CV, GCV, 1-SE rule).
  - Diagnostic tools: variance explained, visualization, heatmaps.
  - Early support for **hybrid data (scalar + functional + image)**.
- **Hybrid Data Extensions**
  - Image–Functional Hybrid PCA $\rightarrow$ simultaneous dimension reduction.
  - Scalar–Functional Integration $\rightarrow$ joint low-dim space.
  - Nonlinear Extensions $\rightarrow$ kernel FPCA, neural nets.
- **Applications:**
  - Neuroimaging
  - Personalized medicine
  - Environmental monitoring

  Takeaway: Smooth + sparse + two-way FPCA offers a **theoretical foundation, practical algorithms, and open software** to enable next-generation functional data analysis.

References

Hossein Haghbin, Yue Zhao, and Mehdi Maadooliat. Regularized multivariate functional principal component analysis for data observed on different domains. *Foundations of Data Science*, 2025. doi: 10.3934/fods.2025018. URL https://www.aimsciences.org/article/id/68b562c1bd10eb1421fa6ef0.

Clara Happ and Sonja Greven. Multivariate functional principal component analysis for data observed on different (dimensional) domains. *Journal of the American Statistical Association*, 113(522):649–659, February 2018. ISSN 1537-274X.

Georges Hebrail and Alice Berard. Individual household electric power consumption. UCI Machine Learning Repository, 2012.

Jianhua Z. Huang, Haipeng Shen, and Andreas Buja. Functional principal components analysis via penalized rank one approximation. *Electronic Journal of Statistics*, 2:678 – 695, 2008. doi: 10.1214/08-EJS218.

Haipeng Shen Jianhua Z. Huang and Andreas Buja. The analysis of two-way functional data using two-way regularized singular value decompositions. *Journal of the American Statistical Association*, 104(488):1609–1620, 2009.

Yunlong Nie and Jiguo Cao. Sparse functional principal component analysis in a new regression framework. *Computational Statistics & Data Analysis*, 152:107016, 2020. ISSN 0167-9473.

J. Ramsay and B.W. Silverman. *Functional Data Analysis*. Springer Series in Statistics. Springer, 2005. ISBN 9780387400808.

Haipeng Shen and Jianhua Z. Huang. Sparse principal component analysis via regularized low rank matrix approximation. *Journal of Multivariate Analysis*, 99(6): 1015–1034, 2008. ISSN 0047-259X.

Bernard W Silverman. Smoothed functional principal components analysis by choice of norm. *The Annals of Statistics*, 24(1):1–24, 1996.

Liangliang Wang Zhenhua Lin, Jiguo Cao and Haonan Wang. Locally sparse estimator for functional linear regression models. *Journal of Computational and Graphical Statistics*, 26(2):306–318, 2017.

Thank you!

MARQUETTE UNIVERSITY

BE THE DIFFERENCE.