

Ring Main Unit

The best solution for Power Distribution



P-Sec 12KV

SF6 Ring Main Unit

PSEC12(3+1+M)

A Compact Switchgear Solution for Secondary Power Distribution Networks

OFFER NO	PL-2026-0001
DATE	2026-06-07
PROJECT	Deploy Test
CUSTOMER	Vercel Check

General Data / Type of apparatus

Type	RMU - Powerline
Application	Standard IEC 62271-200
Type of apparatus	Switch disconnecter type SF6
Packing	Domestic
Ambient temperature	For working: from -5 °C to +40 °C / For storage: -5 °C
Altitude	Altitude for installation above sea level: under 1,000 m
Humidity	Relative humidity: max. 95 %
FAT	Powerline standard FAT (One day)
Protection index	IP3x on front face
Internal Arc Classification (IAC)	Front Accessibility (AF)
Switchgear color	RAL 7035
Busbars treatment	insulated

Electrical Data

Rated voltage	12kV
Service voltage	11kV
Power frequency withstand voltage	28kV
BIL	75kV
Rated frequency	50Hz
Rated busbar current	630A
Rated short circuit current	25kA
Rated short circuit current duration	1s
Peak current	63kA

Additional Data

Pressure indicator for switch disconnecter	With Manometer
Flag Relays (AC/DC Loss – Any MCB Trip – SF6 Leakage/Low Gas)	Yes
Limit Switch 220V, 5A	Yes

General Notes

- Earthing switch is interlocked with LBS operation.
- Mechanical interlocking is provided between any cell door and the earthing switch.
- Mimic panel for LBS and earthing-switch position indication is provided.

Ring Main Unit Structure

QTY 3 Cubical: QPSC (Powerline LBS Cubical)-630A(554*1070*1700)mm², each consisting of:

QTY	DESCRIPTION
1	Cubical type: SF6 LBS LSC2A – load break Switch disconnecter unit
1	Cable entry for 1-phase cables up to 300 mm ² (Single core)
1	Voltage presence indicator with fixed lamps type VPIS
1	Anti-condensation heater for cable compartment 230VAC with MCB
1	Internal light
1	Insulated bar
1	G-Sec – ABB Three position switch-disconnector with earthing switch and 1-spring operating device
1	low voltage compartment
1	Earth fault indicator

QTY 1 Cubical: QPSF (Powerline LBS Cubical)-630A(554*1070*1700)mm², each consisting of:

QTY	DESCRIPTION
1	Cubical type: SF6 LBS.F, LSC2A- Load break Switch with fuse combination unit with cable
1	Cable entry for 1-phase cables up to 95 mm ² (Single core)
1	Voltage presence indicator with fixed lamps type VPIS
1	Operating Handle for Switch-disconnector and Earthing switch
1	Anti-condensation heater for cable compartment 230VAC with MCB
1	Internal light
1	Insulated bar
1	G-Sec – ABB Three position switch-disconnector with earthing switch and 2-spring operating device
1	3 MV fuse 12 kV – up to 100 A – P&C
1	Downstream earthing switch with limited making capacity (2kA)
1	Fuse base
1	Fuse tripping
1	Indication of fuse status
1	Low voltage compartment

QTY 1 Cubical: PMC (Powerline Measurement Cubical)-630A (500*1070*1700)mm², each consisting of:

QTY	DESCRIPTION
1	Cubical type: measurement, LSC2A – Universal Metering Panel
1	Sealable door lock
1	Insulated bar
1	Low voltage compartment
3	Generic Cast Epoxy DIN CT X KV, Ip=X A (X: to be determined by the client)
3	Core1: X/5; 10-15 VA; CL 0.5; fs 5; Frequency: 50Hz
3	Voltage Transformer Phase-earth
3	Core 1: Us=11000/" 3 : 110/" 3 V; 50-100 VA; CL 0.5
3	Ammeter ; CL0.5
1	Voltmeter ; CL0.5
1	Selector 7 position