CRA Article 14 Reporting Kit: Lite

A decision guide and a 24-hour early-warning template for manufacturers of connected products.

Version 1.0 · 12 November 2026 · Free edition

11 Sep 2026
Article 14 reporting duty applies to manufacturers

24 h
Early warning, counted from the moment you become aware

72 h
Detailed notification, counted from awareness

What this kit is for

Since 11 September 2026, manufacturers of products with digital elements must report two kinds of event through ENISA's Single Reporting Platform: **actively exploited vulnerabilities** and **severe incidents**. The duty also covers products placed on the market before the Act's main obligations start on 11 December 2027. A security policy is not a runbook for the first 24 hours. This kit gives you the questions to ask and the page to fill in.

The reporting clock

Stage	Actively exploited vulnerability	Severe incident
Early warning	Within 24 hours of awareness	Within 24 hours of awareness
Notification	Within 72 hours of awareness	Within 72 hours of awareness
Final report	No later than 14 days after a corrective or mitigating measure is available	Within one month of the 72-hour notification

Where and to whom you report

- Through ENISA's Single Reporting Platform (SRP). One submission reaches both ENISA and the coordinating CSIRT you select.
- The platform launched in English only, with no API: reports are entered through the web form.
- Only the manufacturer can submit a mandatory notification. Anyone else should contact their national CSIRT.

Awareness is the trigger. You do not wait for a finished root-cause analysis. The early warning carries what you know at hour 24.

Read this first. This kit is a practical aid, not legal advice. It summarises ENISA's published FAQ and third-party guides as of 12 November 2026. Rules and platform fields can change: check the Regulation (EU) 2024/2847 text and ENISA's pages before you file.

Do we have to report this?

Work through the four questions in order, as soon as someone on your team raises a possible exploit or incident.

1

Are we the manufacturer of the product?

YES Go to question 2. NO You cannot file the mandatory report. Contact your national CSIRT directly.

2

Is it a product with digital elements that is, or was, on the EU market?

Hardware or software with a data connection counts, including products you sold before 11 December 2027.

YES Go to question 3. NO / UNSURE Check scope and exemptions in the Regulation before closing the case.

3

Is there reliable evidence that someone exploited a vulnerability in our product without the owner's permission?

YES This is an **actively exploited vulnerability**: go to "Start now". One check first: a third-party guide states that exploitation you already knew about before 11 September 2026 does not have to be notified. Confirm this against the Regulation and write down the date you first knew.

NO Go to question 4.

4

Did an incident negatively affect, or could it affect, the product's ability to protect the availability, authenticity, integrity or confidentiality of data or functions?

YES Check the severity criteria in Article 14(5). If they are met, this is a **severe incident**: go to "Start now".

NO Not reportable under Article 14. Handle it through your normal vulnerability management (fix, advisory) and write down why you decided it was out of scope.

Start now (reportable)

1. Write down the four timestamps (page 4).
2. Pick the coordinating CSIRT (page 4).
3. Fill in the early-warning page (page 3) and submit within 24 hours.
4. Diary the 72-hour notification.

Not reportable, or unclear

Write down why, with the date and who decided. If you are unsure whether a threshold is met, escalate to your legal or compliance contact straight away: the 24-hour clock may already be running.

24-hour early warning: what to prepare

Fill in the editable Word template that comes with this kit, then copy each line into the matching field of the SRP form.

Item	What to enter	Notes
Type and level	Early warning. Track: actively exploited vulnerability or severe incident.	Choose the track from page 2.
Manufacturer	Legal name of the manufacturer, and the person filing.	The filer needs an EU Login account.
Product	Product name, affected versions, product type.	List every affected product line you know of.
Title	One sentence: what is happening, in plain words.	Facts only. No speculation about cause.
Malicious acts suspected?	Yes, no or unknown.	Severe-incident track only.
Member States	Countries where the product is available, if you already know.	Leave blank rather than guess.
Identifiers	CVE ID and/or EUVD ID if one exists.	Optional but useful from the first stage.

> **Check the real form.** The ENISA FAQ says some fields are optional at the early-warning stage but required later, and points to the SRP Glossary for field names. This table follows a third-party summary of the Glossary, so confirm the exact fields and character limits on the platform before you rely on it.

Tips from practice

- **Pre-approve your templates** before an event happens, so legal and management sign-off does not eat your 24 hours.
- **Name a primary filer and a backup.** A single person on holiday must not be a single point of failure.
- **Record what you knew, and when.** The early warning is a snapshot; the 72-hour notification adds the nature of the exploit or incident, and what users can do.
- **Do not wait for certainty.** A short, accurate early warning beats a late, complete one.

Clock log, CSIRT choice and platform set-up

Clock log: record four timestamps for every candidate event

Timestamp (UTC)	Date and time	Recorded by
T1: first signal received		
T2: triage started		
T3: evidence met the definition (awareness)		
T4: early warning submitted		

Your legal deadlines run from awareness (T3). The platform's own 72-hour counter runs from the early-warning submission, so it can show a different due time: keep your own clock.

Which coordinating CSIRT do you select?

- **EU-based manufacturer:** the Member State of your main EU establishment, where cybersecurity decisions for the product are mainly made. If that cannot be determined, use the Member State of your largest EU establishment by number of employees.
- **Manufacturer outside the EU:** take the first option that applies, in this order: the Member State where your authorised representative acts for the most products; then your importer; then your distributor; then where most users are located.
- Selecting the wrong CSIRT can lead to the report being invalidated and having to be resubmitted.

Platform set-up checklist (do this before you need it)

- ☐ Every person who may file creates their own EU Login account, with multi-factor authentication switched on.
- ☐ On the SRP portal, choose "Assigned Representative" and log in.
- ☐ The Primary Assigned Representative (one per manufacturer) registers: selects the CSIRT and enters manufacturer details.
- ☐ Wait for "Verified" status before inviting Secondary representatives (up to 20).
- ☐ Name at least one backup filer and store the contact details in your on-call document.
- ☐ Agree what to do if the platform is down: contact the CSIRT directly, then submit through the SRP once it returns.

Sources

- ENISA, CRA Single Reporting Platform, FAQ: enisa.europa.eu/cra-srp
- Regulation (EU) 2024/2847 (Cyber Resilience Act): eur-lex.europa.eu/eli/reg/2024/2847/oj
- Third-party guides used for field lists and practical tips: cyberresilienceact.eu (Article 14 reporting) and BD Emerson (Article 14 reporting obligations, 23 Oct 2026)