


The Keyboard user manual.

Connect your board, make your first change, and learn every part of Keyboard.

11 chapters Illustrated walkthroughs Browser editor + desktop Trainer



The screenshot displays the Keyboard software interface. On the left is a sidebar with a menu containing: keyboard, Standard Keys, Pointing Devices, Special Keys, Layer Keys, Mouse Keys, Tap Dance Keys, Macro Keys, Alt-Repeat, Leaders, Combos, Overrides, Layouts, Trainer, Quick Start, About, and Settings. The main panel is titled 'Standard Keys' and shows a virtual keyboard layout for 'English (US)'. Below the keyboard are sections for 'Modifiers' (None, SHIFT, CTRL, ALT, GUI), 'Mod, Mod-Tap, and One-Shot Mod' (MOD, MT, MT, QSM, QSM), 'Blank and Transparent' (a small square icon), 'Numpad' (a numeric keypad layout), and 'Function Keys' (F1-F14). On the right, a larger virtual keyboard layout is shown for 'Layer 0', with keys like W, E, R, T, Y, U, I, O, P, A, S, D, F, G, H, J, K, L, N, M, and various modifier keys. At the bottom right, there are buttons for 'NORMAL', 'MEDIUM', 'SMALL', and 'AUTO', along with a small icon and another 'AUTO' button. A branch name 'docs/launch-user-manual' is visible at the bottom right.

Open the panel. Drag a letter. See the change. Open Standard Keys, drag A onto Q, and release. The key now shows A. Actual offline example; no keyboard writes.


Written against launch Keyboard `6d9bd1f`. Screenshots use the bundled example and may show fewer behavior slots than current firmware. Connected hardware exposes additional controls. All screenshots can be enlarged.

Start with a keyboard—or an example

Keyboard lets you configure your Svalboard, organize layers, create advanced bindings, and set up an on-screen trainer. You can explore the editor before connecting hardware. This guide starts with one ordinary key change, then builds toward reusable layouts and reliable backups.

Choose a starting point on the welcome screen:

Choose	What happens	Use it for
Connect Keyboard	The browser asks which keyboard to open, then Keyboard reads its configuration.	Editing your connected Svalboard.
Load File	A saved layout opens as an offline draft.	Inspecting a backup or continuing exported work.
QWERTY Example	A bundled example opens without a keyboard.	Learning the controls safely.



Open an example and make a first edit. Open QWERTY Example, open Standard Keys, and drag A directly onto Q. This is an offline draft; no keyboard is changed. Offline example.

Three places your work can live

ON YOUR SVALBOARD

The saved configuration

Runs on the keyboard.
Connecting reads it;
applying edits changes
it.

IN THIS BROWSER SESSION

The current draft

May include unsaved
changes. The layout you
see is not always what
the board runs.

ON YOUR COMPUTER

An exported file

A copy you keep. Export
downloads it; import
reviews which parts can
be applied.

Take the five-minute tour

1. Choose **QWERTY Example**.
2. If only icons are showing, click the logo at the top of the left navigation rail to reveal its labels. Hovering an icon also identifies it.
3. Open **Standard Keys** and drag a letter from the palette onto the position you want to change. Release it and check the new legend.
4. Switch layer tabs to see how the same physical positions can carry different bindings.
5. Choose **Export Layout** in the editor toolbar if you want to keep your experiment.

Offline means no keyboard writes. An example or loaded file is a draft in the current session. Export it before closing or refreshing. Connecting a keyboard later reads that keyboard; it does not automatically install your draft.

Demonstrations play automatically when visible. Autoplay is enabled even when your system requests reduced motion.

Most illustrations use the bundled offline example. Captions explicitly identify connected controls shown with controlled test-board data. No screenshot is presented as proof of a hardware write.

Connect and protect your starting point

Welcome → Connect Keyboard → browser device chooser

Use a desktop browser that supports WebHID, such as Chrome or Edge, and a USB data connection. The connection button is unavailable when the browser lacks the required API. Keyboard's browser editor expects compatible Svalboard firmware; seeing a keyboard in a device chooser does not establish firmware compatibility.

1. Connect your Svalboard by USB, open Keyboard, and choose **Connect Keyboard**.
2. Select the intended keyboard in the browser's chooser and grant access. With several keyboards attached, check which one you selected.
3. Wait for the layout to load. Hover the connection/update controls to check the editing target before changing anything.
4. Choose **Export Layout**. Keep the native **.svil (Recommended)** and **Include Macros** enabled, then choose **Export**.
5. Name the downloaded file clearly—for example, `before-first-edit.svil`—and keep it somewhere you can find again.

Back up before editing. Export captures the configuration currently shown in the editor, including staged changes. Exporting after experiments does not recover the untouched configuration you originally connected to.

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

Connect

0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 mouse

Layer 0

Q W E I O

ESC S B ' D T R Y K : N L LT14 P

DEL A [X C * F G H J ' '] ; \

Z

V

M

LT1 ENTER CAPS LGUI TAB BACKSP MO SPACE

SHIFT CTRL ALT MO

1

NORMAL MEDIUM SMALL AUTO

AUTO

PR #3 : 6d9bd1f - Merge pull request #3 from svalboard/refactor/keyboard-service-names

Branch: docs/launch-user-manual

Export a backup. Open Export Layout and export the native .svil file. The recording verifies a downloaded file; this example uses the browser download fallback. Browsers with a native save picker show a Save dialog instead. Offline example.

Coming from an older configuration tool

Keep your existing layout backup before changing firmware. You can open a legacy .vil file offline to inspect it, but Keyboard blocks direct import of old-protocol layouts into connected Sval firmware when keycode migration is required. Renaming the file extension is not a conversion.

For Svalboard Vial-QMK v2025-11-01 with the vial keymap, the firmware can migrate supported configuration on first boot. Follow the [firmware upgrade instructions](#), connect in Keyboard, and verify layers, macros, modifier options, timing and pointing settings. Then export a fresh native .svil. Other old or custom builds are not covered; keep the old file as a reference and recreate anything not migrated. A supported firmware migration is different from importing a legacy file in the browser.

Understand the editing target

State	Meaning
Editing keyboard	Changes can be written to the connected device.
Offline draft	Changes affect the loaded file or example in this session. Export to keep them.
Pending changes	The editor has changes waiting to be written; the displayed layout may differ from the board.
Not saved	A write failed. Some writes may already have succeeded; follow the retry guidance.

CHAPTER 03 / YOUR FIRST EDIT

Make and verify your first change

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

Connect

0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 mouse

Layer 0

W E I O

ESC S B . D T R Y K : N L LT14

DEL A [X C " F G H J ' , P

Z V M

LT1 ENTER CAPS LGUI TAB BACKSP MO SPACE

SHIFT CTRL ALT MO 1

NORMAL MEDIUM SMALL AUTO

Branch: docs/launch-user-manual

An offline example of the editing workspace: navigation on the left, layer selection above the layout.

Start with one easy-to-recognize binding on a known layer. Keep the keys you need for navigation and switching layers intact until you are comfortable restoring changes.

The screenshot displays the QMK Settings application. On the left, a sidebar lists various settings categories: Standard Keys, Pointing Devices, Special Keys, Layer Keys, Mouse Keys, Tap Dance Keys, Macro Keys, Alt-Repeat, Leaders, Combos, Overrides, Layouts, Trainer, Quick Start, About, and Settings. The main panel shows the 'QMK Settings' configuration for 'Layer 0'. It includes sections for 'Magic', 'Grave Escape', 'Tap-Hold', and 'Auto Shift'. The 'Tap-Hold' section is expanded, showing settings like 'Tapping Term' (02), 'Permissive Hold (new)' (disabled), 'Hold On Other Key Press' (disabled), 'Retro Tapping (new)' (disabled), 'Quick Tap Term' (200), 'Tap Code Delay' (0), 'Tap Hold Caps Delay' (80), 'Tapping Toggle' (5), 'Chordal Hold' (disabled), and 'Flow Tap' (0). The 'Auto Shift' section is also expanded, showing 'Combo' (disabled) and 'One Shot Keys' (disabled). On the right, the 'Layer 0' keyboard layout is shown, featuring a standard QWERTY arrangement with some keys highlighted in green. The bottom of the screen shows a status bar with 'No pending change' and a list of layers (0-12).


Choose when changes reach the board

Live Updating is on by default. While connected, ordinary queued edits are saved as you make them. For a controlled first experiment, use the lightning control labeled **Switch to Manual Updates**. You can then review pending edits before applying them.

Control	Effect
Live Updating	Edits are saved as you make them; watch for saving or error messages.
Apply N Changes	Writes the pending changes in Manual mode.
Discard pending edits	Discards the current unsaved edits. It does not reverse changes already applied.
Switch to Live Updating	Applies pending changes before enabling Live Updating.

1. Select the layer you intend to edit.
2. Open **Standard Keys**.

3. Drag the replacement key from the palette onto the target position and release. Alternatively, select the position first and click a palette key.
4. Check the resulting legend. In connected Manual mode, open **Pending (N)** to review what will be written.
5. Choose **Apply N Changes** and wait for saving to finish. Do not assume a changed legend alone means the board was updated.
6. Deselect the key, switch to a text editor, activate the appropriate layer, and test the result.
7. Export the verified configuration as a new file.



Drag A onto the Q position. Watch the pointer pick up A from Standard Keys, drag it onto Q, and release. The position now shows A. This changes the offline example only.

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

Connect

0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 mouse

Layer 0

Q

ESC

W

S

B

DEL

A

[

X

E

D

T

C

R

F

G

V

U

H

J

I

Y

K

:

M

N

L

LT14

P

;

\

/

LT1

ENTER

CAPS

LGU_L

TAB

BACKSP

MO

2

SPACE

SHIFT

CTRL

ALT

MO

1

1

NORMAL

MEDIUM

SMALL

AUTO

1

2

AUTO

PR #3 · 6d9bdf · Merge pull request #3 from svalboard/refactor/keyboard-service-names

Branch: docs/launch-user-manual

Swap two existing keys. Drag Q onto A to exchange their bindings, then drag them back to restore the original layout. Palette-to-layout dragging assigns; layout-to-layout dragging swaps. Offline example.

Typing can assign a key. **Typing Binds a Key** is enabled by default. With an editing target selected, pressing a physical key can assign that key, including modifiers, to the target. Deselect before testing normal typing, or turn this option off in **Settings → General**.

Dragging an existing layout key onto another position swaps bindings, including across layers. Use this deliberately: it is different from copying a palette key. If an **Undo** button appears, its tooltip identifies the operation it can reverse; do not treat it as unlimited editing history.

CHAPTER 04 / WORK WITH LAYERS

Build a layout you can navigate

A layer is another set of bindings for the same physical key positions. Editing a layer tab changes what you are looking at in Keyboard; using a layer binding on the physical keyboard

changes what the keyboard types.

Term	Meaning
Base/default layer	The starting layer used when no higher active layer provides a binding.
Transparent key	Looks through to a lower active layer for its binding.
Blank key	Produces no action at that position instead of falling through.
Momentary layer key	Activates another layer while held.
Layer-tap key	Types one action when tapped and activates a layer when held.

Open **Layer Keys** for layer bindings. Start with a momentary key leading to a small navigation or symbols layer. Keep the activation key usable while that layer is active; a transparent binding at the corresponding position is often appropriate.

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

Layer Keys

MO DF PDF TG TT OSL TO LT

Momentary

Momentarily activates the layer. As soon as you let go of the key, the layer is deactivated.

0

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

MO 0

MO 1

MO 2

MO 3

MO 4

MO 5

MO 6

MO 7

MO 8

MO 9

MO 10

MO 11

MO 12

MO 13

MO 14

MO 15

Connect

Undo

1

2

3

4

5

6

7

8

9

10

11

12

13

Layer 0

W

E

I

O

DEL

A

I

X

ESC

S

B

Q

D

T

R

U

Y

K

:

N

L

LT14

P

Z

C

"

F

G

H

J

'

M

V

LT1

ENTER

CAPS

LGUIT

TAB

BACKSP

MO 2

SPACE

SHIFT

CTRL

ALT

MO 1

NORMAL

MEDIUM

SMALL

AUTO

AUTO

Build a small navigation layer. On unused layer 3, select three positions and press Left, Down, and Right to assign them using Typing Binds a Key. Return to base and assign MO(3). The remaining layer-3 positions inherit through Transparent. Offline example.

Combine a tap key with a layer hold. Assign A, select it again, choose Layer Keys → LT, then choose layer 3. The resulting key is A on tap and layer 3 on hold. Offline example.

Build a simple navigation layer


1. Choose an unused layer, such as layer 3, and assign a small group of arrow keys from Standard Keys. Make the other positions transparent if they should inherit the base.
2. Return to the base layer and select a spare position for entering navigation.
3. Open **Layer Keys**, choose **Momentary (MO)**, and assign the tile for layer 3 to that position.
4. Review and apply the edits, then deselect the target. In a text editor, hold the new key and try the arrows. Release it and confirm normal typing returns.

For a tap action on the same key, assign its desired tap key first, select the position again if needed, then choose **Layer Tap (LT)** and its destination. The composer derives the tap action from the selected position.

Layer Keys choice	When to use it
Momentary · MO	Activate a layer only while held.
Layer Tap · LT	Send a key on tap; activate a layer on hold.
Toggle Layer · TG	Turn a layer on or off with a tap. Keep a way to toggle it off.
Tap Toggle · TT	Hold momentarily, or tap the configured number of times to toggle.
One Shot Layer · OSL	Activate a layer for the next key.
To Layer · TO	Replace other active layers while retaining the default. Plan a return binding.
Default Layer · DF	Change the base for this power session.
Persistent Default Layer · PDF	Save the chosen base across power cycles.

Name, inspect, and reuse layers

Give a layer a useful name. Click Layer 0, enter Base, and leave the field to save the name in this offline layout. Offline example.



Compare layers together. Use Show Multiple Layers, then 3D View to change the presentation. Viewing a layer does not activate it on the keyboard. Offline example.

Save a reusable layer. Open the layer actions, choose Save Layer..., give it a name, and find it in Layouts. This is local browser storage, not a complete backup file. Offline example.

Click a layer name to rename it. Use its color control to make related layers easier to recognize. The layer's actions menu offers **Copy Layer**, **Paste Layer**, **Make All Blank**, **Make All Transparent**, and conversions between blank and transparent keys. Whole-layer operations affect many positions; check the target layer first.

Show Multiple Layers helps compare layers. **3D View** changes their presentation. **Hide All Transparent Keys** helps inspect inherited bindings; it does not rewrite those transparent keys. **Show All Layers** reveals layers hidden by the transparent-layer filter.

1. Open a layer's actions menu and choose **Save Layer...** to put a reusable copy in the local **Layouts** library.
2. Open **Layouts** and expand a saved or imported layout.
3. Drag the desired layer onto the destination layer in the editor.
4. Read the replacement confirmation and confirm only when the destination is correct.
5. Review and apply the resulting changes according to your update mode.

 keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

Layouts

Drag and drop to apply a layout to one of your layers or drag and drop individual keys. Default layouts are provided by Svalboard. You can save any of your own layers here, or import any .svil file.

Search layouts...

Import

sval-default

4 layers

0 Layer 0

1 Layer 1

2 Layer 2

15 Layer 15

Connect

0 1 2 3 4 5 6 7 8 9 10 11 12 13

Layer 3

W E I O

ESC S B D T R U Y K : N L LT14 P

DEL A [X C * F G H J ' .

Z V M

LT1 ENTER CAPS LGU/LT TAB BACKSP MO 2 SPACE

SHIFT CTRL ALT MO 1

1


NORMAL MEDIUM SMALL **AUTO** **AUTO**

Apply a layer from the library.

Choose destination layer 3, drag the library's Layer 0 preview onto it, read the replacement confirmation, and choose OK. Check the destination before confirming. Offline example.

PR #3 - 6d9bd1f - Merge pull request #3 from...

Branch: docs/launch-user-manual



Choose Transparent or Blank in Keyboard. On layer 3, set the A position to Transparent, then Blank. Return to base: A is still there. The comparison below explains what happens when the upper layer is active. Offline example.

Local library, not a backup service. Saved layers and imported library items belong to this browser's local storage. Export important configurations to files; clearing browser data can remove local library content.

Transparent keeps the key underneath. Blank turns it off.

Suppose a position types **A** on your base layer. You hold a key to activate another layer. What should that same position do while you hold it?

Keep typing A

Set that position to **Transparent** on the upper layer.

Upper layer · active while held

▽ **Transparent**

Use the assignment underneath ↓

Base layer · underneath

A

Press this position → **A**

Make this position do nothing

Set that position to **Blank** on the upper layer.

Upper layer · active while held

Blank

Stop here. Do not use the key underneath.

Base layer · blocked

A

Press this position → **nothing**

Release the layer key: you return to the base layer, so this position types A again in both cases. Blank disables it only while the upper layer applies.

If you assign a different key—such as **1**—on the upper layer, the position types 1 while that layer is active.

Give a key more than one job

Special Keys groups additional actions such as media and system controls; **Layer Keys** and **Mouse Keys** have their own palettes. Use the same select-and-assign or drag-and-drop interaction as Standard Keys.


A normal assignment sends a key. A behavior can send a sequence, distinguish a tap from a hold, or recognize several keys together. Start with one small example, verify it in an empty document, and then build on it. The maintained Svalboard firmware provides 256 slots each for macros, tap dances, combos, overrides, alternate-repeat mappings, and leader sequences. Available entries depend on the firmware or file you have loaded.

Editing and using are different steps. A macro or tap dance needs both a definition and a key that invokes it. Combos and overrides respond to their configured triggers. Leaders need a Leader key as well as a sequence. In **Manual Updates**, apply the queue with **Apply N Changes** before testing on the board. In Live Updating, supported edits reach the board as you make them. Close the binding editor, deselect the assignment target, and focus a disposable text document before testing: typing while an assignment target is selected may change the layout.

Macros: send a short sequence

Macro Keys → edit a slot

A macro runs its actions in order. Begin with something harmless, such as the text “hello”. You can author a macro in an offline layout; executing it requires assigning it on a connected board.



Create and assign a text macro. Add a Text action containing hello, close the editor, and drag Macro 0 onto Q. Both the definition and the invoking key are now in the offline draft. Offline example.

1. Open **Macro Keys** and edit an unused numbered entry. In the compact bottom-panel presentation, the plus control opens an empty entry.
2. Add **Text** and enter `hello`. Give the macro a useful name by clicking its title where renaming is available.
3. Close the editor. Select a spare position in your layout, then choose that macro's numbered key tile, or drag its tile onto the position.
4. Apply queued changes if necessary. Deselect the assignment and focus an empty document. Press the physical key once; it should type your text.
5. Return to the editor to add actions only after the small example works. Export a fresh backup when you are happy with it.

Key Tap presses and releases a key. **Key Down** holds it, and **Key Up** releases it. **Delay** inserts a pause in milliseconds. For a chord, use a modifier down, a key tap, and a matching modifier up. Always balance held keys with releases. Macro storage is shared across entries, rather than a separate fixed allowance for each macro.

Text macros send keyboard input, not clipboard contents. The operating system's keyboard layout affects the resulting characters; do not assume arbitrary Unicode text will work. Start

with simple text and test punctuation in your actual OS layout. Avoid using passwords or other secrets as examples: a macro and an exported configuration are not a secure secret store.

Tap dances: tap, hold, or tap twice

Tap Dance Keys → edit a slot

A tap dance gives one physical position several outputs. A simple learning example is **Tap: A** and **Double-Tap: B**, with unused actions left empty. This makes the difference easy to see in a scratch document.

keyboard

Standard Keys
Pointing Devices
Special Keys
Layer Keys
Mouse Keys
Tap Dance Keys
Macro Keys
Alt-Repeat
Leaders
Combos
Overrides
Layouts
Trainer
Quick Start
About
Settings

Tap Dance Keys

Allows a single key to perform multiple, different actions based on the number of times it is tapped in sequence (e.g., tap once for 'A', twice for 'B', or hold for a modifier).

	Tap	Hold	Tap-Hold	Double-Tap	
0	A			B	h 0
1					h 1
2					h 2
3					h 3
4					h 4
5					h 5
6					h 6
7					h 7
8					h 8
9					h 9
10					h 10
11					h 11
12					h 12
13					h 13
14					h 14
15					h 15

Connect | Undo | [Icons] | Layer 0 : [Keyboard Layout]

NORMAL MEDIUM SMALL **AUTO** [Icons] **AUTO**

Branch: docs/launch-user-manual

Configure and assign a tap dance. Enable entry 0, assign A to Tap and B to Double-Tap, then drag its tile onto Q. The recording shows configuration; test physical tap timing on your board. Offline example.

1. Open an unused entry in **Tap Dance Keys**.
2. Select the **Tap** slot and assign A. Select **Double-Tap** and assign B. **Hold** is a sustained press; **Tap-Hold** is a tap followed by a held press.
3. Review the timing field and leave **Enabled** on. Avoid changing timing and every action at once.
4. Close the editor and assign the entry's tap-dance tile to a spare keyboard position. Apply queued changes.

5. Deselect and test a single tap, then a quick double tap in an empty document. Adjust the timing if your deliberate double taps are being separated.

Release before editing. Release a held tap-dance key before changing its action. The launch firmware has a known edge case where editing a held dance can leave its previous output held.

Combos: press a small chord

Combos → edit a slot

A combo recognizes up to four input keycodes pressed within its timing window, and emits an **Output**. For example, A and B together can send Escape. These are keycode triggers, not a named pair of physical positions: consider where those assignments appear in your layers.

Make A + B send Escape. Enable a combo, choose A and B as its first two inputs, then set Output to Escape. No separate combo key is needed. Offline example.

1. Choose an unused combo. Fill the first two input slots with A and B and choose Escape for **Output**.

2. Leave the remaining input slots empty and enable the entry.
3. Apply changes. Deselect, focus a safe test window, and try each key separately before pressing them together.
4. If the chord is difficult to catch, review **Combo Timeout** in the Combos panel while connected. Increase it cautiously: a generous window may catch ordinary typing rolls.

Choose combinations that are comfortable but uncommon in your normal text. After verifying the mechanics, replace the demonstration with your preferred inputs. There is no separate assignment step beyond having those input keycodes available on the keyboard.

Modifiers, mod-taps, and one-shots

Standard Keys → Modifiers → Mod, Mod-Tap, and One-Shot Mod

A modifier chord, a held modifier, and a mod-tap are different tools. A chord such as Ctrl+C sends a shortcut. A mod-tap can send A when tapped and hold Control when held. A one-shot modifier lets you tap Shift, release it, and then type a shifted key without holding both keys together.

1. For the A/Control example, first assign A to the target position then select that position again if assignment cleared the selection.
2. In **Standard Keys**, select Control under **Modifiers**. The constructed keys use the currently selected position's base assignment.
3. Choose the generated **Mod-Tap** tile. Do not choose the standalone modifier or one-shot tile by mistake.
4. Apply changes, deselect, and test a tap in a scratch document. Then hold the key while pressing another key to verify the modifier behavior.

For a one-shot Shift, choose Shift and the generated one-shot tile instead. Test by tapping that key, releasing it, and typing a letter. Modifier controls include left/right choices; other composer presentations offer **MEH** (Control, Shift, Alt) and **HYPER** (those plus GUI). GUI is the Windows/Command-style modifier interpreted by your OS.

Use **QMK Settings → One Shot Keys** to review timeout and repeated-tap locking. Mod-tap decisions also depend on the Tap-Hold settings described below. Test typing rolls as well as isolated presses; a configuration that works slowly can feel different at speed.

Make one key A on tap and Control on hold. Assign A, select the position again, choose CTRL, then choose the generated mod-tap tile. Assignment can clear selection, so reselect before composing. Offline example.

Make one key A on tap and Control on hold. Assign A, select the position again, choose CTRL, then choose the generated mod-tap tile. Assignment can clear selection, so reselect before composing. Offline example.

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

Standard Keys

English (US)

ESC

F1

F2

F3

F4

F5

F6

F7

F8

F9

F10

F11

F12

~

!

@

#

\$

%

&

*

(

)

+

BACKSP

TAB

Q

W

E

R

T

Y

U

I

O

P

|

CAPS

A

S

D

F

G

H

J

K

L

;

'

SHIFT

Z

X

C

V

B

N

M

,

.

?

SHIFT

CTRL

ALT

GUI

SPACE

GUI

ALT

CTRL

Modifiers

None

SHIFT

CTRL

ALT

GUI

Mod, Mod-Tap, and One-Shot Mod

LSFT

SFT

OSM

Blank and Transparent

▽

Numpad

PRINT

CRCL

PAUSE

NUM

=

/

*

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

INSER

HOME

PAGE

7

8

9

-

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

DEL

END

PAGE

4

5

6

+

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

↑

1

2

NUM

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

←

→

0

.

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

Function Keys

F1

F2

F3

F4

F5

F6

F7

F8

F9

F10

F11

F12

F13

F14

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

F15

F16

F17

F18

F19

F20

F21

F22

F23

F24

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

LSFT

Connect

Undo

0

1

2

3

4

5

6

7

8

9

10

11

12

1:

Layer 0

OSM

ESC

S

B

'

D

T

C

R

U

Y

K

:

N

L

LT14

P

DEL

A

[

X

Z

*

F

G

H

J

'

V

M

]

:

/

LT1

ENTER

CAPS

LGUILT

TAB

BACKSP

MO

2

SPACE

SHIFT

CTRL

ALT

MO

1

1

NORMAL

MEDIUM

SMALL

AUTO

1

2


AUTO

Assign one-shot Shift. Select a position, choose SHIFT, and select the OSM tile. On your board, tap and release this key before typing the letter you want shifted. Offline example.

Overrides: change an action under a modifier

Overrides → edit a slot

An override replaces a trigger when its modifier and layer conditions match. A useful example is Shift+Backspace producing Delete. It changes how an existing assignment behaves, so you do not place an “override key” in your layout.



Make Shift + Backspace send Delete. Enable the entry, choose Backspace and Delete, and select Shift in both Trigger and Suspended. Suspending Shift means the replacement is Delete without Shift. Offline example.

1. Set **Trigger** to Backspace and **Replacement** to Delete.
2. In the **Trigger** modifier tab, select the Shift modifier you use. Review handedness if you use both Shift keys.
3. Use **Suspended** for the triggering modifier you do not want included with the replacement. **Negative** specifies modifiers that prevent the override; leave it empty for this basic example.
4. Select the intended **Layers**, enable the entry, and keep advanced activation options at their existing defaults unless you have a reason to change them.
5. Apply, deselect, and test against expendable text: Backspace should retain its normal action, while the configured Shift combination should perform Delete.

Leaders: type an ordered sequence

Leaders → Leader key and sequence entries

A leader sequence is ordered input after a dedicated Leader key. Unlike a combo, its keys are typed in succession. For a harmless first example, Leader, A, B can trigger a macro that types “hello”.

The screenshot displays the 'Keyboard Layout Editor' interface. On the left, a sidebar lists various configuration options: Standard Keys, Pointing Devices, Special Keys, Layer Keys, Mouse Keys, Tap Dance Keys, Macro Keys, Alt-Repeat, Leaders, Combos, Overrides, Layouts, Trainer, Quick Start, About, and Settings. The 'Alt-Repeat' section is currently selected.

The main area is titled 'Alt-Repeat Keys' and includes a close button (X). Below the title, a description states: 'Alt-Repeat keys remap what happens when you press Alt-Repeat after a specific key. Click on a key slot to assign a keycode.' A small icon labeled 'ALT-REP' is shown. A toggle switch for 'ON' and 'OFF' is visible, currently set to 'ON'.

Below the description, there are 12 rows of key slots, each with a number (0-11) and a right-pointing arrow. The first row (0) shows a mapping from 'A' to 'B'. The other rows (1-11) are currently empty.

On the right side of the interface, a keyboard layout is shown. The 'A' key is highlighted in red and labeled 'ALT-REP'. The layout includes standard keys like W, E, D, T, R, U, Y, K, I, O, P, N, L, M, V, F, G, H, J, ' ', Z, X, C, V, B, S, A, ESC, DEL, and function keys like LT1, ENTER, CAPS, LGU/LT, TAB, BACKSP, MO, SPACE, SHFT, CTRL, ALT, and MO 1.


At the bottom right, there are buttons for 'NORMAL', 'MEDIUM', 'SMALL', 'AUTO', and 'INFO'. The 'AUTO' button is highlighted. Below these buttons, the text 'Branch: docs/launch-user-manual' is visible.

1. Choose an unused entry, set **Trigger** to A and **Alternate** to B, and enable it.
2. Assign the alternate-repeat action from the panel to a physical position. Apply the changes and deselect.
3. Test the simple mapping before exploring **Bidirectional**, **Ignore mod handedness**, or **Default to alternate**.

Set up your pointing devices

Pointing Devices

Connect the board to see its sensor-specific controls. A loaded file can supply assignable pointing keys through the picker, but offline previews cannot demonstrate sensor behavior. The controls and ranges depend on the installed pointer, so your panel may differ from the example.



Adjust one pointer setting. Change the left pointer from 800 to 1200 DPI. This uses controlled test-board data to demonstrate the controls; it is not a recommended sensitivity or a sensor test.

1. Start with ordinary pointer movement. Adjust the left or right sensitivity in small steps, applying queued edits as needed.
2. Test scrolling and its direction. Review per-side scrolling controls, axis lock, and natural scrolling where available.
3. Assign a **Sniper** hold key to try slower, precise movement. **Boost** does the opposite. The 2×, 3×, and 5× versions choose the factor; toggle versions stay active without holding the key.
4. If you use automouse, confirm its target layer contains useful mouse bindings and a comfortable way back to ordinary typing. Check which pointer may activate it, then tune

threshold, decay, and timeout one at a time.

5. Verify normal movement, scrolling, and layer return before exporting a backup.

Mouse Keys are keyboard-generated mouse movement and button actions; they are not the same as physical sensor sensitivity. TrackPoint recalibration applies to TrackPoint hardware. Avoid copying a sensitivity number between different sensor types and expecting identical movement.

Known firmware edge cases include buffered scrolling, combinations of speed factors, and disabling an active automouse layer. Keep the first configuration simple and verify the behavior you actually use.

CHAPTER 07 / SETTINGS & DIAGNOSTICS

Settings, timing, and board identity

Settings → General → QMK Settings...

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

QMK Settings

QMK Settings
Configure firmware behavior. Changes follow your update mode.

Magic

Grave Escape

Tap-Hold

Tapping Term
Range: 0 - 10000

02

Permissive Hold (new)

Hold On Other Key Press

Retro Tapping (new)

Quick Tap Term
Range: 0 - 10000

200

Tap Code Delay
Range: 0 - 1000

0

Tap Hold Caps Delay
Range: 0 - 1000

80

Tapping Toggle
Range: 0 - 100

5

Chordal Hold

Flow Tap
Range: 0 - 10000

0

Auto Shift

Combo

One Shot Keys

Mouse keys

Pen (1)

Apply 1 Change

Pending changes (1)
QMK setting 7

Layer 0

Q W E I O
DEL A [X C R U Y K : N L LT14 P
Z
V M
LT1 ENTER CAPS LGU/LT TAB BACKSP MO 2 SPACE
SHIFT CTRL ALT MO 1

NORMAL MEDIUM SMALL AUTO

AUTO

Branch: docs/launch-user-manual

Stage a timing change and inspect it.

Change Tapping Term from 200 to 210 ms and open Pending (1). Controlled test-board data; the recording does not write physical hardware.

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layers

Trainer

Quick Start

About

Settings

Settings

General

Fragments

Developer

Appearance

Light

Typing Binds a Key

ON

Serial Assignment

None

International Keyboards

English (US)

QMK Settings...

Print Layers...

Connect

0 1 2 3 4 5 6 7 8 9 10 11 12 13

Layer 0

W E I O

ESC S B ' D T R U Y K : N L LT14 P

DEL A [X C * F G H J ' . /

Z V M

LT1 ENTER CAPS LGU/LT TAB BACKSP MO 2 SPACE

SHIFT CTRL ALT MO 1

NORMAL MEDIUM SMALL AUTO

1

AUTO

Change appearance and turn off typing assignment.

Try Dark, return to Light, and switch Typing Binds a Key off.

These preferences belong to this browser.

Offline example.

Browser choices include appearance, assignment behavior, and international palette selection. Choose a palette matching your OS keyboard layout; this does not change the OS layout itself. **Settings → Fragments** selects the finger and thumb assemblies used to draw your board. It describes the installed arrangement rather than rewiring it.


For timing, export a baseline first. Change one control, apply it, and test both slow deliberate presses and normal typing. **Tapping Term** influences tap-versus-hold decisions. **Quick Tap Term** affects repeated dual-role tapping. **Permissive Hold (new)**, **Hold On Other Key Press**, and **Retro Tapping (new)** control how other presses and releases affect that decision. **Chordal Hold** uses the hand relationship between keys; **Flow Tap** can favor taps during rapid typing and is off at zero.

Tap Code Delay controls generated tap duration, **Tap Hold Caps Delay** handles generated Caps Lock taps, and **Tapping Toggle** controls TT’s tap count. Their launch defaults are 0 ms, 80 ms, and five taps; a stored toggle count of zero behaves as one. **Grave Escape** provides separate “Always send Escape” options for Alt, Control, GUI, and Shift.

A visible setting is not a guarantee that a firmware feature is enabled. Standard launch builds do not include Auto Shift, and some mouse-key settings have no runtime consumer. Use the launch notes for those limits rather than repeatedly adjusting an ineffective field.

Where supported, **Board name** changes how the keyboard appears to your computer. **Save now** writes immediately, even in manual mode; restart the keyboard for the USB name to change. Apply or export outstanding edits before restarting. Board identity is separate from a layout backup.

Settings → Developer → Scan Lab... is for advanced scanning, power, and firmware diagnostics. Its timing application and bootloader controls can affect hardware immediately. For a simple “does this switch register?” check, use Matrix Tester instead. Power estimates are not battery-life measurements, and longer idle intervals can delay the first response after inactivity.




Change a fragment and restore it. Open Settings → Fragments, change the first finger cluster in the offline example, then restore its original selection. On your own board, choose the arrangement matching your hardware. Offline example.

Check every physical switch

Editor toolbar → Matrix Tester

1. Connect the board and open **Matrix Tester** from the toolbar.
2. Press each finger direction and each thumb key, holding briefly so the polling display can see it. Compare the highlighted position with the one you pressed.
3. Use **Clear Matrix** to clear the visual test history and try again. It does not erase your layout or board settings.
4. Exit Matrix Tester to return to editing.

This is a physical-switch check, not a monitor of the final text produced by macros, combos or tap dances. Very brief presses can fall between snapshots. If the matrix sees the switch but typing is wrong, inspect its layer and binding rather than assuming the switch failed.



Read and clear Matrix Tester history. Open Matrix Tester, see three switch reports, then use Clear Matrix. Reports are simulated test-board data; this is not a physical switch test.

Print a desk reference

Open **Settings → General → Print Layers...** Review the non-empty layers and choose **Print**, then use the browser's print dialog to print them or save a PDF. A printed diagram is a learning reference; export a `.svil` as well for an editable backup.

4 layers with configured keys

The diagram illustrates a keyboard layout where keys are organized into sets of three, four, and five. The sets are as follows:

- Set of three:** {Q, W, E}, {A, D, T}, {Z, X, C}, {U, Y, K}, {H, J, '}, {I, O, P}, {N, L, ;}, {M, V, /}, {BKSP, LALT}, {MO(2), MO(1)}, and {SPACE}.
- Set of four:** {ESC, S, B} and {R, F, G}.
- Set of five:** {LT(KC, LENTE, R), CAPS LOCK, LSHIF T, LGUI (TMC, TAB), and LCTRL}.

The diagram shows a standard QWERTY keyboard layout with the following labels:

- Top Row:** !, @ 2, # 3, \$ 4, % 5, ^ 6, & 7, * 8, (9, 0 .
- Second Row:** ~ (underscore), Q, W, E, R, T, Y, U, I, O, P (semicolon/apostrophe)
- Third Row:** Caps Lock, A, S, D, F, G, H, J, K, L (semicolon/apostrophe), Enter
- Fourth Row:** Shift, Z, X, C, V, B, N, M, Comma/less-than, Greater-than/equals, Shift
- Bottom Row:** Ctrl, Alt, Spacebar, Ctrl, Alt, Fn, Windows key, Fn, Alt, Ctrl

CHAPTER 08 / BACKUPS & REUSABLE LAYOUTS

Editor toolbar → Export Layout or Import Layout

Use native `.svil` for your working backups. Enable **Include Macros** so the backup contains your macro definitions. The legacy `.vil` export retains QMK settings, but does not preserve all Sval-specific hardware values and metadata, including names, colors, and cluster selections.

Operation	What it preserves or changes
Export Layout	Downloads the editor's current configuration, including staged work.
Load File on welcome screen	Opens an offline draft; does not write a board.
Import Layout in editor toolbar	Reviews configuration changes for the current target.
Import in Layouts panel	Adds reusable layouts to the browser library.
Save Layer...	Saves one layer locally for reuse, not a complete device backup.

Import a compatible backup onto a connected keyboard

1. Connect the destination board and export its current configuration before making changes.
2. Apply or discard pending edits before beginning an import.
3. Choose **Import Layout**, select the file, and read **Review layout import**.
4. Check the destination, counts, warnings, and errors. **Back up current layout** is available in the review.
5. In Manual mode, choose **Stage import**, review pending changes, then **Apply**. In Live Updating, **Apply import** writes the changes. Offline, **Open layout** replaces the current draft.
6. Check the imported bindings and test important actions before relying on them.

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

Layout opened offline. No keyboard was changed.

Connect

0

1

2

3

4

5

6

7

8

9

10

11

12

13

14

mouse

Layer 0

Q

W

ESC

S

B

DEL

A

[

X

E

D

T

C

R

F

G

V

H

J

U

I

Y

K

:

N

L

LT14

P

;

\

/

LT1

ENTER

CAPS

LGUILT

TAB

BACKSP

MO

SPACE

SHIFT

CTRL

ALT

MO

1

NORMAL

MEDIUM

SMALL

AUTO

AUTO

Review and open an imported layout.

Use Import Layout, read the offline review, then choose Open layout. On a connected board the review and write controls differ; see the steps below. Offline example.

Import is not a complete device-image restore. The current importer keeps the board's alt-repeat entries, leaders, one-shot configuration, layer colors, and fragment state. It reports unsupported fields and settings. Entries beyond the incoming file's layers and tables are kept rather than erased.

A file may be rejected for mismatched matrix dimensions, too many layers or table entries, incompatible keycodes, unsupported macro content, or capacity limits. Read the specific message instead of forcing the file through. Native backups preserve information even when a particular field cannot yet be restored automatically.


CHAPTER 09 / THE DESKTOP TRAINER

Trainer and the desktop overlay


Trainer, directly below Layouts

Trainer previews the appearance and controls the optional desktop overlay. The browser is useful for choosing a style or reviewing an offline layout. Keyboard Host supplies the native

transparent window above your other applications and reads live board state directly. Its board operations are read-only.



Choose a readable overlay style. Apply High contrast, then try the Busy background to judge readability. This is the browser appearance preview.



See the overlay respond to layer changes. The actual shared native renderer receives controlled reports: base, symbols, function keys, then base with held-key highlighting. This demonstrates rendering; it is not a Windows desktop recording or a hardware latency test.

Install and show the Windows overlay

1. Select **Download for Windows** at the top of Trainer. Extract the ZIP and run **Start-Windows.cmd**.
2. Allow the first launch to download its private runtime. It needs internet, but no administrator rights, system Python, or PATH changes.
3. The app opens Keybard. Connect your keyboard normally and select Trainer. If needed, use **Connect to Keybard Host** and allow the browser's local-device access request. The install panel also links to local Keybard when Host is running.
4. Choose the board in the host selector and use **Show overlay**. Host remembers its selected board for reconnection.
5. Drag the overlay into place. In **Overlay**, optionally enable **Click through keyboard**; the small handle remains available for moving or hiding it. **Place at bottom** provides a convenient starting position.

The companion stays in the system tray when you close the browser. Use **Hide overlay** or the overlay's handle controls to get it out of the way. After editing the keyboard layout, choose **Reload layout** so the companion refreshes its cached copy. If reconnection fails, check the host board selection and USB connection rather than importing a different layout to mask the problem.

The Windows download is a portable preview, not a signed installer. Linux source launch is available, with Wayland limitations for placement, stacking, click-through, and modifier reporting. macOS remains unverified; equivalent validated packages for all platforms are not promised.

Choose what you can see

Start with an **Appearance** preset, then adjust **Key fill**, **Outline**, and **Legend** colors and opacity independently. Try **Contrasting legend halo** over busy backgrounds. Use **Outline thickness** for definition without making the fill more opaque. **Hands** and **Overlay size** are in Overlay.

In **Feedback**, choose **Layer-change highlight**: Off, Quick flash, or Short fade, and its duration. Enable **Highlight held keys** for a matrix-tester-like indication. Matrix polling can miss very brief taps and does not describe every generated macro or combo output. The preview's **Preview held keys** button simulates a chord.

Current firmware reports active and default layers automatically, including changes during use. Older firmware may require **Default layer (older firmware)**. For offline previews, choose **Default layer** and **Preview layer**. **Layout source** distinguishes a loaded snapshot, editor draft, example, imported trainer layout, and a live read-only board. **Import for trainer** changes the preview source; it does not write that file to the keyboard.

- Standard Keys
- Pointing Devices

- Special Keys
- Layer Keys
- Mouse Keys
- Tap Dance Keys
- Macro Keys

- Alt-Repeat
- Leaders
- Combos
- Overrides

- Layouts

- Trainer

- Quick Start
- About
- Settings

Use Trainer on your desktop

Install Keyboard Host to show the overlay above your other apps.


Extract the ZIP, then run **Start-Windows.cmd**. First launch needs internet to install its local runtime. No administrator access needed. The app opens Keyboard in your browser. Connect your board, then select **Trainer**. The overlay stays running in the system tray. Is Keyboard Host running? Connect this page to it. If your browser asks to let this site access apps on your device, allow it.

[Connect to Keyboard Host](#)

[Already running? Open local Keyboard](#)

[Release notes](#)

[Download for Windows](#)



Preview background

Light Dark Busy

Layout source

Loaded snapshot

[Import for trainer](#)

Default layer

0 - Layer 0

Preview layer

0 - Layer 0

Overlay Appearance **Feedback** Practice

Layer-change highlight

Short fade

Duration 150 ms

Pressed-key color

Try a simulated chord. No key activity is being monitored.

[Preview held keys](#)

Saving...

PR #3 - 6d9bd1f - Merge pull request #3 from svalboard/refactor/keyboard-service-names

Preview highlighting. Choose Short fade and use Preview held keys to see a simulated chord. The browser preview does not measure native overlay latency.

Standard Keys
Pointing Devices

Special Keys
Layer Keys
Mouse Keys
Tap Dance Keys
Macro Keys

Alt-Repeat
Leaders
Combos
Overrides

Layouts

Trainer


Quick Start
About
Settings

Use Trainer on your desktop

Install Keyboard Host to show the overlay above your other apps.

[Download for Windows](#)

Extract the ZIP, then run **Start-Windows.cmd**. First launch needs internet to install its local runtime. No administrator access needed. The app opens Keyboard in your browser. Connect your board, then select **Trainer**. The overlay stays running in the system tray. Is Keyboard Host running? Connect this page to it. If your browser asks to let this site access apps on your device, allow it.

[Connect to Keyboard Host](#)[Already running? Open local Keyboard](#)[Release notes](#)

Preview background

Light Dark Busy

Layout source

Loaded snapshot

Import for trainer

Default layer

0 - Layer 0

Preview layer

0 - Layer 0

Overlay Appearance Feedback Practice

Preset

Outline only

Key fill

0%

Outline

86%

Legend

100%

Outline thickness


1 px

Contrasting legend halo

Layer change Pressed key

Look at different layers in Trainer. Change Preview layer from base to symbols to function keys, then return to base. This only changes the preview.

Practice recall without recording your typing



The screenshot shows the 'keybard' web application interface. On the left is a sidebar menu with categories like 'Standard Keys', 'Pointing Devices', 'Special Keys', 'Layer Keys', 'Mouse Keys', 'Tap Dance Keys', 'Macro Keys', 'Alt-Repeat', 'Leaders', 'Combos', 'Overrides', 'Layouts', and 'Trainer'. The 'Trainer' section is active. The main content area has a header 'Trainer' and a section 'Use Trainer on your desktop' with instructions and a 'Download for Windows' button. Below this is a 'Connect to Keyboard Host' button and links for 'Already running?', 'Open local Keyboard', and 'Release notes'. The central part of the interface features a large keyboard layout preview with a dark background and light-colored keys. Below the preview are controls for 'Preview background' (Light, Dark, Busy), 'Layout source' (Loaded snapshot, Import for trainer), 'Default layer' (0 - Layer 0), and 'Preview layer' (0 - Layer 0). On the right side, there is a 'Recall practice' section with a toggle switch, a 'FIND THIS BINDING' prompt, the binding 'LGui_T Tab', 'Left hand', a 'Reveal' button, 'Remembered' and 'Again' buttons, and a progress indicator '1 remembered - 1 attempts'. Below this is a 'Familiar bindings' section with instructions to select a key in the preview to mark its current binding familiar.

Practice one recall prompt. Enable Recall practice, decide where the requested binding lives, Reveal it, then choose Remembered to advance. Grading is your own assessment.

1. Open **Practice** and enable **Recall practice**. Read the requested binding and hand, and decide where you would press.
2. Choose **Reveal**, then **Remembered** or **Again** to advance. This is not an automatic typing test.
3. For selective help, choose a key in the preview or the binding selector, click **Mark familiar**, and enable **Hide familiar legends**.
4. Turn practice off to return to ordinary reference. Closing the temporary controls also returns the desktop overlay to reference mode.

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

Trainer

Use Trainer on your desktop

Install Keyboard Host to show the overlay above your other apps.

Extract the ZIP, then run `Start-Windows.cmd`. First launch needs internet to install its local runtime. No administrator access needed.

The app opens Keyboard in your browser. Connect your board, then select **Trainer**. The overlay stays running in the system tray.

Is Keyboard Host running? Connect this page to it. If your browser asks to let this site access apps on your device, allow it.

Connect to Keyboard Host

Already running? Open local Keyboard

Release notes

Preview background

LightDarkBusy

Layout source

Loaded snapshot

Import for trainer

Default layer

Preview layer

0 - Layer 0

0 - Layer 0

OverlayAppearanceFeedbackPractice

Recall practice

Self-assessed practice. Nothing is recorded from your typing. While following the board, recall also hides the desktop legends. Closing these controls returns the overlay to reference mode.

Familiar bindings

Select a key in the preview to mark its current binding familiar.

Left - Control - 0

Mark familiarClear

Hide familiar legends

PR #3 - 6d9bd1f - Merge pull request #3 from svalboard/refactor/keyboard-service-names

Hide a binding you already know.

Select a familiar binding, choose Mark familiar, and enable Hide familiar legends. The preview hides that binding's legend.

Recall counts and familiar selections are temporary practice state, not a durable learning-history service. Appearance preferences are saved separately. When following the board, recall can also hide desktop legends; otherwise you are practicing against the selected preview layout.

CHAPTER 10 / RETURN TO YOUR WORK

Return to your work

After a refresh, Keyboard intentionally returns to the welcome screen. Previously permitted keyboards can appear under **or reconnect without the chooser**. Select the correct device to read its saved state again.

keyboard

Standard Keys

Pointing Devices

Special Keys

Layer Keys

Mouse Keys

Tap Dance Keys

Macro Keys

Alt-Repeat

Leaders

Combos

Overrides

Layouts

Trainer

Quick Start

About

Settings

Connect

0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 mouse

Layer 0

W E I O

ESC S B D T R Y K : N L LT14

Q A [X C F G H J ' , P

Z V U M

LT1 ENTER CAPS LGUI_T TAB BACKSP MO SPACE

SHIFT CTRL ALT MO

1

NORMAL MEDIUM SMALL AUTO

AUTO

PR #3 - 6d9bdf - Merge pull request #3 from svalboard/refactor/keyboard-service-names

Branch: docs/launch-user-manual

Return to a saved file. Choose Load File on the welcome screen and open a .svil file. The operating-system file chooser is not included in this browser recording. Offline example.

To continue offline work, choose **Load File** and reopen your exported draft. Browser preferences and the local Layouts library can persist, but they are not an automatic recovery copy of the current editor session.

Before each editing session, check the target, update mode, selected layer, and whether a key is selected. Use a small naming convention for backups: one before a major change, one after verification. Keep both until the new layout is comfortable.

CHAPTER 11 / TROUBLESHOOTING

Recover from common problems

I cannot connect

Check WebHID browser support, the USB data connection, the chosen device, and compatible firmware. Close other configuration applications if they are holding the device, then reconnect. A previously granted browser permission is not proof that the cable, firmware, or current device connection is working.

The layout changed, but typing did not

Check whether you are editing an offline draft or have pending Manual changes. Confirm the physical keyboard is on the layer you edited. Transparent keys may inherit a different binding, and a layer-tap key waits to distinguish a tap from a hold.

Typing unexpectedly changed a binding

Deselect the target and check **Typing Binds a Key**. In Manual mode, inspect and discard unwanted pending edits. If a change was already applied, explicitly restore the previous binding; discarding does not undo saved writes.

A save failed

Read the **Not saved** message. Pending edits remain, and some earlier writes may already have succeeded. If still connected, use **Retry**. If the device disconnected, **export the retained draft before reconnecting**. Reconnection reads the board again and may discard pending edits. Compare that state with your saved draft, then review an import if appropriate, observing the restore limitations above.

A name will not save

Layer, macro and tap-dance names have a 16-byte UTF-8 limit on supported firmware. Accented characters and emoji can use several bytes each. Shorten the name and read the error. A board's USB name is a separate setting with its own limits.

Controls or layers seem missing

Expand the navigation rail, reveal **Show editor controls** if the toolbar is collapsed, or use **Show All Layers**. Some settings depend on firmware capabilities and attached hardware; an offline example cannot demonstrate every connected-device function.

Keyboard · Svalboard-QMK launch manual

Browser state, files and the board are different places to keep your work. Check the editing target, make one change at a time, and keep an exported copy you have verified.

[Back to the beginning](#) ↑ · [Report an issue](#)