

Photo	Product Standard							
 	Model:	RDJ-D12			RDJ-D12-5G EU		RDJ-D12-5G US	
	Channel	Signal system	Frequency	Power	Signal system	Frequency	Signal system	Frequency
	1	CDMA&868	851-894MHz	30W	GSM	925-960MHz	CDMA/GSM&LORA	850-960MHz
	2	GSM&915&LORA	900-960MHz	30W	DCS	1805-1880MHz	DCS/PCS	1805-2000MHz
	3	DCS/PCS	1805-1880/1920-1990MHz	20W	3G	2110-2170MHz	3G	2110-2180MHz
	4	3G	2110-2180MHz	20W	4GLTE Low	738-821MHz	4GLTE Low	698-798MHz
	5	4GLTE Low	698-798/738-821MHz	30W	4GLTE High	2570-2690MHz	4GLTE High	2496-2690MHz
	6	4GLTE High	2496-2690/2570-2690MHz	20W	5G3.5G/3.7G	3400-3800MHz	5G3.5G/3.7G	3400-3800MHz
	7	WiFi2.4G/4G2300	2400-2485/2300-2485MHz	20W	WiFi2.4G/4G2300	2300-2485MHz	WiFi2.4G/4G2300	2300-2485MHz
	8	WiFi5.2G+5.8G	5125-5850MHz	10W	WiFi5.2G+5.8G	5125-5850MHz	WiFi5.2G+5.8G	5125-5850MHz
	9	GPS&Glonass L1	1560-1610MHz	20W	GPS/5G1500	1427-1610MHz	GPSL1	1560-1610MHz
	10	RC433/UHF&CDMA450	433/400-470MHz	20W	GPSL2L3L4L5	1170-1390MHz	GPSL2L3L4L5	1170-1390MHz
	11	RC315	315MHz	20W	UHF&RC433&CDMA450	400-470MHz	5G600	617-698MHz
	12	VHF&LOJACK	135-175MHz	20W	VHF&LOJACK	135-175MHz	VHF&LOJACK	135-175MHz
	customized							
		4G2300	2300-2400MHz	20W				
		4G1700	1710-1780MHz	20W				
		GPSL2L3L4L5	1170-1390MHz	20W				
Jamming range	20-150M @ depends on the strength signal in given area			★New 12 bands high power indoor using signal jammer,Have good Jamming for all mobile phone 2G,3G,4G 5G signal and VHF/UHF Walkie-Talkie,WIFI,GPS bands.				
Product Size	520X310X90mm		Output Power	260-300 Watt				
Power supply	AC100-240V IN DC24-27V Working				★Total output power: 260-300W , 10-30W each band,Jamming range up to 150m			
Cooling System	10 Cooling fan inside		Working time	non-stopped				
Box Size			G.W/Set	15kg				
Carton Size	60x50x30cm		G.W/CTN	18kg				
Delivery Date	5-10days		Warranty Date	1 Year				
Application Area	Meetingroom,Classroom,Churches,Banks,Cars,Etc.							★ODM and OEM orders are welcome.You can select any 12 bands for your require.

 	Model:	RDJ-D8			RDJ-D8-5G EU		RDJ-D8-5G US		
	Channel	Signal system	Frequency	Power	Signal system	Frequency	Signal system	Frequency	
	1	VHF&LOJACK	135-175MHz	20W	5G1500/GPS/Glonass L1	1427-1610MHz	GPSL1/Glonass L1	1560-1610MHz	
	2	CDMA/GSM&LORA	851-894 /900-960MHz	30W	GSM	925-960MHz	CDMA/GSM&LORA	850-960MHz	
	3	DCS/PCS	1805-1880/1920-1990MHz	20W	DCS	1805-1880MHz	DCS/PCS	1805-2000MHz	
	4	3G	2110-2180MHz	20W	3G	2110-2170MHz	3G	2110-2180MHz	
	5	4GLTE Low	698-798/738-821MHz	30W	4GLTE Low	738-821MHz	4GLTE Low	698-798MHz	
	6	4GLTE High	2496-2690/2570-2690MHz	20W	4GLTE High	2570-2690MHz	4GLTE High	2496-2690MHz	
	7	WiFi2.4G/4G2300	2400-2485/2300-2485MHz	20W	WiFi2.4G/4G2300	2400-2485/2300-2485MHz	WiFi2.4G/4G2300	2400-2485/2300-2485MHz	
	8	GPS&Glonass L1	1560-1610MHz	20W	5G3500/3700	3400-3800MHz	5G600	617-698MHz	
	customized	RC315	315MHz	20W	WiFi5.2G+5.8G	5125-5850MHz	WiFi5.2G+5.8G	5125-5850MHz	
		RC433/UHF&CDMA450	433/400-470MHz	20W					
		4G1700	1710-1780MHz	20W					
		GPSL2L3L4L5	1170-1390MHz	20W					
	Jamming range	20-150M @ depends on the strength signal in given area			★8 bands high power indoor using signal jammer,Have good Jamming for all mobile phone 2G,3G,4G 5G signal and VHF/UHF Walkie-Talkie,WIFI,GPS bands.				
	Product Size	550X190X80mm		Output Power	180 Watt				
	Power supply	AC100-240V TO DC24V IN				★Total output power:180-200W , 10-30W each band,Jamming range up to 150m			
	Cooling System	8 Cooling fan inside		Working time	non-stopped				
Box Size			G.W/Set	10kg					
Carton Size			G.W/CTN	12kg					
Delivery Date	5-10days		Warranty Date	1 Year					
Application Area	Meetingroom,Classroom,Churches,Banks,Cars,Etc.							★ODM and OEM orders are welcome.You can select any 8 bands for your require.	

	Model:	RDJ-D6						
	Channel	Signal system	Frequency	Power				
	1	CDMA/GSM&LORA	851-894 /900-960MHz	30W				
	2	DCS/PCS	1805-1880/1920-1990MHz	20W				
	3	3G	2110-2180MHz	20W				
	4	4GLTE Low	698-798/738-821MHz	30W				
	5	4GLTE High	2496-2690/2570-2690MHz	20W				
	6	WiFi2.4G/4G2300	2400-2485/2300-2485MHz	20W				



customized	RC315	315MHz	20W					
	VHF&LOJACK	135-175MHz	20W					
	RC433UHF&CDMA450	433/400-470MHz	20W					
	4G1700	1710-1780MHz	20W					
	4G1700	1710-1780MHz	20W					
	GPS&Glonass L1	1560-1610MHz	20W					
	4G2300	2300-2400MHz	20W					
Jamming range	20-150M @ depends on the strength signal in given area			#6 bands high power indoor using signal jammer,Have good Jamming for all mobile phone 2G,3G,4G signal and VHF/UHF Walkie-Talkie,WIFI,GPS bands.				
Product Size	450X190X80mm	Output Power	140 Watt	#Total output power:140W , 10-30W each band,Jamming range up to 150m				
Power supply	AC100-240V TO DC24V IN			#Can adjust output power or turn off any single band without influencing the other bands operation				
Cooling System	8 Cooling fan inside	Working time	non-stopped	#Each band PCB board is independent design with frequency source,Replace damaged parts directly,convenient maintenance. Each band has LED pilot light for working				
Box Size		G.W/Set	8kg	#Good cooling system with 8 cooling fans inside				
Carton Size		G.W/CTN	10kg	#Use External High gain Omni-directional antennas,all the TX frequency covered down link only				
Delivery Date	1-3days	Warranty Date	1 Year	#ODM and OEM orders are welcome,You can select any 6 bands for your require.				
Application Area	Meetingroom,Classroom,Churches,Banks,Cars,Etc.							

Remarks:

1)The price is basis on factory price without tax,Just reference.Final price is decided to order quantity and your special require.

2)Validity:2020