


CONNECTORS (USB)

USB 1.x/2.0

Pin 1	Vbus (+5V)
Pin 2	Data-
Pin 3	Data+
Pin 4	Ground

Type A



Example part number:
WM7087CT-ND

Type B



Example part number:
WM17113-ND

USB 2.0/2.0 R

Pin 1	Vbus (+5V)
Pin 2	Data-
Pin 3	Data+
Pin 4	NC/OTG ID (On-the-Go) ID distinguishes cable ends: A Plug (host): connected to GND B Plug (device): not connected
Pin 5	Ground

Type B Mini



Example part number:
WM5461CT-ND

Type B Micro



Example part number:
609-4618-1-ND

USB 3.x Standard A Type

Pin 1	Vbus (+5V)
Pin 2	Data-
Pin 3	Data+
Pin 4	Ground
Pin 5	RX-
Pin 6	RX+
Pin 7	Ground (Drain)
Pin 8	TX-
Pin 9	TX+

Type A



Example part number:
WM10413CT-ND

USB 3.x Standard B Type

Pin 1	Vbus (+5V)
Pin 2	Data-
Pin 3	Data+
Pin 4	Ground
Pin 5	TX-
Pin 6	TX+
Pin 7	Ground (Drain)
Pin 8	RX-
Pin 9	RX+

Type B




Example part number:
553-2263-ND

USB C Type

Pin A1	Ground
Pin A2	TX1+
Pin A3	TX1-
Pin A4	Vbus (+5V)
Pin A5	CC1
Pin A6	Data+
Pin A7	Data-
Pin A8	SBU1 (Side Band Use)
Pin A9	Vbus (+5V)
Pin A10	RX2-
Pin A11	RX2+
Pin A12	Ground

Pin B1	Ground
Pin B2	TX2+
Pin B3	TX2-
Pin B4	Vbus (+5V)
Pin B5	CC2
Pin B6	Data+
Pin B7	Data-
Pin B8	SBU2 (Side Band Use)
Pin B9	Vbus (+5V)
Pin B10	RX1-
Pin B11	RX1+
Pin B12	Ground

Type C



Example part number:
WM12856CT-ND


CONNECTORS

Ethernet – EIA/TIA T568A


Pin 1	TX+
Pin 2	TX-
Pin 3	RX+
Pin 4	
Pin 5	
Pin 6	RX-
Pin 7	
Pin 8	

Ethernet – EIA/TIA T568B

Pin 1	TX+
Pin 2	TX-
Pin 3	RX+
Pin 4	
Pin 5	
Pin 6	RX-
Pin 7	
Pin 8	



Example part number:
WM7131CT-ND




Example part number:
RJE73-188-00140CT-ND

HDMI

Pin 1	Data 2+
Pin 2	Data 2 (Shield)
Pin 3	Data 2-
Pin 4	Data 1+
Pin 5	Data 1 (Shield)
Pin 6	Data 1-
Pin 7	Data 0+
Pin 8	Data 0 (Shield)
Pin 9	Data 0-
Pin 10	CLK+ (Clock)
Pin 11	CLK (Shield)
Pin 12	CLK - (Clock)
Pin 13	CEC
Pin 14	Reserved
Pin 15	SCL (I ² C Serial clock)
Pin 16	SDA (I ² C Serial Data)
Pin 17	DDC/CEC Ground
Pin 18	Vbus (+ 5 V)
Pin 19	HPD (Hot Plug Detect)

Type A Standard




Example part number:
1175-1703-ND



Example part number:
WM25457-ND

Type C Mini



Example part number:
A108261CT-ND



Example part number:
TL714-ND

Type D Micro




Example part number:
609-4617-1-ND




Example part number:
WM1284-ND

JTAG 6 Pin




Pin 1	VTref (Target Voltage Ref.)
Pin 2	TMS (Test Mode Select)
Pin 3	TRST (Test Reset)
Pin 4	TCK (Test Clock)
Pin 5	Ground
Pin 6	TDO (Test Data Out)

ARM Cortex 10 Pin JTAG/SWD



Pin 1	Vcc
Pin 2	SDWIO/TMS
Pin 3	Ground
Pin 4	SWDCLK/TCLK
Pin 5	Ground
Pin 6	SWO/TDO
Pin 7	KEY
Pin 8	NC/TDI
Pin 9	GNDDetect
Pin 10	nRESET

RS232 DB9



Pin 1	DCD (Data Carrier Detect)
Pin 2	RXD (Serial Data Input)
Pin 3	TXD (Serial Data Output)
Pin 4	DTR (Data Terminal Ready)
Pin 5	Ground (Signal)
Pin 6	DSR (Data Set Ready)
Pin 7	RTS (Request to Send)
Pin 8	CTS (Clear to Send)
Pin 9	RI (Ring Indicator)

Micro SD



Pin 1	Data 2
Pin 2	CD/Data 3
Pin 3	CMD (I/O Command)
Pin 4	Ground
Pin 5	CLK (Clock)
Pin 6	Vbus (3.3 V)
Pin 7	Data 0
Pin 8	Data 1

OTHER TOP CONNECTORS AT DIGI-KEY



WM1837CT-ND
20-24 AWG Crimp



WM2501CT-ND
18-24 AWG Crimp



A98333-ND
2 Pos Terminal Block




CP-102A-ND
Power Barrel
2.10 mm ID, 5.50 mm OD



839-1291-ND
Power Barrel
2.10 mm ID, 5.50 mm OD




ED1543-ND
10 Pos .1" Header




S1011EC-40-ND
40 Pos .1" Header



609-3695-1-ND
10 Pos SMD
.05" Header



S7037-ND
4 Pos 0.1" Header



S7006-ND
8 Pos 0.1" Header



A97594-ND
50 Ohm SMA



AE11063-ND
9 Pos D-Sub Female



AE10921-ND
9 Pos D-Sub Female



AE10972-ND
9 Pos D-Sub Male



AE10968-ND
9 Pos D-Sub Male



J152-ND
Banana Jack



501-1076-ND
Banana Plug



J151-ND
Banana Jack



501-1077-ND
Banana Plug



455-1165-ND
2 Pos Receptacle



455-1704-ND
2 Pos Through
Hole



455-1749-1-ND
2 Pos Surface
Mount



900-0022232021-ND
2 Pos .1"
Through Hole



900-0022013027-ND
2 Pos .1"
Receptacle



455-1184-ND
3 Pos Receptacle



455-1640-ND
3 Pos Through Hole




455-2267-ND
4 Pos Receptacle



455-2249-ND
4 Pos Through Hole



WM1845-ND
2 Pos 3 mm
Receptacle



WM1855-ND
2 Pos 3 mm Plug



WM1784-ND
4 Pos 3 mm
Receptacle



WM2772-ND
4 Pos 3 mm Plug



WM1785-ND
6 Pos 3 mm
Receptacle



WM2762-ND
6 Pos 3 mm Plug

For more information, visit [DIGIKEY.COM/NOTEBOOK](https://www.digikey.com/notebook)