Motor_SOP_v2 - Scope & Safety

Document: Motor_SOP_v2.pdf Revision: A Section: Motor Overheating

Scope: maintenance procedure for motor overheating on plant equipment.

PPE: ISI helmet, cut-resistant gloves, safety goggles. Isolate power and apply lockout/tagout (LOTO). Operator fatigue below 70%. Written supervisor approval is required before starting.

Motor Overheating - Procedure

Follow these steps in order:

1. Check coolant >80%
2. Clean air filter
3. Check sensor 10k ohm
4. Cool 10min
5. Restart

Motor Overheating - Symptoms, Limits & Escalation

Symptoms and limits: Motor overheating >85C. Causes: coolant low, filter clogged.

Keywords: motor, overheat, garam, heat, temperature, hot

Escalate to the maintenance supervisor if the fault persists after one attempt.