BLOC VALVES STATION " BVS 01 "

DEPARTS		EQUIPEMENT	TENSION (V)	RATED POWER Pn (W)	Qty	TOTAL RATED POWER Pnt (W)	Time on H/Day	Power x Hour (Watt.H)	TOTAL Power x Hour (Watt.H)
1	RTU cabinet	24V DC DC/DC Converter (Pro Top DCDC 480 W)	24	136,8	1	136,80	24	**3283,20**	**3433,20**
		24V DC to 230V AC Inverter (NTS-450-224EU) Laptp charging	24	150	1	150	1	**150**	
2	TELECOM cabinet	ETH-SW (Switch 8*10/100/1000, 4*10GE SFP+, PoE+, AC)	24	29,78	2	59,56	24	**1429,44**	**2919,08**
		INTERPHONE-SW (Switch 8*10/100/1000, 4*10GE SFP+, PoE+, AC)		29,78	1	29,78	24	**714,72**	
		Industrial Interphone (SIP-VoIP)		2	1	2	24	**48**	
		Cabinet LIGHT		11	1	11	1	**11**	
		Cabinet FANs		15	4	60	6	**360**	
		Power Inverter 750W, 24VDC/230VAC		11,36	1	11,36	24	**272,64**	
		Redundancy module 24VDC		3,47	1	3,47	24	**83,28**	
3	SDV-01	Motor Power	24	392	1	392	0,1	**39,2**	**1719,20**
		Internal Electronics		70	1	70	24	**1 680**	
4	C P C U	CATHODIC PROTECTION CONTROL UNIT CPCU	24	240	1	240	24	**5 760**	**5760,00**
5	DC to AC Converter	EXTRACTEUR D'AIR	230	180	1	180	1	**180**	**180,00**
		Eclairage Local batterie		20	1	20	1	**20**	**20,00**
TOTAL CONSUMPTION OF ENERGY " BVS01"									**14 031,48**
TOTAL POWER CONSUMPTION BVS01 (+20%) FINAL									**16 837,78**

BLOC VALVES STATION " BVS 02 "

DEPARTS		EQUIPEMENT	TENSION (V)	RATED POWER Pn (W)	Qty	TOTAL RATED POWER Pnt (W)	Time on H/Day	Power x Hour (Watt.H)	TOTAL Power x Hour (Watt.H)
1	RTU cabinet	24V DC DC/DC Converter (Pro Top DCDC 480 W)	24	136,8	1	136,80	24	**3283,20**	**3433,20**
		24V DC to 230V AC Inverter (NTS-450-224EU) Laptp charging	24	150	1	150	1	**150**	
2	TELECOM cabinet	ETH-SW (Switch 8*10/100/1000, 4*10GE SFP+, PoE+, AC)	24	29,78	2	59,56	24	**1429,44**	**2919,08**
		INTERPHONE-SW (Switch 8*10/100/1000, 4*10GE SFP+, PoE+, AC)		29,78	1	29,78	24	**714,72**	
		Industrial Interphone (SIP-VoIP)		2	1	2	24	**48**	
		Cabinet LIGHT		11	1	11	1	**11**	
		Cabinet FANs		15	4	60	6	**360**	
		Power Inverter 750W, 24VDC/230VAC		11,36	1	11,36	24	**272,64**	
		Redundancy module 24VDC		3,47	1	3,47	24	**83,28**	
3	SDV-02	Motor Power	24	392	1	392	0,1	**39,2**	**1719,20**
		Internal Electronics	24	70	1	70	24	**1680**	
4	DC to AC Converter	EXTRACTEUR D'AIR	230	180	1	180	1	**180**	**180,00**
		Eclairage Local batterie		20	1	20	1	**20**	**20,00**
TOTAL CONSUMPTION OF ENERGY " BVS02" (FINAL)									**8 271,48**
TOTAL POWER CONSUMPTION BVS02 (+20%) FINAL									**9 925,78**

SONATRACH	N° DOCUMENT CLIENT	22011-GREB-CE-EL-81-EZ-003	
	N° PROJET ENAC	N° DOCUMENT ENAC	Rev
ENAC	22011	N/A	3
	Date 26/02/2026	Page **5** sur **5**	
BILAN DE PUISSANCE	PRÉPARÉ S. ALIOUAT VÉRIFIÉ A. KADDOUR APPROUVÉ S. AMOURA		

BLOC VALVES STATION " TERMINAL ARRIVEE "

DEPARTS		EQUIPEMENT	TENSION (V)	RATED POWER Pn (W)	Qty	TOTAL RATED POWER Pnt (W)	Time on H/Day	Power x Hour (Watt.H)	TOTAL Power x Hour (Watt.H)
1	RTU cabinet	24V DC DC/DC Converter (Pro Top DCDC 480 W)	24	178,9	1	178,9	24	4293,6	4443,60
		24V DC to 230V AC Inverter (NTS-450-224EU)	24	150	1	150	1	150	
2	TELECOM cabinet	ETH-SW (Switch 8*10/100/1000, 4*10GE SFP+, PoE+, AC)	24	29,78	2	60	24	1429,4	2832,07
		INTERPHONE-SW (Switch 8*10/100/1000, 4*10GE SFP+, PoE+, AC)	24	29,78	1	29,8	24	714,7	
		Industriel interphone (SIP-VoIP)	24	2	1	2	24	48	
		Cabinet LIGHT	24	11	1	11	1	11	
		Cabinet FANs	24	15	4	60	6	360	
		Power Inverter 750W, 24VDC/230VAC	24	6,39	1	6,4	24	153,5	
		10/100TX To 100FX industriel Media Converter, SC, SM, 30KM	24	2,8	1	2,8	24	67,2	
		Redundancy module 24VDC	24	2,01	1	2,0	24	48,3	
3	CPCU	CATHODIC PROTECTION CONTROL UNIT CPCU	24	240	1	240	24	5760	5760,00
4	SDV-03	Motor Power	24	392	1	392	0,1	39,2	1 719,20
		Internal Electronics	24	70	1	70	24	1 680	
5	SDV-04	Motor Power	24	392	1	392	0,1	39,2	1 719,20
		Internal Electronics	24	70	1	70	24	1 680	
6	ESDV-02	Motor Power	24	414	1	414	0,1	41,4	1 721,40
		Internal Electronics	24	70	1	70	24	1 680	
7	ESDV-03	Motor Power	24	414	1	414	0,1	41,4	1 721,40
		Internal Electronics	24	70	1	70	24	1 680	
8	SKID-COMP	SKID DE COMPTAGE	24	196,81	1	196,81	24	4723,4	4723,44
9	L.BATT & AUX	SKID DE FILTRATION	24	3	1	3	24	72	72,00
10	D-M	Débimètre coriolis	24	15	1	15	24	360	360,00
11	DC to AC Converter	EXTRACTEUR D'AIR	230	180	1	180	1	180	180,00
		Eclairage Local batterie		20	1	20	1	20	20,00
TOTAL CONSUMPTION OF ENERGY " TERMINAL ARRIVEE"									25 272,31
TOTAL POWER CONSUMPTION TERMINAL ARRIVEE (+20%) (FINAL)									31 127,62