

Solar[®] Turbines

A Caterpillar Company

Wire List

Wire List

PD/Unit Number:

4K761 / 1

Project Name:

DTE-CAL

Sheet Name:

GEN CTRL

Revision:

B.2

PERSONNEL / SWS SIGN-IN

BADGE #	DATE	TIME	WIRER	IPV
-----	--/--/----	--:--	☐	☐
-----	--/--/----	--:--	☐	☐
-----	--/--/----	--:--	☐	☐
-----	--/--/----	--:--	☐	☐
-----	--/--/----	--:--	☐	☐
-----	--/--/----	--:--	☐	☐

Table of Contents

#	SECTION	ROWS	PAGE
INTERNAL			
GEN CTRL			
1	Grounds	16	3
2	AF/AU Jumpers	8	3
3	Clips	35	3
4	Relay Mechanical Jumpers	3	4
KA			
	<i>L A2: KA0330 → KA0331</i>	1	4
	<i>L A2: KA0332 → KA0333</i>	1	4
	<i>L A2: KA0335 → KA0336</i>	1	4
5	VIO Jumpers	4	5
AF			
	<i>L AF0122</i>	1	5
	<i>L AF0182</i>	3	5
6	KA Twin Ferrules	8	5
KA			
	<i>L KA0128:11 / FU0333</i>	2	5
	<i>L KA0310:24 / KA0333A1</i>	2	5
	<i>L KA0333:11 / KA033311</i>	2	5
	<i>L KA0333:14 / KA033314</i>	2	5
7	FU Jumpers	2	5
FU			
	<i>L FU0120-FU0121</i>	1	5
	<i>L FU0180-FU0181</i>	1	5
8	Single Connections	95	5
AF			
	<i>L AF0121</i>	10	5
	<i>L AF0122</i>	8	5
	<i>L AF0181</i>	10	5
AT			
	<i>L AT0140</i>	23	5
KA			
	<i>L KA0123</i>	3	5
	<i>L KA0185</i>	3	5
	<i>L KA0332</i>	3	5
	<i>L KA0335</i>	4	5
	<i>L KA0121</i>	2	5
	<i>L KA0128</i>	2	5
	<i>L KA0184</i>	2	5
	<i>L KA0336</i>	2	5
	<i>L KA:A1 - XT</i>	2	5

#	SECTION	ROWS	PAGE
	<i>L</i> KA0331	2	5
	<i>L</i> KA0333	2	5
	AF		
	<i>L</i> AF0182	2	5
	AU		
	<i>L</i> AU0120	2	5
	<i>L</i> AU0180	2	5
	FU		
	<i>L</i> FU0333	2	5
	<i>L</i> FU0334	2	5
	<i>L</i> FU - FU	2	5
	<i>L</i> FU - XT	3	5
	XT		
	<i>L</i> XT0336	2	5
9	Cables	16	8

4K761 DTE-CAL - Wire List

Unit: 1 Rev: B.2 Rows: 215

INTERNAL
GEN CTRL

Grounds (16)

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
☐	AT0140:16 VGEN-N	VBUSN	GRN/YEL	12	☐	XT0351:8	☐	
☐	AT0140:20 VBUS-N	VBUSN	GRN/YEL	12	☐	XT0351:7	☐	
☐	AT0140:56 FG	AT0140G	GRN/YEL	12	☐	FRAME	☐	
☐	PEG0140:3	EXCS	GRN/YEL	16	☐	XT0370:6	☐	
☐	PEG0140:2	PMGS	GRN/YEL	14	☐	XT0313:1	☐	
☐	PEG0140:4	PEG01404	GRN/YEL	12	☐	XT0352:7	☐	
☐	AF0184:SH	AF0184G	GRN	14	☐	AF0185:SH	☐	
☐	AF0123:SH	AU0120G	GRN	14	☐	AU0120:GND	☐	
☐	AF0184:SH	AU0180G	GRN	14	☐	AU0180:GND	☐	
☐	AF0123:SH	IEG01405	GRN	14	☐	IEG0140:5	☐	
☐	AF0185:SH	IEG01408	GRN	14	☐	IEG0140:8	☐	
☐	GR0143	GR0143	GRN/YEL	14	☐	FRAME	☐	
☐	GR0144	GR0144	GRN/YEL	14	☐	FRAME	☐	
☐	GR0142	GR0142	GRN	14	☐	IEG0140:4	☐	
☐	GR0241	IEG01401	GRN	14	☐	IEG0140:1	☐	
☐	IEG0140:7	AT0140LS(S)	GRN	14	☐	XT0354:3	☐	

INTERNAL
GEN CTRL

AF/AU Jumpers (8)

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
☐	AF0122:V+	AF0122P	WHT	16	☐	AF0123:V+	☐	
☐	AF0122:COM	AF0122N	WHT	16	☐	AF0123:COM	☐	
☐	AF0182:V+	AF0182P	WHT	16	☐	AF0183:V+	☐	
☐	AF0182:COM	AF0182N	WHT	16	☐	AF0183:COM	☐	
☐	AF0183:V+	AF0183P	WHT	16	☐	AF0184:V+	☐	
☐	AF0183:COM	AF0183N	WHT	16	☐	AF0184:COM	☐	

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
☐	AF0184:V+	AF0184P	WHT	16	☐	AF0185:V+	☐	
☐	AF0184:COM	AF0184N	WHT	16	☐	AF0185:COM	☐	

INTERNAL
GEN CTRL

Clips (35)

FROM			TO			
COMPLETE	DEVICE ID	WIRE ID	COMPLETE	DEVICE ID	IPV	NOTES
☐	XT0335:1	CLIP	☐	XT0335:2	☐	
☐	XT0335:2	CLIP	☐	XT0335:3	☐	
☐	XT0335:3	CLIP	☐	XT0335:4	☐	
☐	XT0335:4	CLIP	☐	XT0335:5	☐	
☐	XT0335:5	CLIP	☐	XT0335:6	☐	
☐	XT0335:6	CLIP	☐	XT0335:7	☐	
☐	XT0335:7	CLIP	☐	XT0335:8	☐	
☐	XT0335:8	CLIP	☐	XT0335:9	☐	
☐	XT0335:9	CLIP	☐	XT0335:10	☐	
☐	XT0336:1	CLIP	☐	XT0336:2	☐	
☐	XT0336:2	CLIP	☐	XT0336:3	☐	
☐	XT0336:3	CLIP	☐	XT0336:4	☐	
☐	XT0336:4	CLIP	☐	XT0336:5	☐	
☐	XT0336:5	CLIP	☐	XT0336:6	☐	
☐	XT0336:6	CLIP	☐	XT0336:7	☐	
☐	XT0336:7	CLIP	☐	XT0336:8	☐	
☐	XT0336:8	CLIP	☐	XT0336:9	☐	
☐	XT0336:9	CLIP	☐	XT0336:10	☐	
☐	XT0351:1	CLIP	☐	XT0351:2	☐	
☐	XT0351:3	CLIP	☐	XT0351:4	☐	
☐	XT0351:5	CLIP	☐	XT0351:6	☐	
☐	XT0351:7	CLIP	☐	XT0351:8	☐	
☐	XT0351:9	CLIP	☐	XT0351:10	☐	
☐	XT0351:11	CLIP	☐	XT0351:12	☐	
☐	XT0351:13	CLIP	☐	XT0351:14	☐	
☐	XT0352:4	CLIP	☐	XT0352:5	☐	
☐	XT0352:5	CLIP	☐	XT0352:6	☐	

FROM			TO			
COMPLETE	DEVICE ID	WIRE ID	COMPLETE	DEVICE ID	IPV	NOTES
☐	XT0352:6	CLIP	☐	XT0352:7	☐	
☐	XT0370:1	CLIP	☐	XT0370:2	☐	
☐	XT0370:4	CLIP	☐	XT0370:3	☐	
☐	XT0370:5	CLIP	☐	XT0370:6	☐	
☐	XT0120:1	CLIP	☐	XT0120:2	☐	
☐	XT0120:3	CLIP	☐	XT0120:2	☐	
☐	XT0350:2	CLIP	☐	XT0350:1	☐	
☐	XT0350:4	CLIP	☐	XT0350:3	☐	

INTERNAL

GEN CTRL

Relay Mechanical Jumpers (3)

FROM			TO			
COMPLETE	DEVICE ID	WIRE ID	COMPLETE	DEVICE ID	IPV	NOTES
A2: KA0330 -> KA0331						
☐	KA0330:A2	WHT	☐	KA0331:A2	☐	
A2: KA0332 -> KA0333						
☐	KA0332:A2	WHT	☐	KA0333:A2	☐	
A2: KA0335 -> KA0336						
☐	KA0335:A2	WHT	☐	KA0336:A2	☐	

INTERNAL

GEN CTRL

VIO Jumpers (4)

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
AF0122								
☐	AF0122:06	JP5	VIO	20	☐	AF0122:38	☐	
AF0182								
☐	AF0182:01	JP1	VIO	20	☐	AF0182:33	☐	
☐	AF0182:07	JP4	VIO	20	☐	AF0182:39	☐	
☐	AF0182:15	JB19	VIO	20	☐	AF0182:47	☐	

INTERNAL

GEN CTRL

KA Twin Ferrules (8)

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
KA0128:11 / FU0333								
☐	KA0128:11	FU0333	WHT	20	☐	KA0335:21	☐	
☐	KA0128:11	FU0333	WHT	20	☐	XT0338:1	☐	
KA0310:24 / KA0333A1								
☐	KA0310:24	KA0333A1	WHT	20	☐	KA0335:22	☐	
☐	KA0310:24	KA0333A1	WHT	20	☐	XT0338:2	☐	
KA0333:11 / KA033311								
☐	KA0333:11	KA033311	WHT	20	☐	KA0335:11	☐	
☐	KA0333:11	KA033311	WHT	20	☐	XT0337:5	☐	
KA0333:14 / KA033314								
☐	KA0333:14	KA033314	WHT	20	☐	KA0335:12	☐	
☐	KA0333:14	KA033314	WHT	20	☐	XT0337:6	☐	

INTERNAL

GEN CTRL

FU Jumpers (2)

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
FU0120-FU0121								
☐	FU0120:LI	FU0122	WHT	14	☐	FU0121:LI	☐	
FU0180-FU0181								
☐	FU0180:LI	FU0182	WHT	14	☐	FU0181:LI	☐	

INTERNAL

GEN CTRL

Single Connections (95)

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
AF0121								
☐	AF0121:V+	FU0121	WHT	16	☐	FU0121:LD	☐	
☐	AF0121:COM	-0V	WHT	16	☐	XT0120:2	☐	
☐	AF0121:30	KA4100A2	WHT	20	☐	KA4100:A2	☐	
☐	AF0121:24	-012124	WHT	20	☐	KA0128:A2	☐	

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
☐	AF0121:19	KA0123A2	WHT	20	☐	KA0123:A2	☐	
☐	AF0121:17	-012117	WHT	20	☐	KA0121:A2	☐	
☐	AF0121:14	KA033611	WHT	20	☐	KA0336:11	☐	
☐	AF0121:08	-012108	WHT	20	☐	KA0128:A1	☐	
☐	AF0121:03	KA0123A1	WHT	20	☐	KA0123:A1	☐	
☐	AF0121:01	-012101	WHT	20	☐	KA0121:A1	☐	
AF0122								
☐	AF0122:V+	AU0120P	WHT	16	☐	AU0120:V+	☐	
☐	AF0122:34	KA031014	WHT	20	☐	KA0310:14	☐	
☐	AF0122:33	-012233	WHT	20	☐	KA0331:14	☐	
☐	AF0122:32	-012232	WHT	20	☐	KA0330:14	☐	
☐	AF0122:COM	AU0120N	WHT	16	☐	AU0120:COM	☐	
☐	AF0122:02	KA031011	WHT	20	☐	KA0310:11	☐	
☐	AF0122:01	-012201	WHT	20	☐	KA0331:11	☐	
☐	AF0122:00	-012200	WHT	20	☐	KA0330:11	☐	
AF0181								
☐	AF0181:V+	FU0181	WHT	16	☐	FU0181:LD	☐	
☐	AF0181:COM	-0V	WHT	16	☐	XT0180:1	☐	
☐	AF0181:28	KA0184A2	WHT	20	☐	KA0184:A2	☐	
☐	AF0181:26	-018126	WHT	20	☐	XT0181:2	☐	
☐	AF0181:18	KA0181A2	WHT	20	☐	KA0181:A2	☐	
☐	AF0181:16	-018116	WHT	20	☐	KA0180:A2	☐	
☐	AF0181:12	KA0184A1	WHT	20	☐	KA0184:A1	☐	
☐	AF0181:10	-018110	WHT	20	☐	KA0185:A1	☐	
☐	AF0181:02	KA0181A1	WHT	20	☐	KA0181:A1	☐	
☐	AF0181:00	-018100	WHT	20	☐	KA0180:A1	☐	
AT0140								
☐	AT0140:3 EX-D(-)	-0V	WHT	16	☐	XT0336:6	☐	
☐	AT0140:4 EX-D(+)	KA012314	WHT	16	☐	KA0123:14	☐	
☐	AT0140:13 VGEN-A	VGENA	RED	16	☐	XT0351:9	☐	
☐	AT0140:14 VGEN-B	VGENB	RED	16	☐	XT0351:11	☐	
☐	AT0140:15 VGEN-C	VGENC	RED	16	☐	XT0351:13	☐	
☐	AT0140:17 VBUS-A	VBUSA	RED	16	☐	XT0351:2	☐	
☐	AT0140:18 VBUS-B	VBUSB	RED	16	☐	XT0351:3	☐	
☐	AT0140:19 VBUS-C	VBUSC	RED	16	☐	XT0351:5	☐	
☐	AT0140:27 ID RLY	CCT1(+)	BLU	12	☐	XT0350:2	☐	

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
☐	AT0140:28 ID RLY	CCT1(-)	BLU	12	☐	XT0350:4	☐	
☐	AT0140:33 ID RES(+)	CCT1(+)	BLU	12	☐	XT0350:1	☐	
☐	AT0140:34 ID RES(-)	AT014034	WHT	16	☐	AT0140:42 ID(+)	☐	
☐	AT0140:36 I1(+)	MCTA	BLU	12	☐	XT0352:1	☐	
☐	AT0140:37 I1(-)	MCTAN	BLU	12	☐	XT0352:6	☐	
☐	AT0140:38 I2(+)	MCTB	BLU	12	☐	XT0352:2	☐	
☐	AT0140:39 I2(-)	MCTBN	BLU	12	☐	XT0352:5	☐	
☐	AT0140:40 I3(+)	MCTC	BLU	12	☐	XT0352:3	☐	
☐	AT0140:41 I3(-)	MCTN	BLU	12	☐	XT0352:4	☐	
☐	AT0140:43 ID(-)	CCT1(-)	BLU	12	☐	XT0350:3	☐	
☐	AT0140:BAT(-) 48	-0V	WHT	16	☐	XT0336:6	☐	
☐	AT0140:BAT(+) 47	FU0334	WHT	16	☐	XT0339:1	☐	
☐	AT0140:FLT 29	KA0310A2	WHT	20	☐	KA0310:A2	☐	
☐	AT0140:FLT 30	-0V	WHT	16	☐	XT0336:6	☐	
KA0123								
☐	KA0123:11	FU0334	WHT	16	☐	XT0339:1	☐	
☐	KA0123:A1	KA0123A1	WHT	20	☐	KA0313:2	☐	
☐	KA0123:A2	KA0123A2	WHT	20	☐	KA0313:7	☐	
KA0185								
☐	KA0185:11	KA018511	WHT	20	☐	XT0338:3	☐	
☐	KA0185:14	KA0332A1	WHT	20	☐	XT0338:4	☐	
☐	KA0185:A2	KA0185A2	WHT	20	☐	XT0181:1	☐	
KA0332								
☐	KA0332:11	KA033211	WHT	20	☐	XT0337:3	☐	
☐	KA0332:14	KA033214	WHT	20	☐	XT0337:4	☐	
☐	KA0332:A1	KA0332A1	WHT	20	☐	XT0338:4	☐	
KA0335								
☐	KA0335:21	FU0333	WHT	20	☐	KA0310:21	☐	
☐	KA0335:22	KA0333A1	WHT	20	☐	KA0128:14	☐	
☐	KA0335:A1	ESTOP	WHT	16	☐	XT0120:4	☐	
☐	KA0335:A2	-0V	WHT	20	☐	XT0120:3	☐	
AF0182								
☐	AF0182:V+	AU0180P	WHT	16	☐	AU0180:V+	☐	
☐	AF0182:COM	AU0180N	WHT	16	☐	AU0180:COM	☐	
KA0121								
☐	KA0121:11	FU0333	WHT	20	☐	XT0338:1	☐	

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
☐	KA0121:14	KA018511	WHT	20	☐	XT0338:3	☐	
KA0128								
☐	KA0128:21	KA012821	WHT	20	☐	XT0337:1	☐	
☐	KA0128:24	KA012824	WHT	20	☐	XT0337:2	☐	
KA0184								
☐	KA0184:11	CC71771	WHT	20	☐	XT2100:1	☐	
☐	KA0184:14	CC71772	WHT	20	☐	XT2100:2	☐	
AU0120								
☐	AU0120:V+	FU0120	WHT	16	☐	FU0120:LD	☐	
☐	AU0120:COM	-0V	WHT	16	☐	XT0120:2	☐	
AU0180								
☐	AU0180:V+	FU0180	WHT	16	☐	FU0180:LD	☐	
☐	AU0180:COM	-0V	WHT	16	☐	XT0180:1	☐	
FU - FU								
☐	FU0120:LI	FU0122	WHT	14	☐	FU0122:LD	☐	
☐	FU0180:LI	FU0182	WHT	14	☐	FU0182:LD	☐	
FU - XT								
☐	FU0122:LI	FU0332	WHT	14	☐	XT0335:2	☐	
☐	FU0182:LI	FU0332	WHT	14	☐	XT0335:3	☐	
☐	FU0332:LD	FU0332	WHT	12	☐	XT0335:1	☐	
FU0333								
☐	FU0333:LD	FU0333	WHT	16	☐	XT0338:1	☐	
☐	FU0333:LI	FU0332	WHT	16	☐	XT0335:4	☐	
FU0334								
☐	FU0334:LD	FU0334	WHT	16	☐	XT0339:1	☐	
☐	FU0334:LI	FU0332	WHT	16	☐	XT0335:6	☐	
KA0336								
☐	KA0336:14	KA4100A1	WHT	20	☐	KA4100:A1	☐	
☐	KA0336:A1	KA0131A1	WHT	16	☐	XT0120:5	☐	
KA:A1 - XT								
☐	KA0310:A1	FU0334	WHT	20	☐	XT0339:1	☐	
☐	KA0330:A1	KA0330A1	WHT	20	☐	XT0338:5	☐	
KA0331								
☐	KA0331:A1	KA0331A1	WHT	20	☐	XT0338:6	☐	
☐	KA0331:A2	-0V	WHT	20	☐	XT0336:5	☐	
KA0333								
☐	KA0333:A1	KA0333A1	WHT	20	☐	XT0338:2	☐	

FROM					TO			
COMPLETE	DEVICE ID	NO.	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
☐	KA0333:A2	-0V	WHT	20	☐	XT0336:4	☐	
XT0336								
☐	XT0336:2	-0V	WHT	14	☐	XT0120:1	☐	
☐	XT0336:3	-0V	WHT	14	☐	XT0180:1	☐	

INTERNAL
GEN CTRL

Cables (16)

FROM					TO			
COMPLETE	DEVICE ID	TYPE	WIRE ID	SIZE	COMPLETE	DEVICE ID	IPV	NOTES
Cable: WC8009								
☐	AT0140:1 LS(+)	WC8009	CLR	16	☐	XT0354:1	☐	
☐	AT0140:2 LS(-)	WC8009	BLK	16	☐	XT0354:2	☐	
☐	FW5:1	WC8009	SH	16	☐	XT0354:3	☐	
Cable: WC8101								
☐	FU0313:LD	WC8101	WHT	12	☐	XT0360:1	☐	
☐	FU0314:LD	WC8101	BLK	12	☐	XT0360:2	☐	
☐	XT0360:4	WC8101	SH	12	☐	XT0360:3	☐	
Cable: WC8102								
☐	AT0140:54 EXC(+)	WC8102	WHT	12	☐	XT0370:2	☐	
☐	AT0140:55 EXC(-)	WC8102	BLK	12	☐	XT0370:3	☐	
☐	FW3:1	WC8102	SH	12	☐	XT0370:6	☐	
Cable: WC8201								
☐	FU0313:LI	WC8201	WHT	12	☐	KA0313:1	☐	
☐	FU0314:LI	WC8201	BLK	12	☐	KA0313:8	☐	
☐	XT0360:3	WC8201	SH	12	☐	XT0313:1	☐	
Cable: WC8301								
☐	AT0140:50 PMG-B	WC8301	WHT	12	☐	KA0313:3	☐	
☐	AT0140:51 PMG-C	WC8301	BLK	12	☐	KA0313:6	☐	
☐	FLOATING	WC8301	SH	12	☐	XT0313:1	☐	
Cable: WC0018								
☐	AT0140:P1	WC0018	ENET	CABLE	☐	AU0180:L2	☐	