CWS White List Credit Card Numbers

The following credit card numbers are to be used in the IP Commerce Sandbox testing environment only. All other transactions that contain PAN or track data not mentioned below will be rejected. Transactions submitted with track data must strip off the start and end sentinels. Only one track can be submitted within a transaction.

Master Card

PAN	545454545454
Track 1	%B54545454545454541PCOMMERCE/TESTCARD^1312101013490000000001000880000?
Track 2	;5454545454545454=13121010134988000010?

Master Card - Pcard

PAN	5480020605154711
Track 1	%B5480020605154711^IPCOMMERCE/TESTCARD^1312101100000001000000218000000?
Track 2	;5480020605154711=13121011000017026218?

Master Card - Sig Debit

PAN	9999989900007723
Track 1	%B9999989900007723^IPCOMMERCE/TESTCARD^13121015432112345678?
Track 2	;9999989900007723=13121015432112345678?

Visa

PAN	4111111111111
Track 1	%B4111111111111111111111111111111111111
Track 2	;41111111111111=13121010454541500010?

Visa - Pcard

PAN	4005765777003
Track 1	%B4005765777003^IPCOMMERCE/TESTCARD^13121015432112345678?
Track 2	;4005765777003=13121015432112345678?

AmericanExpress

PAN	371449635398456	
Track 1	%B371449635398456^IPCOMMERCE/TESTCARD^1312060523319?	
Track 2	;371449635398456=1312060523319?	

Discover

PAN	6011000995504101	
Track 1	%B6011000995504101^IPCOMMERCE/TESTCARD^13121011000627210201?	
Track 2	ck 2 ;6011000995504101=13121011000627210201?	

Debit Card (Private Label)

PAN	8818889876543211
Track 1	
Track 2	;8818889876543211=13121014764094900001?

CVData Trigger Table

CVData Trigger Value	CVData Response Value
111 (1111)	Match
222 (2222)	NoMatch
333 (3333)	NotProcessed
444 (4444)	MerchantIndNoCodePresent
555 (5555)	ShouldHaveBeenPresent
666 (6666)	IssuerNotCertified
777 (7777)	Invalid
888 (8888)	NoResponseFromCardAssociation
999 (9999)	NotApplicable

AVS Trigger Table

AVSData/ Street	AVSData/ PostalCode	Actual Booult	AdduDassife	Described and Provide
Trigger Value <no avsdata<="" td=""><td>Trigger Value</td><td>Actual Result <no avsresult<="" td=""><td>AddrResult</td><td>PostalCodeResult</td></no></td></no>	Trigger Value	Actual Result <no avsresult<="" td=""><td>AddrResult</td><td>PostalCodeResult</td></no>	AddrResult	PostalCodeResult
provided on non-		returned>		
AVSONLY		returneu>		
transaction type>				
<no avsdata<="" td=""><td></td><td>-1</td><td>NotIncluded</td><td>NotIncluded</td></no>		-1	NotIncluded	NotIncluded
provided on		-	Notificiaded	Notificiaca
AVSONLY				
transaction type>				
<empty> (with</empty>		0	NotIncluded	Notincluded
other AVSData				
provided)				
1000 1st Av	10101	Υ	Match	Match
<empty></empty>	10101	Z	NotIncluded	Match
<default any<="" td=""><td>10101</td><td>Χ</td><td>NoMatch</td><td>Match</td></default>	10101	Χ	NoMatch	Match
provided value>	10101			
1000 1st Av	<empty></empty>	Α	Match	NotIncluded
1000 1st Av	<default any="" provided="" value=""></default>	X	Match	NoMatch
2000 2nd Av	20202	E	IssuerNotCertified	IssuerNotCertified
<empty></empty>	20202	Е	NotIncluded	IssuerNotCertified
<default any="" provided="" value=""></default>	20202	E	NoMatch	IssuerNotCertified
2000 2nd Av	<empty></empty>	E	IssuerNotCertified	NotIncluded
	<default any<="" td=""><td>E</td><td>IssuerNotCertified</td><td>NoMatch</td></default>	E	IssuerNotCertified	NoMatch
2000 1st Av	provided value>			
3000 3rd Av	30303	R	NoResponseFromCardAssociation	NoResponseFromCardAssociation
<empty></empty>	30303	R	NotIncluded	NoResponseFromCardAssociation
<default any<="" td=""><td>30303</td><td>R</td><td>NoMatch</td><td>NoResponseFromCardAssociation</td></default>	30303	R	NoMatch	NoResponseFromCardAssociation
provided value>	30303			
3000 3rd Av	<empty></empty>	R	NoResponseFromCardAssociation	NotIncluded
3000 1st Av	<default any="" provided="" value=""></default>	R	NoResponseFromCardAssociation	NoMatch

4000 4th Av	40404	S	NotVerified	NotVerified
<empty></empty>	40404	S	NotIncluded	NotVerified
<default any="" provided="" value=""></default>	40404	S	NoMatch	NotVerified
4000 4th Av	<empty></empty>	S	NotVerified	NotIncluded
4000 1st Av	<default any="" provided="" value=""></default>	S	NotVerified	NoMatch
5000 5th Av	50505	F	BadFormat	BadFormat
<empty></empty>	50505	F	NotIncluded	BadFormat
<default any="" provided="" value=""></default>	50505	F	NoMatch	BadFormat
5000 5th Av	<empty></empty>	F	BadFormat	NotIncluded
1000 1st Av	<default any="" provided="" value=""></default>	F	BadFormat	NoMatch
<default any="" provided="" value=""></default>	<default any="" provided="" value=""></default>	N	NoMatch	NoMatch
<empty></empty>	<default any="" provided="" value=""></default>	N	Notincluded	NoMatch
<default any="" provided="" value=""></default>	<empty></empty>	N	NoMatch	Notincluded

Note, the following triggers are for testing purposes only and are only valid against the Sandbox test system. The values do not reflect errors that may be generated in production.

Service Status Codes

Table 12 and Table 13 provide the trigger values, service status codes, messages, and associated descriptions for all service and transaction classes supported by the test Sandbox.

Service Class: BCP

Table 12 provides the service trigger values and status codes for the all BCP transaction classes.

Table 12. BCP Service Status Codes

Service Class: BCP	StatusCode	StatusMsg	Description
*.10	108	Invalid Amount	Amount is invalid.
*.52	150	Invalid Merchant Number	The Merchant Number is incorrect.
*.53	151	Invalid Term Number	The merchant ID is not valid or active.
*.54	152	Invalid Store	Invalid Store Number
*.55	153	Invalid Bank Info	Invalid banking information (such as ABA or ICA).
*.72	170	Invalid Tran Fmt	The transaction format isn't valid.
*.73	171	Request Denied	Transaction is not valid for this authorizer.
*.74	172	Tran Not Allowed	Requested transaction type is not allowed for this card/merchant.
*.75	173	BIN Invalid	BIN not set up for this merchant in routing table.
*.76	174	Invalid Function	Merchant is Authorization Only and a capture record was sent.
*.92	190	Failed - Call	Transaction failed, please call.
*.96	900	Fatal Comm Error	Fatal communications error.
*.97	901	No Reply	Processing network is temporarily unavailable.
*.98	902	Err - Retry	Merchant number not on file.
*.99 903 Err - No Retry		Err - No Retry	Error, do not retry, call issuer.

Transaction Class: CREDIT

<u>Table 13</u> provides the service trigger values and status codes for the CREDIT transaction class.

Table 13. CREDIT Service Status Codes

Trigger	StatusCode	StatusMsg	Description
*.00	0	APPROVED	Authorization success.
*.01	1	ОК	No reason to decline.
*.02	100	Auth Declined	Cardholder's bank did not approve transaction.
*.03	101	Call Voice Oper	Authorizer needs more information for approval.
*.04	102	Hold - Call	Card issuer does not want that card used. Call for further instructions.
*.05	103	Pick Up Card	Pick up card and call issuer.
*.06	104	Call Voice Oper	Authorizer didn't respond within allotted time.
*.07	105	Invalid Card	Account #/mag stripe is invalid.
*.08	106	Invalid Exp	Expiration date is either incorrect format or prior to today.
*.09	107	Invalid PIN	The Personal ID (such as PIN for a debit transaction) is incorrect.
*.22	120	Call Voice Oper	Authorization center cannot be reached.
*.23	121	Pick Up Card	Card has been reported lost or stolen. Pick up card and call issuer.
*.32	130	Declined	Amount requested exceeds available funds or credit.
*.33	131	Declined	Card is on negative file.
*.56	154	Card Not Allowed	Merchant can not accept this card.
*.57	155	Setup Required	Merchant not set up for Private Label, Corporate Card, or other program.
*.58	156	BIN Not Allowed	Merchant cannot accept this BIN range.
*.77	175	Tran Not Allowed	The batch containing the transaction to void has been released.
*.78	176	Invalid Function	Merchant is Authorization Only and a debit record was sent.
*.79	177	Invalid Function	Manually entered transactions are not allowed for this terminal ID.
*.80	178	Exceeded Amount	Maximum sale amount exceeded.
*.81	179	Exceeded Amount	Maximum return amount exceeded.
*.82	180	Rev Not Allowed	The batch containing the transaction has been

			released.
*.83	181	CV Error	CVC2 or CID data entered is not correct for the card.