

Aria Floodlight Cam — Owner's Manual

Aria Home · SKU ARIA-FLOOD · camera · \$229

This manual covers the Aria Floodlight Cam (model ARIA-FLOOD) only. Other Aria products have their own manuals; procedures and error codes are not interchangeable between models.

1. Specifications

Video	1080p HD, HDR, 140° field of view
Lights	two adjustable LED panels, 2,000 lumens total, 3000 K
Siren	105 dB remote-activated
Detection	passive infrared, 270° motion coverage
Weather rating	IP65
Power	hardwired 100–240 V AC to a junction box

2. In the box

Floodlight Cam, mounting plate, wire nuts, gasket, screws.

3. Setup

1. Turn off the breaker and confirm with a tester before touching wires.
2. Connect black to black, white to white, and green to the ground screw on the plate.
3. Tilt each light panel; the camera aims independently.
4. Pair from the Aria app by holding the setup button on the underside for 3 seconds.

4. Status light

Blue dot: live view.

Red dot: recording.

Both lights flashing: siren active.

5. Power and battery

Aria Floodlight Cam: Hardwired 100–240 V AC. Average draw 12 W with lights off, 27 W with lights on.

6. Troubleshooting

Aria Floodlight Cam — Lights turn on all night. Light schedule is set to Dusk to dawn; change to Motion only under Lights.

Aria Floodlight Cam — Motion missed on the driveway. PIR is best at 90° to the path; angle the unit so cars cross the field rather than approach head-on. Range is 30 feet.

Aria Floodlight Cam — Camera works but lights never come on. Lights are controlled separately; confirm Lights > Motion-activated is On and brightness is above 20 percent.

7. Error codes

Aria Floodlight Cam error F-03: Light driver over-temperature — lights dim until the unit cools.

Aria Floodlight Cam error F-08: Siren circuit fault — the siren is disabled until restart.

8. Factory reset

To factory reset the Aria Floodlight Cam: Hold the underside setup button for 30 seconds until the light panels blink twice.

9. Warranty and compatibility

The Aria Floodlight Cam carries a two-year standard warranty covering manufacturing defects, from the delivery date. Unwanted returns follow the Aria Home returns policy: 30 days from delivery for the Aria Floodlight Cam (most devices have a 30-day window). Damage caused by the customer is handled as a warranty repair, not a refund.

Works with: Aria app, Aria Video plan, Google Home, Amazon Alexa.