mahindra Rise

powerol by Mahindra

30kVA Generator

GENSET PARAMETERS	
kVA (Prime)	30
kW (Prime)	24
Engine Make & Model	Mahindra & Mahindra Ltd. (3445 TCIGM C2-G18)
Alternator Make	Leroy Somer
Phase	1 phase/3 phase
Voltage	240, 1 phase 400 V, 3 phase
Frequency / Engine Speed	60 Hz /1800 rpm
Rated Current (A)	130.4 / 41.7
Power Factor (p.f.)	0.8 (Lag)
Fuel Tank Capacity (Litre)	115
Type of Genset	Genset with acoustic enclosure.
Conformance to Standards	ISO 8528

ENGINE PARAMETERS	
Model	3445 TCIGM C2-G18
Make	Mahindra & Mahindra Ltd.
Rated Engine power @100% Load (HP)	44
Cylinders	3
Aspiration	TCI
Displacement (in CC)	2047
Bore x Stroke (in mm)	88.9 X 110
Governing Class	A1
Lubricant Capacity (in Litre)	6
Radiator Coolant Capacity (in Litre)	12.5
Fuel	High Speed Diesel
Lube Oil Specification	SAE15W40 CI4+
Starting System (V)	12 V, Electrical
Cooling System	Water cooled with Radiator

FUEL CONSUMPTION	
Fuel Consumption @ 100% Load (Prime)	7.3 Litre/hrs.
Fuel Consumption @ 75% Load (Prime)	5.7 Litre/hrs.
LOGISTIC DATA	
Dimensions (L x W x H) (in mm)	Silent Set : 2200 x 980 x 1342 (H-w/o silencer & foot)
Approx. Net Wt. (in Kg.)	Silent Set : Approx.935
ALTERNATOR PARAMETERS	
Make	Stamford/ Leroy Somer
Type	Brushless, Single Bearing, Self Excited
Voltage	240V/400 V
Phase	1 phase/3 Phase
Frequency	60 Hz
Speed	1800 RPM
Voltage Regulation	+/- 1%
Insulation class	H
Ingress Protection	IP 23
CONTROL PANEL PARAMETERS	
Control Panel Type	Manual control Panel with microprocessor based controller (Standard)/ AMF (Optional)
Controller Make & Type	Deep Sea Controller (4520MKII/7320MKII)
Protection Features offered by controller	Engine - High Water Temperature, Low Lube oil pressure, Low Fuel Level Electrical - Generator Under/ Over Voltage, Generator Under/Over Frequency, Generator Over Current, Generator kW Overload

powerol by Mahindra

Mahindra & Mahindra Ltd.
Mahindra Powerol
MHEL, 1st Floor, Gate No. 12,
A-1/1, Talawade Chakan Rd,
Chakan Industrial Area, Phase-IV, Nigoje,
Maharashtra, 410501.

poweroldg@mahindra.com
mahindrapowerol.com

kVA CPCB2 - DEC 22