Revisions			
Rev.	Date	Author	Description
A	21/01/2018	Florent de Labarre	Creation
B	15/06/2020	Florent de Labarre	Replaced FBA_03 by KE_01 on keybox engine connector label
C	08/09/2020	P.L.P	Modifs nom étiquette
D	16/09/2021	E.P	MaJ Faisceau complet

Main_MC42

Cavity	To	Conductor	Color	Gauge	Length
1	CanBus_Main_to_MC4_10.B	W22.White		0,75 mm²	≥ 1,7 m
2	Engine.B	W23.White		0,75 mm²	≥ 1,7 m
3	Can_Drive.B	W57.White		0,75 mm²	≥ 0,7 m
4	IDTAG_1.2	W50.White		0,75 mm²	≥ 0,1 m
7	Vref_Plus	W59.White		0,75 mm²	
8	R8.POS	W16.White		0,75 mm²	
9	Pressure_block.2	W17.White		0,75 mm²	
10	Pressure_tracks.2	W19.White		0,75 mm²	
14	Splice_Right	W45.White		0,75 mm²	
15	Splice_Left	W48.White		0,75 mm²	
17	CanBus_Main_to_MC4_10.A	W21.White		0,75 mm²	≥ 1,7 m
18	Engine.A	W24.White		0,75 mm²	≥ 1,7 m
19	Can_Drive.A	W56.White		0,75 mm²	≥ 0,7 m
20	IDTAG_1.1	W49.White		0,75 mm²	≥ 0,1 m
23	Vref_Minus	W60.White		0,75 mm²	
25	Temp_Oil.2	W8.White		0,75 mm²	
26	Pump_State.2	W9.White		0,75 mm²	
39	Right_Pump_1.1	W46.White		0,75 mm²	
40	Left_pump_1.1	W63.White		0,75 mm²	
41	ByPass.2	W1.White		0,75 mm²	
42	Landing_DOWN.2	W3.White		0,75 mm²	
43	Landing_Unblock.2	W5.White		0,75 mm²	
44	Brake.2	W7.White		0,75 mm²	
46	Splice_C1_46	W14.White		0,75 mm²	
47	Splice_C1_47	W15.White		0,75 mm²	
55	Right_pump_2.1	W47.White		0,75 mm²	
56	Left_Pump_2.1	W64.White		0,75 mm²	
57	Landing_UP.2	W2.White		0,75 mm²	
58	Track_Tension.2	W4.White		0,75 mm²	
59	Landing_Block.2	W6.White		0,75 mm²	
65	12V	W43.Red		2,5 mm²	
66	Supply.B	W44.Black		2,5 mm²	≥ 2 m

Couper les Cables non utilisés à 30 cm de la prise. Isoler avec gaines thermo chaque cable non utilisés. Faire une chaussette avec gaine thermo de l'ensemble des cables non utilisés.

Supply

Cavity	To	Conductor	Color	Gauge
A	12V	W58.Red		2,5 mm²
B	Main_MC42.66	W44.Black		2,5 mm²

Supply (MC16)(IM05) — 2 m [14] — Supply [5, 11, 16, 30]

IDTAG_1

Cavity	To	Conductor	Color	Gauge
1	Main_MC42.20	W49.White		0,75 mm²
2	Main_MC42.4	W50.White		0,75 mm²

Pièce fourni à connecter avec des monchons

IDTAG_1 [1] — [14] — 0,1 m — IDTAG (MC 21)

Main_MC42 [3] — [14] — MC42

12V

From	To	Conductor	Color	Gauge
12V	Main_MC42.65	W43.Red		2,5 mm²
12V	Supply.A	W58.Red		2,5 mm²

12V [19] — Splice_C1_47 [19]

Splice_C1_47

From	To	Conductor	Color	Gauge
Splice_C1_47	Main_MC42.47	W15.White		0,75 mm²
Splice_C1_47	Splice_C1_47_Distributeur	W83.Orange		1 mm²

Vref_Minus [19] — Vref_Plus [19]

Vref_Minus, Vref_Plus

From	To	Conductor	Color	Gauge
Vref_Minus	Main_MC42.23	W60.White		0,75 mm²
Vref_Minus	Oil_Level.B	W28.Black		1 mm²
Vref_Minus	Vref_Minus_Distributor	W79.Black		1 mm²
Vref_Plus	Main_MC42.7	W59.White		0,75 mm²
Vref_Plus	R7.NEG	W34.Red		1 mm²
Vref_Plus	Vref_Plus_Distributor	W77.Red		1 mm²

R7 [18] — Splice_Oil_level [19] — R8 [18] — Oil (MC17)(GW01) — [14] — 0,6 m — Oil_Level [6, 10, 17, 29]

R7

From	To	Conductor	Color	Gauge
R7.NEG	Vref_Plus	W34.Red		1 mm²
R7.POS	Splice_Oil_level	W35.Red		1 mm²

R8

From	To	Conductor	Color	Gauge
R8.NEG	Splice_Oil_level	W37.Red		1 mm²
R8.POS	Main_MC42.8	W16.White		0,75 mm²

Splice_Oil_level

From	To	Conductor	Color	Gauge
Splice_Oil_level	Oil_Level.A	W36.Red		1 mm²
Splice_Oil_level	R7.POS	W35.Red		1 mm²
Splice_Oil_level	R8.NEG	W37.Red		1 mm²

Oil_Level

Cavity	To	Conductor	Color	Gauge
A	Splice_Oil_level	W36.Red		1 mm²
B	Vref_Minus	W28.Black		1 mm²

Main (MC_18)(MD_09) — 1,7 m [14] — CanBus_Main_to_MC4_10 [4, 9, 15, 28]

Can Bus Engine (xMC20)(xFE03) — [14] 1,7 m — Engine [4, 9, 15, 28]

Candrive (xMC19)(xKE01) — [14] 0,7 m — Can_Drive [4, 9, 15, 28]

CanBus_Main_to_MC4_10

Cavity	To	Conductor	Color	Gauge
A	Main_MC42.17	W21.White		0,75 mm²
B	Main_MC42.1	W22.White		0,75 mm²

Engine

Cavity	To	Conductor	Color	Gauge
A	Main_MC42.18	W24.White		0,75 mm²
B	Main_MC42.2	W23.White		0,75 mm²

Can_Drive

Cavity	To	Conductor	Color	Gauge
A	Main_MC42.19	W56.White		0,75 mm²
B	Main_MC42.3	W57.White		0,75 mm²

Supply = alimentation
Water = eau
Level = niveau
Splice = épissure
Seat = fauteil
hal captor = capteur de vitesse
Ladder = echelle
Oil = huile
Track = chenille
Pressure = pression

Splice_C1_46

From	To	Conductor	Color	Gauge
Splice_C1_46	ByPass.1	W82.Black		1 mm²
Splice_C1_46	Landing_DOWN.1	W81.Black		1 mm²
Splice_C1_46	Landing_UP.1	W78.Black		1 mm²
Splice_C1_46	Main_MC42.46	W14.White		0,75 mm²
Splice_C1_46	Track_Tension.1	W80.Black		1 mm²

Vref_Plus_Distributor [19] — Vref_Minus_Distributor [19]

Vref_Plus_Distributor, Vref_Minus_Distributor

From	To	Conductor	Color	Gauge
Vref_Minus_Distributor	Pressure_block.1	W26.Black		1 mm²
Vref_Minus_Distributor	Pressure_tracks.1	W27.Black		1 mm²
Vref_Minus_Distributor	Pump_State.1	W69.Black		1 mm²
Vref_Minus_Distributor	Temp_Oil.1	W31.Black		1 mm²
Vref_Minus_Distributor	Vref_Minus	W79.Black		1 mm²
Vref_Plus_Distributor	Pressure_block.3	W32.Red		1 mm²
Vref_Plus_Distributor	Pressure_tracks.3	W33.Red		1 mm²
Vref_Plus_Distributor	Pump_State.3	W40.Red		1 mm²
Vref_Plus_Distributor	Temp_Oil.3	W38.Red		1 mm²
Vref_Plus_Distributor	Vref_Plus	W77.Red		1 mm²

Splice_C1_46 [19] — [14]

- By Pass (MC01) — [14] — ByPass [2]
- UP (MC02) — [14] — Landing_UP [2]
- DOWN (MC03) — [14] — Landing_DOWN [2]
- Track (MC04) — [14] — Track_Tension [2]
- Splice_C1_47_Distributeur [19] — Block (MC05) — [14] — Landing_Block [2]
- Unblock (MC06) — [14] — Landing_Unblock [2]
- Brake (MC07) — [14] — Brake [2]
- P Block (MC08) — [14] — Pressure_block [7, 12, 28]
- P Track (MC09) — [14] — Pressure_tracks [7, 12, 28]
- Temp (MC10) — [14] — Temp_Oil [7, 12, 28]
- State (MC11) — [14] — Pump_State [8, 13, 31]

Splice_C1_47_Distributeur

From	To	Conductor	Color	Gauge
Splice_C1_47_Distributeur	Brake.1	W86.Orange		1 mm²
Splice_C1_47_Distributeur	Landing_Block.1	W85.Orange		1 mm²
Splice_C1_47_Distributeur	Landing_Unblock.1	W87.Orange		1 mm²
Splice_C1_47_Distributeur	Splice_C1_47	W83.Orange		1 mm²

Right_Pump_1, Right_pump_2

From	Cavity	To	Conductor	Color	Gauge
Right_Pump_1.1	1	Main_MC42.39	W46.White		0,75 mm²
Right_Pump_1.2	2	Splice_Right	W29.Black		1 mm²
Right_pump_2.1	1	Main_MC42.55	W47.White		0,75 mm²
Right_pump_2.2	2	Splice_Right	W30.Black		1 mm²

Splice_Right [19] — [14] — RP1 (MC12) — Right_Pump_1 [2]; [14] — RP2 (MC13) — Right_pump_2 [2]

Left_pump_1, Left_Pump_2

From	Cavity	To	Conductor	Color	Gauge
Left_Pump_2.1	1	Main_MC42.56	W64.White		0,75 mm²
Left_Pump_2.2	2	Splice_Left	W92.Blue		1 mm²
Left_pump_1.1	1	Main_MC42.40	W63.White		0,75 mm²
Left_pump_1.2	2	Splice_Left	W93.Blue		1 mm²

Splice_Left [19] — [14] — LP1 (MC14) — Left_pump_1 [2]; [14] — LP2 (MC15) — Left_Pump_2 [2]

Attention aux cavitées par rapport aux splices

Splice_Right

From	To	Conductor	Color	Gauge
Splice_Right	Main_MC42.14	W45.White		0,75 mm²
Splice_Right	Right_Pump_1.2	W29.Black		1 mm²
Splice_Right	Right_Pump_2.2	W30.Black		1 mm²

Splice_Left

From	To	Conductor	Color	Gauge
Splice_Left	Left_Pump_2.2	W92.Blue		1 mm²
Splice_Left	Left_pump_1.2	W93.Blue		1 mm²
Splice_Left	Main_MC42.15	W48.White		0,75 mm²

1 = Marron
2 = Bleu
Sur 20694

ByPass

Cavity	To	Conductor	Color	Gauge
1	Splice_C1_46	W82.Black		1 mm²
2	Main_MC42.41	W1.White		0,75 mm²

Landing_UP

Cavity	To	Conductor	Color	Gauge
1	Splice_C1_46	W78.Black		1 mm²
2	Main_MC42.57	W2.White		0,75 mm²

Landing_DOWN

Cavity	To	Conductor	Color	Gauge
1	Splice_C1_46	W81.Black		1 mm²
2	Main_MC42.42	W3.White		0,75 mm²

Track_Tension

Cavity	To	Conductor	Color	Gauge
1	Splice_C1_46	W80.Black		1 mm²
2	Main_MC42.58	W4.White		0,75 mm²

Landing_Block

Cavity	To	Conductor	Color	Gauge
1	Splice_C1_47_Distributeur	W85.Orange		1 mm²
2	Main_MC42.59	W6.White		0,75 mm²

Landing_Unblock

Cavity	To	Conductor	Color	Gauge
1	Splice_C1_47_Distributeur	W87.Orange		1 mm²
2	Main_MC42.43	W5.White		0,75 mm²

Brake

Cavity	To	Conductor	Color	Gauge
1	Splice_C1_47_Distributeur	W86.Orange		1 mm²
2	Main_MC42.44	W7.White		0,75 mm²

Pressure_block

Cavity	To	Conductor	Color	Gauge
1	Vref_Minus_Distributor	W26.Black		1 mm²
2	Main_MC42.9	W17.White		0,75 mm²
3	Vref_Plus_Distributor	W32.Red		1 mm²

Pressure_tracks

Cavity	To	Conductor	Color	Gauge
1	Vref_Minus_Distributor	W27.Black		1 mm²
2	Main_MC42.10	W19.White		0,75 mm²
3	Vref_Plus_Distributor	W33.Red		1 mm²


Temp_Oil

Cavity	To	Conductor	Color	Gauge
1	Vref_Minus_Distributor	W31.Black		1 mm²
2	Main_MC42.25	W8.White		0,75 mm²
3	Vref_Plus_Distributor	W38.Red		1 mm²

Pump_State

From	Cavity	To	Conductor	Color	Gauge
Pump_State.1	1	Vref_Minus_Distributor	W69.Black		1 mm²
Pump_State.2	2	Main_MC42.26	W9.White		0,75 mm²
Pump_State.3	3	Vref_Plus_Distributor	W40.Red		1 mm²

Wiring diagram



Voir Fiche méthode pour branchement bloc hydraulique

	Name	Date
Drawn By	----	----
Eng Approved	----	----
Mfg Approved	----	----
QA	----	----

Title: #22679 - MC42_X100 (xMC) - IND D
Description
Revision: ----

This document contains confidential and proprietary information that cannot be reproduced or divulged, in whole or in part, without written authorization.

Title:	#22679 - MC42_X100 (xMC) - IND D
Description:	

Id	Type	Part Number	Quantity	Description	Manufacturer
1	Connector	#21436 - Parker_IDTAG_1	1	5030061	
2	Connector	#20694 - Phoenix_valve_2_way	11	651-1410723	
3	Connector	#24679 - Parker_C1_66_way	1		
4	Connector	#15215 - Delphi_150_2_way_male	3	Delphi 12162000	Delphi
5	Connector	#17183 - Delphi_480_2_way_male	1	Delphi 12065863	Delphi
6	Connector	#17351 - Delphi_280_2_way_female	1	Delphi 15300027	Delphi
7	Connector	#12189 - Te_Timer_3_way_female	3	571-2821911	TE
8	Connector	#28977- AMP Superseal 3 ways	1		
9	Contact	#10019 Delphi_150_contact_male 0.5-1.0mm² 1.69-2.78mm	6	Delphi 12045773	Delphi
10	Contact	#14173 Delphi_280_contact_female 2.0-3.0mm² 2.45-3.80mm	2	Delphi 12129493	Delphi
11	Contact	#17237 Delphi_480_contact_male 5mm² 3.49-5.24mm	2	Delphi 12052172	Delphi
12	Contact	#15166 - Junior TIMER RECPT Contact - JPT	9		TE Connectivity
13	Contact	#25149 - AMP socket contact	3		
14	Label	Generic White Label	22	Generic Label	
15	Lock	#19468 - Delphi_150_2_way_lock	3	Delphi 12052634	Delphi
16	Lock	#10273 - Delphi_480_2_way_lock	1	Delphi 12059897	Delphi
17	Lock	#18797 - Delphi_280_2_way_lock	1	Delphi 15300014-B	Delphi
18	Resistor	#21463 - 240 Ohm resistor	2		
19	Splice	Generic Splice	11	Generic Splice	
20	Wire	1mm² Black	≥ 0,6 m		
21	Wire	1mm² Red	≥ 0,6 m		
22	Wire	2.5mm² - Black	≥ 2 m		
23	Wire	2.5mm² - Red	≥ 2 m		
24	Wire	C1_Wire	≥ 8,4 m		
25	Wire	1 mm² - Orange			
26	Wire	1 mm² Orange		Generic Wire	
27	Wire	1mm² - Blue			
28	Wire Seal	#17898 - Delphi 150 Cable seal – White – 1.60-2.15	15	Delphi 12089442	Delphi
29	Wire Seal	#13381 - Delphi 280 Cable seal – Green– 2.03-2.85	2	Delphi 12015284	Delphi
30	Wire Seal	#15414 - Delphi 480 Cable seal – Red – 2.81-3.76	2	Delphi 12052452	Delphi
31	Wire Seal	#24093 - AMP Seal	3		