Revisions			
Rev.	Date	Author	Description
A	21-Feb-23	Iguana Yachts	Création pour le #76

Supply_VREF

From	To	Conductor	Color	Gauge
Supply_VREF	Joystick_Left.2	W53.Violet		1 mm²
Supply_VREF	Joystick_Right.2	W54.Violet		1 mm²
Supply_VREF	MD3_C2_Black.11	W55.Violet		1 mm²

R3

From	To	Conductor	Color	Gauge
R3.NEG	Buzzer.B	W78.Black		1 mm²
R3.POS	Buzzer.A	W71.Red		1 mm²

Buzzer

Cavity	To	Conductor	Color	Gauge
A	MD3_C2_Black.3	W34.Red		1 mm²
A	R3.POS	W71.Red		1 mm²
B	R3.NEG	W78.Black		1 mm²
B	Supply_0V	W40.Black		1 mm²

From	To	Conductor	Color	Gauge
R1.NEG	RTC_Power_Box.A	W57.Violet		1 mm²
R1.POS	MD3_C2_Black.12	W87.Violet		1 mm²

From	To	Conductor	Color	Gauge
R2.NEG	Supply_0V	W44.Black		1 mm²
R2.POS	RTC_Power_Box.B	W45.Black		1 mm²

MD3_C2_Black

Cavity	To	Conductor	Color	Gauge	From Contact PN	Length
1	Joystick_Left.3	W19.Orange		1 mm²	Contact deutsch DTMO6	≥ 1.1 m
2	Joystick_Right.3	W20.Orange		1 mm²	Contact deutsch DTMO6	≥ 1.1 m
3	Buzzer.A	W34.Red		1 mm²	Contact deutsch DTMO6	0.6 m
11	Supply_VREF	W55.Violet		1 mm²	Contact deutsch DTMO6	0.2 m
12	R1.POS	W87.Violet		1 mm²	Contact deutsch DTMO6	≥ 0.1 m

R3 [23]

Résistance utille pour la dernière Réf de buzzer (vérifier si utile ici)

Buzzer (MD4_01)

0.1 m [17]

0.4 m Buzzer [2, 12, 19, 33]

Joystick_Left

Cavity	To	Conductor	Color	Gauge
1	Supply_0V	W41.Black		1 mm²
2	Supply_VREF	W53.Violet		1 mm²
3	MD3_C2_Black.1	W19.Orange		1 mm²

Joystick_Right

Cavity	To	Conductor	Color	Gauge
1	Supply_0V	W37.Black		1 mm²
2	Supply_VREF	W54.Violet		1 mm²
3	MD3_C2_Black.2	W20.Orange		1 mm²

Joystick : 150 Femelle
A : Noir
B : Rouge
C : Jaune

MD3_C2_Black [6, 11, 20]

C2_Black

[17] 0.1 m

0.1 m 1 Supply_VREF [24] 0.9 m

[17] Left (MD4_03) Joystick_Left [4, 16, 33, 34]

[17] Righ (MD4_02) Joystick_Right [4, 16, 33, 34]

IDTAG_1 [10]

ID_M [3]

ID_F [2]

0 m

[17]

MD3_C1_Grey [5, 11, 20]

C1_Grey

2

Supply_0V [24]
Supply_12V [24]

0 m

1 R1 [23]

1 R2 [23]

Supp (MD4_04)(IM02) [17] 1.2 m Supply [8, 13, 21, 32]

RTC (MD4_05)(IM03) [17] 1.3 m RTC_Power_Box [3, 14, 19, 33]

Supply

Cavity	To	Conductor	Color	Gauge
A	Supply_12V	W26.Red		1 mm²
B	Supply_0V	W35.Black		1 mm²

RTC_Power_Box

Cavity	To	Conductor	Color	Gauge
A	R1.NEG	W57.Violet		1 mm²
B	R2.POS	W45.Black		1 mm²

MD3_C1_Grey

Cavity	To	Conductor	Color	Gauge	From Contact PN	Length
1	Supply_0V	W39.Black		1 mm²	Contact deutsch DTMO6	
2	CanLow_B_Main	W3.Blue		1 mm²	Contact deutsch DTMO6	≥ 0 m
3	Wifi_Supply_CanBus_B.D	W4.Blue		1 mm²	Contact deutsch DTMO6	≥ 0 m
4	CanBus_C.B	W15.Blue		1 mm²	Contact deutsch DTMO6	≥ 0 m
6	ID_F.A	W5.Blue		1 mm²	Contact deutsch DTMO6	
7	ID_F.B	W6.Blue		1 mm²	Contact deutsch DTMO6	
9	CanBus_C.A	W7.White		1 mm²	Contact deutsch DTMO6	≥ 0 m
10	Wifi_Supply_CanBus_B.C	W11.White		1 mm²	Contact deutsch DTMO6	≥ 0 m
11	CanHigh_A_Main	W8.White		1 mm²	Contact deutsch DTMO6	≥ 0 m
12	Supply_12V	W32.Red		1 mm²	Contact deutsch DTMO6	

Supply_0V, Supply_12V

From	To	Conductor	Color	Gauge
Supply_0V	Buzzer.B	W40.Black		1 mm²
Supply_0V	Joystick_Left.1	W41.Black		1 mm²
Supply_0V	Joystick_Right.1	W37.Black		1 mm²
Supply_0V	MD3_C1_Grey.1	W39.Black		1 mm²
Supply_0V	Modem_G11.1	W36.Black		1 mm²
Supply_0V	R2.NEG	W44.Black		1 mm²
Supply_0V	Supply.B	W35.Black		1 mm²
Supply_0V	Wifi_Supply_CanBus_B.B	W38.Black		1 mm²
Supply_12V	MD3_C1_Grey.12	W32.Red		1 mm²
Supply_12V	Modem_G11.2	W47.Red		1 mm²
Supply_12V	Supply.A	W26.Red		1 mm²
Supply_12V	Wifi_Supply_CanBus_B.A	W27.Red		1 mm²

IDTAG_1

Cavity	To	Conductor	Color	Gauge
1	ID_M.A	W12.Blue		1 mm²
2	ID_M.B	W13.Blue		1 mm²

ID_M

Cavity	To	Conductor	Color	Gauge
A	IDTAG_1.1	W12.Blue		1 mm²
B	IDTAG_1.2	W13.Blue		1 mm²

ID_F

Cavity	To	Conductor	Color	Gauge
A	MD3_C1_Grey.6	W5.Blue		1 mm²
B	MD3_C1_Grey.7	W6.Blue		1 mm²

NOTE : Longueur totale faisceau = 1.25 m

Modem_G11

Cavity	To	Conductor	Color	Gauge
1	Supply_0V	W36.Black		1 mm²
2	Supply_12V	W47.Red		1 mm²
3	CanLow_B_Main	W1.Blue		1 mm²
4	CanHigh_A_Main	W9.White		1 mm²

CanHigh_A_Main, CanLow_B_Main

From	To	Conductor	Color	Gauge
CanHigh_A_Main	CanBus_MC42.A	W10.White		1 mm²
CanHigh_A_Main	MD3_C1_Grey.11	W8.White		1 mm²
CanHigh_A_Main	Modem_G11.4	W9.White		1 mm²
CanLow_B_Main	CanBus_MC42.B	W2.Blue		1 mm²
CanLow_B_Main	MD3_C1_Grey.2	W3.Blue		1 mm²
CanLow_B_Main	Modem_G11.3	W1.Blue		1 mm²

0.7 m

CanHigh_A_Main [24]
CanLow_B_Main [24]

G11 (MD4_08) [17] Modem_G11 [7, 15]

2

Main (MD4_09)(MC_18) [17] 1.3 m CanBus_MC42 [2, 12, 19, 33]

CanBus_MC42

Cavity	To	Conductor	Color	Gauge
A	CanHigh_A_Main	W10.White		1 mm²
B	CanLow_B_Main	W2.Blue		1 mm²

Wifi_Supply_CanBus_B [9, 12, 22, 33]

[17] Wifi (MD4_11)(WI_01) Bouchon [1, 18, 34]

Wifi_Supply_CanBus_B

Cavity	To	Conductor	Color	Gauge
A	Supply_12V	W27.Red		1 mm²
B	Supply_0V	W38.Black		1 mm²
C	MD3_C1_Grey.10	W11.White		1 mm²
D	MD3_C1_Grey.3	W4.Blue		1 mm²

CanBus_Garmin_Cable_Male

Cavity	To	Conductor	Color	Gauge
A	White	W14.White		1 mm²
B	Blue	W16.Blue		1 mm²

CanBus_C

Cavity	To	Conductor	Color	Gauge
A	MD3_C1_Grey.9	W7.White		1 mm²
B	MD3_C1_Grey.4	W15.Blue		1 mm²

[17] CanBus C Garmin CanBus_C [3, 14, 19, 33]

CanBus_Garmin_Cable_Male [2, 12, 19, 33]

[17] Can Bus Garmin 2

Blue [24]
White [24]

Blue, White

From	To	Conductor	Color	Gauge
Blue	CanBus_Garmin_Cable_Male.B	W16.Blue		1 mm²
White	CanBus_Garmin_Cable_Male.A	W14.White		1 mm²

Title	#33530 - MD4 - X100 - (xMD4) - IND A
Description	Création pour premier X100 en MD4-5 : #76
Revision	B

	Name	Date
Drawn By	----	----
Eng Approved	----	----
Mfg Approved	----	----
QA	----	----

This document contains confidential and proprietary information that cannot be reproduced or divulged, in whole or in part, without written authorization.

Title:	#33530 - MD4 - X100 - (xMD4) - IND A
Description:	Création pour premier X100 en MD4-5 : #76

Id	Type	Part Number	Quantity	Description	Manufacturer
1	Connector	#26525 - Delphi_150_4_way_male	1	Delphi 12160825	Delphi
2	Connector	#14869 - Delphi_150_2_way_female	4	Delphi 12052641	Delphi
3	Connector	#15215 - Delphi_150_2_way_male	3	Delphi 12162000	Delphi
4	Connector	# 19975 - Automotive Connectors 4P J-P-TIM GEH KPL	2	571-1-963207-1	
5	Connector	#17593 - DEUTSCH DTM06-12SA FICHE DTM GRIS A KEY 12VOIES	1	571-DTM06-12SA	Deutsh
6	Connector	#19047 - DEUTSCH DTM06-12SB FICHE DTM NOIR B KEY 12VOIES	1	571-DTM06-12SB	Deutsh
7	Connector	#29830 - Connector 4 voie Deutsch DT06-4S	1	915-6553	
8	Connector	#16777 - Delphi_280_2_way_male	1	Delphi 12065863	Delphi
9	Connector	#28050 - Delphi_150_4_way_female	1	Delphi 12160482-B	Delphi
10	Connector	#21436 Adress ID TAG UNIT 1	1		
11	Contact	Contact deutsch DTMO6	24	#11235 - 571-0462-201-20141	DEUTSCH
12	Contact	#13657 Delphi_150_contact_female 0.5-1.0mm² 2.03-2.80mm	10	Delphi 12048074	Delphi
13	Contact	#13581 Delphi_280_contact_male 0.5-0.8mm² 1.69-2.78mm	2	Delphi 12048159	Delphi
14	Contact	#10019 Delphi_150_contact_male 0.5-1.0mm² 1.69-2.78mm	4	Delphi 12045773	Delphi
15	Contact	#24131 Contact AT62-16-0122 pour DT06-4S	4		Amphenol
16	Contact	#15166 - Junior TIMER RECPT Contact - JPT	6		TE Connectivity
17	Label	Generic White Label	12	Generic Label	
18	Lock	#23010 - Delphi_150_4_way_male_lock	1	Delphi 12176368	Delphi
19	Lock	#19468 - Delphi_150_2_way_lock	5	Delphi 12052634	Delphi
20	Lock	DTM WEDGELOCK 12 WAY PLUG	2	#14923 - 571-WM-12S	DEUTSCH
21	Lock	#18797 - Delphi_280_2_way_lock	1	Delphi 15300014-B	Delphi
22	Lock	#22024 - Delphi_150_4_way_female_lock	1	Delphi 12160480	Delphi
23	Resistor	1.5 kOhm	3		
24	Splice	Generic Splice	7	Generic Splice	
25	Wire	1mm² - Blue	≥ 2 m		
26	Wire	1mm² - White	≥ 2 m		
27	Wire	1 mm² - Orange	≥ 2.2 m		
28	Wire	1mm² Red	≥ 2.9 m		
29	Wire	1mm² Black	≥ 6.1 m		
30	Wire	1 mm² Purple	≥ 3.3 m		
31	Wire	1 mm² Violet	≥ 0.1 m	Generic Wire	
32	Wire Seal	#13381 - Delphi 280 Cable seal – Green– 2.03-2.85	2	Delphi 12015284	Delphi
33	Wire Seal	#17898 - Delphi 150 Cable seal – White – 1.60-2.15	20	Delphi 12089442	Delphi
34	Wire Seal	#19593 - Delphi 150 Cavity plug	6	Delphi 12059168	Delphi