



NRC7394 Evaluation Kit

User Guide

(S1G Channel)

Ultra-low power & Long-range Wi-Fi

Ver 1.5
Mar. 23, 2026

NEWRACOM, Inc.

NRC7394 Evaluation Kit User Guide (S1G Channel)

Ultra-low power & Long-range Wi-Fi

© 2026 NEWRACOM, Inc.

All right reserved. No part of this document may be reproduced in any form without written permission from Newracom.

Newracom reserves the right to change in its products or product specification to improve function or design at any time without notice.

Office

Newracom, Inc.

505 Technology Drive, Irvine, CA 92618 USA

<http://www.newracom.com>

Contents

- 1 Overview..... 6**
- 2 Channel..... 6**
 - 2.1 US (United States) Channel.....6
 - 2.2 KR (Korea) Channel9
 - 2.2.1 KR USN1 (K1) Package9
 - 2.2.2 KR USN5 (K2) Package9
 - 2.3 JP (Japan) channel.....9
 - 2.4 TW (Taiwan) channel10
 - 2.4.1 TW 840MHz licensed band channel.....10
 - 2.4.2 TW 920MHz unlicensed band channel.....10
 - 2.4.3 TW 920MHz band channel for NCC certification11
 - 2.5 EU (Europe) channel11
 - 2.6 NZ (New Zealand) channel12
 - 2.7 AU (Australia) channel13
 - 2.8 SG (Singapore) Channel.....13
- 3 Revision history..... 14**

List of Tables

Table 2.1	US channels (Op1, 2, and 3)	6
Table 2.2	US channels (Op35 and 36)	8
Table 2.3	KR USN1 (K1) channel	9
Table 2.4	KR USN5 (K2) channel	9
Table 2.5	JP channel.....	9
Table 2.6	TW 840MHz band channel (Licensed)	10
Table 2.7	TW 920MHz band channel (Unlicensed).....	10
Table 2.8	TW 920MHz band channel (NCC/T2)	11
Table 2.9	EU channels (Op 6 and 7)	11
Table 2.10	EU channels (Op30).....	12
Table 2.11	NZ channel	12
Table 2.12	AU channel	13
Table 2.13	SG channel.....	13

List of Figures

Figure 2.1 Channel mapping in configuration file..... 7

1 Overview

The wpa_supplicant is required for the NRC7394 STA operation. As the wpa_supplicant does not natively support S1G (Sub-1 GHz) channels, an internal channel mapping table is used within the firmware to uniquely associate each S1G channel to its pre-determined channel in the traditional 2.4/5GHz band.

As the set of available S1G channels is region-specific, a separate wpa_supplicant configuration file is used to handle the usage for each supported region.

The rest of the document will present the channel mapping table for each supported region and explain how to modify the configuration file.

2 Channel

2.1 US (United States) Channel

Table 2.1 presents the US channels for S1G operating class 1, 2, and 3, along with their indices.

Table 2.1 US channels (Op1, 2, and 3)

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
1 / 1	1	902.5	2412
3 / 3	1	903.5	2422
5 / 5	1	904.5	2432
7 / 7	1	905.5	2442
9 / 9	1	906.5	2452
11 / 11	1	907.5	2462
36 / 13	1	908.5	5180
37 / 15	1	909.5	5185
38 / 17	1	910.5	5190
39 / 19	1	911.5	5195
40 / 21	1	912.5	5200
41 / 23	1	913.5	5205
42 / 25	1	914.5	5210
43 / 27	1	915.5	5215
44 / 29	1	916.5	5220
45 / 31	1	917.5	5225
46 / 33	1	918.5	5230
47 / 35	1	919.5	5235
48 / 37	1	920.5	5240

149 / 39	1	921.5	5745
150 / 41	1	922.5	5750
151 / 43	1	923.5	5755
152 / 45	1	924.5	5760
100 / 47	1	925.5	5500
104 / 49	1	926.5	5520
108 / 51	1	927.5	5540
2 / 2	2	903	2417
6 / 6	2	905	2437
10 / 10	2	907	2457
153 / 14	2	909	5765
154 / 18	2	911	5770
155 / 22	2	913	5775
156 / 26	2	915	5780
157 / 30	2	917	5785
158 / 34	2	919	5790
159 / 38	2	921	5795
160 / 42	2	923	5800
161 / 46 (Default)	2	925	5805
112 / 50	2	927	5560
8 / 8	4	906	2447
162 / 16	4	910	5810
163 / 24	4	914	5815
164 / 32	4	918	5820
165 / 40	4	922	5825
116 / 48	4	926	5580

New channel can be used by adding the channel in the configuration file (ex. ap_halow_open.conf or sta_halow_open.conf) as shown below.

```
#2MHz
#909MHz
#channel=153
#915MHz
#channel=156
#921MHz
#channel=159
#925MHz
#channel=161
#927MHz
channel=112
```

2.159(921)	2.161(925)	2.112(927)	4.162(910)
5795	5805	5560	5810
5795	5805	5560	5810

Figure 2.1 Channel mapping in configuration file

The following Table 2.2 shows the newly supported channels defined in S1G operating classes 35 and 36, which were newly added in IEEE 802.11-2024.

Table 2.2 US channels (Op35 and 36)

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
50/128	2	904	5260
52/132	2	906	5280
54/136	2	908	5300
56/140	2	910	5320
58/144	2	912	5340
60/148	2	914	5480
62/152	2	916	5600
64/156	2	918	5620
66/160	2	920	5640
68/164	2	922	5660
70/168	2	924	5680
72/172	2	926	5700
76/130	4	905	5720
80/138	4	909	5740
84/146	4	913	5845
88/154	4	917	5865
92/162	4	921	5885
96/170	4	925	5905

2.2 KR (Korea) Channel

2.2.1 KR USN1 (K1) Package

Table 2.3 KR USN1 (K1) channel

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
36 / 9 (Default)	1	921.5	5180
37 / 11	1	922.5	5185

2.2.2 KR USN5 (K2) Package

Table 2.4 KR USN5 (K2) channel

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
36 / 17	1	925.5	5180
37 / 19	1	926.5	5185
38 / 21	1	927.5	5190
39 / 23 (Default)	1	928.5	5195
40 / 25	1	929.5	5200
41 / 27	1	930.5	5205
42 / 20	2	927.0	5210
43 / 24	2	929.0	5215

2.3 JP (Japan) channel

Table 2.5 JP channel

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
40 / 9 (Default)	1	921.0	5200
42 / 13	1	923.0	5210
43 / 15	1	924.0	5215
44 / 17	1	925.0	5220
45 / 19	1	926.0	5225
46 / 21	1	927.0	5230
36 / 2	2	923.5	5180
37 / 4	2	924.5	5185
38 / 6	2	925.5	5190
39 / 8	2	926.5	5195
47 / 36	4	924.5	5235
48 / 38	4	925.5	5240

2.4 TW (Taiwan) channel

2.4.1 TW 840MHz licensed band channel

Table 2.6 TW 840MHz band channel (Licensed)

Channel Number (NRC)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
36	1	839.0	5180
37	1	840.0	5185
38	1	841.0	5190
39	1	842.0	5195
40	1	843.0	5200
41	1	844.0	5205
42	1	845.0	5210
43	1	846.0	5215
44	1	847.0	5220
45	1	848.0	5225
46	1	849.0	5230
47	1	850.0	5235
48	1	851.0	5240
149	2	839.5	5745
150	2	841.5	5750
151 (Default)	2	843.5	5755
152	2	845.5	5760
153	2	847.5	5765
154	2	849.5	5770
155	4	840.5	5775
156	4	844.5	5780
157	4	848.5	5785

2.4.2 TW 920MHz unlicensed band channel

Table 2.7 TW 920MHz band channel (Unlicensed)

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
158 / 38	1	921.0	5790
159 / 40	1	922.0	5795
160 / 42	1	923.0	5800
161 / 44	1	924.0	5805
162 / 39	2	921.5	5810
163 / 43	2	923.5	5815
164 / 41	4	922.5	5820

2.4.3 TW 920MHz band channel for NCC certification

Table 2.8 TW 920MHz band channel (NCC/T2)

Channel Number (NRC)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
36	1	920.5	5180
37	1	921.5	5185
38	1	922.5	5190
39	1	923.5	5195
40	1	924.5	5200
41	2	921	5205
42	2	923	5210
43	4	922	5215

2.5 EU (Europe) channel

The EU channels have been applied to the following EU-compliant country codes, in accordance with ISO 3166-1 alpha-2 standard:

AT(Austria), BE(Belgium), BG(Bulgaria), CY(Cyprus), CZ(Czechia), DE(Germany), DK(Denmark), EE(Estonia), ES(Spain), FI(Finland), FR(France), GR(Greece), HR(Croatia), HU(Hungary), IE(Ireland), IT(Italy), LT(Lithuania), LU(Luxembourg), LV(Latvia), MT(Malta), NL(Netherlands), PL(Poland), PT(Portugal), RO(Romania), SE(Sweden), SI(Slovenia), SK(Slovakia), GB(Great Britain) and SA(Saudi Arabia).

Table 2.9 EU channels (Op 6 and 7)

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
36 / 1 (Default)	1	863.5	5180
37 / 3	1	864.5	5185
38 / 5	1	865.5	5190
39 / 7	1	866.5	5195
40 / 9	1	867.5	5200
41 / 11 (*)	1	868.5	5205
42 / 13 (*)	1	869.5	5210
43 / 2 (*)	2	864.0	5215
44 / 6	2	866.0	5220
45 / 10 (*)	2	868.0	5225
46 / 4 (*)	4	865.0	5230
47 / 8 (*)	4	867.0	5235

(*) denotes an experimental channel.

The following Table 2.10 shows the newly supported channels defined in S1G operating classes 30, which were newly redefined in IEEE 802.11-2024.

Table 2.10 EU channels (Op30)

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
149/31	1	916.9	5745
150/33	1	917.9	5750
151/35	1	918.9	5755

2.6 NZ (New Zealand) channel

Table 2.11 NZ channel

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
36 / 27 (Default)	1	915.5	5180
37 / 29	1	916.5	5185
38 / 31	1	917.5	5190
39 / 33	1	918.5	5195
40 / 35	1	919.5	5200
41 / 37	1	920.5	5205
42 / 39	1	921.5	5210
43 / 41	1	922.5	5215
44 / 43	1	923.5	5220
45 / 45	1	924.5	5225
46 / 47	1	925.5	5230
47 / 49	1	926.5	5235
48 / 51	1	927.5	5240
153 / 30	2	917.0	5765
154 / 34	2	919.0	5770
155 / 38	2	921.0	5775
156 / 42	2	923.0	5780
157 / 46	2	925.0	5785
158 / 50	2	927.0	5790
162 / 32	4	918.0	5810
163 / 40	4	922.0	5815
164 / 48	4	926.0	5820

2.7 AU (Australia) channel

Table 2.12AU channel

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
36 / 27(Default)	1	915.5	5180
37 / 29	1	916.5	5185
38 / 31	1	917.5	5190
39 / 33	1	918.5	5195
40 / 35	1	919.5	5200
41 / 37	1	920.5	5205
42 / 39	1	921.5	5210
43 / 41	1	922.5	5215
44 / 43	1	923.5	5220
45 / 45	1	924.5	5225
46 / 47	1	925.5	5230
47 / 49	1	926.5	5235
48 / 51	1	927.5	5240
153 / 30	2	917.0	5765
154 / 34	2	919.0	5770
155 / 38	2	921.0	5775
156 / 42	2	923.0	5780
157 / 46	2	925.0	5785
158 / 50	2	927.0	5790
162 / 32	4	918.0	5810
163 / 40	4	922.0	5815
164 / 48	4	926.0	5820

2.8 SG (Singapore) Channel

Table 2.13SG channel

Channel Number (NRC/S1G)	Bandwidth (MHz)	Sub-1GHz frequency	2.4 / 5G frequency
36 / 7	1	866.5	5180
37 / 9	1	867.5	5185
38 / 11	1	868.5	5190
39 / 10 (Default)	2	868	5195
40 / 31	1	917.5	5200
41 / 33	1	918.5	5205
42 / 35	1	919.5	5210
43 / 37	1	920.5	5215

44 / 39	1	921.5	5220
45 / 41	1	922.5	5225
46 / 43	1	923.5	5230
47 / 45	1	924.5	5235
149 / 32	2	918	5745
150 / 36	2	920	5750
151 / 40	2	922	575
152 / 44	2	924	5760
153 / 34	4	919	5765
154 / 42	4	923	5770

3 Revision history

Revision No	Date	Comments
Ver 1.0	4/5/2023	Initial version
Ver 1.1	7/31/2023	Update KR channels
Ver 1.2	9/14/2023	Update CN channels
Ver 1.3	8/21/2024	Fix legacy channel frequency value for K1 channels Add SG channels Update EU channels with EU-compliant country codes Update TW channels: T8/T9
Ver 1.4	8/7/2025	Remove CN channels Update TW/EU/SG channels Add S1G channel numbers
Ver 1.5	3/23/2026	Add US channels for S1G operating class 35 and 36 Add EU channels for S1G operating class 30 Add T2 channels for NCC certification