

regular controls

|                             |                                                                                                                                                         |
|-----------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------|
| <i>Turn Main</i>            | <b>Navigate/edit.</b> Numeric: plain coarse; <i>Fn</i> fine; <i>Shift</i> and <i>Shift+Fn</i> stay coarse. Enum, boolean, and text turns stay ordinary. |
| <i>Click Main</i>           | <b>Menu selection</b> / select, edit, confirm                                                                                                           |
| <i>Back</i>                 | <b>Exit location</b> / exit edit, overlay, or menu level                                                                                                |
| <i>Play</i>                 | <b>Transport</b> / play or pause                                                                                                                        |
| <i>Shift + Play</i>         | <b>Stop</b> / external sync arms a one-shot resync                                                                                                      |
| <i>Fn + Play</i>            | <b>Reset stop</b> / stop, reset position, silence owned notes                                                                                           |
| <i>Fn + turn Main right</i> | <b>Single step</b> / advance one tick while paused/stopped                                                                                              |
| <i>Shift + Back</i>         | <b>Clear layer</b> / re-initialize active layer                                                                                                         |
| <i>Shift + Fn + Main</i>    | <b>Context help</b> / hold modifiers, click menu item                                                                                                   |

navigation + bindings

|                          |                                                                   |
|--------------------------|-------------------------------------------------------------------|
| <i>Fn + left column</i>  | <b>Navigate to Layer 1-8</b> / bottom row = layer 1               |
| <i>Hold Fn</i>           | <b>Preview</b> / layers and Play pages                            |
| <i>Fn + right column</i> | <b>Navigate Play pages</b> / exits if already active              |
| <i>Fn + Aux click</i>    | <b>Bind focused value/action</b> / value to turn, action to click |
| <i>Fn + click Main</i>   | <b>Open Aux mapping</b> / 12-slot scrollable modal                |

**Aux map:** Release *Fn* to keep its 12-slot scrollable modal open; turn *Main* to scroll, click *Main* or press *Back* to close. *Fn* alone previews navigation only.

Auto-map fills unbound *Aux* 1-3 slots with values/actions for this menu area; manual bindings take priority.

1-Cutoff

*Aux* 1 turn 

1!Assign

*Aux* 1 click

special grid modes

|                        |                                                                                                                 |
|------------------------|-----------------------------------------------------------------------------------------------------------------|
| <b>Sample assign</b>   | <i>Shift</i> + cell maps row; <i>Shift + Fn</i> + cell maps column                                              |
| <b>Drum assign</b>     | <i>Shift</i> +cell: row; <i>Shift+Fn</i> +cell: column; Cell Tune: one cell                                     |
| <b>Probability map</b> | Trigger chance: never, low, high, always. <i>Shift</i> + cell = row; <i>Shift + Fn</i> + cell = column          |
| <b>Play Mix</b>        | Grid becomes a mixer for each layer's volume                                                                    |
| <b>Play Pan</b>        | Grid moves around layers' stereo positions                                                                      |
| <b>Play FX</b>         | Press mapped cells to trigger live effects                                                                      |
| <b>Trigger Gate</b>    | Block, allow, or use custom probability per layer. <i>Shift+Fn</i> together + left layer cell toggles its gate. |

behaviors

|                  |                            |                  |                        |
|------------------|----------------------------|------------------|------------------------|
| <b>none</b>      | Inactive layer             | <b>keys</b>      | Finger-drumming        |
| <b>sequencer</b> | Manual rhythm anchor       | <b>looper</b>    | Recorded grid gestures |
| <b>life</b>      | Birth/survival/death cells | <b>brain</b>     | Pulses and trails      |
| <b>ant</b>       | Walking grid agent         | <b>bounce</b>    | Moving collisions      |
| <b>shapes</b>    | Geometric regions          | <b>raindrops</b> | Drops and ripples      |
| <b>dla</b>       | Branching growth           |                  |                        |

triggers

|                      |                              |
|----------------------|------------------------------|
| <b>activate</b>      | Cell turns on                |
| <b>stable</b>        | Cell stays on                |
| <b>deactivate</b>    | Cell turns off               |
| <b>scanned</b>       | Scanner finds active cell    |
| <b>scanned empty</b> | Scanner visits inactive cell |

other play controls

|                   |                                                                   |
|-------------------|-------------------------------------------------------------------|
| <b>XY</b>         | Mappable two-axis surface for live-manipulating parameters        |
| <b>Play Drums</b> | Tap assigned cells for the selected Drum slot, even while stopped |
| <b>Transpose</b>  | Synth, FM, Plucked & enabled MIDI; not Sampler/Drum               |

patch orientation

1. Route **sequencer** or **looper** to **sampler** for a rhythm loop.
2. Add **life**, **raindrops**, **bounce**, or **dla** to a **synth**.
3. Use probability on sequencer cells so patterns feel alive.
4. Bind aux encoders to parameters or actions you keep reaching for.

**Aux turns:** Normal target: plain coarse, *Fn* fine. Shifted custom bank: *Shift* coarse, *Shift+Fn* fine; no fallback. Other turns are discrete. *Shift+Fn* is one combined modifier.

Factory preset hint: **life** on Layer 1, **sequencer** rhythm on Layer 2.

**Sample browser:** . . parent; [folder] folder; file rows are samples; (empty) means no entries. *Play* / *Space* previews the highlighted sample. Long names clip or scroll without overlapping other OLED text.

**Bench safety:** Power through the enclosure USB-C breakout; remove both the board microSD card and OLED microSD card before closing the case.

If the grid behaves unexpectedly, check the OLED. You are probably in an overlay or Play page. Use *Back* or *Fn* to leave.

# cell state to sound

From behavior state and direct input to MIDI, internal audio, routing, and optional live FX.

