AMAZON BASE BUILDING COMPLIANCE STANDARD

Task Title	Electric shock protective equipment
APM Object	CT.ELEC.SHOCKPROTECTION
APM Description	Earthing and electrical discharging systems All sites with indoor and/or outdoor lighting systems.
General tasks always required	Follow safety procedures - e.g. 1MRA, LOTO, PPE, etc. Ensure that all WOs are carried out by qualified, certified staff with appropriate familiarisation and supervision as required Add notes for each observation and create a FWO if necessary to eliminate defects Use appropriate tools, chemicals and industry standard practices (RME policy permitting) Ensure relevant logs, readings and certification is uploaded to APM prior to WO closure. CT evidence must be additionally uploaded to the DMS (WorkDocs in DE) To suggest improvements please raise a SIM or contact document authors Leonardo Vitale (LEOVITAL) Rob Gisby (EWARTGXR) or APM, Benito Sanchez Sanchez de Puerta (BPPUERTA) SIM - Link to SIM template

Last Update: (Version)	ago-23	**Last Update Change Detail:**	Transfer to new template. Rationalisation of EU RME Minimum standards. Alignment with dependant PM. Released as Draft.	**Activities may be covered by No-Go restrictions:**	Not Specified	**Special Certification Required:**	**Delivered By:**
Evidenced part or full by PM:	Not Specified	**Related BBM PM:**	Not Specified	**Related CT Areas:**	Not Specified		

Scope

Any site with an electrical installation. Inspection of the earthing and electrical discharging systems is mandatory as part of the inspection of the electrical installation as a whole.
More than 36 kV - high voltage
However, EU RME simplifies to LV < 1 kV AC and HV ≥ 1 kV AC.
Any site where an emergency lighting system (including battery) is installed to aid safety in the event of power failure and/or safe evacuation of the site in emergency situations.
Inspection requirements of electrical installations are covered by "Compliance HV inspection and test", "High/Medium Voltage" and "Low Voltage" Standards.
Any site with an electrical installation. CEN and CENELEC standards define incoming electricity at:
Less than 1 kV - low voltage installations
Between 1 kV and 36 kV - medium voltage installation
Any site where diesel power generators are commissioned to produce electricity, generally as a back-up in emergency situations. This includes all diesel generators, whether stationary or mobile.
This Compliance Standard only covers the inspection requirements associated with the electrical components of diesel generators. The maintenance of a UPS is covered in CT.ELEC.UPS.

Using this document

This document is intended as a guide and may not be exhaustive. Whilst this document is based extensively on professional guidance and subject to periodic review, individual sites must be diligent to ensure they are aware of, and comply to, local and changing regulations.
The format of these standards is intended to improve navigation between maintenance and compliance standards and to allow frequent, minor updates to a single living resource. Please avoid offline or printed versions and check version dates and change log.
In the event of becoming aware of errors or omissions in this document, sites must provide detail, including references to relevant source information to their local planner for escalation - SIM Link above.
This document is considered released as draft.
For Information contact Authors: R Gisby (ewartgxr), Leonardo Vitale (leovital) and Benito Sanchez Sanchez de Puerta (bppuerta)

Maintenance and Compliance Relationship

Where relevant, associated Base Building PM's are listed on the header . In many cases maintenance contributes to, or fulfils compliance requirement. This may not be exhaustive and is intended to assist users to identify relevant maintenance.
If a BBM Maintenance activity fully meets the compliance requirements below, periodic upload of PM evidence will be required to APM and DMS / Workdays depending on region.

Key to Abbreviations

The key to the below document is as follows:
CT - Amazon compliance / statutory task - not otherwise covered by a BBM Standard PM. Evidence to be provided into APM and DMS upon task closure.
CT* - This is a conditional task based or based on findings from previous inspections. If a frequency is not used, a further appropriate frequency needs to be in either the region, or 'ALL'. Local teams must ensure appropriate frequency.
(CT) - Compliance task which is likely met or exceeded by a CT task in [ALL] and therefore achieved by proxy BUT local site must satisfy themselves that requirements are fully met.
PM - Requirement can demonstrated through appropriate maintenance - Refer to relevant PM Standard
(PM) - Maintenance task which is met or exceeded by a PM task in [ALL] and therefore achieved by proxy BUT local site must satisfy themselves that requirements are fully met including regional / manufacturer requirements.
EVID - Periodic upload of evidence to DMS, for non-CT task lines. For example, evidence of PM completion, certification, licence etc.
EVID* - Conditional requirement to upload evidence at the interval provided
N A R - No Additional Requirement

Required Tasks

Region	Task Index	Task Frequency	Task Requirements	Qualification of Inspector	Records Required	PM	Weekly	Monthly	3 Monthly	6 Monthly	12 Monthly	24 Monthly	Additional
All	1	Based on risk assessment, but at least every 6 months for hand protection clothing and 12 months for other protective equipment	Regular inspection of all insulating protective equipment	Competent person (Electrician accredited by NICEIC, ECA or SELECT.)	Risk assessment Inspection records					CT*	CT*		
IT	2	No additional requirements.	No additional requirements.	No additional requirements.	CE Declaration of Conformity.								N A R

Related Regional Legislation

Region	Relevant legislation	Vendor Certification	Statutory requirement
CZ	ČSN EN 60903, ČSN 35 9700, ČSN EN 61481, ČSN EN 50508, ČSN EN 62193, ČSN EN 60855, ČSN EN 61243	Competent electrician	Frequency determined by the type of protective equipment, between 6 and 60 months.
DE	DGUV Vorschrift 3 - Elektrische Anlagen und Betriebsmittel (Tabelle 1C: Prüfungen für Schutz- und Hilfsmittel)	Qualified electrician (Elektrofachkraft)	Regular inspections based on risk assessment. For insulating protective clothing: Visual inspection before each use by user, general inspection at least every 12 months, but every 6 months for insulating gloves. For insulated tools: visual inspection before each use, and functional observation during each use by user. For voltage testers, phase comparators and voltage testing systems for nominal voltages above 1 kV: at least every 6 years.

ES	RD 614/2001, of June 8, about health and safety protection for workers toward electric risks. Technical guide for the assessment and prevention of electric risks.	Competent person	Regular maintenance in accordance with manufacturer's instructions.
FR	Labor Code Article R4322-1 https://www.legifrance.gouv.fr/codes/article_lc/LEGIARTI000018531543/ Labor Code Article R4323-99 https://www.legifrance.gouv.fr/codes/article_lc/LEGIARTI000018531296/	N/A	N/A
IT	Legislative Decree 9/04/2008 n.81 CEI EN 60903 (Hand protection clothing) CEI EN 60984 (Protective sleeves) CEI EN 50321-1 (Dielectric protective footwear) CEI EN 61482 (Protective clothing against the thermal effect of the electric arc) CEI EN 60895 (Dielectric protective clothing) CEI EN 50365 (Helmets- requirements for dielectric protection) UNI EN 397:2013 (Protective helmets) UNI EN 166:2004 (Personal eye protection)	Competent person	Maintenance in accordance with manufacturer's instructions. Every 6 months for hand protection gear (every 12 months for gloves used under 1000V).
PL	Regulation of minister of Labor and Social Policy on general health and safety regulations (Journal of Laws 2003, numer 169, item 1650) Regulation of the Minister of Energy of August 28, 2019 on health and safety at work with energy devices (Journal of Laws 2019, item 1830)	Competent person	Regular maintenance in accordance with manufacturer's instructions.
ROI	S.I. No. 299/2007 - Safety, Health and Welfare at Work (General Application) Regulations 2007 (irishstatutebook.ie) NSAI - IS 10101:2020 on 6 March 2020	Competent person	Routine maintenance, repair or replacements based on use and operating conditions.
SK	Act No. 124/2006 Coll. on safety and health at work Ordinance No. 205/2010 Coll. on designated technical equipment and designated activities and activities on designated technical equipment Ordinance No. 508/2009 Coll. on details for ensuring safety and health protection at work with pressure, lifting, electrical and gas technical equipment. STN 33 2000-4-41: Low voltage electrical installations. Part 4-41: Ensuring safety. Protection against electric shock.	Qualified and certified person	Routine maintenance, repair or replacements based on use and operating conditions.
UK	Health and Safety at Work etc. Act 1974 (legislation.gov.uk) The Electricity at Work Regulations 1989 (legislation.gov.uk) The Personal Protective Equipment (Enforcement) Regulations 2018 (legislation.gov.uk) The Personal Protective Equipment at Work Regulations 1992 (legislation.gov.uk) Health and Safety at Work (Northern Ireland) Order 1978 (legislation.gov.uk) The Electricity At Work Regulations (Northern Ireland) 1991 (legislation.gov.uk) Personal Protective Equipment at Work Regulations (Northern Ireland) 1993 (legislation.gov.uk)	Competent person	Routine maintenance, repair or replacements based on use and operating conditions.