amazon rme

AMAZON BASE BUILDING MAINTENANCE STANDARD

GLOBAL CENTRAL RME STANDARDS & COMPLIANCE

Task Title	ELECTRICAL SYSTEM, LOW VOLTAGE, POWER FACTOR CORRECTION - 11
APM Object	ELEC.LV.PFC
APM EC	AMZ.ELEC.LV.PFC
BBM Handbook Title	Low Voltage Power Factor Correction
General tasks always required	Follow safety procedures - e.g. 1MRA, LOTO, PPE, etc. Ensure that all WOs are carried out by qualified, certified staff with appropriate familiarisation and supervision as required Add notes for each observation and create a FWO if necessary to eliminate defects Use appropriate tools, chemicals and industry standard practices (RME policy permitting) Ensure relevant logs, readings and certification is uploaded to APM prior to WO closure These tasks are based on industry guidance, SME knowledge and HIE learning. Please ensure vendor specific requirements are followed. To suggest improvements please raise a SIM SIM - Link to SIM template

Last Update: (Version)	Jul-23	**Geo Applied:**	Intl APM Instance	**F-Gas**	Not Identified	**Activies may be covered by No-Go restrictions:**	Yes	**Special Certificaion Required:**	TBC	**Delivered By:**	Carried out by trained on site technician certified in the electrical field	**OCB:**	BBM
Evidence for CT:	TBC	**Pricing template Position:**	11	**Related CT Areas:**	Not Identified			**Assets included in this PM:**	POWER FACTOR CORRECTION CABINET	**Schedule With:**	ELEC.LV.CABS ELEC.LV.BSBR ELEC.MET ELEC.LV.SWBD BLDG.EARTHING		

Description of System / Technology (According to BBM Handbook)

Low Voltage Power factor correction (PFC) aims to improve power factor in systems less than 1kV, and therefore power quality. It reduces the load on the electrical distribution system, increases energy efficiency and reduces electricity costs. It also decreases the likelihood of instability and failure of equipment. These are often installed to meet utility requirements for minimum PF.

Additional Information

All sites with the above listed Base Building Asset should conduct routine maintenance and inspections according to this standard PM package. The Amazon maintenance standard supports compliance, reduces safety risks,improves asset reliability & efficiency. Some maintenances captures several assets within one PM package -> Ensure that corrective/reactive maintenance for assets where proactive maintenance is contained under another asset is created against the original asset.

Task Index	Component	Tasks	Tasks Nested for frequencies > weekly									
			Daily	Weekly	Monthly	3 Monthly	6 Monthly	12 Monthly	24 Monthly	36 Monthly	48 Monthly	60 Monthly
1	General check	Is the panel/cabinet clean - free from debris						PM				
2	General check	Is the air filter of the electrical panel/cabinet clean -> Please clean or change if necessary						PM				
3	General check	Is the cooling fan operating appropriately and doesn`t make any unusual noise					PM	PM				
4	General check	Visual check of the panel outside & inside for damage & missing components					PM	PM				
5	General check	Are there any alarms indicated					PM	PM				
6	General check	Did any circuit breaker trip					PM	PM				
7	General check	Are disconnecting devices lockable in the open position (LOTO)					PM	PM				
8	General check	Are the circuit diagrams and relevant technical documentation available and complete						PM				
9	General check	Are there manual entries in the drawings or technical documentation that indicate changes to the installation						PM				
10	Thermographic scan	Perform thermographic scans & create a WO for over-temperature to determine the root cause immediately					PM	PM				
11	Thermographic scan value	Add a detailed note for all over-temperature measurements -> list the location and temperature -> Upload the thermographic scan					PM	PM				
12	Electrical components	Inspect all cables and connections insulation/shields for damage						PM				
13	Electrical components	Inspect all cable/busbar terminations and capacitors for signs of overheating						PM				
14	Electrical components	Inspect the capacitors for visual damage						PM				
15	Electrical components	Check if the system is properly connected to the PE (ground), check also for damage & corrosion						PM				
16	Measurement	Measure the capacitance of the capacitors and compare to manufacturer specification -> schedule an exchange if required						PM				
17	Functional cleaning	Carry out functional cleaning						PM				
18	Final Check	Check the O&M manual and carry out additional required tasks						PM				

Change Log

July 2023 - First issue in new format. Simplification of task scope, alignment with CT.