AMAZON BASE BUILDING COMPLIANCE STANDARD

Task Title	Portable Appliance Testing
APM Object	CT.ELEC.PAT
APM Description	Portable Appliances
General tasks always required	Follow safety procedures - e.g. 1MRA, LOTO, PPE, etc. Ensure that all WOs are carried out by qualified, certified staff with appropriate familiarisation and supervision as required Add notes for each observation and create a FWO if necessary to eliminate defects Use appropriate tools, chemicals and industry standard practices (RME policy permitting) Ensure relevant logs, readings and certification is uploaded to APM prior to WO closure. CT evidence must be additionally uploaded to the DMS (WorkDocs in DE) To suggest improvements please raise a SIM or contact document authors Leonardo Vitale (LEOVITAL) Rob Gisby (EWARTGXR) or APM, Benito Sanchez Sanchez de Puerta (BPPUERTA) SIM - Link to SIM template

Last Update: (Version)	ago-23	**Last Update Change Detail:**	Transfer to new template. Rationalisation of EU RME Minimum standards. Alignment with dependant PM. Released as Draft.	**Activities may be covered by No-Go restrictions:**	Not Specified	**Special Certification Required:**	**Delivered By:**
Evidenced part or full by PM:	Not Specified	**Related BBM PM:**	Not Specified	**Related CT Areas:**	Not Specified		

Scope

Any site where Portable Appliances are used. This includes hand-held and moveable equipment, such as computers, photocopiers, kitchen equipment, floor cleaners, hand-held or moveable power tools, etc.

Using this document

This document is intended as a guide and may not be exhaustive. Whilst this document is based extensively on professional guidance and subject to periodic review, individual sites must be diligent to ensure they are aware of, and comply to, local and changing regulations.
The format of these standards is intended to improve navigation between maintenance and compliance standards and to allow frequent, minor updates to a single living resource. Please avoid offline or printed versions and check version dates and change log.
In the event of becoming aware of errors or omissions in this document, sites must provide detail, including references to relevant source information to their local planner for escalation - SIM Link above.
This document is considered released as draft.
For Information contact Authors: R Gisby (ewartgxr), Leonardo Vitale (leovital) and Benito Sanchez Sanchez de Puerta (bppuerta)

Maintenance and Compliance Relationship

Where relevant, associated Base Building PM's are listed on the header . In many cases maintenance contributes to, or fulfils compliance requirement. This may not be exhaustive and is intended to assist users to identify relevant maintenance.
If a BBM Maintenance activity fully meets the compliance requirements below, periodic upload of PM evidence will be required to APM and DMS / Workdays depending on region.

Key to Abbreviations

The key to the below document is as follows:
CT - Amazon compliance / statutory task - not otherwise covered by a BBM Standard PM. Evidence to be provided into APM and DMS upon task closure.
CT* - This is a conditional task based or based on findings from previous inspections. If a frequency is not used, a further appropriate frequency needs to be in either the region, or 'ALL'. Local teams must ensure appropriate frequency.
(CT) - Compliance task which is likely met or exceeded by a CT task in [ALL] and therefore achieved by proxy BUT local site must satisfy themselves that requirements are fully met.
PM - Requirement can demonstrated through appropriate maintenance - Refer to relevant PM Standard
(PM) - Maintenance task which is met or exceeded by a PM task in [ALL] and therefore achieved by proxy BUT local site must satisfy themselves that requirements are fully met including regional / manufacturer requirements.
EVID - Periodic upload of evidence to DMS, for non-CT task lines. For example, evidence of PM completion, certification, licence etc.
EVID* - Conditional requirement to upload evidence at the interval provided
N A R - No Additional Requirement

Required Tasks

Region	Task Index	Task Frequency	Task Requirements	Qualification of Inspector	Records Required	PM	Weekly	Monthly	3 Monthly	6 Monthly	12 Monthly	24 Monthly	Additional
All		In accordance with manufacturer's instructions and recommendations.	Regular maintenance of all portable appliances	Competent person	Maintenance logbook						CT		
All		Frequency determined by risk assessment (type of equipment, frequency of use and operating conditions) of each individual appliance. Additionally, following any repair or modification.	Visual checks to assess whether the appliance is suitable for its intended use, including any use changes, damages to the appliance, cables or plug, any previously reported issues, earthing, etc. If any defects are identified, prevent subsequent use through quarantine prior to repair or destruction – do Not use. Report issue.	Competent person	Inspection records. Risk assessment						CT		
All		Frequency determined by risk assessment (type of equipment, frequency of use and operating conditions) of each individual appliance. Additionally, following any repair or modification.	Inspection and testing of portable appliances (PAT) to check correct polarity of supply cables, correct fusing, any potential loss of earth integrity, deterioration of insulations or contamination of surfaces, suitability of the equipment for its intended use. If any defects are identified, prevent subsequent use through quarantine prior to repair or destruction – do Not use. Report issue	Competent person	Inspection records. Risk assessment								
All		In accordance with manufacturer's instructions and recommendations.	Regular maintenance of all portable appliances	Competent person	Maintenance logbook						CT		
All		Frequency determined by risk assessment (type of equipment, frequency of use and operating conditions) of each individual appliance. Additionally, following any repair or modification.	Visual checks to assess whether the appliance is suitable for its intended use, including any use changes, damages to the appliance, cables or plug, any previously reported issues, earthing, etc. If any defects are identified, prevent subsequent use through quarantine prior to repair or destruction – do Not use. Report issue.	Competent person	Inspection records. Risk assessment						CT		

All		Frequency determined by risk assessment (type of equipment, frequency of use and operating conditions) of each individual appliance. Additionally, following any repair or modification.	Inspection and testing of portable appliances (PAT) to check correct polarity of supply cables, correct fusing, any potential loss of earth integrity, deterioration of insulations or contamination of surfaces, suitability of the equipment for its intended use. If any defects are identified, prevent subsequent use through quarantine prior to repair or destruction – do Not use. Report issue	Competent person	Inspection records. Risk assessment						CT		
IT	6	No additional requirements	No additional requirements	No additional requirements	CE Declaration of Conformity								
SK	5	Group A: Inspection before every lease. Group B: Once per three months (III.: Once per six months). Group C: Once per six months (I.), Once per 12 months (II.), Depends on their function (III.). Group D: Once per twelve months (III.: Depends on their	Inspection requirements depend on the way how appliances are used.	No additional requirements	No additional requirements					CT*	CT*	CT*	On demand EVID
SK	5	Group A: Inspection before every lease. Group B: Once per three months (III.: Once per six months). Group C: Once per six months (I.), Once per 12 months (II.), Depends on their function (III.). Group D: Once per twelve months (III.: Depends on their	Inspection requirements depend on the way how appliances are used.	No additional requirements	No additional requirements								

Related Regional Legislation

Region	Relevant legislation	Vendor Certification	Statutory requirement
CZ	Decree 73/2010 Coll., ČSN 33 1600 ed.2, Decree No. 50/1978 Coll.	Review technician	Frequency depends on type of space, equipment and type of insulation, between 6 and 24 months.
DE	Betriebssicherheitsverordnung (BetrSichV) Technische Regeln für Betriebssicherheit: TRBS 1201 - Prüfungen und Kontrollen von Arbeitsmitteln und überwachungsbedürftigen Anlagen DGUV Vorschrift 3 - Elektrische Anlagen und Betriebsmittel DIN VDE 0105-100 - Betrieb von elektrischen Anlagen	Qualified electrician (Elektrofachkraft).	Frequency of inspections based on risk assessment (type, use and failure rate). If failure rate is <2%: - yearly on construction sites, manufacturing plants, etc. - 2 yearly in offices.
ES	RD 1215/97 establishing minimum security provisions and Health for the use by workers of work equipment.	Competent person	Maintenance in accordance with manufacturer's instructions. Regular Inspections and tests where appropriate.
FR	Arrêté du 26 décembre 2011 relatif aux vérifications ou processus de vérification des installations électriques ainsi qu'au contenu des rapports correspondants - Légifrance (legifrance.gouv.fr)	Accredited organisation or employee who is qualified or trained.	Annual inspection
IT	Legislative Decree 8/04/2008 n.81 Directive 2006/42/EC on machinery Directive 2014/35/EU CEI EN 60335-1 (Safety of household and similar electric appliances) CEI EN 60730-1 (Automatic electrical control devices) CEI EN 60320-1/EC (Connectors for household and similar electric appliances) CEI EN 60745-1 (Safety of hand-held electric power tools)	Competent person.	Periodic maintenance in accordance with manufacturer's instructions. Inspection and testing frequency of portable equipment depend on risk assessment. Inspection every 12 months for hand-held or movable power tools.
PL	Regulation of the Minister of Economy of 30 October 2002 on the minimum requirements for occupational health and safety in the use of machines by employees at work. (Journal of Laws of 2002, No. 191, item 1596)	Competent person	Regular inspections and tests based on risk assessment of each individual appliance, but up to 5 years.
ROI	Guide to the Safety, Health and Welfare at (Work General Application) Regulations 2007 - Health and Safety Authority (hsa.ie) Maintaining portable electrical equipment in low-risk environments (INDG236(rev2)) (hse.gov.uk)	Competent person, registered electrician approved by RECI or ECSSA.	Regular visual checks based on risk assessment, generally between 6 months and 4 years. Regular inspections and tests based on risk assessment of each individual appliance, but up to 5 years.

SK	Act No. 124/2006 Coll. on safety and health at work Act No. 314/2001 on fire prevention Ordinance No. 508/2009 Coll. on details for ensuring safety and health protection at work with pressure, lifting, electrical and gas technical equipment STN 33 1610: Revisions and inspections of electrical appliances during their use STN 33 1500: Electrical engineering regulations. Inspection and testing of electrical installations	Competent & certified person.	Pre-use checks and regular inspections in accordance with manufacturer's instructions and depending on use (A-E) and type of coverage (I-III). Group A: Leased appliances. Group B: Appliances used in exterior space. Group C: Appliances used in interior space. Group D: Appliances used in public interior space. Group E: Appliances used for administrative activities. I.: Hand-held equipment. II.: Moveable equipment. III.: Stationary equipment.
UK	The Electricity at Work Regulations 1989 (legislation.gov.uk) The Electricity at Work Regulations 1989. Guidance on Regulations (hse.gov.uk) The Provision and Use of Work Equipment Regulations 1998 (legislation.gov.uk) puwer.pdf (hse.gov.uk) Maintaining portable electrical equipment in low-risk environments (INDG236(rev2)) (hse.gov.uk) The Electricity At Work Regulations (Northern Ireland) 1991 (legislation.gov.uk) Provision and Use of Work Equipment Regulations (Northern Ireland) 1999 (legislation.gov.uk)	Competent person, trained and skilled in electrical work.	Regular visual checks based on risk assessment, generally between 6 months and 4 years. Regular inspections and tests based on risk assessment of each individual appliance, but up to 5 years.