AMAZON BASE BUILDING COMPLIANCE STANDARD

Task Title	Residual Current Device
APM Object	CT.ELEC.RCDMETER
APM Description	Residual-current devices (RCDs).
General tasks always required	Follow safety procedures - e.g. 1MRA, LOTO, PPE, etc. Ensure that all WOs are carried out by qualified, certified staff with appropriate familiarisation and supervision as required Add notes for each observation and create a FWO if necessary to eliminate defects Use appropriate tools, chemicals and industry standard practices (RME policy permitting) Ensure relevant logs, readings and certification is uploaded to APM prior to WO closure. CT evidence must be additionally uploaded to the DMS (WorkDocs in DE) To suggest improvements please raise a SIM or contact document authors Leonardo Vitale (LEOVITAL) Rob Gisby (EWARTGXR) or APM, Benito Sanchez Sanchez de Puerta (BPPUERTA) SIM - Link to SIM template

Last Update: (Version)	ago-23	**Last Update Change Detail:**	Transfer to new template. Rationalisation of EU RME Minimum standards. Alignment with dependant PM. Released as Draft.	**Activities may be covered by No-Go restrictions:**	Not Specified	**Special Certification Required:**	**Delivered By:**
Evidenced part or full by PM:	Not Specified	**Related BBM PM:**	Not Specified	**Related CT Areas:**	Not Specified		

Scope

Any site where Residual-current devices (RCDs) are used to prevent fires and harm (electric shock) to employees using electrical equipment by switching circuits off when it detects electricity flowing down an unintended path (e.g. a person).

Using this document

This document is intended as a guide and may not be exhaustive. Whilst this document is based extensively on professional guidance and subject to periodic review, individual sites must be diligent to ensure they are aware of, and comply to, local and changing regulations.
The format of these standards is intended to improve navigation between maintenance and compliance standards and to allow frequent, minor updates to a single living resource. Please avoid offline or printed versions and check version dates and change log.
In the event of becoming aware of errors or omissions in this document, sites must provide detail, including references to relevant source information to their local planner for escalation - SIM Link above.
This document is considered released as draft.
For Information contact Authors: R Gisby (ewartgxr), Leonardo Vitale (leovital) and Benito Sanchez Sanchez de Puerta (bppuerta)

Maintenance and Compliance Relationship

Where relevant, associated Base Building PM's are listed on the header . In many cases maintenance contributes to, or fulfils compliance requirement. This may not be exhaustive and is intended to assist users to identify relevant maintenance.
If a BBM Maintenance activity fully meets the compliance requirements below, periodic upload of PM evidence will be required to APM and DMS / Workdays depending on region.

Key to Abbreviations

The key to the below document is as follows:
CT - Amazon compliance / statutory task - not otherwise covered by a BBM Standard PM. Evidence to be provided into APM and DMS upon task closure.
CT* - This is a conditional task based or based on findings from previous inspections. If a frequency is not used, a further appropriate frequency needs to be in either the region, or 'ALL'. Local teams must ensure appropriate frequency.
(CT) - Compliance task which is likely met or exceeded by a CT task in [ALL] and therefore achieved by proxy BUT local site must satisfy themselves that requirements are fully met.
PM - Requirement can demonstrated through appropriate maintenance - Refer to relevant PM Standard
(PM) - Maintenance task which is met or exceeded by a PM task in [ALL] and therefore achieved by proxy BUT local site must satisfy themselves that requirements are fully met including regional / manufacturer requirements.
EVID - Periodic upload of evidence to DMS, for non-CT task lines. For example, evidence of PM completion, certification, licence etc.
EVID* - Conditional requirement to upload evidence at the interval provided
N A R - No Additional Requirement

Required Tasks

Region	Task Index	Task Frequency	Task Requirements	Qualification of Inspector	Records Required	PM	Weekly	Monthly	3 Monthly	6 Monthly	12 Monthly	24 Monthly	Additional
All	1	In accordance with manufacturer's instructions and recommendations.	Periodic maintenance of all RCDs.	Competent person	Maintenance logbook					CT			
All	2	Based on risk assessment, but at least every 6 months.	Regular RCD button checks, consisting in manually tripping and stopping the current by pressing the "Test" button. If defects are identified, prevent subsequent use through quarantine prior to repair or destruction and replacement – do Not use. Report issue.	Competent person	Inspection records, report or certificate. Risk assessment					CT			
All	3	Based on risk assessment, but at least once every 12 months.	Functional inspection of RCDs, consisting on measuring their response time or tripping time to ensure compliance. If defects are identified, prevent subsequent use through quarantine prior to repair or destruction and replacement – do Not use. Report issue.	Competent Person (Accredited Electrician on the Electrical Safety Register e.g. NICEIC, ECA, SELECT)	Inspection records, report or certificate. Risk assessment						CT		
DE	4	Monthly inspections	Additional inspection and testing of RCDs in non-stationary installations.	No additional requirements	No additional requirements			CT					
ES	5	Monthly inspections	Inspection as per [4].	Accredited company	No additional requirements			(CT)					

Related Regional Legislation

Region	Relevant legislation	Vendor Certification	Statutory requirement
CZ	Decree 73/2010 Coll., ČSN 331500, ČSN 333320 ed.2, ČSN 332570, ČSN 332000, ČSN EN 62305, ČSN 331600.ed.2, Decree 50/1978	Competent electrician Review technician	Frequency determined by the Protocol on the list of external influences, between 6 and 60months.
DE	Betriebssicherheitsverordnung (BetrSichV) Technische Regeln für Betriebssicherheit: TRBS 1201- Prüfungen und Kontrollen von Arbeitsmitteln und überwachungsbedürftigen Anlagen DGUV Vorschrift 3 - Unfallverhütungsvorschrift Elektrische Anlagen und Betriebsmittel DGUV Information 203-032 - Auswahl und Betrieb von Stromerzeugern auf Bau- und Montagestellen DIN VDE 0105-100- Betrieb von elektrischen Anlagen	Button checks conducted by user. RCD test meter inspection by qualified electrician (Elektrofachkraft)	RCDs in non-stationary systems must be checked for effectiveness by a qualified electrician at least once a month. RCD button check to be conducted at least every 6 months. RCD test meter inspection to be conducted at least every 4 years as part of the periodic inspection of the electrical installation.
ES	RD 842/2002, of August 2, which approves the electrotechnical regulation for low voltage and its 52 Complementary Technical Instructions. RD 337/2014, of May 9, which approves the high voltage electric systems and its 23 Complementary Technical Instructions.	Accredited company (OCA) by ENAC.	Low voltage Inspections and testing at least every 5 years. High Voltage inspections and testing to be conducted at least every 3 years.
FR	26th December 2011 Decree about electrical installations verification ""Arrêté du 26 décembre 2011 relatif aux vérifications ou processus de vérification des installations électriques ainsi qu'au contenu des rapports correspondants" https://www.legifrance.gouv.fr/loda/id/JORFTEXT000025046978/	Accredited organisation or employee who is qualified or trained.	Annual inspection
IT	Legislative Decree 8/04/2008 n.81 DM 22/01/2008 n.37 CEI 64-8/6 (Electric installations under 1000V-Inspections) CEI IEC 60755 (RCD-safety requirements) CEI 23-98 (Maintenance)	RCD inspection by competent person.	Periodic maintenance. RCD button check to be conducted at least every 6 months. RCD test meter inspection every 12 months.
PL	Act of 7 July 1994 - Construction Law (Journal of Laws 1994 No. 89 pos. 414), as amended Act of April 10, 1997 - Energy Law (Journal of Laws of 1997, No. 54, item 348) Regulation of the Minister of Economy, Labor and Social Policy of 28 April 2003 on the detailed rules for confirming qualifications by persons involved in the operation of devices, installations and networks (Journal of Laws of 2003, No. 89, item 828) Act of April 24, 2009 on batteries and accumulators (Journal of Laws 2020, item 1850) Regulation of the Minister of Energy of August 28, 2019 on health and safety at work with energy devices (Journal of Laws 2019, item 1830)	Qualified & competent person, authorised according to Construction Law.	Periodic maintenance. RCD button check to be conducted at least every 12 months.
ROI	S.I. No. 299/2007 - Safety, Health and Welfare at Work (General Application) Regulations 2007 (irishstatutebook.ie) The NSAI - IS 10101:2020 March 2020	Competent, registered electrician. Approved by RECI or ECSSA.	RCD button checks conducted regularly. Test meter conducted at least every 12 months.
SK	Act No. 124/2006 Coll. on safety and health at work Ordinance No. 205/2010 Coll. on designated technical equipment and designated activities and activities on designated technical equipment Ordinance No. 508/2009 Coll. on details for ensuring safety and health protection at work with pressure, lifting, electrical and gas technical equipment Ordinance No. 121/2002 Coll. on fire prevention STN 33 2000 Low voltage electrical installations. Part 4-41: Ensuring safety	Qualified (based at the level of education and the length of experience) & certified person.	Frequency according to the technical documentation.
UK	IET Wiring Regulations/BS 7671	Competent, registered electrician on Electrical Safety Register. Approved by NICEIC, ECA or SELECT.	Test button check conducted at least every 6 months. Test meter conducted at least every 12 months.