AMAZON BASE BUILDING COMPLIANCE STANDARD

amazon rme

Task Title	Uninterrupted power supply (UPS)
APM Object	CT.ELEC.UPS
APM Description	Uninterrupted power supply (UPS)
General tasks always required	Follow safety procedures - e.g. 1MRA, LOTO, PPE, etc. Ensure that all WOs are carried out by qualified, certified staff with appropriate familiarisation and supervision as required Add notes for each observation and create a FWO if necessary to eliminate defects Use appropriate tools, chemicals and industry standard practices (RME policy permitting) Ensure relevant logs, readings and certification is uploaded to APM prior to WO closure. CT evidence must be additionally uploaded to the DMS (WorkDocs in DE) To suggest improvements please raise a SIM or contact document authors Leonardo Vitale (LEOVITAL) Rob Gisby (EWARTGXR) or APM, Benito Sanchez Sanchez de Puerta (BPPUERTA) SIM - Link to SIM template

Last Update: (Version)	abr-24	**Last Update Change Detail:**	PM evidence changed from 3M to 12M.	**Activities may be covered by No-Go restrictions:**	Not Specified	**Special Certification Required:**	**Delivered By:**
Evidenced part or full by PM:	Not Specified	**Related BBM PM:**	ELEC.UPS	**Related CT Areas:**	Not Specified		

Scope

Any site where Uninterrupted Power Supply (UPS) systems (e.g. back-up batteries) are used to provide back-up sources of electricity when the mains service fails.
The maintenance of Generators is covered in Power Generators.

Using this document

This document is intended as a guide and may not be exhaustive. Whilst this document is based extensively on professional guidance and subject to periodic review, individual sites must be diligent to ensure they are aware of, and comply to, local and changing regulations.
The format of these standards is intended to improve navigation between maintenance and compliance standards and to allow frequent, minor updates to a single living resource. Please avoid offline or printed versions and check version dates and change log.
In the event of becoming aware of errors or omissions in this document, sites must provide detail, including references to relevant source information to their local planner for escalation - SIM Link above.
This document is considered released as draft.
For Information contact Authors: R Gisby (ewartgxr), Leonardo Vitale (leovital) and Benito Sanchez Sanchez de Puerta (bppuerta)

Maintenance and Compliance Relationship

Where relevant, associated Base Building PM's are listed on the header . In many cases maintenance contributes to, or fulfils compliance requirement. This may not be exhaustive and is intended to assist users to identify relevant maintenance.
If a BBM Maintenance activity fully meets the compliance requirements below, periodic upload of PM evidence will be required to APM and DMS / Workdays depending on region.

Key to Abbreviations

The key to the below document is as follows:
CT - Amazon compliance / statutory task - not otherwise covered by a BBM Standard PM. Evidence to be provided into APM and DMS upon task closure.
CT* - This is a conditional task based or based on findings from previous inspections. If a frequency is not used, a further appropriate frequency needs to be in either the region, or 'ALL'. Local teams must ensure appropriate frequency.
(CT) - Compliance task which is likely met or exceeded by a CT task in [ALL] and therefore achieved by proxy BUT local site must satisfy themselves that requirements are fully met.
PM - Requirement can demonstrated through appropriate maintenance - Refer to relevant PM Standard
(PM) - Maintenance task which is met or exceeded by a PM task in [ALL] and therefore achieved by proxy BUT local site must satisfy themselves that requirements are fully met including regional / manufacturer requirements.
EVID - Periodic upload of evidence to DMS, for non-CT task lines. For example, evidence of PM completion, certification, licence etc.
EVID* - Conditional requirement to upload evidence at the interval provided
N A R - No Additional Requirement

Required Tasks

Region	Task Index	Task Frequency	Task Requirements	Qualification of Inspector	Records Required	PM	Weekly	Monthly	3 Monthly	6 Monthly	12 Monthly	24 Monthly	Additional
All		In accordance with manufacturer's recommendations and instructions.	Routine maintenance and remedial actions as required.	Competent person, best practice to outsource	Maintenance logbook	PM					EVID		
All		Based on risk assessment, but at least every 12 months.	Full inspection of UPS systems to ensure correct operation and integrity, including visual checks, review of electrical connections, functionality, environmental conditions, etc. If defects are identified, remedial actions should be addressed as soon as possible.	Competent person, best practice to outsource	Inspection records, report or certificate. Risk assessment	PM					EVID		

Related Regional Legislation

Region	Relevant legislation	Vendor Certification	Statutory requirement
CZ	Decree 73/2010 Coll., ČSN 331500, ČSN 333320 ed.2, ČSN 332570, ČSN 332000, ČSN EN 62305, ČSN 331600.ed.2, Decree 50/1978	Competent electrician Review technician	Frequency determined by the Protocol on the list of external influences, between 6and 60months.
DE	Betriebssicherheitsverordnung (BetrSichV) Technische Regeln für Betriebssicherheit: TRBS 1201 - Prüfungen und Kontrollen von Arbeitsmitteln und überwachungsbedürftigen Anlagen DGUV Vorschrift 3 (§5) - Unfallverhütungsvorschrift Elektrische Anlagen und Betriebsmittel DIN VDE 0105-100 - Betrieb von elektrischen Anlagen	Qualified electrician (Elektrofachkraft)	Every 4 years for stationary facilities which do not fall under group 700. Group 700 facilities require yearly inspections and include: ·Rooms with a bathtub or shower ·Rooms with swimming pools or other basins ·Rooms with sauna heaters ·Building sites ·Electrical installations in agriculture or horticulture ·Conductive areas with limited freedom of movement ·Campsites and similar areas

ES	RD 842/2002, of August 2, which approves the electrotechnical regulation for low voltage & its 52 complementary Technical Instructions. ITC-BT-36. Very low voltage devices. ITC-BT-40. Low voltage generator facilities. RD 1215/97 Working equipment	Accredited company (OCA) by ENAC.	Low voltage Inspections and testing at least every 5 years Inspections in accordance with manufacturer's instructions.
FR	N/A	N/A	Not stipulated by regulations
IT	Directive 2004/108/EC Directive 2006/95/EC CEI EN IEC 62040-1 (Safety requirements) CEI EN 50171 (General requirements) CEI 11-20 (UPS installation) CEI EN 60896-11 (Open-type batteries) CEI EN 60896-21 (Valve-regulated batteries)	Competent person.	Inspections in accordance with manufacturer's instructions. Best practice: every 6 months for Systems > 20 kVA and every 12 months for systems </= 20 kVA.
PL	Act of 7 July 1994 - Construction Law (Journal of Laws 1994 No. 89 pos. 414), as amended Act of April 10, 1997 - Energy Law (Journal of Laws of 1997, No. 54, item 348) Regulation of the Minister of Economy, Labor and Social Policy of 28 April 2003 on the detailed rules for confirming qualifications by persons involved in the operation of devices, installations and networks (Journal of Laws of 2003, No. 89, item 828) Regulation of the Minister of Energy of August 28, 2019 on health and safety at work with energy devices (Journal of Laws 2019, item 1830)	Qualified or competent person, authorised by Construction Law and Energy Law	Inspections in accordance with manufacturer's instructions. Measurements insulation resistance / impedance measurement every 5 years.
ROI	Safety, Health and Welfare at Work Act 2005 Safety, Health and Welfare at Work (General Application) Regulations 2007 to 2012. c 30-31	Competent person, best practice to outsource to specialist.	Routine maintenance. Inspection/service frequency not stipulated in regulations, in accordance with manufacturer's recommendations.
SK	Ordinance No. 508/2009 Coll. on details for ensuring safety and health protection at work with pressure, lifting, electrical and gas technical equipment Government Regulation No. 391/2006 on the minimum safety and health requirements for the workplace Government Regulation No. 392/2006 Coll. on the minimum safety and health requirements for the use of work equipment	Competent person, best practice to outsource to specialist.	Routine maintenance. Inspection/service frequency not stipulated in regulations, in accordance with manufacturer's recommendations.
UK	Provision and Use of Work Equipment Regulations 1998 (PUWER) Reg. 5 Health and Safety at Work Act 1974	Competent person, best practice to outsource to specialist.	Routine maintenance. Inspection/service frequency not stipulated in regulations, but it is best practice to inspect UPS systems every 12 months.