Title	**Modbus Parameter List**
Subject	**Modbus Register Definition**
Project	**NBEGESAM**
PID	**226012**

Abstract: Definition of Modbus Objects

Keywords: Modbus, Slave

Related Product(s)	RVS21 / RVS61
Document Storage	ProjectShare
Document Category	ProjectRecord
Document Number	SD226012-SS-01001
Revision	1.6.1
Revision Date	27-Juli-2017
Document Status	Final - valid without Approval
Company	Siemens Schweiz AG, Building Technologies Division
OrgUnit	Control Products and Systems
Classification	Unrestricted
Based on Template	Standard;16;2011-09-30;dh3531

Revision History

Rev	Date	Author	Remarks, Changes
1.6.1	27. Jul 2017	Armin Reichlin	Status=Final - valid without Approval identical to V1.6, without OV-Version Modbus "V1.x"
1.6	23. Mai 2017	Armin Reichlin	Status=Final - valid without Approval Complete parameterlist for RVS21/61 V8.6
1.5	02-Jun-2015	Gallus Fritsche	Status=Final - valid without Approval Complete parameterlist (according user manual) implemented
1.4	17-Sep-2014	Roland Von Büren	Status=Final - valid without Approval Some new objects defined
1.3	20-Mrz-2014	Philipp Constantin	Status=Final - valid without Approval New Modbus objects defined
1.2	20-Mrz-2014	Philipp Constantin	Status=Working
1.2	20-Aug-2013	Philipp Constantin	Status=Final - valid without Approval
1.1	20-Apr-2013	Philipp Constantin	Status=Review Switch-on command heat pump added
1.0	05-Apr-2013	Philipp Constantin	Status=Review First external version

General Modbus consideration

In terms of data formats, the Modbus interface is very open, and access is only partly restricted. The available/writable value range of the registers can be greater than the range functionally used.
For this reason, please note that it is not permitted to write non-specified values in the registers, since this can lead to undefined states or malfunctions of the control system.
We recommend – especially in connection with user interfaces – to take apporopriate measures on your application which prevents the setting and writing of non-specified values.

OV-Version Modbus	MdB Register (see sheet "ProtocolIDescription" Address [dec]	R/W	Parameter Number	Group	Parameter	Enumeration/ Description	Lower Limit	Upper Limit	Unit	Resolution
	0x0400...0x07FF	BL		Heating circuit 1						
1.0	**1024**	R/W	700		Operating Mode	0: Protection x 1: Automatic 2: Reduced 3: Comfort	0	3		1
1.0	**1025**	R/W	710		Comfort setpoint		4	35	°C	1/64
1.0	**1026**	R/W	712		Reduced setpoint		4	35	°C	1/64
1.0	**1027**	R/W	714		Frost protection setpoint		4	35	°C	1/64
1.0	**1028**	R/W	720		Heating curve slope		0.1	4		1/50
1.0	**1029**	R/W	721		Heating curve displacement		-4.5	4.5	°C	1/64
1.0	**1030**	R/W	730		Summer/winter heating limit		8	30	°C	1/64
1.0	**1031**	R/W	730		Status/Comand	**See sheet "Status_Command"** Status: (Read) Bit0:ObjectUnused Bit1:SensorShortCircuit Bit6:DeviceFailure Comand: (Write) 0: Release 1: Write 5: SetOutOfService 6: ResetOutOfService				
1.0	**1032**	R/W	732		24-hour heating limit		-10	10	°C	1/64
1.0	**1033**	R/W	732		Status/Comand	see description				
1.0	**1034**	R/W	740		Flow temp setpoint min		8	95	°C	1/64
1.0	**1035**	R/W	741		Flow temp setpoint max		8	95	°C	1/64
1.0	**1036**	R/W	742		Flow temp setpoint room stat		8	95	°C	1/64
1.0	**1037**	R/W	742		Status/Comand	see description				
1.0	**1038**	R/W	750		Room influence		1	100	%	1
1.0	**1039**	R/W	750		Status/Comand	see description				
1.0	**1040**	R	8739		Relative room humidity 1		0	100	%	1
1.0	**1041**	R	8739		Status	Status: (Read) Bit0:ObjectUnused Bit1:SensorShortCircuit Bit6:DeviceFailure				
1.0	**1042**	R	8740		Room temperature 1		0	50	°C	1/64
1.0	**1043**	R	8740		Status	see description				
1.0	**1044**	R	8741		Room setpoint 1		4	35	°C	1/64
1.0	**1045**	R	8741		Status	see description				
1.0	**1046**	R	8743		Flow temperature 1		0	140	°C	1/64
1.0	**1047**	R	8743		Status	see description				
1.0	**1048**	R	8744		Flow temperature setpoint 1		0	140	°C	1/64
1.0	**1049**	R	8744		Status	see description				
1.0	**1050**	R	8749		Room thermostat 1	x 0: No demand 1: Demand	0	1		1
1.0	**1051**	R	8749		Status	see description				
1.0	**1052**	R/W	6740		Flow temp 1 alarm		10	240	min	1
1.0	**1053**	R/W	6740		Status/Comand	see description				
1.0	**1054**	R	8000		State heating circuit 1	see description: status codes	0	1000		1
1.3	**1055**	R/W	5710		Heating circuit 1	0: Off 1: On	0	1		1
1.5	**1056**	R/W	701		Warmer / Cooler	0: Cooler x 1: ... 2: Warmer	0	2		1
1.5	**1057**	R			Warmer / Cooler Lower Limit	x 0: Cooler 1: ... 2: Warmer	0	2		1
1.5	**1058**	R			Warmer / Cooler Upper Limit	x 0: Cooler 1: ... 2: Warmer	0	2		1
1.5	**1059**	R/W	716		Comfort setpoint max heating circuit 1		4	35	°C	1/64
1.5	**1060**	R/W	726		Heating curve adaptation heat circuit 1	x 0: Off 1: On	0	1		1
1.5	**1061**	R/W	733		Ext'n 24-hour heating limit HC1	0: No x 1: Yes	0	1		1
1.5	**1062**	R/W	744		Swi on ratio room thermosta HC1		1	99	%	1
1.5	**1063**	R/W	744		Status/Comand	see description				
1.5	**1064**	R/W	760		Room temperature limitation heating circuit 1		0	4	°C	1/64
1.5	**1065**	R/W	760		Status/Comand	see description				
1.5	**1066**	R/W	770		Room temp setpoint boost HC1 (boost heating)		0	20	°C	1/64
1.5	**1067**	R/W	770		Status/Comand	see description				
1.5	**1068**	R/W	780		Quick setback heat circuit 1	0: Off x 1: Up to reduced setpoint 2: Up to protection setpoint	0	2		1
1.5	**1069**	R/W	790		Optimum start control max forward shift HC1		00:00	06:00	h:m	1/60
1.5	**1070**	R/W	791		Optimum stop control max forward shift HC1		00:00	06:00	h:m	1/60
1.5	**1071**	R/W	794		Heat up gradient		0	600	min/K	1
1.5	**1072**	R/W	800		Start reduced room temp setpoint increase HC1		-30	10	°C	1/64
1.5	**1073**	R/W	800		Status/Comand	see description				
1.5	**1074**	R/W	801		End reduced room temp setpoint increase HC1		-30	10	°C	1/64
1.5	**1075**	R/W	810		Frost protection for heating circuit pump HC1	0: Off x 1: On	0	1		1
1.5	**1076**	R/W	820		Pump heating circuit overtemp protection HC1	0: Off x 1: On	0	1		1
1.5	**1077**	R/W	830		Mixing valve setpoint boost heating circuit 1		0	50	°C	1/64
1.5	**1078**	R/W	832		Actuator control mode heat circuit 1	0: Two-position x 1: Three-position	0	1		1

1.5	**1079**	R/W	833		Actuator switching differential heat circuit 1		0	20	°C	1/64
1.5	**1080**	R/W	834		Actuator running time heat circuit 1		30	650	s	1
1.5	**1081**	R/W	835		P-band (Xp) heat circuit 1		1	100	°C	1/64
1.5	**1082**	R/W	836		Integral action time (Tn) heat circuit 1		10	650	s	1
1.5	**1083**	R/W	850		Flooring plaster dry up function HC1	x 0: Off 1: Functional heating 2: 'Belegreif' heating 3: Functional + 'Belegreif' heating 4: Belegreif' + functional heating 5: Manuell	0	5		1
1.5	**1084**	R/W	851		Floor setpoint manually HC1		0	95	°C	1/64
1.5	**1085**	R	855		Flow temp setpoint flooring plaster dry up HC1		0	95	°C	1/64
1.5	**1086**	R	855		Status					
1.5	**1087**	R	856		Flooring plaster dry up day HC1		0	32		1
1.5	**1088**	R	857		Floor curing HC1 days fulfilled		0	32		1
1.5	**1089**	R/W	861		Overtemperature drop heating circuit 1	0: Off 1: Heating mode x 2: Always	0	2		1
1.5	**1090**	R/W	870		Heating circuit 1 with buffer	0: No x 1: Yes	0	1		1
1.5	**1091**	R/W	872		Heating circuit 1 with precontr/primary pump	0: No x 1: Yes	0	1		1
1.5	**1092**	R/W	882		Pump speed min heating circuit 1		0	100	%	1
1.5	**1093**	R/W	883		Pump speed max heating circuit 1		0	100	%	1
1.5	**1094**	R/W	900		Operating mode changeover heating circuit 1	0: None x 1: Protection 2: Reduced 3: Comfort 4: Automatic	0	4		1
1.5	**1095**	R	8730		Status heat circuit pump 1	x 0: Off 1: On	0	1		1
1.5	**1096**	R	8730		Status					
1.5	**1097**	R	8731		Status heat circuit mixing valve 1 opens	x 0: Off 1: On	0	1		1
1.5	**1098**	R	8731		Status					
1.5	**1099**	R	8732		Status heat circuit mixing valve 1 closes	x 0: Off 1: On	0	1		1
1.5	**1100**	R	8732		Status					
1.5	**1101**	R	8735		Heat circuit pump speed HC1		0	100	%	1
1.5	**1102**	R	8735		Status					
1.5	**1103**	R/W	8742		Room temperature model 1		0	50	°C	1/64
1.5	**1104**	R	8742		Status		0	50	°C	1/64
1.5	**1105**	R			State 2nd speed heating circuit pump (Q21)	x 0: Off 1: On	0	1		
1.5	**1106**	R			Status					
1.5	**1107**	R			Operating mode changeover zone 1	x 0: Inactive 1: Active	0	1		
1.5	**1108**	R	8739		Relative room humidity 1		0	100	%	1/100
1.5	**1109**	R	8739		Status	Status: (Read) Bit0:ObjectUnused Bit1:SensorShortCircuit Bit6:DeviceFailure				
1.5	**1110**	W			Operating level override 1	x 0: No override 1: Override to reduced level 2: Override to nominal level	0	2		1
1.5	**1111**	R/W	813		Frost protection room model 1	0: Off x 1: On	0	1		1
1.5	**1112**	R/W	862		Max room temp ex heat draw		4	35	°C	1/64
1.5	**1113**	R/W	862		Status/Comand	see description				
1.6	**1114**	R/W	761		Heating limit room control HC1		0	100	%	1
1.6	**1115**	R/W	761		Status/Comand	see description				
1.6	**1116**	R/W	762		Prop band Xp room contr		0.5	32	°C	1/64
1.6	**1117**	R/W	763		Int act time Tn room contr		10	24000	s	1
1.6	**1118**	R/W	764		Der act time Tv room contr		10	2400	s	1
1.6	**1119**	R/W	766		SD room tempertaure limitation		0	100	%	1
1.6	**1120**	R/W	863		Minimum flow function	0: Off x 1: On	0	1		1
1.6	**1121**	R/W	880		Pump speed reduction heating circuit 1	0: According HC operating level x 1: According characteristic curve	0	1		1
1.6	**1122**	R/W	881		Starting speed HC1		0	100	%	1
1.6	**1123**	R/W	881		Status/Comand	see description				
1.6	**1124**	R/W	885		Pump speed min OEM heating circuit 1		0	100	%	1
1.6	**1125**	R/W	886		Pump speed max OEM HC1		0	100	%	1
1.6	**1126**	R/W	888		Curve readj at 50% speed HC1		0	100	%	1
1.6	**1127**	R/W	890		Flow setp readj speed ctrl HC1	0: No x 1: Yes	0	1		1
	0x0800...0x0BFF	BL		Cooling circuit 1						
1.0	**2048**	R/W	901		Operating mode	0: Off x 1: Automatic	0	3		1
1.0	**2049**	R/W	902		Comfort setpoint		15	40	°C	1/64
1.6	**2050**	R/W	907		Release cooling circuit 1	x 1: Time program heating circuit 2: Time program cooling circuit	1	2		1
1.0	**2051**	R/W	908		Flow temp setp at OT 25°C		6	35	°C	1/64
1.0	**2052**	R/W	909		Flow temp setp at OT 35°C		6	35	°C	1/64
1.0	**2053**	R/W	912		Cooling limit at OT		8	35	°C	1/64
1.0	**2054**	R/W	912		Status/Comand	see description				
1.0	**2055**	R/W	913		Lock time at end of heating		8	100	h	1
1.0	**2056**	R/W	913		Status/Comand	see description				
1.0	**2057**	R/W	918		Summer comp start at OT		20	50	°C	1/64
1.0	**2058**	R/W	919		Summer comp end at OT		20	50	°C	1/64
1.0	**2059**	R/W	920		Summer comp setp increase		1	10	°C	1/64
1.0	**2060**	R/W	920		Status/Comand	see description				
1.0	**2061**	R/W	923		Flow temp setp min OT 25°C		6	35	°C	1/64
1.0	**2062**	R/W	924		Flow temp setp min OT 35°C		6	35	°C	1/64
1.0	**2063**	R/W	928		Room influence		1	100	%	1
1.0	**2064**	R/W	928		Status/Comand	see description				

1.0	**2065**	R	8747		Dewpoint temp 1		0	50	°C	1/64
1.0	**2066**	R	8747		Status/Comand	see description				
1.0	**2067**	R	8756		Flow temp cooling 1		0	140	°C	1/64
1.0	**2068**	R	8756		Status	see description				
1.0	**2069**	R	8757		Flow temp setp cooling 1		0	140	°C	1/64
1.0	**2070**	R	8757		Status	see description				
1.0	**2071**	R/W	6746		Flow temp cooling 1 alarm		10	240	min	1
1.0	**2072**	R/W	6746		Status/Comand	see description				
1.0	**2073**	R	8004		State cooling circuit 1	see description: status codes	0	1000		1
1.5	**2074**	R/W	903		Room temp Reduced setpoint cooling circuit 1		5	40	°C	1/64
1.5	**2075**	R/W	904		Room temp protective setpoint cooling circuit 1		5	40	°C	1/64
1.5	**2076**	R/W	905		Comfort setpoint min cooling circuit 1		5	40	°C	1/64
1.5	**2077**	R/W	914		24-hour cooling limit CC1		-10	10	°C	1/64
1.5	**2078**	R/W	914		Status/Comand	see description				
1.5	**2079**	R/W	915		Ext'n 24-hour cooling limit CC1	0: No x 1: Yes	0	1		1
1.5	**2080**	R/W	932		Room temp limitation cooling circuit 1		0	4	°C	1/64
1.5	**2081**	R/W	932		Status/Comand	see description				
1.5	**2082**	R/W	935		Quick increase cooling circuit 1	0: Off x 1: Up to reduced setpoint 2: Up to protection setpoint	0	2		1
1.5	**2083**	R/W	937		Frost prot plant for cooling circuit pump 1	x 0: Off 1: On	0	1		1
1.5	**2084**	R/W	938		Mixing valve decrease cooling circuit 1		0	20	°C	1/64
1.5	**2085**	R/W	939		Actuator control mode cooling circuit 1	0: Two-position x 1: Three-position	0	1		1
1.5	**2086**	R/W	940		Actuator switching diff cooling circuit 1		0	20	°C	1/64
1.5	**2087**	R/W	941		Running time actuator cooling circuit 1		30	650	s	1
1.5	**2088**	R/W	942		P-band (Xp) cooling circuit 1		1	100	°C	1/64
1.5	**2089**	R/W	943		Integral action time (Tn) cooling circuit 1		10	650	s	1
1.5	**2090**	R/W	945		Mixing valve cooling circuit 1 in heating mode	1: Wert 687; 0 x 2: Open	1	2		1
1.5	**2091**	R/W	946		Locking time dew point limit CC1		10	600	min	1
1.5	**2092**	R/W	946		Status/Comand	see description				
1.5	**2093**	R/W	947		Flow boost hygrostat cooling circuit 1		1	20	°C	1/64
1.5	**2094**	R/W	947		Status/Comand	see description				
1.5	**2095**	R/W	948		Flow setp incr start at rel Humidity CC1		0	100	%	1
1.5	**2096**	R/W	950		Flow temp diff dewpoint		0	5	°C	1/64
1.5	**2097**	R/W	950		Status/Comand	see description				
1.5	**2098**	R/W	962		Cooling circuit 1 with buffer	0: No x 1: Yes	0	1		1
1.5	**2099**	R/W	963		Cooling circuit 1 with precontr/primary pump	0: No x 1: Yes	0	1		1
1.5	**2100**	R/W	969		Operating mode changeover cooling circuit 1	0: None x 1: Protection 2: Reduced 3: Comfort 4: Automatic	0	4		1
1.5	**2101**	R/W	5711		Cooling circuit 1	x 0: Off 1: 4-pipe system cooling 2: 2-pipe system cooling	0	2		1
1.5	**2102**	R/W	5712		Mixing valve 1 application	1: None 2: Cooling x 3: Heating and cooling	1	3		1
1.5	**2103**	R	8751		State cooling circuit pump 1	x 0: Off 1: On	0	1		1
1.5	**2104**	R	8751		Status	see description				
1.5	**2105**	R	8752		State cooling circuit mixing valve 1 opening	x 0: Off 1: On	0	1		1
1.5	**2106**	R	8752		Status	see description				
1.5	**2107**	R	8753		State cooling circuit mixing valve 1 closing	x 0: Off 1: On	0	1		1
1.5	**2108**	R	8753		Status	see description				
1.5	**2109**	R	8754		State diverting valve cooling	x 0: Off 1: On	0	1		1
1.5	**2110**	R	8754		Status	see description				
1.5	**2111**	R	9010		Room temp measurement 1		0	50	°C	1/64
1.5	**2112**	R	9010		Status	see description				
1.6	**2113**	R/W	929		Prop band Xp room contr		0.5	32	°C	1/64
1.6	**2114**	R/W	930		Int act time Tn room contr		10	24000	s	1
1.6	**2115**	R/W	931		Der act time Tv room contr		10	2400	s	1
	0x0C00…0x0FFF	BL		Ventilation 1						
1.5	**3072**	R/W	970		Operating mode	0: Off x 1: Automatic 2: stage 1 3: stage 2 4: stage 3	0	4		1
1.5	**3073**	R/W	974		Air quality Comfort		0	2000	ppm	1
1.5	**3074**	R/W	975		Air quality Reduced		0	2000	ppm	1
1.5	**3075**	R/W	977		Boost ventilation	x 0: … 1: Boost ventilation	0	1		1
1.5	**3076**	R/W	978		Duration boost ventilation		0	240	min	1
1.5	**3077**	R/W	979		Stage boost ventilation	0: Off 1: stage 1 2: stage 2 x 3: stage 3	0	3		1
1.5	**3078**	R/W	981		Forward shift night cooling		0	1440	min	1
1.5	**3079**	R/W	983		Stage night cooling	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**3080**	R/W	985		Room humidity limit		1	99	%	1
1.5	**3081**	R/W	985		Status/Comand	see description				

1.5	**3082**	R/W	987		Stage room humidity limit	x 0: Off 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**3083**	R/W	989		Stage Comfort	0: Off 1: stage 1 x 2: stage 2 3: stage 3	0	3		1
1.5	**3084**	R/W	991		Stage Reduced	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**3085**	R/W	992		Stage Protection	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**3086**	R/W	995		Operating mode changeover	0: None x 1: Off 2: stage 1 3: stage 2 4: stage 3	0	4		1
1.5	**3087**	R/W	996		Duration ventilation switch		0	240	min	1
1.5	**3088**	R/W	997		Stage ventilation switch	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**3089**	R/W			P-band (Xp) indoor air quality		0	2000	ppm	1
1.5	**3090**	R/W			Min duration night cooling		0	720	min	1
1.5	**3091**	R/W			Outside temp limit night cooling		0	50	°C	1/64
1.5	**3092**	R/W			Min temp diff room/outside for night cooling		0	20	°C	1/64
1.5	**3093**	R/W			Room humidity limitation, switching differential		0	20	%	1
1.5	**3094**	R/W			Room humidity limitation, on time		0	720	min	1
1.5	**3095**	R/W			Room humidity limitation, off time		0	720	min	1
1.5	**3096**	R/W			Holiday mode, switch-on time ventilation		00:00	23:50	hh:mm	1/60
1.5	**3097**	R/W			Holiday mode, on time ventilation		0	360	min	1
1.5	**3098**	R/W	9901		Operating mode	0: Protection x 1: Automatic 2: Reduced 3: Comfort	0	3		1
1.5	**3099**	R/W	9902		Comfort setpoint		5	40	°C	1/64
1.5	**3100**	R/W	9903		Reduced setpoint		5	40	°C	1/64
1.5	**3101**	R/W			Start of summer compensation at outside temp		20	35	°C	1/64
1.5	**3102**	R/W			End of summer compensation at outside temp		20	35	°C	1/64
1.5	**3103**	R/W			Summer compensation, setpoint increase		1	10	°C	1/64
1.5	**3104**	R/W			Status/Comand	see description				
1.5	**3105**	R/W			Release	1: Wert 682; 0 x 2: Time program heating circuit 3: Time program 5 4: Time program ventilation	1	4		
1.5	**3106**	R	8935		Indoor air quality 1		0	2000	ppm	1
1.5	**3107**	R	8935		Status	see description				
1.5	**3108**	R	8937		Ventilation stage 1	x 0: Off 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**3109**	R	8932		Outside air temperature		-50	50	°C	1/64
1.5	**3110**	R	8932		Status	see description				
1.5	**3111**	R	8027		State ventilation 1		0	1000		1
1.5	**3112**	R			State of outside air temp control (Q17)	x 0: Off 1: On	0	1		1
1.5	**3113**	R			Status	see description				
1.5	**3114**	R			State of ventilation fan 1 (K51)	x 0: Off 1: On	0	1		1
1.5	**3115**	R			Status	see description				
1.5	**3116**	R			State of ventilation bypass 1 (K54)	x 0: Off 1: On	0	1		1
1.5	**3117**	R			Status	see description				
1.5	**3118**	R			Room temp setpoint air cooling 1		4	35	°C	1/64
1.5	**3119**	R			Status	see description				
1.5	**3120**	R/W	7084		Maintenance interval ventilation 1		100	10000	h	1
1.5	**3121**	R/W	7084		Status/Comand	see description				
1.5	**3122**	R/W	7085		Time since maintenance ventilation 1		0	10000	h	1
	0x1000...0x13FF	BL		Heating circuit 2						
1.0	**4096**	R/W	1000		Op.mode	0: Protection x 1: Automatic 2: Reduced 3: Comfort	0	3		1
1.0	**4097**	R/W	1010		Comfort setpoint		4	35	°C	1/64
1.0	**4098**	R/W	1012		Reduced setpoint		4	35	°C	1/64
1.0	**4099**	R/W	1014		Frost protection setpoint		4	35	°C	1/64
1.0	**4100**	R/W	1020		Heating curve slope		0.1	4		1/50
1.0	**4101**	R/W	1021		Heating curve displacement		-4.5	4.5	°C	1/64
1.0	**4102**	R/W	1030		Summer/winter heating limit		8	30	°C	1/64
1.0	**4103**	R/W	1030		Status/Comand	see description				
1.0	**4104**	R/W	1032		24-hour heating limit		-10	10	°C	1/64
1.0	**4105**	R/W	1032		Status/Comand	see description				
1.0	**4106**	R/W	1040		Flow temp setpoint min		8	95	°C	1/64
1.0	**4107**	R/W	1041		Flow temp setpoint max		8	95	°C	1/64
1.0	**4108**	R/W	1042		Flow temp setpoint room stat		8	95	°C	1/64
1.0	**4109**	R/W	1042		Status/Comand	see description				
1.0	**4110**	R/W	1050		Room influence		1	100	%	1
1.0	**4111**	R/W	1050		Status/Comand	see description				
1.0	**4112**	R	8769		Relative room humidity 2		0	100	%	1
1.0	**4113**	R	8769		Status	see description				
1.0	**4114**	R	8770		Room temp 2		0	50	°C	1/64
1.0	**4115**	R	8770		Status	see description				

1.0	**4116**	R	8771		Room setpoint 2		4	35	°C	1/64
1.0	**4117**	R	8771		Status	see description				
1.0	**4118**	R	8773		Flow temp 2		0	140	°C	1/64
1.0	**4119**	R	8773		Status	see description				
1.0	**4120**	R	8774		Flow temp setpoint 2		0	140	°C	1/64
1.0	**4121**	R	8774		Status	see description				
1.0	**4122**	R	8779		Room thermostat 2	x 0: No demand 1: Demand	0	1		1
1.0	**4123**	R	8779		Status	see description				
1.0	**4124**	R/W	6741		Flow temp 2 alarm		10	240	min	1
1.0	**4125**	R/W	6741		Status/Comand	see description				
1.0	**4126**	R	8001		State heating circuit 2	see description: status codes	0	1000		1
1.3	**4127**	R/W	5715		Heating circuit 2	0: Off 1: On	0	1		1
1.5	**4128**	R/W	1001		Warmer / Cooler	0: Cooler x 1: ... 2: Warmer	0	2		1
1.5	**4129**	R			Warmer / Cooler Lower Limit	x 0: Cooler 1: ... 2: Warmer	0	2		1
1.5	**4130**	R			Warmer / Cooler Upper Limit	x 0: Cooler 1: ... 2: Warmer	0	2		1
1.5	**4131**	R/W	1016		Comfort setpoint max HC2		4	35	°C	1/64
1.5	**4132**	R/W	1026		Heating curve adaptation heat circuit 2	x 0: Off 1: On	0	1		1
1.5	**4133**	R/W	1033		Ext'n 24-hour heating limit HC2	0: No x 1: Yes	0	1		1
1.5	**4134**	R/W	1044		Swi on ratio room thermosta HC2		1	99	%	1
1.5	**4135**	R/W	1044		Status/Comand	see description				
1.5	**4136**	R/W	1060		Room temperature limitation heating circuit 2		0	4	°C	1/64
1.5	**4137**	R/W	1060		Status/Comand	see description				
1.5	**4138**	R/W	1070		Room temp setpoint boost HC2 (boost heating)		0	20	°C	1/64
1.5	**4139**	R/W	1070		Status/Comand	see description				
1.5	**4140**	R/W	1080		Quick setback heat circuit 2	0: Off x 1: Up to reduced setpoint 2: Up to protection setpoint	0	2		1
1.5	**4141**	R/W	1090		Optimum start control max forward shift HC2		00:00	06:00	h:m	1/60
1.5	**4142**	R/W	1091		Optimum stop control max forward shift HC2		00:00	06:00	h:m	1/60
1.5	**4143**	R/W	1094		Heat up gradient		0	600	min/K	1
1.5	**4144**	R/W	1100		Start reduced room temp setpoint increase HC2		-30	10	°C	1/64
1.5	**4145**	R/W	1100		Status/Comand	see description				
1.5	**4146**	R/W	1101		End reduced room temp setpoint increase HC2		-30	10	°C	1/64
1.5	**4147**	R/W	1110		Frost protection for heating circuit pump HC2	0: Off x 1: On	0	1		1
1.5	**4148**	R/W	1120		Pump heating circuit overtemp protection HC2	0: Off x 1: On	0	1		1
1.5	**4149**	R/W	1130		Mixing valve setpoint boost heating circuit 2		0	50	°C	1/64
1.5	**4150**	R/W	1132		Actuator control mode heat circuit 2	0: Two-position x 1: Three-position	0	1		1
1.5	**4151**	R/W	1133		Actuator switching differential heat circuit 2		0	20	°C	1/64
1.5	**4152**	R/W	1134		Actuator running time heat circuit 2		30	650	s	1
1.5	**4153**	R/W	1135		P-band (Xp) heat circuit 2		1	100	°C	1/64
1.5	**4154**	R/W	1136		Integral action time (Tn) heat circuit 2		10	650	s	1
1.5	**4155**	R/W	1150		Flooring plaster dry up function HC1	x 0: Off 1: Functional heating 2: 'Belegreif' heating 3: Functional + 'Belegreif' heating 4: Belegreif' + functional heating 5: Manuell	0	5		1
1.5	**4156**	R/W	1151		Floor setpoint manually HC2		0	95	°C	1/64
1.5	**4157**	R	1155		Flow temp setpoint flooring plaster dry up HC2		0	95	°C	1/64
1.5	**4158**	R	1155		Status					
1.5	**4159**	R	1156		Flooring plaster dry up day HC2		0	32		1
1.5	**4160**	R	1157		Floor curing HC2 days fulfilled		0	32		1
1.5	**4161**	R/W	1161		Overtemperature drop heating circuit 2	0: Off 1: Heating mode x 2: Always	0	2		1
1.5	**4162**	R/W	1170		Heating circuit 2 with buffer	0: No x 1: Yes	0	1		1
1.5	**4163**	R/W	1172		Heating circuit 2 with precontr/primary pump	0: No x 1: Yes	0	1		1
1.5	**4164**	R/W	1182		Pump speed min heating circuit 2		0	100	%	1
1.5	**4165**	R/W	1183		Pump speed max heating circuit 2		0	100	%	1
1.5	**4166**	R/W	1200		Operating mode changeover heating circuit 2	0: None x 1: Protection 2: Reduced 3: Comfort 4: Automatic	0	4		1
1.5	**4167**	R	8760		State heating circuit pump 2	x 0: Off 1: On	0	1		1
1.5	**4168**	R	8760		Status					
1.5	**4169**	R	8761		State heating circuit mixing valve 2 opening	x 0: Off 1: On	0	1		1
1.5	**4170**	R	8761		Status					
1.5	**4171**	R	8762		State heating circuit mixing valve 2 closing	x 0: Off 1: On	0	1		1
1.5	**4172**	R	8761		Status					
1.5	**4173**	R	8765		Heat circuit pump speed HC2		0	100	%	1
1.5	**4174**	R	8761		Status					
1.5	**4175**	R/W	8772		Room temperature model 2		0	50	°C	1/64
1.5	**4176**	R	8772		Status		0	50	°C	1/64
1.5	**4177**	R			State 2nd speed heating circuit pump (Q22)	x 0: Off 1: On	0	1		
1.5	**4178**	R			Status					

1.5	**4179**	R			Operating mode changeover zone 2	x 0: Inactive 1: Active	0	1		
1.5	**4180**	R	8769		Relative room humidity 2		0	100	%	1/100
1.5	**4181**	R	8769		Status	see description				
1.5	**4182**	R/W			Operating level override 2	x 0: No override 1: Override to reduced level 2: Override to nominal level	0	2		1
1.5	**4183**	R/W	1113		Frost protection room model 2	0: Off x 1: On	0	1		1
1.5	**4184**	R/W	1162		Max room temp ex heat draw		4	35	°C	1/64
1.5	**4185**	R/W	1162		Status/Comand	see description				
1.6	**4186**	R/W	1061		Heating limit room control HC2		0	100	%	1
1.6	**4187**	R/W	1061		Status/Comand	see description				
1.6	**4188**	R/W	1062		Prop band Xp room contr		0.5	32	°C	1/64
1.6	**4189**	R/W	1063		Int act time Tn room contr		10	24000	s	1
1.6	**4190**	R/W	1064		Der act time Tv room contr		10	2400	s	1
1.6	**4191**	R/W	1066		SD room tempertaure limitation		0	100	%	1
1.6	**4192**	R/W	1163		Minimum flow function	0: Off x 1: On	0	1		1
1.6	**4193**	R/W	1180		Pump speed reduction heating circuit 2	0: According HC operating level x 1: According characteristic curve	0	1		1
1.6	**4194**	R/W	1181		Starting speed HC2		0	100	%	1
1.6	**4195**	R/W	1181		Status/Comand	see description				
1.6	**4196**	R/W	1185		Pump speed min OEM heating circuit 2		0	100	%	1
1.6	**4197**	R/W	1186		Pump speed max OEM HC2		0	100	%	1
1.6	**4198**	R/W	1188		Curve readj at 50% speed HC2		0	100	%	1
1.6	**4199**	R/W	1190		Flow setp readj speed ctrl HC2	0: No x 1: Yes	0	1		1
	0x1400...0x17FF	BL		Cooling circuit 2						
1.0	**5120**	R/W	1201		Operating mode cooling circuit 2	0: Off x 1: Automatic	0	1		1
1.0	**5121**	R/W	1202		Room temp Comfort setpoint cooling circuit 2		15	40	°C	1/64
1.6	**5122**	R/W	1207		Release cooling circuit 2	x 1: Time program heating circuit 2: Time program cooling circuit	1	2		1
1.0	**5123**	R/W	1208		Flow setpoint at outside temp 25°C CC2		6	35	°C	1/64
1.0	**5124**	R/W	1209		Flow setpoint at outside temp 35°C CC2		6	35	°C	1/64
1.0	**5125**	R/W	1212		Cooling limit at outs temp cooling circuit 2		8	35	°C	1/64
1.0	**5126**	R/W	1212		Status/Comand	see description				
1.0	**5127**	R/W	1213		Remaining time after heating cooling circuit 2		8	100	h	1
1.0	**5128**	R/W	1213		Status/Comand	see description				
1.0	**5129**	R/W	1218		Summer comp start at OT		20	50	°C	1/64
1.0	**5130**	R/W	1219		Summer comp end at OT		20	50	°C	1/64
1.0	**5131**	R/W	1220		Summer comp setp increase		1	10	°C	1/64
1.0	**5132**	R/W	1220		Status/Comand	see description				
1.0	**5133**	R/W	1223		Flow setpoint min at outside temp 25°C CC2		6	35	°C	1/64
1.0	**5134**	R/W	1224		Flow setpoint min at outside temp 35°C CC2		6	35	°C	1/64
1.0	**5135**	R/W	1228		Room temperature gain factor cooling circuit 2		1	100	%	1
1.0	**5136**	R/W	1228		Status/Comand	see description				
1.0	**5137**	R	8777		Dewpoint temp 2		0	50	°C	1/64
1.0	**5138**	R	8777		Status/Comand	see description				
1.0	**5139**	R	8786		Flow temp cooling 2		0	140	°C	1/64
1.0	**5140**	R	8786		Status	see description				
1.0	**5141**	R	8787		Flow temp setp cooling 2		0	140	°C	1/64
1.0	**5142**	R	8787		Status	see description				
1.0	**5143**	R/W	6747		Flow temp cooling 2 alarm		10	240	min	1
1.0	**5144**	R/W	6747		Status/Comand	see description				
1.0	**5145**	R	8025		State cooling circuit 2	see description: status codes	0	1000		1
1.5	**5146**	R/W	1203		Room temp Reduced setpoint cooling circuit 2		5	40	°C	1/64
1.5	**5147**	R/W	1204		Room temp protective setpoint cooling circuit 2		5	40	°C	1/64
1.5	**5148**	R/W	1205		Comfort setpoint min cooling circuit 2		5	40	°C	1/64
1.5	**5149**	R/W	1214		24-hour cooling limit CC2		-10	10	°C	1/64
1.5	**5150**	R/W	1214		Status/Comand	see description				
1.5	**5151**	R/W	1215		Ext'n 24-hour cooling limit CC2	0: No x 1: Yes	0	1		1
1.5	**5152**	R/W	1232		Room temp limitation cooling circuit 2		0	4	°C	1/64
1.5	**5153**	R/W	1232		Status/Comand	see description				
1.5	**5154**	R/W	1235		Quick increase cooling circuit 2	0: Off x 1: Up to reduced setpoint 2: Up to protection setpoint	0	2		1
1.5	**5155**	R/W	1237		Frost prot plant for cooling circuit pump 2	x 0: Off 1: On	0	1		1
1.5	**5156**	R/W	1238		Mixing valve decrease cooling circuit 2		0	20	°C	1/64
1.5	**5157**	R/W	1239		Actuator control mode cooling circuit 2	0: Two-position x 1: Three-position	0	1		1
1.5	**5158**	R/W	1240		Actuator switching diff cooling circuit 2		0	20	°C	1/64
1.5	**5159**	R/W	1241		Running time actuator cooling circuit 2		30	650	s	1
1.5	**5160**	R/W	1242		P-band (Xp) cooling circuit 2		1	100	°C	1/64
1.5	**5161**	R/W	1243		Integral action time (Tn) cooling circuit 2		10	650	s	1
1.5	**5162**	R/W	1245		Mixing valve cooling circuit 2 in heating mode	1: Wert 687; 0 x 2: Open	1	2		1
1.5	**5163**	R/W	1246		Locking time dew point limit CC2		10	600	min	1
1.5	**5164**	R/W	1246		Status/Comand	see description				
1.5	**5165**	R/W	1247		Flow boost hygrostat cooling circuit 2		1	20	°C	1/64
1.5	**5166**	R/W	1247		Status/Comand	see description				
1.5	**5167**	R/W	1248		Flow setp incr start at rel Humidity CC2		0	100	%	1
1.5	**5168**	R/W	1250		Flow temp diff dewpoint CC2		0	5	°C	1/64
1.5	**5169**	R/W	1250		Status/Comand	see description				
1.5	**5170**	R/W	1262		Cooling circuit 2 with buffer	0: No x 1: Yes	0	1		1
1.5	**5171**	R/W	1263		Cooling circuit 2 with precontr/primary pump	0: No x 1: Yes	0	1		1
1.5	**5172**	R/W	1269		Operating mode changeover cooling circuit 2	0: None x 1: Protection 2: Reduced 3: Comfort 4: Automatic	0	4		1

1.5	**5173**	R/W	5716		Cooling circuit 2	x 0: Off 1: 4-pipe system cooling 2: 2-pipe system cooling	0	2		1
1.5	**5174**	R/W	5717		Mixing valve 2 application	1: None 2: Cooling x 3: Heating and cooling	1	3		1
1.5	**5175**	R	8781		State cooling circuit pump 2	x 0: Off 1: On	0	1		1
1.5	**5176**	R	8781		Status	see description				
1.5	**5177**	R	8782		State cooling circuit mixing valve 2 opening	x 0: Off 1: On	0	1		1
1.5	**5178**	R	8782		Status	see description				
1.5	**5179**	R	8783		State cooling circuit mixing valve 2 closing	x 0: Off 1: On	0	1		1
1.5	**5180**	R	8783		Status	see description				
1.5	**5181**	R	8784		State diverting valve cooling 2	x 0: Off 1: On	0	1		1
1.5	**5182**	R	8784		Status	see description				
1.5	**5183**	R	9011		Room temp measurement 2		0	50	°C	1/64
1.5	**5184**	R	9011		Status	see description				
1.6	**5185**	R/W	1229		Prop band Xp room contr		0.5	32	°C	1/64
1.6	**5186**	R/W	1230		Int act time Tn room contr		10	24000	s	1
1.6	**5187**	R/W	1231		Der act time Tv room contr		10	2400	s	1
	0x1800...0x1BFF	BL		Ventilation 2						
1.5	**6144**	R/W	1270		Operating mode	0: Off x 1: Automatic 2: stage 1 3: stage 2 4: stage 3	0	4		1
1.5	**6145**	R/W	1274		Air quality Comfort		0	2000	ppm	1
1.5	**6146**	R/W	1275		Air quality Reduced		0	2000	ppm	1
1.5	**6147**	R/W	1277		Boost ventilation	x 0: ... 1: Boost ventilation	0	1		1
1.5	**6148**	R/W	1278		Duration boost ventilation		0	240	min	1
1.5	**6149**	R/W	1279		Stage boost ventilation	0: Off 1: stage 1 2: stage 2 x 3: stage 3	0	3		1
1.5	**6150**	R/W	1281		Forward shift night cooling		0	1440	min	1
1.5	**6151**	R/W	1283		Stage night cooling	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**6152**	R/W	1285		Room humidity limit		1	99	%	1
1.5	**6153**	R/W	1285		Status/Comand	see description				
1.5	**6154**	R/W	1287		Stage room humidity limit	x 0: Off 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**6155**	R/W	1289		Stage Comfort	0: Off 1: stage 1 x 2: stage 2 3: stage 3	0	3		1
1.5	**6156**	R/W	1291		Stage Reduced	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**6157**	R/W	1292		Stage Protection	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**6158**	R/W	1295		Operating mode changeover	0: None x 1: Off 2: stage 1 3: stage 2 4: stage 3	0	4		1
1.5	**6159**	R/W	1296		Duration ventilation switch		0	240	min	1
1.5	**6160**	R/W	1297		Stage ventilation switch	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**6161**	R/W			P-band (Xp) indoor air quality		0	2000	ppm	1
1.5	**6162**	R/W			Min duration night cooling		0	720	min	1
1.5	**6163**	R/W			Outside temp limit night cooling		0	50	°C	1/64
1.5	**6164**	R/W			Min temp diff room/outside for night cooling		0	20	°C	1/64
1.5	**6165**	R/W			Room humidity limitation, switching differential		0	20	%	1
1.5	**6166**	R/W			Room humidity limitation, on time		0	720	min	1
1.5	**6167**	R/W			Room humidity limitation, off time		0	720	min	1
1.5	**6168**	R/W			Holiday mode, switch-on time ventilation		00:00	23:50	hh:mm	1/60
1.5	**6169**	R/W			Holiday mode, on time ventilation		0	360	min	1
1.5	**6170**	R/W	9904		Operating mode	0: Protection x 1: Automatic 2: Reduced 3: Comfort	0	3		1
1.5	**6171**	R/W	9905		Comfort setpoint		5	40	°C	1/64
1.5	**6172**	R/W	9906		Reduced setpoint		5	40	°C	1/64
1.5	**6173**	R/W			Start of summer compensation at outside temp		20	35	°C	1/64
1.5	**6174**	R/W			End of summer compensation at outside temp		20	35	°C	1/64
1.5	**6175**	R/W			Summer compensation, setpoint increase		1	10	°C	1/64
1.5	**6176**	R/W			Status/Comand	see description				
1.5	**6177**	R/W			Release	1: Wert 682; 0 x 2: Time program heating circuit 3: Time program 5 4: Time program ventilation	1	4		
1.5	**6178**	R	8940		Indoor air quality 2		0	2000	ppm	1
1.5	**6179**	R	8940		Status	see description				

1.5	**6180**	R	8942		Ventilation stage 2	x 0: Off 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**6181**	R	8028		State ventilation 2		0	1000		1
1.5	**6182**	R			State of ventilation fan 2 (K52)	x 0: Off 1: On	0	1		1
1.5	**6183**	R			Status	see description				
1.5	**6184**	R			State of ventilation bypass 2 (K55)	x 0: Off 1: On	0	1		1
1.5	**6185**	R			Status	see description				
1.5	**6186**	R			Room temp setpoint air cooling 2		4	35	°C	1/64
1.5	**6187**	R			Status	see description				
1.5	**6188**	R/W	7086		Maintenance interval ventilation 2		100	10000	h	1
1.5	**6189**	R/W	7086		Status/Comand	see description				
1.5	**6190**	R/W	7087		Time since maintenance ventilation 2		0	10000	h	1
	0x1C00...0x1FFF	BL		Heating circuit 3						
1.0	**7168**	R/W	1300		Operating mode	0: Protection x 1: Automatic 2: Reduced 3: Comfort	0	3		1
1.0	**7169**	R/W	1310		Comfort setpoint		4	35	°C	1/64
1.0	**7170**	R/W	1312		Reduced setpoint		4	35	°C	1/64
1.0	**7171**	R/W	1314		Frost protection setpoint		4	35	°C	1/64
1.0	**7172**	R/W	1320		Heating curve slope		0.1	4		1/50
1.0	**7173**	R/W	1321		Heating curve displacement		-4.5	4.5	°C	1/64
1.0	**7174**	R/W	1330		Summer/winter heating limit		8	30	°C	1/64
1.0	**7175**	R/W	1330		Status/Comand	see description				
1.0	**7176**	R/W	1332		24-hour heating limit		-10	10	°C	1/64
1.0	**7177**	R/W	1332		Status/Comand	see description				
1.0	**7178**	R/W	1340		Flow temp setpoint min		8	95	°C	1/64
1.0	**7179**	R/W	1341		Flow temp setpoint max		8	95	°C	1/64
1.0	**7180**	R/W	1342		Flow temp setpoint room stat		8	95	°C	1/64
1.0	**7181**	R/W	1342		Status/Comand	see description				
1.0	**7182**	R/W	1350		Room influence		1	100	%	1
1.0	**7183**	R/W	1350		Status/Comand	see description				
1.0	**7184**	R	8799		Relative room humidity 3		0	100	%	1
1.0	**7185**	R	8799		Status	see description				
1.0	**7186**	R	8800		Room temp 3		0	50	°C	1/64
1.0	**7187**	R	8800		Status	see description				
1.0	**7188**	R	8801		Room setpoint 3		4	35	°C	1/64
1.0	**7189**	R	8801		Status	see description				
1.0	**7190**	R	8803		Flow temp setpoint 3		0	140	°C	1/64
1.0	**7191**	R	8803		Status	see description				
1.0	**7192**	R	8804		Flow temp 3		0	140	°C	1/64
1.0	**7193**	R	8804		Status	see description				
1.0	**7194**	R	8809		Room thermostat 3	x 0: No demand 1: Demand	0	1		1
1.0	**7195**	R	8809		Status	see description				
1.0	**7196**	R/W	6742		Flow temp 3 alarm		10	240	min	1
1.0	**7197**	R/W	6742		Status/Comand	see description				
1.0	**7198**	R	8002		State heating circuit 3	see description: status codes	0	1000		1
1.3	**7199**	R/W	5721		Heating circuit 3	0: Off 1: On	0	1		1
1.5	**7200**	R/W	1301		Warmer / Cooler	0: Cooler x 1: ... 2: Warmer	0	2		1
1.5	**7201**	R			Warmer / Cooler Lower Limit	x 0: Cooler 1: ... 2: Warmer	0	2		1
1.5	**7202**	R			Warmer / Cooler Upper Limit	x 0: Cooler 1: ... 2: Warmer	0	2		1
1.5	**7203**	R/W	1316		Comfort setpoint max HC3/P		4	35	°C	1/64
1.5	**7204**	R/W	1326		Heating curve adaption HC3/P	x 0: Off 1: On	0	1		1
1.5	**7205**	R/W	1333		Ext'n 24-hour heating limit HC3	0: No x 1: Yes	0	1		1
1.5	**7206**	R/W	1344		Swi on ratio room thermosta HC3/P		1	99	%	1
1.5	**7207**	R/W	1344		Status/Comand	see description				
1.5	**7208**	R/W	1360		Room temperature limitation HC3/P		0	4	°C	1/64
1.5	**7209**	R/W	1360		Status/Comand	see description				
1.5	**7210**	R/W	1370		Room setpoint boost HC3/P (boost heating)		0	20	°C	1/64
1.5	**7211**	R/W	1370		Status/Comand	see description				
1.5	**7212**	R/W	1380		Quick setback HC3/P	0: Off x 1: Up to reduced setpoint 2: Up to protection setpoint	0	2		1
1.5	**7213**	R/W	1390		Optimum start control max forward shift HC3/P		00:00	06:00	h:m	1/60
1.5	**7214**	R/W	1391		Optimum stop control max forward shift HC3/P		00:00	06:00	h:m	1/60
1.5	**7215**	R/W	1394		Heat up gradient		0	600	min/K	1
1.5	**7216**	R/W	1400		Start reduced room temp setpoint increase HC3/P		-30	10	°C	1/64
1.5	**7217**	R/W	1400		Status/Comand	see description				
1.5	**7218**	R/W	1401		End reduced room temp setpoint increase HC3/P		-30	10	°C	1/64
1.5	**7219**	R/W	1410		Frost protection for heating circuit pump HC3/P	0: Off x 1: On	0	1		1
1.5	**7220**	R/W	1420		Pump heating circuit overtemp protection HC3/P	0: Off x 1: On	0	1		1
1.5	**7221**	R/W	1430		Mixing valve setpoint boost heating circuit 3/P		0	50	°C	1/64
1.5	**7222**	R/W	1432		Actuator control mode heat circuit 3/P	0: Two-position x 1: Three-position	0	1		1
1.5	**7223**	R/W	1433		Actuator switching differential heat circuit 3/P		0	20	°C	1/64
1.5	**7224**	R/W	1434		Actuator running time heat circuit 3/P		30	650	s	1
1.5	**7225**	R/W	1435		P-band (Xp) heat circuit 3/P		1	100	°C	1/64
1.5	**7226**	R/W	1436		Integral action time (Tn) heat circuit 3/P		10	650	s	1

1.5	**7227**	R/W	1450		Floor curing function HC3/P	x 0: Off 1: Functional heating 2: 'Belegreif' heating 3: Functional + 'Belegreif' heating 4: Belegreif' + functional heating 5: Manuell	0	5		1
1.5	**7228**	R/W	1451		Floor setpoint manually HC3/P		0	95	°C	1/64
1.5	**7229**	R	1455		Flow temperature setpoint floor curing HC3/P		0	95	°C	1/64
1.5	**7230**	R	855		Status					
1.5	**7231**	R	1456		Floor curing day HC3/P		0	32		1
1.5	**7232**	R	1457		Floor curing HC3/P days fulfilled		0	32		1
1.5	**7233**	R/W	1461		Overtemperature drop heating circuit 3/P	0: Off 1: Heating mode x 2: Always	0	2		1
1.5	**7234**	R/W	1470		Heating circuit 3/P with buffer	0: No x 1: Yes	0	1		1
1.5	**7235**	R/W	1472		Heating circuit 3/P with precontr/primary pump	0: No x 1: Yes	0	1		1
1.5	**7236**	R/W	1482		Pump speed min heating circuit 3/P		0	100	%	1
1.5	**7237**	R/W	1483		Pump speed max heating circuit 3/P		0	100	%	1
1.5	**7238**	R/W	1500		Operating mode changeover HC3/P	0: None x 1: Protection 2: Reduced 3: Comfort 4: Automatic	0	4		1
1.5	**7239**	R	8790		State heating circuit pump 3	x 0: Off 1: On	0	1		1
1.5	**7240**	R	855		Status					
1.5	**7241**	R	8791		State heating circuit mixing valve 3 opening	x 0: Off 1: On	0	1		1
1.5	**7242**	R	855		Status					
1.5	**7243**	R	8792		State heating circuit mixing valve 3 closing	x 0: Off 1: On	0	1		1
1.5	**7244**	R	855		Status					
1.5	**7245**	R	8795		Heat circuit pump speed HC3		0	100	%	1
1.5	**7246**	R	855		Status					
1.5	**7247**	R/W	8802		Room temperature model 3		0	50	°C	1/64
1.5	**7248**	R	8802		Status		0	50	°C	1/64
1.5	**7249**	R			Stat 2nd speed heating circuit pump (Q23)	x 0: Off 1: On	0	1		1
1.5	**7250**	R			Status					
1.5	**7251**	R			Operating mode changeover zone 3	x 0: Inactive 1: Active	0	1		1
1.5	**7252**	R	8799		Relative room humidity 3		0	100	%	1/100
1.5	**7253**	R	8799		Status	see description				
1.5	**7254**	R/W			Operating level override 3	x 0: No override 1: Override to reduced level 2: Override to nominal level	0	2		1
1.5	**7255**	R/W	1413		Frost protection room model 3	0: Off x 1: On	0	1		1
1.5	**7256**	R/W	1462		Max room temp ex heat draw		4	35	°C	1/64
1.5	**7257**	R/W	1462		Status/Comand	see description				
1.6	**7258**	R/W	1361		Heating limit room control HC3/P		0	100	%	1
1.6	**7259**	R/W	1361		Status/Comand	see description				
1.6	**7260**	R/W	1362		Prop band Xp room contr		0.5	32	°C	1/64
1.6	**7261**	R/W	1363		Int act time Tn room contr		10	24000	s	1
1.6	**7262**	R/W	1364		Der act time Tv room contr		10	2400	s	1
1.6	**7263**	R/W	1366		SD room tempertaure limitation		0	100	%	1
1.6	**7264**	R/W	1463		Minimum flow function	0: Off x 1: On	0	1		1
1.6	**7265**	R/W	1480		Pump speed reduction heating circuit 3/P	0: According HC operating level x 1: According characteristic curve	0	1		1
1.6	**7266**	R/W	1481		Starting speed HC3		0	100	%	1
1.6	**7267**	R/W	1481		Status/Comand	see description				
1.6	**7268**	R/W	1485		Pump speed min OEM heating circuit 3		0	100	%	1
1.6	**7269**	R/W	1486		Pump speed max OEM HC3		0	100	%	1
1.6	**7270**	R/W	1488		Curve readj at 50% speed HC3		0	100	%	1
1.6	**7271**	R/W	1490		Flow setp readj speed ctrl HC3	0: No x 1: Yes	0	1		1
	0x2000...0x23FF	BL		Cooling circuit 3						
1.0	**8192**	R/W	1501		Operating mode cooling circuit 3	0: Off x 1: Automatic	0	1		1
1.0	**8193**	R/W	1502		Room temp Comfort setpoint cooling circuit 3		17	40	°C	1/64
1.6	**8194**	R/W	1507		Release cooling circuit 3	x 1: Time program heating circuit 2: Time program cooling circuit	1	2		1
1.0	**8195**	R/W	1508		Flow setpoint at outside temp 35°C CC3		6	35	°C	1/64
1.0	**8196**	R/W	1509		Flow setpoint at outside temp 35°C CC3		6	35	°C	1/64
1.0	**8197**	R/W	1512		Cooling limit at outs temp cooling circuit 3		8	35	°C	1/64
1.0	**8198**	R/W	1512		Status/Comand	see description				
1.0	**8199**	R/W	1513		Remaining time after heating cooling circuit 3		8	100	h	1
1.0	**8200**	R/W	1513		Status/Comand	see description				
1.0	**8201**	R/W	1518		Summer comp start at OT		20	50	°C	1/64
1.0	**8202**	R/W	1519		Summer comp end at OT		20	50	°C	1/64
1.0	**8203**	R/W	1520		Summer comp setp increase		1	10	°C	1/64
1.0	**8204**	R/W	1520		Status/Comand	see description				
1.0	**8205**	R/W	1523		Flow setpoint min at outside temp 35°C CC3		6	35	°C	1/64
1.0	**8206**	R/W	1524		Flow setpoint min at outside temp 35°C CC3		6	35	°C	1/64
1.0	**8207**	R/W	1528		Room temperature gain factor cooling circuit 3		1	100	%	1
1.0	**8208**	R/W	1528		Status/Comand	see description				
1.0	**8209**	R	8807		Dewpoint temp 3		0	50	°C	1/64
1.0	**8210**	R	8807		Status/Comand	see description				
1.0	**8211**	R	8816		Flow temp cooling 3		0	140	°C	1/64
1.0	**8212**	R	8816		Status	see description				
1.0	**8213**	R	8817		Flow temp setp cooling 3		0	140	°C	1/64
1.0	**8214**	R	8817		Status	see description				
1.0	**8215**	R/W	6748		Flow temp cooling 3 alarm		10	240	min	1

1.0	**8216**	R/W	6748		Status/Comand	see description				
1.0	**8217**	R	8026		State cooling circuit 3	see description: status codes	0	1000		1
1.5	**8218**	R/W	1503		Room temp Reduced setpoint cooling circuit 3		5	40	°C	1/64
1.5	**8219**	R/W	1504		Room temp protective setpoint cooling circuit 3		5	40	°C	1/64
1.5	**8220**	R/W	1505		Comfort setpoint min cooling circuit 3		5	40	°C	1/64
1.5	**8221**	R/W	1514		24-hour cooling limit CC3		-10	10	°C	1/64
1.5	**8222**	R/W	1514		Status/Comand	see description				
1.5	**8223**	R/W	1515		Ext'n 24-hour cooling limit CC3	0: No x 1: Yes	0	1		1
1.5	**8224**	R/W	1532		Room temp limitation cooling circuit 3		0	4	°C	1/64
1.5	**8225**	R/W	1532		Status/Comand	see description				
1.5	**8226**	R/W	1535		Quick increase cooling circuit 3	0: Off x 1: Up to reduced setpoint 2: Up to protection setpoint	0	2		1
1.5	**8227**	R/W	1537		Frost prot plant for cooling circuit pump 3	x 0: Off 1: On	0	1		1
1.5	**8228**	R/W	1538		Mixing valve decrease cooling circuit 3		0	20	°C	1/64
1.5	**8229**	R/W	1539		Actuator control mode cooling circuit 3	0: Two-position x 1: Three-position	0	1		1
1.5	**8230**	R/W	1540		Actuator switching diff cooling circuit 3		0	20	°C	1/64
1.5	**8231**	R/W	1541		Running time actuator cooling circuit 3		30	650	s	1
1.5	**8232**	R/W	1542		P-band (Xp) cooling circuit 3		1	100	°C	1/64
1.5	**8233**	R/W	1543		Integral action time (Tn) cooling circuit 3		10	650	s	1
1.5	**8234**	R/W	1545		Mixing valve cooling circuit 3 in heating mode	1: Wert 687; 0 x 2: Open	1	2		1
1.5	**8235**	R/W	1546		Locking time dew point limit CC3		10	600	min	1
1.5	**8236**	R/W	1546		Status/Comand	see description				
1.5	**8237**	R/W	1547		Flow boost hygrostat cooling circuit 3		1	20	°C	1/64
1.5	**8238**	R/W	1547		Status/Comand	see description				
1.5	**8239**	R/W	1548		Flow setp incr start at rel Humidity CC3		0	100	%	1
1.5	**8240**	R/W	1550		Flow temp diff dewpoint CC3		0	5	°C	1/64
1.5	**8241**	R/W	1550		Status/Comand	see description				
1.5	**8242**	R/W	1562		Cooling circuit 3 with buffer	0: No x 1: Yes	0	1		1
1.5	**8243**	R/W	1563		Cooling circuit 3 with precontr/primary pump	0: No x 1: Yes	0	1		1
1.5	**8244**	R/W	1569		Operating mode changeover cooling circuit 3	0: None x 1: Protection 2: Reduced 3: Comfort 4: Automatic	0	4		1
1.5	**8245**	R/W	5722		Cooling circuit 3	x 0: Off 1: 4-pipe system cooling 2: 2-pipe system cooling	0	2		1
1.5	**8246**	R/W	5723		Mixing valve 3 application	1: None 2: Cooling x 3: Heating and cooling	1	3		1
1.5	**8247**	R	8811		State cooling circuit pump 3	x 0: Off 1: On	0	1		1
1.5	**8248**	R	8811		Status	see description				
1.5	**8249**	R	8812		State cooling circuit mixing valve 3 opening	x 0: Off 1: On	0	1		1
1.5	**8250**	R	8812		Status	see description				
1.5	**8251**	R	8813		State cooling circuit mixing valve 3 closing	x 0: Off 1: On	0	1		1
1.5	**8252**	R	8813		Status	see description				
1.5	**8253**	R	8814		State diverting valve cooling 3	x 0: Off 1: On	0	1		1
1.5	**8254**	R	8814		Status	see description				
1.5	**8255**	R	9012		Room temp measurement 3		0	50	°C	1/64
1.5	**8256**	R	9012		Status	see description				
1.6	**8257**	R/W	1529		Prop band Xp room contr		0.5	32	°C	1/64
1.6	**8258**	R/W	1530		Int act time Tn room contr		10	24000	s	1
1.6	**8259**	R/W	1531		Der act time Tv room contr		10	2400	s	1
	0x2400…0x27FF	BL		Ventilation 3						
1.5	**9216**	R/W	1570		Operating mode	0: Off x 1: Automatic 2: stage 1 3: stage 2 4: stage 3	0	4		1
1.5	**9217**	R/W	1574		Air quality Comfort		0	2000	ppm	1
1.5	**9218**	R/W	1575		Air quality Reduced		0	2000	ppm	1
1.5	**9219**	R/W	1577		Boost ventilation	x 0: … 1: Boost ventilation	0	1		1
1.5	**9220**	R/W	1578		Duration boost ventilation		0	240	min	1
1.5	**9221**	R/W	1579		Stage boost ventilation	0: Off 1: stage 1 2: stage 2 x 3: stage 3	0	3		1
1.5	**9222**	R/W	1581		Forward shift night cooling		0	1440	min	1
1.5	**9223**	R/W	1583		Stage night cooling	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**9224**	R/W	1585		Room humidity limit		1	99	%	1
1.5	**9225**	R/W	1585		Status/Comand	see description				
1.5	**9226**	R/W	1587		Stage room humidity limit	x 0: Off 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**9227**	R/W	1589		Stage Comfort	0: Off 1: stage 1 x 2: stage 2 3: stage 3	0	3		1

1.5	**9228**	R/W	1591		Stage Reduced	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**9229**	R/W	1592		Stage Protection	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**9230**	R/W	1595		Operating mode changeover	0: None x 1: Off 2: stage 1 3: stage 2 4: stage 3	0	4		1
1.5	**9231**	R/W	1596		Duration ventilation switch		0	240	min	1
1.5	**9232**	R/W	1597		Stage ventilation switch	0: Off x 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**9233**	R/W			P-band (Xp) indoor air quality		0	2000	ppm	1
1.5	**9234**	R/W			Min duration night cooling		0	720	min	1
1.5	**9235**	R/W			Outside temp limit night cooling		0	50	°C	1/64
1.5	**9236**	R/W			Min temp diff room/outside for night cooling		0	20	°C	1/64
1.5	**9237**	R/W			Room humidity limitation, switching differential		0	20	%	1
1.5	**9238**	R/W			Room humidity limitation, on time		0	720	min	1
1.5	**9239**	R/W			Room humidity limitation, off time		0	720	min	1
1.5	**9240**	R/W			Holiday mode, switch-on time ventilation		00:00	23:50	hh:mm	1/60
1.5	**9241**	R/W			Holiday mode, on time ventilation		0	360	min	1
1.5	**9242**	R/W	9907		Operating mode	0: Protection x 1: Automatic 2: Reduced 3: Comfort	0	3		1
1.5	**9243**	R/W	9908		Comfort setpoint		5	40	°C	1/64
1.5	**9244**	R/W	9909		Reduced setpoint		5	40	°C	1/64
1.5	**9245**	R/W			Start of summer compensation at outside temp		20	35	°C	1/64
1.5	**9246**	R/W			End of summer compensation at outside temp		20	35	°C	1/64
1.5	**9247**	R/W			Summer compensation, setpoint increase		1	10	°C	1/64
1.5	**9248**	R/W			Status/Comand	see description				
1.5	**9249**	R/W			Release	1: Wert 682; 0 x 2: Time program heating circuit 3: Time program 5 4: Time program ventilation	1	4		1
1.5	**9250**	R	8945		Indoor air quality 3		0	2000	ppm	1
1.5	**9251**	R	8945		Status	see description				
1.5	**9252**	R	8947		Ventilation stage 3	x 0: Off 1: stage 1 2: stage 2 3: stage 3	0	3		1
1.5	**9253**	R	8029		State ventilation 3		0	1000		1
1.5	**9254**	R			State of ventilation fan 3 (K53)	x 0: Off 1: On	0	1		1
1.5	**9255**	R			Status	see description				
1.5	**9256**	R			State of ventilation bypass 3 (K56)	x 0: Off 1: On	0	1		1
1.5	**9257**	R			Status	see description				
1.5	**9258**	R			Room temp setpoint air cooling 3		4	35	°C	1/64
1.5	**9259**	R			Status	see description				
1.5	**9260**	R/W	7088		Maintenance interval ventilation 3		100	10000	h	1
1.5	**9261**	R/W	7088		Status/Comand	see description				
1.5	**9262**	R/W	7089		Time since maintenance ventilation 3		0	10000	h	1
	0x2800...0x2BFF	BL		Domestic hot water						
1.0	**10240**	R/W	1600		DHW Operating mode	0: Off x 1:On 2: Eco	0	2		1
1.0	**10241**	R/W	1610		Nominal setpoint		8	80	°C	1/64
1.0	**10242**	R/W	1612		Reduced setpoint		8	80	°C	1/64
1.0	**10243**	R/W	1620		Release	0: 24h/day 1: Time programs HCs x 2: Time program 4/DHW 3: Low-tariff 4: T'prog 4/DHW or low-tariff	0	4		1
1.0	**10244**	R/W	1640		Legionella function	x 0: Off 1: Periodically 2: Fixed weekday	0	2		1
1.0	**10245**	R/W	1641		Legionella funct periodically		1	7		1
1.0	**10246**	R/W	1642		Legionella funct weekday	x 1: Monday 2: Tuesday 3: Wednesday 4: Thursday 5: Friday 6: Saturday 7: Sunday	1	7		1
1.0	**10247**	R/W	1644		Legionella funct time		00:00	23:50	h:m	10min
1.0	**10248**	R/W	1644		Status/Comand	see description				
1.0	**10249**	R/W	1645		Legionella funct setpoint		55	95	°C	1/64
1.0	**10250**	R/W	1646		Legionella funct duration		2	360	min	1
1.0	**10251**	R/W	1646		Status/Comand	see description				
1.0	**10252**	R/W	6745		DHW charging alarm		1	48	h	1
1.0	**10253**	R/W	6745		Status/Comand	see description				
1.0	**10254**	R	8003		State DHW	see description: status codes	0	1000		1
1.5	**10255**	R/W	1601		Optg mode selection Eco	x 0: None 1: --- 2: DHW storage tank	0	2		1
1.5	**10256**	R/W	1614		DHW temperature nominal setpoint max		0	80	°C	1/64

1.5	**10257**	R/W	1630		DHW charging priority	x 0: Absolute 1: Shifting 2: None (parallel) 3: Shifting, absolute	0	3		1
1.5	**10258**	R/W	1647		Circul. pump operation during legionella func	0: Off x 1: On	0	1		1
1.5	**10259**	R/W	1648		Legio funct circ temp diff		0	20	°C	1/64
1.5	**10260**	R/W	1648		Status/Comand	see description				
1.5	**10261**	R/W	1660		DHW circulating pump release	x 1: Wert 1117; 0 2: DHW release 3: Time switch program 4 4: Time switch program 5	1	4		1
1.5	**10262**	R/W	1661		DHW circulating pump cycling	0: Off x 1: On	0	1		1
1.5	**10263**	R/W	1663		DHW circulating setpoint		8	80	°C	1/64
1.5	**10264**	R/W	1680		Operating mode changeover DHW	0: None x 1: Off 2: On 3: Eco	0	3		1
1.5	**10265**	R/W	5731		DHW actuating device Q3	0: No charging request x 1: Charging pump 2: Diverting valve	0	2		1
1.5	**10266**	R/W	5734		Basic pos DHW div valve	0: Last request x 1: Heating circuit 2: DHW	0	2		1
1.5	**10267**	R/W	5736		Dhw dedicated	x 0: Off 1: On	0	1		1
1.5	**10268**	R/W	5740		Output el imm heater K6		0.1	99	kW	1/10
1.5	**10269**	R/W	5742		Restart lock pump Q34	x 0: Off 1: On	0	1		1
1.5	**10270**	R/W	5743		Cooling with DHW	x 0: Off 1: On	0	1		1
1.6	**10271**	R/W	1631		DHW temperature request selection	x 1: Max limitation 2: Maximum selection	1	2		1
1.6	**10272**	R/W	5728		DHW storage tank	0: Off x 1: On	0	1		1
	0x2C00...0x2FFF	BL		DHW storage tank						
1.0	**11264**	R	8830		DHW temp 1		0	140	°C	1/64
1.0	**11265**	R	8830		Status	see description				
1.0	**11266**	R	8832		DHW temp 2		0	140	°C	1/64
1.0	**11267**	R	8832		Status	see description				
1.0	**11268**	R/W	8840		Hours run DHW pump		0	199'999	h	1/3600
1.0	11269					(32 Bit Data)				
1.0	**11270**	R/W	8841		Start counter DHW pump		0	199999		1
1.0	11271					(32 Bit Data)				
1.0	**11272**	R/W	8842		Hours run el DHW		0	199'999	h	1/3600
1.0	11273					(32 Bit Data)				
1.0	**11274**	R/W	8843		Start counter el DHW		0	199999		1
1.0	11275					(32 Bit Data)				
1.0	**11276**	R/W	7091		DHW stor tank since maint		0	240	Months	1
1.0	**11277**	R/W	7092		DHW charg temp HP min		8	80	°C	1/64
1.0	**11278**	R/W	7092		Status/Comand	see description				
1.0	**11279**	R/W	7093		Curr DHW charg temp HP		8	80	°C	1/64
1.3	**11280**	R/W	5030		DHW charging time limitation		10	600	min	1
1.3	**11281**	R/W	5030		Status/Comand	see description				
1.3	**11282**	R/W	5060		DHW electric immersion heater operating mode	x 1: Backup mode 2: Summer only 3: Always 4: Cooling mode 5: Emergency operation 6: Legionella function	1	6		1
1.3	**11283**	R/W	5061		DHW electric immersion heater release	1: 24h/day x 2: DHW release 3: Time switch program 4	1	3		1
1.5	**11284**	R/W	5007		Charging request	x 1: Wert 998; 0 2: With sensor B3 3: With sensor B31	1	3		1
1.5	**11285**	R/W	5008		Charging request timed		1	240	min	1
1.5	**11286**	R/W	5008		Status/Comand	see description				
1.5	**11287**	R/W	5010		DHW charging	0: Once/day x 1: Several times/day	0	1		1
1.5	**11288**	R/W	5013		Charging opt energy	x 0: Off 1: Current setpoint 2: Nominal setpoint	0	2		1
1.5	**11289**	R/W	5016		Charging opt energy contact	x 0: Off 1: Nominal setpoint 2: Legionella funct setpoint	0	2		1
1.5	**11290**	R/W	5020		DHW flow setpoint boost		0	30	°C	1/64
1.5	**11291**	R/W	5021		Dhw transfer boost		0	30	°C	1/64
1.5	**11292**	R/W	5022		DHW recharging control	1: --- x 2: Full charging 3: Full charging legio 4: Full charg. first time of day 5: Full charg. first time, Legio	1	5		1
1.5	**11293**	R/W	5023		Setpoint reduction B31		0	20	°C	1/64
1.5	**11294**	R/W	5024		DHW switching differential		0	20	°C	1/64
1.5	**11295**	R/W	5032		Max temp DHW charging abort		8	80	°C	1/64
1.5	**11296**	R/W	5032		Status/Comand	see description				
1.5	**11297**	R/W	5040		DHW discharging protection	0: Off 1: Always x 2: Automatically	0	2		1
1.5	**11298**	R/W	5041		Discharging protect sensor	1: None x 2: With sensor B31	1	2		1
1.5	**11299**	R/W	5050		DHW charging temperatrure max		8	95	°C	1/64
1.5	**11300**	R/W	5051		DHW storage tank temperature max		8	95	°C	1/64
1.5	**11301**	R/W	5055		DHW storage tank return cooling temperature		8	95	°C	1/64

1.5	**11302**	R/W	5056		DHW storage tank return cooling Producer/HC	x 0: Off 1: On	0	1		1
1.5	**11303**	R/W	5057		DHW storage tank return cooling Collector	x 0: Off 1: Summer 2: Always	0	2		1
1.5	**11304**	R/W	5062		DHW electric immersion heater control	1: Wert 511; 0 x 2: DHW sensor	1	2		1
1.5	**11305**	R/W	5070		DHW automatic push	x 0: Off 1: On	0	1		1
1.5	**11306**	R/W	5071		charging priority time push		0	120	min	1
1.5	**11307**	R/W	5072		DHW push	x 0: ... 1: Recharging	0	1		1
1.5	**11308**	R/W	5085		DHW storage tank overtemperature drop	0: Off x 1: On	0	1		1
1.5	**11309**	R/W	5090		DHW storage tank with buffer	x 0: No 1: Yes	0	1		1
1.5	**11310**	R/W	5092		DHW storage tank with precontr/primary pump	x 0: No 1: Yes	0	1		1
1.5	**11311**	R/W	5093		DHW storage tank with solar	0: No x 1: Yes	0	1		1
1.5	**11312**	R/W	5101		Pump speed min DHW		0	100	%	1
1.5	**11313**	R/W	5102		Pump speed max DHW		0	100	%	1
1.5	**11314**	R/W	5103		Pump speed P-band XP DHW		1	100	°C	1/64
1.5	**11315**	R/W	5104		Pump speed Integral action time Tn DHW		1	650	s	1
1.5	**11316**	R/W	5105		Speed Tv		0	60	s	1/4
1.5	**11317**	R/W	5108		Starting speed charg pump		0	100	%	1
1.5	**11318**	R/W	5108		Status/Comand	see description				
1.5	**11319**	R/W	5109		St speed interm circ pump		0	100	%	1
1.5	**11320**	R/W	5109		Status/Comand	see description				
1.5	**11321**	R/W	5120		Mixing valve setpoint boost DHW precontr		0	50	°C	1/64
1.5	**11322**	R/W	5124		Actuator running time DHW precontr		30	650	s	1
1.5	**11323**	R/W	5125		P-band (Xp) DHW precontr		1	100	°C	1/64
1.5	**11324**	R/W	5126		Integral action time (Tn) DHW precontr		10	650	s	1
1.5	**11325**	R/W	5130		Transfer strategy	0: Off x 1: Always 2: DHW release	0	2		1
1.5	**11326**	R/W	5131		Comparative temperatur transfer	x 1: None 2: With sensor B31 3: With sensor B3 and B31	1	3		1
1.5	**11327**	R/W	5140		DHW charging circuit boost		0	10	°C	1/64
1.5	**11328**	R/W	5142		Delay flow set point contr		0	60	s	1
1.5	**11329**	R/W	5142		Status/Comand	see description				
1.5	**11330**	R/W	5143		Prop band flow setp. contr		1	100	°C	1/64
1.5	**11331**	R/W	5144		Int act time flow setp. contr		1	650	s	1
1.5	**11332**	R/W	5145		Der act time flow setp. contr		0	60	s	1
1.5	**11333**	R/W	5146		Full charge with B36	x 0: No 1: Yes	0	1		1
1.5	**11334**	R/W	5147		Minimum overrun Q33		0	250	s	1
1.5	**11335**	R/W	5148		Min start temp diff Q33		-20	20	°C	1/64
1.5	**11336**	R/W	5148		Status/Comand	see description				
1.5	**11337**	R/W	5156		Actuator running time, DHW intermediate circuit		30	650	s	1
1.5	**11338**	R/W	5157		P-band (Xp) DHW intermediate circuit		1	100	°C	1/64
1.5	**11339**	R/W	5158		Integral action time (Tn), DHW interm circuit		10	650	s	1
1.5	**11340**	R/W	5159		Use of intermediate circuit mixing valve	x 0: Always 1: Only high-temperature charging	0	1		1
1.5	**11341**	R/W	5160		Legionella funct mixing pump	0: Off 1: With charging x 2: With charging and duration	0	2		1
1.5	**11342**	R/W	5165		Restratification	x 0: Off 1: On	0	1		1
1.5	**11343**	R/W	5166		Restrat temp min		8	95	°C	1/64
1.5	**11344**	R/W	5167		Restrat temp diff min		0	40	°C	1/64
1.5	**11345**	R/W	5170		DHW High-temperature charging	x 0: Off 1: Own source in heating mode 2: Own source in heating/cooling mode 3: All sources in heating mode	0	3		1
1.5	**11346**	R/W	5171		DHW high-temperature charging setpoint		40	80	°C	1/64
1.5	**11347**	R/W	5171		Status/Comand	see description				
1.5	**11348**	R/W	5172		DHW high-temp min charging differential flow		0.5	20	°C	1/64
1.5	**11349**	R/W	5172		Status/Comand	see description				
1.5	**11350**	R/W	5173		DHW high-temp min charging differential hot-gas		0.5	20	°C	1/64
1.5	**11351**	R/W	5173		Status/Comand	see description				
1.5	**11352**	R/W	5177		DHW heat pump off time minimum		0	120	min	1
1.5	**11353**	R/W	5178		DHW heat pump source temperature minimum		0	20	°C	1/64
1.5	**11354**	R/W	5179		DHW heat pump source pump	x 0: None 1: Heat circuit pump HC1 Q2 2: Heat circuit pump HC2 Q6 3: Heat circuit pump HC3 Q20 4: Condenser pump Q9 5: Cooling circuit pump CC1 Q24 6: Cooling circuit pump CC2 Q28 7: Cooling circuit pump CC3 Q29	0	7		1
1.5	**11355**	R/W			DHW high-temp charging, duration start kick		0	120	s	
1.5	**11356**	R/W			Status/Comand	see description				
1.5	**11369**	R	8820		State DHW pump	x 0: Off 1: On	0	1		1
1.5	**11370**	R	8820		Status	see description				
1.5	**11371**	R	8821		State electric immersion heater DHW	x 0: Off 1: On	0	1		1
1.5	**11372**	R	8821		Status	see description				
1.5	**11373**	R	8825		DHW pump speed		0	100	%	1
1.5	**11374**	R	8825		Status	see description				
1.5	**11375**	R	8826		DHW intermediate circuit pump speed		0	100	%	1
1.5	**11376**	R	8826		Status	see description				
1.5	**11379**	R	8831		DHW temperature setpoint current		0	80	°C	1/64
1.5	**11380**	R	8831		Status	see description				

1.5	**11381**	R	8835		DHW circulating temperatur		0	140	°C	1/64
1.5	**11382**	R	8835		Status	see description				
1.5	**11383**	R	8836		DHW charging temperature		0	140	°C	1/64
1.5	**11384**	R	8836		Status	see description				
1.5	**11385**	R	8837		DHW charging setpoint		0	100	°C	1/64
1.5	**11386**	R	8837		Status	see description				
1.5	**11387**	R	8850		DHW precontroller temperatur actual value		0	140	°C	1/64
1.5	**11388**	R	8850		Status	see description				
1.5	**11389**	R	8851		DHW precontroller temperatur setpoint		0	140	°C	1/64
1.5	**11390**	R	8851		Status	see description				
1.5	**11395**	R			State DHW circulating pump (Q4)	x 0: Off 1: On	0	1		1
1.5	**11396**	R			Status	see description				
1.5	**11397**	R			State of DHW precontr mix valve Open (Y31)	x 0: Off 1: On	0	1		1
1.5	**11398**	R			Status	see description				
1.5	**11399**	R			State of DHW precontr mix valve Closed (Y32)	x 0: Off 1: On	0	1		1
1.5	**11400**	R			Status	see description				
1.5	**11407**	R			State storage transfer pump (Q11)	x 0: Off 1: On	0	1		1
1.5	**11408**	R			Status	see description				
1.5	**11409**	R			State DHW stirring pump (Q35)	x 0: Off 1: On	0	1		1
1.5	**11410**	R			Status	see description				
1.5	**11411**	R			DHW intermediate circuit pump (Q33)	x 0: Off 1: On	0	1		1
1.5	**11412**	R			Status	see description				
1.5	**11413**	R			State of DHW intermed circ mix valve Open (Y37)	x 0: Off 1: On	0	1		1
1.5	**11414**	R			Status	see description				
1.5	**11415**	R			State of DHW interme circ mix valve Closed (Y38)	x 0: Off 1: On	0	1		1
1.5	**11416**	R			Status	see description				
1.5	**11417**	R			State DHW Heatpump (K33)	x 0: Off 1: On	0	1		1
1.5	**11418**	R			Status	see description				
1.6	**11419**	R			Operating mode changeover DHW	x 0: Inactive 1: Active	0	1		1
1.5	**11420**	R/W	7090		DHW storage tank time maintenance interval		1	240	Month	1
1.5	**11421**	R/W	7090		Status/Comand	see description				
1.6	**11422**	R/W	5031		Heating time limitation		10	600	min	1
1.6	**11423**	R/W	5031		Status/Comand	see description				
1.6	**11424**	R/W	5033		Dynamic switching differential DHW	x 0: Off 1: On	0	1		1
1.6	**11425**	R/W	5066		DHW el immersion heater in legionella function	x 1: --- 2: Alone	1	2		1
1.6	**11426**	R/W	5169		Functions Q35 with Q33	x 0: No 1: Yes	0	1		1
1.6	**11427**	R/W			Heating output reduction per degree		0	10		1/100
1.6	**11428**	R/W	5018		DHW storage tank charging priority photovoltaics	0: None x 1: Priority 1 2: Priority 2 3: Priority 3	0	3		1
	0x3000...0x33FF	BL		Instantaneous water heater						
1.5	**12288**	R/W	5406		Min setp diff to tank temp		0	20	°C	1/64
1.5	**12289**	R/W	5406		Status/Comand	see description				
1.5	**12290**	R/W	5407		Storage tank setpoint incr		0	20	°C	1/64
1.5	**12291**	R/W	5530		Pump speed min instantaneous heater		0	100	%	1
1.5	**12292**	R/W	5531		Pump speed max instantaneous heater		0	100	%	1
1.5	**12293**	R/W	5532		Pump speed P-band XP instantaneous heater		1	100	°C	1/64
1.5	**12294**	R/W	5533		Pump speed Tn instantaneous heater		4	650	s	1
1.5	**12295**	R/W	5534		Pump speed Tv instantaneous heater		0	60	s	1/4
1.5	**12296**	R/W	5544		Actuator running time DHW instantaneous heater		7.5	480	s	1/2
1.5	**12297**	R/W	5545		P-band (Xp) DHW instantaneous heater		1	200	°C	1/64
1.5	**12298**	R/W	5546		Integral action time (Tn) DHW instan heater		4	650	s	1
1.5	**12299**	R/W	5547		Derivative action time (Tv) instantaneous heater		0	30	s	1/4
1.5	**12300**	R	8827		Speed instantaneous heater pump		0	100	%	1
1.5	**12301**	R	8827		Status	see description				
1.5	**12302**	R	8852		DHW consumption temp		0	140	°C	1/64
1.5	**12303**	R	8852		Status	see description				
1.5	**12304**	R	8853		DHW instantaneous heater setpoint		0	140	°C	1/64
1.5	**12305**	R	8853		Status	see description				
1.5	**12306**	R			Status instantaneous heater pump (Q34)	x 0: Off 1: On	0	1		1
1.5	**12307**	R			Status	see description				
1.5	**12308**	R			Status instantaneous heater opens (Y33)	x 0: Off 1: On	0	1		1
1.5	**12309**	R			Status	see description				
1.5	**12310**	R			Status instantaneous heater closes (Y34)	x 0: Off 1: On	0	1		1
1.5	**12311**	R			Status	see description				
1.5	**12312**	R			Flowswitch	x 0: Off 1: On	0	1		1
	0x3400...0x37FF	BL		Consumer circuit 1						
1.0	**13312**	R/W	1854		Request opt energy	x 0: Off 1: On	0	1		1
1.0	**13313**	R/W	1859		Flow temp setp cons request		8	120	°C	1/64
1.5	**13314**	R/W	1860		Frost prot plant consumer circuit 1 pump	0: Off x 1: On	0	1		1
1.5	**13315**	R/W	1874		DHW charging priority consumer circuit 1	0: No x 1: Yes	0	1		1
1.5	**13316**	R/W	1875		Overtemperature drop consumer circuit 1	0: Off x 1: On	0	1		1
1.5	**13317**	R/W	1878		Consumer circuit 1 with buffer	0: No x 1: Yes	0	1		1

1.5	**13318**	R/W	1880		Consumer circuit 1 with precontr/primary pump	0: No x 1: Yes	0	1		1
1.6	**13319**	R/W	5750		Consumer circuit 1	0: Off x 1: Heating 2: 4-pipe system cooling 3: 2-pipe system cooling	0	3		1
1.5	**13320**	R	8875		Flow temp setpoint VK1		0	130	°C	1/64
1.5	**13321**	R	8875		Status	see description				
1.5	**13322**	R			State CC1 pump (Q15)	x 0: Off 1: On	0	1		1
1.5	**13323**	R			Status	see description				
1.6	**13324**	R	8030		State consumer circuit 1	see description: status codes	0	1000		1
	0x3800...0x3BFF	BL		Consumer circuit 2						
1.0	**14336**	R/W	1904		Request opt energy	x 0: Off 1: On	0	1		1
1.0	**14337**	R/W	1909		Flow temp setp cons request		8	120	°C	1/64
1.5	**14338**	R/W	1910		Frost prot plant consumer circuit 2 pump	0: Off x 1: On	0	1		1
1.5	**14339**	R/W	1924		DHW charging priority consumer circuit 2	0: No x 1: Yes	0	1		1
1.5	**14340**	R/W	1925		Overtemperature drop consumer circuit 2	0: Off x 1: On	0	1		1
1.5	**14341**	R/W	1928		Consumer circuit 2 with buffer	0: No x 1: Yes	0	1		1
1.5	**14342**	R/W	1930		Consumer circuit 2 with precontr/primary pump	0: No x 1: Yes	0	1		1
1.6	**14343**	R/W	5751		Consumer circuit 2	0: Off x 1: Heating 2: 4-pipe system cooling 3: 2-pipe system cooling	0	3		1
1.5	**14344**	R	8885		Flow temp setpoint VK2		0	130	°C	1/64
1.5	**14345**	R	8885		Status	see description				
1.5	**14346**	R			State CC2 pump (Q18)	x 0: Off 1: On	0	1		1
1.5	**14347**	R			Status	see description				
1.6	**14348**	R	8031		State consumer circuit 2	see description: status codes	0	1000		1
	0x3C00...0x3FFF	BL		Swimming pool						
1.0	**15360**	R/W	1959		Flow temp setpoint		8	120	°C	1/64
1.0	**15361**	R/W	2055		Setpoint solar heating		8	80	°C	1/64
1.0	**15362**	R/W	2056		Setpoint source heating		8	35	°C	1/64
1.0	**15363**	R	8900		Swimming pool temp		0	140	°C	1/64
1.0	**15364**	R	8900		Status	see description				
1.0	**15365**	R	8901		Swimming pool setpoint		0	80	°C	1/64
1.0	**15366**	R	8901		Status	see description				
1.0	**15367**	R	8011		State swimming pool	see description: status codes	0	1000		1
1.5	**15368**	R/W	1952		Swimming pool release source heating	0: None x 1: 24h/day 2: Time program 5	0	2		1
1.5	**15369**	R/W	1954		Request opt energy swimming pool	x 0: Off 1: On	0	1		1
1.5	**15370**	R/W	1960		Frost prot plant swimming pool pump	0: Off x 1: On	0	1		1
1.5	**15371**	R/W	1973		Last priority to charge	x 0: No 1: Yes	0	1		1
1.5	**15372**	R/W	1974		DHW charging priority swimming pool circuit	0: No x 1: Yes	0	1		1
1.5	**15373**	R/W	1975		Overtemperature drop swimming pool circuit	0: Off x 1: On	0	1		1
1.5	**15374**	R/W	1978		Swimming pool circuit with buffer	0: No x 1: Yes	0	1		1
1.5	**15375**	R/W	1980		Swimming pool circuit with precontr/primary pump	0: No x 1: Yes	0	1		1
1.5	**15376**	R/W	2057		Swimming pool SD source heating		0.5	3	°C	1/64
1.5	**15377**	R/W	2065		Pool charging priority solar	1: None 2: Priority 2 x 3: Priority 3	1	3		1
1.5	**15378**	R/W	2070		Pool temperature maximum		8	80	°C	1/64
1.5	**15379**	R/W	2080		Pool with solar	0: No x 1: Yes	0	1		1
1.5	**15380**	R	8895		Flow temp setp swimming pool		0	130	°C	1/64
1.5	**15381**	R	8895		Status	see description				
1.5	**15382**	R			Swimming pool pump (Q19)	x 0: Off 1: On	0	1		
1.5	**15383**	R			Status	see description				
1.6	**15384**	R/W	5752		Swimming pool	0: Off x 1: On	0	1		1
1.6	**15385**	R/W	2066		Swimming pool charging priority photovoltaics	0: None 1: Priority 1 2: Priority 2 x 3: Priority 3	0	3		1
	0x4000...0x43FF	BL		Primary contr/system pump						
1.5	**16384**	R/W	2110		Flow temp min limitation precontroller		8	95	°C	1/64
1.5	**16385**	R/W	2111		Flow temp max limitation precontroller		8	95	°C	1/64
1.5	**16386**	R/W	2112		Flow temp min limitation cooling precontroller		8	20	°C	1/64
1.5	**16387**	R/W	2120		Frost protection for plant primary pump	0: Off x 1: On	0	1		1
1.5	**16388**	R/W	2130		Mixing valve setpoint boost precontroller		0	50	°C	1/64
1.5	**16389**	R/W	2131		Mixing valve decrease precontroller		0	20	°C	1/64
1.5	**16390**	R/W	2132		Actuator control mode precontroller	0: Two-position x 1: Three-position	0	1		1
1.5	**16391**	R/W	2133		Actuator switching differential precontroller		0	20	°C	1/64
1.5	**16392**	R/W	2134		Actuator running time precontroller		30	650	s	1
1.5	**16393**	R/W	2135		P-band (Xp)precontroller		1	100	°C	1/64
1.5	**16394**	R/W	2136		Integral action time (Tn) precontroller		10	650	s	1
1.5	**16395**	R/W	2145		DHW charging priority precontroler	0: No x 1: Yes	0	1		1

1.5	**16396**	R/W	2150		Precontroller/primary pump	0: Upstream of buffer x 1: Downstream from buffer	0	1		1
1.5	**16397**	R/W	2160		Frost protection for plant primary pump	0: Off x 1: On	0	1		1
1.5	**16398**	R	8930		Precontroller actual value		0	140	°C	1/64
1.5	**16399**	R	8930		Status	see description				
1.5	**16400**	R	8931		Precontroller setpoint		0	140	°C	1/64
1.5	**16401**	R	8931		Status	see description				
1.5	**16402**	R			Status primary pump (Q14)	x 0: Off 1: On	0	1		1
1.5	**16403**	R			Status	see description				
1.5	**16404**	R			Status precontroller mixing valve opens (Y19)	x 0: Off 1: On	0	1		1
1.5	**16405**	R			Status	see description				
1.5	**16406**	R			Status precontroller mixing valve closes (Y20)	x 0: Off 1: On	0	1		1
1.5	**16407**	R			Status	see description				
1.5	**16408**	R			Status primary pump 2 (Q44)	x 0: Off 1: On	0	1		1
1.5	**16409**	R			Status	see description				
	0x4400...0x47FF	BL		Buffer storage tank						
1.5	**17408**	R/W	8981		Buffer setpoint		0	140	°C	1/64
1.0	**17409**	R	8981		Status/Comand	see description				
1.0	**17410**	R	8980		Buffer temp 1		0	140	°C	1/64
1.0	**17411**	R	8980		Status	see description				
1.0	**17412**	R	8982		Buffer temp 2		0	140	°C	1/64
1.0	**17413**	R	8982		Status	see description				
1.0	**17414**	R/W	8990		Hours run el buffer		0	199'999	h	1/3600
1.0	17415					(32 Bit Data)				
1.0	**17416**	R/W	8991		Start counter el buffer		0	199999		1
1.0	17417					(32 Bit Data)				
1.0	**17418**	R	8010		State buffer	see description: status codes	0	1000		1
1.3	**17419**	R/W	4722		Diff. Buffer/HC temp to producer release		-20	20	°C	1/64
1.5	**17420**	R/W	4705		Forced charging	0: Off x 1: Demand 2: Always	0	2		1
1.5	**17421**	R/W	4708		Buffer forced charging setpoint cooling		6	35	°C	1/64
1.5	**17422**	R/W	4708		Status/Comand	see description				
1.5	**17423**	R/W	4709		Buffer storage forced charg setpoint heating min		20	80	°C	1/64
1.5	**17424**	R/W	4710		Buffer storage forced charg setpoint heating max		20	80	°C	1/64
1.5	**17425**	R/W	4711		Buffer storage tank forced charging time		00:00	23:50	h:m	10min
1.5	**17426**	R/W	4711		Status/Comand	see description				
1.5	**17427**	R/W	4712		Buffer storage tank forced charging max duration		1	20	h	1
1.5	**17428**	R/W	4720		Automatic producer lock	0: None x 1: With B4 2: With B4 and B42/B41 3: With B42 4: With B42 and B41 5: With B4 and B71	0	5		1
1.5	**17429**	R/W	4721		Automatic producer lock switching differential		0	20	°C	1/64
1.5	**17430**	R/W	4723		Temp diff buffer/CC to source release		-20	20	°C	1/64
1.5	**17431**	R/W	4724		Min buffer temp while heating mode		8	95	°C	1/64
1.5	**17432**	R/W	4724		Status/Comand	see description				
1.5	**17433**	R/W	4726		Max buffer temp while cooling mode		10	40	°C	1/64
1.5	**17434**	R/W	4726		Status/Comand	see description				
1.5	**17435**	R/W	4728		Rel temp diff buffer/HC		-50	50	%	1
1.5	**17436**	R/W	4735		Setpoint reduction B42/B41		0	20	°C	1/64
1.5	**17437**	R/W	4739		Buffer stratification protection	x 0: Off 1: Always	0	1		1
1.5	**17438**	R/W	4740		Buffer stratification protect Temp diff max		0	20	°C	1/64
1.5	**17439**	R/W	4743		Buffer stratification protect foreseeable time		0	240	s	1
1.5	**17440**	R/W	4744		Buffer stratification prot integral action time		10	200	s	1
1.5	**17441**	R/W	4749		Min charging setpoint solar		8	95	°C	1/64
1.5	**17442**	R/W	4750		Buffer charging temp max		8	95	°C	1/64
1.5	**17443**	R/W	4751		Buffer temp max		8	95	°C	1/64
1.5	**17444**	R/W	4755		Return cooling temperature buffer		8	95	°C	1/64
1.5	**17445**	R/W	4756		Buffer return cooling DHW/HC	x 0: Off 1: On	0	1		1
1.5	**17446**	R/W	4757		Buffer return cooling Collector	x 0: Off 1: Summer 2: Always	0	2		1
1.5	**17447**	R/W	4760		Charging sensor electric immersion heater	x 1: None 2: With B42/B41	1	2		1
1.5	**17448**	R/W	4761		Forced charging with electric immersion heater	x 0: No 1: Yes 2: Smart grid, draw	0	2		1
1.5	**17449**	R/W	4783		Buffer with solar	x 0: No 1: Yes	0	1		1
1.5	**17450**	R/W	4830		Flow diversion temp		50	95	°C	1/64
1.5	**17451**	R/W	4830		Status/Comand	see description				
1.5	**17452**	R/W	4831		Swi diff flow diversion		0	20	°C	1/64
1.5	**17453**	R/W			Delay flow diversion		0	60	s	1
1.5	**17454**	R/W	5870		Combi storage tank	x 0: No 1: Yes	0	1		1
1.5	**17455**	R/W	5872		Output el imm heater K16		0.1	99	kW	1/10
1.5	**17456**	R/W	8970		State electric immersion heater buffer	x 0: Off 1: On	0	1		1
1.5	**17457**	R/W	8983		Buffer temp actual value middle (B42)		0.1	99	kW	1/10
1.5	**17458**	R			Output heat generation lock (Y4)	x 0: Off 1: On	0	1		1
1.5	**17459**	R			Status	see description				
1.5	**17460**	R/W	4797		Pos Y15 when TWW transfer	x 0: Off 1: On	0	1		1
1.5	**17461**	R/W	4797		Status/Comand	see description				

1.6	**17462**	R/W	4706		Buffer storage tank charging prio photovoltaics	0: None 1: Priority 1 x 2: Priority 2 3: Priority 3	0	3		1
	0x4800...0x4BFF	BL		Common flow						
1.0	**18432**	R	8951		Common flow temp setpoint		0	140	°C	1/64
1.0	**18433**	R	8951		Status	see description				
1.0	**18434**	R	8957		Common flow setp refrig		0	140	°C	1/64
1.0	**18435**	R	8957		Status	see description				
1.5	**18436**	R	8950		Segment flow temperature actual value		0	140	°C	1/64
1.5	**18437**	R	8950		Status	see description				
1.5	**18438**	R	8952		Segment return temp		0	140	°C	1/64
1.5	**18439**	R	8952		Status	see description				
1.5	**18440**	R	8956		Common flow temp 2		0	140	°C	1/64
1.5	**18441**	R	8956		Status	see description				
1.5	**18442**	R			Status heat demand (K27)	x 0: Off 1: On	0	1		1
1.5	**18443**	R	8956		Status	see description				
1.5	**18444**	R			Status cool demand (K28)	x 0: Off 1: On	0	1		1
1.5	**18445**	R	8956		Status	see description				
1.5	**18446**	R			State of diverting valve cooling, flow (Y29)	x 0: Off 1: On	0	1		1
1.5	**18447**	R	8956		Status	see description				
	0x5000...0x53FF	BL		Heat pump						
1.0	**20480**	R	8410		Return temp HP		0	140	°C	1/64
1.0	**20481**	R	8410		Status	see description				
1.0	**20482**	R	8411		Setpoint HP		0	140	°C	1/64
1.0	**20483**	R	8411		Status	see description				
1.0	**20484**	R	8412		Flow temp HP		0	140	°C	1/64
1.0	**20485**	R	8412		Status	see description				
1.0	**20486**	R	8435		Evaporation temp		-50	180	°C	1/64
1.0	**20487**	R	8435		Status	see description				
1.0	**20488**	R	8436		Superheat		-10	180	°C	1/64
1.0	**20489**	R	8436		Status	see description				
1.0	**20490**	R	8436		Superheat setpoint		0	140	°C	1/64
1.0	**20491**	R	8436		Status	see description				
1.0	**20492**	R	8440		Remain sDaye 1 off time min		0	255	min	1
1.0	**20493**	R	8440		Status	see description				
1.0	**20494**	R	8441		Remain sDaye 2 off time min		0	255	min	1
1.0	**20495**	R	8441		Status	see description				
1.0	**20496**	R	8442		Remain sDaye 1 on time min		0	255	min	1
1.0	**20497**	R	8442		Status	see description				
1.0	**20498**	R	8443		Remain sDaye 2 on time min		0	255	min	1
1.0	**20499**	R	8443		Status	see description				
1.0	**20500**	R	8444		Remain limit source temp		0	65'535	h:m	1min
1.0	**20501**	R	8444		Status	see description				
1.0	**20502**	R	8446		Compressor sequence	x 0: 1 - 2 1: 2 - 1	0	1		1
1.0	**20503**	R/W	8449		Hours run refrigerant circuit		0	199'999	h	1/3600
1.0	20504					(32 Bit Data)				
1.0	**20505**	R/W	8450		Hours run compressor 1		0	199'999	h	1/3600
1.0	20506					(32 Bit Data)				
1.0	**20507**	R/W	8451		Start counter compressor 1		0	199999		1
1.0	20508					(32 Bit Data)				
1.0	**20509**	R/W	8452		Hours run compressor 2		0	199'999	h	1/3600
1.0	20510					(32 Bit Data)				
1.0	**20511**	R/W	8453		Start counter compressor 2		0	199999		1
1.0	20512					(32 Bit Data)				
1.0	**20513**	R/W	8454		Locking time HP		0	199'999	h	1/3600
1.0	20514					(32 Bit Data)				
1.0	**20515**	R/W	8455		Counter number of locks HP		0	199999		1
1.0	20516					(32 Bit Data)				
1.0	**20517**	R/W	8456		Hours run el flow		0	199'999	h	1/3600
1.0	20518					(32 Bit Data)				
1.0	**20519**	R/W	8457		Start counter el flow		0	199999		1
1.0	20520					(32 Bit Data)				
1.0	**20521**	R/W			Hours run el 2 flow		0	199'999	h	1/3600
1.0	20522					(32 Bit Data)				
1.0	**20523**	R/W			Start counter el 2 flow		0	199999		1
1.0	20524					(32 Bit Data)				
1.0	**20525**	R	8463		Evaporation temp EVI		-50	180	°C	1/64
1.0	**20526**	R	8463		Status	see description				
1.0	**20527**	R	8464		Superheat EVI		-10	180	°C	1/64
1.0	**20528**	R	8464		Status	see description				
1.0	**20529**	R	8464		Superheat setpoint EVI		0	140	°C	1/64
1.0	**20530**	R	8464		Status	see description				
1.0	**20531**	R	8477		Temp diff defrost act value		-50	50	°C	1/64
1.0	**20532**	R	8477		Status	see description				
1.0	**20533**	R	8478		Temp diff defrost setpoint		-50	50	°C	1/64
1.0	**20534**	R	8478		Status	see description				
1.0	**20535**	R	8480		Remain time defrost lock		0	255	min	1
1.0	**20536**	R	8480		Status	see description				
1.0	**20537**	R	8481		Remain time forced defrost		0	65'535	h:m	1min
1.0	**20538**	R	8481		Status	see description				
1.0	**20539**	R	8482		Remain time defrost settling		0	255	min	1
1.0	**20540**	R	8482		Status	see description				
1.0	**20541**	R	8485		Number defrost attempts		0	10		1

1.0	**20542**	R	8487		Defrost state	x 0: HP off,defr release OT off 1: Locked 2: Monitoring ice 3: Preheating for defrost 4: Defrost active 5: Dripping 6: Cooling down evaporator 7: Fault 8: Forced defrost 9: Defrost settling 10: Defrost with fan 11: Defrost with compressor 12: Forced defrost fan 13: Forced defrost compressor 14: Start delay defrost	0	14		1
1.0	**20543**	R/W	2909		Release below outside temp		-50	50	°C	1/64
1.0	20544	R/W	2909		Status/Comand	see description				
1.0	**20545**	R/W	2910		Release above outside temp		-30	30	°C	1/64
1.0	**20546**	R/W	2910		Status/Comand	see description				
1.0	**20547**	R/W	6711		Reset HP	x 0: No 1: Yes	0	1		1
1.0	**20548**	R/W	7071		HP time since maint		0	240	Months	1
1.0	**20549**	R/W	7073		Cur starts compr1/hrs run		0	12		1/10
1.0	**20550**	R/W	7075		Cur starts compr2/hrs run		0	12		1/10
1.0	**20551**	R/W	7077		Cur diff condens max/week		0	250		1
1.0	**20552**	R/W	7079		Cur diff condens min/week		0	250		1
1.0	**20553**	R/W	7081		Cur diff evap max/week		0	250		1
1.0	**20554**	R/W	7083		Cur diff evap min/week		0	250		1
1.0	**20555**	R/W	7152		Triggering defrost	x 0: No	0	1		1
1.0	**20556**	R	8006		State heat pump	see description: status codes	0	1000		1
1.3	**20557**	R/W	2792		Pump speed min condensator pump	**Must not be bigger than parameter 2793**	0	100	%	1
1.3	**20558**	R/W	2793		Pump speed max condensator pump	**Must not be smaller than parameter 2792**	0	100	%	1
1.3	**20559**	R/W	2801		Control condenser pump	x 1: Automatically 2: Temperature request 3: Parallel compressor operation	1	3		1
1.3	**20560**	R/W	2802		Prerun time condenser pump		0	600	s	1
1.3	**20561**	R/W	2803		Overrun time condenser pump		0	600	s	1
1.3	**20562**	R/W	2805		Setpoint temperature differential condenser	**Must not be bigger than parameter 2804**	1	20	°C	1/64
1.3	**20563**	R/W	2805		Status/Comand	see description				
1.3	**20564**	R/W	2816		Source temperature minimum brine HP		-30	50	°C	1/64
1.3	**20565**	R/W	2816		Status/Comand	see description				
1.3	**20566**	R/W	2819		Source temperature minimum brine HP		0	600	s	1
1.3	**20567**	R/W	2820		Overrun time source		0	600	s	1
1.3	**20568**	R/W	2823		Setpoint temperature differential evaporator		1	20	°C	1/64
1.3	**20569**	R/W	2840		Switching differential return temperature		1	20	°C	1/64
1.3	**20570**	R/W	2842		Compressor running time min		0	120	min	1
1.3	**20571**	R/W	2843		Compressor off time min		0	120	min	1
1.3	**20572**	R/W	2844		Switch-off temperature max		8	100	°C	1/64
1.3	**20573**	R/W	2880		Use electric flow	1: Substitute x 2: Complem operation HC 3: Complem operation DHW 4: Complem operation HC+DHW 5: End DHW charging 6: Emergency operation 7: Legionella function	1	7		1
1.3	**20574**	R/W	2881		Locking time electric flow		0	255	min	1
1.3	**20575**	R/W	2882		Release integral electric flow		0	500	°C*min	1
1.3	**20576**	R/W	2883		Reset integral electric flow		0	500	°C*min	1
1.3	**20577**	R/W	2884		Release electric flow below outside temperature		-30	30	°C	1/64
1.3	**20578**	R/W	2884		Status/Comand	see description				
1.3	**20579**	R/W	2885		Electric flow on below flow temperature		5	20	°C	1/64
1.3	**20580**	R/W	2885		Status/Comand	see description				
1.3	**20581**	R/W	3009		Modulation fan/source pump	0: None 1: --- inadmissible setting --- 2: Compressor output x 3: Temp diff evaporator	0	3		1
1.3	**20582**	R/W	3010		Speed maximal fan/source pump	**Must not be smaller than parameter 3011**	0	100	%	1
1.3	**20583**	R/W	3011		Speed minimal fan/source pump	**Must not be bigger than parameter 3010**	0	100	%	1
1.3	**20584**	R/W	3017		Locking time control		0	250	s	1
1.3	**20585**	R/W	3017		Status/Comand	see description				
1.3	**20586**	R/W	3019		Start speed fan/sce pump		0	100	%	1
1.3	**20587**	R/W	3019		Status/Comand	see description				
1.3	**20588**	R/W	5806		Type electric flow	0: None 1: 3-stage 2: 2-stage alternative 3: 2-stage complementary	0	3		1
1.4	**20589**	R/W	2855		Switch-off temp max HC		8	100	°C	1/64
1.4	**20590**	R/W	2855		Status/Comand	see description				
1.5	**20591**	R/W	2776		Pump speed min condensator pump with DHW		0	100	%	1
1.5	**20592**	R/W	2776		Status/Comand	see description				
1.5	**20593**	R/W	2777		Pump speed max condensator pump with DHW		0	100	%	1
1.5	**20594**	R/W	2777		Status/Comand	see description				
1.5	**20595**	R/W	2778		Pump speed min condensator pump cooling mode		0	100	%	1
1.5	**20596**	R/W	2778		Status/Comand	see description				
1.5	**20597**	R/W	2779		Pump speed max condensator pump cooling mode		0	100	%	1
1.5	**20598**	R/W	2779		Status/Comand	see description				
1.5	**20599**	R/W	2785		Max condensation temp		8	100	°C	1/64
1.5	**20600**	R/W	2786		Max condensation temp SD		1	20	°C	1/64
1.5	**20601**	R/W	2787		Max condensation temp red		0	20	°C	1/64
1.6	**20602**	R/W	2788		Modulation condens pump DHW	0: None 1: Heat pump setpoint 2: Compressor output 3: Temp diff condensor 4: --- inadmissable setting --- 5: Flow supplementary source	0	5		1
1.5	**20603**	R/W	2788		Status/Comand	see description				

1.5	**20604**	R/W	2789		Condenser pump with DHW	0: Off x 1: On	0	1		1
1.6	**20605**	R/W	2790		Condensator pump modulation	0: None x 1: Heat pump setpoint 2: Compressor output 3: Temp diff condensor 4: --- inadmissable setting --- 5: Flow supplementary source	0	5		1
1.5	**20606**	R/W	2794		Pump speed P-band XP condensator pump		1	100	°C	1/64
1.5	**20607**	R/W	2795		Pump speed Integ action time Tn condensator pump		1	650	s	1
1.5	**20608**	R/W	2796		Pump speed derivative action time (Tv) boiler		0	60	s	1/4
1.5	**20609**	R/W	2799		Pump setpoint reduction little condens output		0	20	°C	1/64
1.5	**20610**	R/W	2800		Frost protection plant condenser pump	x 0: Off 1: On	0	1		1
1.5	**20611**	R/W	2804		Max temp diff condensator		1	30	°C	1/64
1.5	**20612**	R/W	2804		Status/Comand	see description				
1.5	**20613**	R/W	2806		Max deviation differential condenser		1	10	°C	1/64
1.5	**20614**	R/W	2806		Status/Comand	see description				
1.5	**20615**	R/W	2807		Min temp diff cond DHW		1	10	°C	1/64
1.5	**20616**	R/W	2807		Status/Comand	see description				
1.5	**20617**	R/W	2808		Req temp diff condens DHW		1	15	°C	1/64
1.5	**20618**	R/W	2808		Status/Comand	see description				
1.5	**20619**	R/W	2809		Temperature frost alarm		0	10	°C	1/64
1.5	**20620**	R/W	2809		Status/Comand	see description				
1.5	**20621**	R/W	2810		Condenser frost protection		-15	8	°C	1/64
1.5	**20622**	R/W	2810		Status/Comand	see description				
1.5	**20623**	R/W	2811		Overrun cond frost protect		0	600	s	1
1.5	**20624**	R/W	2812		Operation limit outside temperature minimum air		-50	20	°C	1/64
1.5	**20625**	R/W	2812		Status/Comand	see description				
1.5	**20626**	R/W	2813		Operation limit outside temperature maximum air		0	50	°C	1/64
1.5	**20627**	R/W	2813		Status/Comand	see description				
1.5	**20628**	R/W	2814		Source temperature maximum		10	60	°C	1/64
1.5	**20629**	R/W	2814		Status/Comand	see description				
1.5	**20630**	R/W	2815		Source temperature minimum water HP		-20	30	°C	1/64
1.5	**20631**	R/W	2815		Status/Comand	see description				
1.5	**20632**	R/W	2817		Switching diff source protection		1	10	°C	1/64
1.5	**20633**	R/W	2818		Increase source temp min when floor curing		0	10	°C	1/64
1.5	**20634**	R/W	2821		Source startup time max		1	10	min	1
1.5	**20635**	R/W	2822		Time limit source temp min brine		1	24	h	1
1.5	**20636**	R/W	2824		Max deviation differential evaporator		1	10	°C	1/64
1.5	**20637**	R/W	2824		Status/Comand	see description				
1.5	**20638**	R/W	2825		Min evaporation temp		-50	50	°C	1/64
1.5	**20639**	R/W	2825		Status/Comand	see description				
1.5	**20640**	R/W	2826		Max evaporation temp		0	50	°C	1/64
1.5	**20641**	R/W	2826		Status/Comand	see description				
1.5	**20642**	R/W	2827		Time limit source temp		1	360	min	1
1.5	**20643**	R/W	2828		Min evaporation temp water		-50	50	°C	1/64
1.5	**20644**	R/W	2828		Status/Comand	see description				
1.5	**20645**	R/W	2829		Extended range min evaporation temp		-20	-0.5	°C	1/64
1.5	**20646**	R/W	2829		Status/Comand	see description				
1.5	**20647**	R/W	2830		Max duration extended min evaporation temp		10	10000	h	1
1.5	**20648**	R/W	2832		Setpoint crankcase heater		-30	50	°C	1/64
1.5	**20649**	R/W	2832		Status/Comand	see description				
1.5	**20650**	R/W	2835		Restart lock compressor		10	1800	s	1
1.5	**20651**	R/W	2836		Start swi-off temp red		-30	20	°C	1/64
1.5	**20652**	R/W	2837		Swi-off temp max reduced		8	100	°C	1/64
1.5	**20653**	R/W	2837		Status/Comand	see description				
1.5	**20654**	R/W	2838		Settl'time process reversal		0	300	s	1
1.5	**20655**	R/W	2839		Settl'time ch'over DHW/HC		15	600	s	1
1.5	**20656**	R/W	2839		Status/Comand	see description				
1.5	**20657**	R/W	2841		Keep compressor run time minimum	x 0: No 1: Yes	0	1		1
1.5	**20658**	R/W	2845		Reduction switch-off temperature max		-20	20	°C	1/64
1.5	**20659**	R/W	2846		Hot-gas temperature max		20	180	°C	1/64
1.5	**20660**	R/W	2847		Switching diff hot-gas temp max		1	40	°C	1/64
1.5	**20661**	R/W	2848		Reduction hot-gas temp max		0	20	°C	1/64
1.5	**20662**	R/W	2849		Setpoint hot-gas temperature		20	180	°C	1/64
1.5	**20663**	R/W	2850		Switching diff setpoint hot-gas temperature		1	40	°C	1/64
1.5	**20664**	R/W	2851		Contact type setpoint hot-gas temperature	0: normal closed x 1: normal opened	0	1		1
1.5	**20665**	R/W	2852		Low-pressure delay on startup		0	120	s	1
1.5	**20666**	R/W	2853		Low-pressure delay during operation		0	120	s	1
1.5	**20667**	R/W	2854		Low-pressure supervision	1: Wert 678; 0 x 2: Without defrosting	1	2		1
1.5	**20668**	R/W	2860		Lock compressor 2 for DHW charging	x 0: Off 1: On	0	1		1
1.5	**20669**	R/W	2861		Release stage 2 below outside temp thresh		-30	30	°C	1/64
1.5	**20670**	R/W	2861		Status/Comand	see description				
1.5	**20671**	R/W	2862		Locking time stage2/mod		0	40	min	1
1.5	**20672**	R/W	2863		Release integral stage2/mod		0	500	°C*min	1
1.5	**20673**	R/W	2864		Reset integral stage2/mod		0	500	°C*min	1
1.5	**20674**	R/W	2865		Compressor sequence changeover		10	1000	h	1
1.5	**20675**	R/W	2865		Status/Comand	see description				
1.5	**20676**	R/W	2867		Output optimum		1	100	%	1
1.5	**20677**	R/W	2867		Status/Comand	see description				
1.5	**20678**	R/W	2868		Output nominal heatpump		0	1000		1
1.5	**20679**	R/W	2869		Nominal power first stage		0	1000		1
1.5	**20680**	R/W	2870		Compressor modulation max		0	100	%	1
1.5	**20681**	R/W	2871		Compressor modulation min		0	100	%	1
1.5	**20682**	R/W	2873		Compressor modulation run time		0	600	s	1
1.5	**20683**	R/W	2874		Compressor modulation Xp		1	200	°C	1/64
1.5	**20684**	R/W	2875		Compressor modulation Tn		1	650	s	1
1.5	**20685**	R/W	2878		PWM period digital scroll		5	30	s	1
1.5	**20686**	R/W	2878		Status/Comand	see description				
1.5	**20687**	R/W	2879		Compr mod run time close		0	600	s	1
1.5	**20688**	R/W	2879		Status/Comand	see description				

1.5	**20689**	R/W	2886		Compensation heat deficit	0: Off x 1: On 2: Only with floor curing function	0	2		1
1.5	**20690**	R/W	2889		Duration error repetition		1	40	h	1
1.5	**20691**	R/W	2893		Number of DHW charging attempts		1	10		1
1.5	**20692**	R/W	2893		Status/Comand	see description				
1.5	**20693**	R/W	2894		Delay mains fault		1	40	s	1
1.5	**20694**	R/W	2895		Delay flow switch		0	10	s	1
1.5	**20695**	R/W	2896		Flow switch source active	x 0: Always 1: Heating mode only	0	1		1
1.6	**20696**	R/W	2898		Min throughput flow switch source		1	12000	l/h	1
1.6	**20697**	R/W	2898		Status/Comand	see description				
1.6	**20698**	R/W	2899		Min throughput flow switch consumers		1	12000	l/h	1
1.6	**20699**	R/W	2899		Status/Comand	see description				
1.5	**20700**	R/W	2900		Refrigerant	x 0: None 1: R134A 2: R236FA 3: R290 4: R404A 5: R407A 6: R407B 7: R407C 8: R410A 9: R410B 10: R413A 11: R417A 12: R422A 13: R422D 14: R427A 15: R507A 16: R600 17: R600A 18: R744 19: R1270	0	19		1
1.5	**20701**	R/W	2903		Release strategy	x 1: Off 2: Energy price 3: Coefficient of performance and energy price 4: Coefficient of performance or energy price	1	4		1
1.5	**20702**	R/W	2904		Release of coefficient of performance		1	10		1/10
1.5	**20703**	R/W	2904		Status/Comand	see description				
1.5	**20704**	R/W	2908		OT limit with DHW charging	0: Disregard x 1: Note	0	1		1
1.5	**20705**	R/W	2909		Release heat pump below outside temp thresh		-50	50	°C	1/64
1.5	**20706**	R/W	2909		Status/Comand	see description				
1.5	**20707**	R/W	2910		Heat pump release above outside temperature		-30	30	°C	1/64
1.5	**20708**	R/W	2910		Status/Comand	see description				
1.5	**20709**	R/W	2911		Heat pump for forced buffer charging	0: Locked x 1: Released	0	1		1
1.5	**20710**	R/W	2912		Full charging buffer	0: Off x 1: On	0	1		1
1.5	**20711**	R/W	2922		Condenser overtemp prot	0: Off x 1: Cooling down 2: Switch-on lock + cool down	0	2		1
1.5	**20712**	R/W	2923		Condens prot buffer sensor	x 1: Wert 641; 0 2: Buffer sensor B41 3: Buffer sensor B42	1	3		1
1.5	**20713**	R/W	2941		Use of diverting valve Y28	x 1: --- 2: Active and passive cooling	1	2		1
1.5	**20714**	R/W	2951		Defrost release below outside temperature		5	20	°C	1/64
1.5	**20715**	R/W	2952		Switching differential defrosting		0	15	°C	1/64
1.5	**20716**	R/W	2953		Temperature differential defrosting maximum		5	50	°C	1/64
1.5	**20717**	R/W	2954		Evaporator temperature at defrosting end		2	40	°C	1/64
1.5	**20718**	R/W	2955		Verdichter bei Abtauen	0: Off x 1: On	0	1		1
1.5	**20719**	R/W	2956		Temp differential cooling down end evaporator		-10	10	°C	1/64
1.5	**20720**	R/W	2956		Status/Comand	see description				
1.5	**20721**	R/W	2958		Num defrost repetitions max		0	10		1
1.5	**20722**	R/W	2959		Defrost settling time		1	20	min	1
1.5	**20723**	R/W	2960		Time dT start defrost		5	1200	s	1
1.5	**20724**	R/W	2960		Status/Comand	see description				
1.5	**20725**	R/W	2962		Duration of defrost lock		0	100	min	1
1.5	**20726**	R/W	2963		Duration to forced defrosting		60	600	min	1
1.5	**20727**	R/W	2963		Status/Comand	see description				
1.5	**20728**	R/W	2964		Defrosting time maximum		1	42	min	1
1.5	**20729**	R/W	2965		Dripping time evaporator		0	10	min	1
1.5	**20730**	R/W	2966		Cooling down time evaporator		0	240	s	1
1.5	**20731**	R/W	2966		Status/Comand	see description				
1.5	**20732**	R/W	2967		Temp thresh drip tray heat		-5	10	°C	1/64
1.5	**20733**	R/W	2968		Max compr output defrost		1	100	%	1
1.5	**20734**	R/W	2969		Defrost with DHW charging	x 1: None 2: DHW 3: Heating circuit 4: Heating circ, delay defrost	1	4		1
1.5	**20735**	R/W	2970		Switch-off temperature minimum heat pump		1	40	°C	1/64
1.5	**20736**	R/W	2971		Defrost fan above		1	20	°C	1/64
1.5	**20737**	R/W	2971		Status/Comand	see description				
1.5	**20738**	R/W	2972		Defrost time fan min		1	42	min	1
1.5	**20739**	R/W	2973		Defrost time fan max		1	42	min	1
1.5	**20740**	R/W	2974		Temperature differential end defrost fan		0.5	10	°C	1/64
1.5	**20741**	R/W	2974		Status/Comand	see description				
1.5	**20742**	R/W	3000		Switch-off temperature maximum cooling		20	60	°C	1/64
1.5	**20743**	R/W	3000		Status/Comand	see description				
1.5	**20744**	R/W	3002		Source temperature minimum cooling mode		-20	30	°C	1/64
1.5	**20745**	R/W	3002		Status/Comand	see description				
1.5	**20746**	R/W	3004		Switching diff changeover cooling passive/active		1	10	°C	1/64

1.5	**20747**	R/W	3007		In passive cooling mode	x 0: Condenser pump off 1: Condenser pump on	0	1		1
1.5	**20748**	R/W	3008		Differential condenser cooling mode		0	20	°C	1/64
1.5	**20749**	R/W	3012		Source off below temperature B83		10	60	°C	1/64
1.5	**20750**	R/W	3012		Status/Comand	see description				
1.5	**20751**	R/W	3014		Switching differential		1	10	°C	1/64
1.5	**20752**	R/W	3015		Start speed control B83		10	60	°C	1/64
1.5	**20753**	R/W	3016		End speed control B83		10	60	°C	1/64
1.5	**20754**	R/W	3021		Speed fan/source pump Xp		1	100	°C	1/64
1.5	**20755**	R/W	3022		Speed fan/source pump Tn		1	650	s	1
1.5	**20756**	R/W	3023		Speed fan/source pump Tv		0	60	s	1/4
1.5	**20757**	R/W	3025		Silent mode speed max		0	100	%	1
1.5	**20758**	R/W	3025		Status/Comand	see description				
1.5	**20759**	R/W	3026		Silent mode on		00:00	23:50	h:m	1/60
1.5	**20760**	R/W	3027		Silent mode off		00:00	23:50	h:m	1/60
1.5	**20761**	R/W	3028		Silent mode speed incr start		-50	50	°C	1/64
1.5	**20762**	R/W	3028		Status/Comand	see description				
1.5	**20763**	R/W	3029		Silent mode speed incr end		-50	50	°C	1/64
1.5	**20764**	R/W	3030		Auto readj HP cond sensor	x 0: Off 1: Now 2: After pump prerun	0	2		1
1.5	**20765**	R/W	3031		Readj HP flow sensor		-20	20	°C	1/64
1.5	**20766**	R/W	3032		Readj HP return sensor		-20	20	°C	1/64
1.5	**20767**	R	3033		Readj status	x 0: Not readjusted 1: Manually readjusted 2: Automatically readjusted 3: Readjustment running	0	3		1
1.5	**20768**	R/W	3035		Readj inlet sens HP source		-20	20	°C	1/64
1.5	**20769**	R/W	3036		Readj outlet sens HP source		-20	20	°C	1/64
1.5	**20770**	R/W	3038		Readjust source interm circuit flow sensor B93		-20	20	°C	1/64
1.5	**20771**	R/W	3039		Readjust source interm circuit return sensor B94		-20	20	°C	1/64
1.5	**20772**	R/W	3042		Super heat setpoint		0	15	°C	1/64
1.5	**20773**	R/W	3042		Status/Comand	see description				
1.5	**20774**	R/W	3043		Super heat conntroller Xp		1	200	°C	1/64
1.5	**20775**	R/W	3044		Super heat conntroller Tn		4	650	s	1
1.5	**20776**	R/W	3045		Super heat conntroller Tv		0	60	s	1/4
1.5	**20777**	R/W	3046		Expansion valve run time		1	1000	s	1
1.5	**20778**	R/W	3047		Min superheat		0.5	5	°C	1/64
1.5	**20779**	R/W	3047		Status/Comand	see description				
1.5	**20780**	R/W	3049		Superheat setp cooling mode		0	25	°C	1/64
1.5	**20781**	R/W	3049		Status/Comand	see description				
1.5	**20782**	R/W	3050		Superheat incr silent mode		0	10	°C	1/64
1.5	**20783**	R/W	3051		Delay compressor start		0	120	s	1
1.5	**20784**	R/W	3052		Pos expansion valve start		0	100	%	1
1.5	**20785**	R/W	3053		Delay superheat controller		0	30	s	1
1.5	**20786**	R/W	3054		Superheat setp adaption	x 0: Off 1: Heating mode 2: Cooling mode 3: Heating and cooling mode	0	3		1
1.5	**20787**	R/W	3056		Output control with SHC	x 0: Off 1: Heating mode 2: Cooling mode 3: Heating and cooling mode	0	3		1
1.5	**20788**	R/W	3058		Pump down function	x 0: Off 1: Automatic	0	1		1
1.5	**20789**	R/W	3059		Pump off funct press limit		0	100	bar	1/10
1.5	**20790**	R/W	3059		Status/Comand	see description				
1.5	**20791**	R/W	3062		Superheat setpoint EVI		1	15	°C	1/64
1.5	**20792**	R/W	3063		EVI controller Xp		1	200	°C	1/64
1.5	**20793**	R/W	3064		EVI controller Tn		4	650	s	1
1.5	**20794**	R/W	3065		EVI controller Tv		0	60	s	1/4
1.5	**20795**	R/W	3066		Expansion valve EVI run time		1	1000	s	1
1.5	**20796**	R/W	3071		Threshold hot-gas temp EVI		20	180	°C	1/64
1.5	**20797**	R/W	3071		Status/Comand	see description				
1.5	**20798**	R/W	3072		SD hot-gas temp EVI		1	20	°C	1/64
1.5	**20799**	R/W	3073		Threshold source temp EVI		-50	50	°C	1/64
1.5	**20800**	R/W	3073		Status/Comand	see description				
1.5	**20801**	R/W	3074		SD source temp EVI		1	20	°C	1/64
1.5	**20802**	R/W	3077		Swi-off temp sat vapour op		8	100	°C	1/64
1.5	**20803**	R/W	3077		Status/Comand	see description				
1.5	**20804**	R/W	3078		Thresh hot-gas temp satur		20	180	°C	1/64
1.5	**20805**	R/W	3078		Status/Comand	see description				
1.5	**20806**	R/W	3080		Thresh source temp satur		-50	50	°C	1/64
1.5	**20807**	R/W	3080		Status/Comand	see description				
1.5	**20808**	R/W	5800		Heat source	x 1: Wert 1045; 0 2: Water 3: Air 4: Externally brine 5: Externally water 6: Externally air	1	6		1
1.5	**20809**	R/W	5803		Geräteadresse externe Quelle		1	16		1
1.5	**20810**	R/W	5803		Status/Comand	see description				
1.5	**20811**	R/W	5804		Source protection sensor brine HP	x 1: Wert 677; 0 2: Source outlet B92	1	2		1
1.5	**20812**	R/W	5805		Location of electric immersion heater flow	x 0: Downstream from flow sensor B21 1: Upstream of flow sensor B21 2: Flow desuperheater	0	2		1
1.5	**20813**	R/W	5806		Type electric flow	0: None x 1: 3-stage 2: 2-stage alternative 3: 2-stage complementary 4: --- inadmissable setting --- 5: 1-stage	0	5		1

1.5	**20814**	R/W	5807		Refrigeration	x 0: Off 1: Active and passive cooling 2: Active cooling 3: Passive cooling	0	3		1
1.5	**20815**	R/W	5808		Cooling system	1: Off x 2: 2-pipe system cooling	1	2		1
1.5	**20816**	R/W	5810		Temperature differential HC at -10°C		0	20	°C	1/64
1.5	**20817**	R/W	5811		Output el imm heater K25		0.1	99	kW	1/10
1.5	**20818**	R/W	5813		Output el imm heater K26		0.1	99	kW	1/10
1.5	**20819**	R/W	5822		Press acquisition compr H82	x 0: None 1: With input H1 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**20820**	R/W	5823		Press acquisition cond H83	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**20821**	R/W	5826		Acquisition press EVI H86	x 0: None 1: With input H1 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**20822**	R/W	5827		Messung Feuchte Lufteintritt H91	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3 12: With input H31 13: With input H32 14: With input H33	0	14		1
1.5	**20823**	R	8395		Heat output		0	999.9	kW	1/100
1.5	**20824**					(32 Bit Data)				
1.5	**20825**	R	8395		Status	see description				
1.5	**20826**	R	8396		Heat input source		0	999.9	kW	1/100
1.5	**20827**					(32 Bit Data)				
1.5	**20828**	R	8396		Status	see description				
1.5	**20829**	R	8397		Power consumption		0	999.9	kW	1/100
1.5	**20830**					(32 Bit Data)				
1.5	**20831**	R	8397		Status	see description				
1.5	**20832**	R	8398		Coefficient of performance		0	20		1/100
1.5	**20833**	R	8398		Status	see description				
1.5	**20834**	R	8400		State compressor 1	x 0: Off 1: On	0	1		1
1.5	**20835**	R	8400		Status	see description				
1.5	**20836**	R	8401		State compressor 2	x 0: Off 1: On	0	1		1
1.5	**20837**	R	8401		Status	see description				
1.5	**20838**	R	8402		State electric immersion heater 1 flow	x 0: Off 1: On	0	1		1
1.5	**20839**	R	8402		Status	see description				
1.5	**20840**	R	8403		State electric immersion heater 2 flow	x 0: Off 1: On	0	1		1
1.5	**20841**	R	8403		Status	see description				
1.5	**20842**	R	8404		State source pump	x 0: Off 1: On	0	1		1
1.5	**20843**	R	8404		Status	see description				
1.5	**20844**	R	8405		Speed source pump		0	100	%	1
1.5	**20845**	R	8405		Status	see description				
1.5	**20846**	R	8406		State condenser pump	x 0: Off 1: On	0	1		1
1.5	**20847**	R	8406		Status	see description				
1.5	**20848**	R	8407		Speed of condensor pump		0	100	%	1
1.5	**20849**	R	8407		Status	see description				
1.5	**20850**	R	8408		Diverting valve cool source	x 0: Off 1: On	0	1		1
1.5	**20851**	R	8408		Status	see description				

1.5	**20852**	R	8413		Compressor modulation		0	100	%	1/100
1.5	**20853**	R	8413		Status	see description				
1.5	**20854**	R	8414		Modulation electric flow		0	100	%	1
1.5	**20855**	R	8414		Status	see description				
1.5	**20856**	R	8415		Hot-gas temperature 1		0	180	°C	1/64
1.5	**20857**	R	8415		Status	see description				
1.5	**20858**	R/W	8416		Hot-gas temperature max		20	180	°C	1/64
1.5	**20859**	R	8417		Hot-gas temperature 2		0	180	°C	1/64
1.5	**20860**	R	8417		Status	see description				
1.5	**20861**	R	8420		Refrigerant temperature liquid		0	140	°C	1/64
1.5	**20862**	R	8420		Status	see description				
1.5	**20863**	R	8423		Condenser temp		-50	180	°C	1/64
1.5	**20864**	R	8423		Status	see description				
1.5	**20865**	R	8423		Condenser pressure		-100	500	bar	1/100
1.5	**20866**	R	8423		Status	see description				
1.5	**20867**	R	8425		Temperature differential condenser		-50	140	°C	1/64
1.5	**20868**	R	8425		Status	see description				
1.5	**20869**	R	8426		Temperature differential evaporator		-50	140	°C	1/64
1.5	**20870**	R	8426		Status	see description				
1.5	**20871**	R	8427		Source inlet temperature		-50	50	°C	1/64
1.5	**20872**	R	8427		Status	see description				
1.5	**20873**	R			Source switch-off threshold		-50	50	°C	1/64
1.5	**20874**	R			Status	see description				
1.5	**20875**	R/W	8428		Source inlet temp min		-50	350	°C	1/64
1.5	**20876**	R	8428		Status	see description				
1.5	**20877**	R	8429		Source outlet temperature		-50	50	°C	1/64
1.5	**20878**	R	8429		Status	see description				
1.5	**20879**	R			Source switch-off threshold		-50	50	°C	1/64
1.5	**20880**	R			Status	see description				
1.5	**20881**	R/W	8430		Source outlet temp min		-50	350	°C	1/64
1.5	**20882**	R	8430		Status	see description				
1.5	**20883**	R	8431		Source intermediate circuit flow temperature		-50	50	°C	1/64
1.5	**20884**	R	8431		Status	see description				
1.5	**20885**	R	8432		Source intermediate circuit return temperature		-50	50	°C	1/64
1.5	**20886**	R	8431		Status	see description				
1.5	**20887**	R	8434		Suction gas temp		-50	180	°C	1/64
1.5	**20888**	R	8431		Status	see description				
1.5	**20889**	R	8435		Evaporation temp		-50	180	°C	1/64
1.5	**20890**	R	8435		Status	see description				
1.5	**20891**	R	8435		Evaporation pressure		-100	500	bar	1/100
1.5	**20892**	R	8435		Status	see description				
1.5	**20893**	R	8436		Superheat		-10	180	°C	1/64
1.5	**20894**	R	8436		Status	see description				
1.5	**20895**	R	8436		Super heat setpoint		0	140	°C	1/64
1.5	**20896**	R	8436		Status	see description				
1.5	**20897**	R	8437		Expansionsventil Verdampfer		0	100	%	1
1.5	**20898**	R	8437		Status	see description				
1.5	**20899**	R	8438		Magnetic valve evaporation	x 0: Off 1: On	0	1		1
1.5	**20900**	R	8438		Status	see description				
1.5	**20901**	R/W	8454		Operating hours extended evaporation temp		0	199'999	h	1/3600
1.5	20902					(32 Bit Data)				
1.5	**20903**	R	8458		Status Smart Grid	1: Wert 1054; 0 x 2: Draw free 3: Draw wished 4: Draw forced	1	4		1
1.5	**20904**	R	8458		Status	see description				
1.5	**20905**	R	8460		Heat pump throughput		0	65535	l/min	1/10
1.5	**20906**	R	8460		Status	see description				
1.5	**20907**	R	8461		Source throughput		0	65535	l/min	1/10
1.5	**20908**	R	8461		Status	see description				
1.5	**20909**	R	8462		Suction gas temp EVI		-50	180	°C	1/64
1.5	**20910**	R	8462		Status	see description				
1.5	**20911**	R	8465		Expansionsventil EVI		0	100	%	1
1.5	**20912**	R	8465		Status	see description				
1.5	**20913**	R	8466		Magnetic valve EVI	x 0: Off 1: On	0	1		1
1.5	**20914**	R	8466		Status	see description				
1.5	**20915**	R	8467		Magn valve injection cap	x 0: Off 1: On	0	1		1
1.5	**20916**	R	8467		Status	see description				
1.5	**20917**	R	8469		Speed ventilator		0	100	%	1
1.5	**20918**	R	8469		Status	see description				
1.5	**20919**	R	8470		State ventilator	x 0: Off 1: On	0	1		1
1.5	**20920**	R	8470		Status	see description				
1.5	**20921**	R	8471		State process reversing valve	x 0: Off 1: On	0	1		1
1.5	**20922**	R	8471		Status	see description				
1.5	**20923**	R	8475		Evaporator temperature		-50	50	°C	1/64
1.5	**20924**	R	8475		Status	see description				
1.5	**20925**	R	8488		Relative humidity air inlet		0	100	%	1
1.5	**20926**	R	8488		Status	see description				
1.5	**20927**	R/W			Modulation condens pump cooling	0: None x 1: Heat pump setpoint 2: Compressor output 3: Temp diff condensor	0	3		1
1.5	**20928**	R/W			Status/Comand	see description				
1.5	**20929**	R/W			Increase source temp min		0	10	°C	1/64
1.5	**20930**	R/W			Required temp diff evaporator cooling mode		1	20	°C	1/64
1.5	**20931**	R/W			Status/Comand	see description				
1.5	**20932**	R/W			Min evaporation temp cooling mode		-50	50	°C	1/64
1.5	**20933**	R/W			Status/Comand	see description				
1.5	**20934**	R/W			Max evaporation temp cooling mode		-50	50	°C	1/64
1.5	**20935**	R/W			Status/Comand	see description				
1.5	**20936**	R/W			Min evaporation temp switching diff		0	30	°C	1/64

1.5	**20937**	R/W			Min evaporation temp increase		0	20	°C	1/64
1.5	**20938**	R/W			Max evaporation temp reduction		0	20	°C	1/64
1.5	**20939**	R/W			Max evaporation temp delay		0	120	s	1
1.5	**20940**	R/W			Supervision soft starter	x 1: None 2: With compr operation	1	2		1
1.5	**20941**	R/W			Supervision low-pressure	1: None x 2: With compr operation	1	2		1
1.5	**20942**	R/W			Supervision high-pressure	1: None x 2: With compr operation	1	2		1
1.5	**20943**	R/W			Supervision overload compressor	1: None x 2: With compr operation	1	2		1
1.5	**20944**	R/W			Supervision 3-phase current/mains	1: None x 2: With compr operation	1	2		1
1.5	**20945**	R/W			Supervision overload source	1: None x 2: With compr operation	1	2		1
1.5	**20946**	R/W			Pressure diff min process reversal		0.1	5	bar	1/10
1.5	**20947**	R/W			Status/Comand	see description				
1.5	**20948**	R/W			Min compr run time prior to process reversal		0	30	s	1
1.5	**20949**	R/W			Status/Comand	see description				
1.5	**20950**	R/W			Delay pressure diff error process reversal		5	120	s	1
1.5	**20951**	R/W			Compressor modulation on process reversal		0	100	%	1
1.5	**20952**	R/W			Status/Comand	see description				
1.5	**20953**	R/W			Basic position process reversing valve	x 0: Last request 1: Heating 2: Cooling 3: None	0	3		1
1.5	**20954**	R/W			Source temp 1 for COP		-25	35	°C	1/64
1.5	**20955**	R/W			Source temp 2 for COP		-25	35	°C	1/64
1.5	**20956**	R/W			Flow temp 1 for COP		25	65	°C	1/64
1.5	**20957**	R/W			Flow temp 2 for COP		25	65	°C	1/64
1.6	**20958**	R/W			COP at source temp 1 and flow temp 1		1	10		1/50
1.6	**20959**	R/W			Status/Comand	see description				
1.6	**20960**	R/W			COP at source temp 1 and flow temp 2		1	10		1/50
1.6	**20961**	R/W			Status/Comand	see description				
1.6	**20962**	R/W			COP at source temp 2 and flow temp 1		1	10		1/50
1.6	**20963**	R/W			Status/Comand	see description				
1.6	**20964**	R/W			COP at source temp 2 and flow temp 2		1	10		1/50
1.6	**20965**	R/W			Status/Comand	see description				
1.5	**20966**	R/W			Compressor kick release		0	100	%	1
1.5	**20967**	R/W			Status/Comand	see description				
1.5	**20968**	R/W			Compressor kick modulation		0	100	%	1
1.5	**20969**	R/W			Compressor kick interval		10	600	min	1
1.5	**20970**	R/W			Compressor kick duration		10	120	s	1
1.5	**20971**	R/W			Defrost with electrical utility lock	0: No x 1: Yes	0	1		1
1.5	**20972**	R/W			Defrost with fan above outside temp at 100% r.h.		1	20	°C	1/64
1.5	**20973**	R/W			Delay forced defrost after power up		0	240	s	1
1.5	**20974**	R/W			Status/Comand	see description				
1.5	**20975**	R/W			Position expansion valve when defrost		0	100	%	1
1.5	**20976**	R/W			Status/Comand	see description				
1.5	**20977**	R/W			Modulation fan/source pump cooling mode	x 0: None 1: Refrig temp liquid 2: Compressor output 3: Temp diff evaporator	0	3		1
1.5	**20978**	R/W			Status/Comand	see description				
1.5	**20979**	R/W			Output limitation with modulation source	x 0: Off 1: Heating mode 2: Cooling mode 3: Heating and cooling mode	0	3		1
1.5	**20980**	R/W			Max deviation suction gas temp		0.5	10	°C	1/64
1.5	**20981**	R/W			Status/Comand	see description				
1.5	**20982**	R/W			Superheat setpoint at source temperature 20°C		0	25	°C	1/64
1.5	**20983**	R/W			Status/Comand	see description				
1.5	**20984**	R/W			Superheat setpoint at source temperature 15°C		0	25	°C	1/64
1.5	**20985**	R/W			Status/Comand	see description				
1.5	**20986**	R/W			Superheat setpoint at source temperature 7°C		0	25	°C	1/64
1.5	**20987**	R/W			Status/Comand	see description				
1.5	**20988**	R/W			Superheat setpoint at source temperature 2°C		0	25	°C	1/64
1.5	**20989**	R/W			Status/Comand	see description				
1.5	**20990**	R/W			Superheat setpoint at source temperature -7°C		0	25	°C	1/64
1.5	**20991**	R/W			Status/Comand	see description				
1.5	**20992**	R/W			Superheat setpoint at source temperature -15°C		0	25	°C	1/64
1.5	**20993**	R/W			Status/Comand	see description				
1.5	**20994**	R/W			Superheat setpoint at source temperature -25°C		0	25	°C	1/64
1.5	**20995**	R/W			Status/Comand	see description				
1.5	**20996**	R/W			Output control with SHC Xp		1	200	°C	1/64
1.5	**20997**	R/W			Output control with SHC Tn		1	650	s	1
1.5	**20998**	R/W			Wait time up to red superheat setp adapt		0	600	s	1
1.5	**20999**	R/W			Min deviation superheat setp adapt		0.1	5	°C	1/64
1.5	**21000**	R/W			Max deviation superheat setp adapt		0.1	5	°C	1/64
1.5	**21001**	R/W			Critical deviation superheat setp adapt		0.1	5	°C	1/64
1.5	**21002**	R/W			Adaption step superheat setp		0.1	5	°C	1/64
1.5	**21003**	R/W			Adaption lock upon compressor start		0	30	min	1
1.5	**21004**	R/W			Adaption lock upon change of superheat setp		0	600	s	1
1.5	**21005**	R/W			Adaption lock upon increase of superheat setp		0	30	min	1
1.5	**21006**	R/W			Delay expansion valve evaporator error		0	255	s	1
1.5	**21007**	R/W			Status/Comand	see description				
1.5	**21008**	R/W			Max increase superheat setpoint adapt		0	10	°C	1/64
1.5	**21009**	R/W			Output limitation with SHC	x 0: Off 1: Heating mode 2: Cooling mode 3: Heating and cooling mode	0	3		1
1.5	**21010**	R/W			Max deviation superheat		0.5	10	°C	1/64
1.5	**21011**	R/W			Status/Comand	see description				
1.5	**21012**	R			State of crankcase heater (K40)	x 0: Off 1: On	0	1		1

1.5	**21013**	R			Status	see description				
1.5	**21014**	R			Drip tray heater K41	x 0: Off 1: On	0	1		1
1.5	**21015**	R			Status	see description				
1.5	**21016**	R			State of source interm circuit pump (Q81)	x 0: Off 1: On	0	1		1
1.5	**21017**	R			Status	see description				
1.5	**21018**	R			State of source interm circuit div valve (Y81)	x 0: Off 1: On	0	1		1
1.5	**21019**	R			Status	see description				
1.5	**21020**	R			State of diverting valve cooling condenser (Y27)	x 0: Off 1: On	0	1		1
1.5	**21021**	R			Status	see description				
1.5	**21022**	R			State of condenser reversing valve (Y91)	x 0: Off 1: On	0	1		1
1.5	**21023**	R			Status	see description				
1.5	**21024**	R			State status information heating (K42)	x 0: Off 1: On	0	1		1
1.5	**21025**	R			Status	see description				
1.5	**21026**	R			State status information cooling (K43)	x 0: Off 1: On	0	1		1
1.5	**21027**	R			Status	see description				
1.5	**21028**	R			State status information DHW (K44)	x 0: Off 1: On	0	1		1
1.5	**21029**	R			Status	see description				
1.5	**21030**	R			State status information generation (K45)	x 0: Off 1: On	0	1		1
1.5	**21031**	R			Status	see description				
1.5	**21032**	R			State fault information generation (K46)	x 0: Off 1: On	0	1		1
1.5	**21033**	R			Status	see description				
1.5	**21034**	R/W			Repetition Error 107:Hot-gas compressor 1		0	50		1
1.5	**21035**	R/W			Status/Comand	see description				
1.5	**21036**	R/W			Repetition Error 108:Hot-gas compressor 2		0	50		1
1.5	**21037**	R/W			Status/Comand	see description				
1.5	**21038**	R/W			Repetition Error 134:Disturbance heat pump		0	50		1
1.5	**21039**	R/W			Status/Comand	see description				
1.5	**21040**	R/W			Repetition Error 204:Fan fault (overload)		0	50		1
1.5	**21041**	R/W			Status/Comand	see description				
1.5	**21042**	R/W			Repetition Error 222:High-pressure HP		0	50		1
1.5	**21043**	R/W			Status/Comand	see description				
1.5	**21044**	R/W			Repetition Error 225:Low-pressure HP		0	50		1
1.5	**21045**	R/W			Status/Comand	see description				
1.5	**21046**	R/W			Repetition Error 226:Compressor 1 overload		0	50		1
1.5	**21047**	R/W			Status/Comand	see description				
1.5	**21048**	R/W			Repetition Error 227:Compressor 2 overload		0	50		1
1.5	**21049**	R/W			Status/Comand	see description				
1.5	**21050**	R/W			Repetition Error 228:Flow switch heat source		0	50		1
1.5	**21051**	R/W			Status/Comand	see description				
1.5	**21052**	R/W			Repetition Error 229:Pressure switch heat source		0	50		1
1.5	**21053**	R/W			Status/Comand	see description				
1.5	**21054**	R/W			Repetition Error 230:Source pump overload		0	50		1
1.5	**21055**	R/W			Status/Comand	see description				
1.5	**21056**	R/W			Rep Error 355/385:Three-phase current/undervolt		0	50		1
1.5	**21057**	R/W			Status/Comand	see description				
1.5	**21058**	R/W			Repetition Error 356:Flow switch consumers		0	50		1
1.5	**21059**	R/W			Status/Comand	see description				
1.5	**21060**	R/W			Repetition Error 358/483: Soft starter		0	50		1
1.5	**21061**	R/W			Status/Comand	see description				
1.5	**21062**	R/W			Repetition Error 491:Max evaporation temp		0	50		1
1.5	**21063**	R/W			Status/Comand	see description				
1.5	**21064**	R/W			Repetition error 504:Press diff process reversal		0	50		1
1.5	**21065**	R/W			Status/Comand	see description				
1.5	**21066**	R/W	7070		HP time maintenance interval		1	240	Month	1
1.5	**21067**	R/W	7070		Status/Comand	see description				
1.5	**21068**	R/W	7072		Max starts compressor 1/hour run		0.1	12		1/10
1.5	**21069**	R/W	7072		Status/Comand	see description				
1.5	**21070**	R/W	7074		Max starts compressor 2/hour run		0.1	12		1/10
1.5	**21071**	R/W	7074		Status/Comand	see description				
1.5	**21072**	R/W	7076		Max differentials condenser max/week		1	250		1
1.5	**21073**	R/W	7076		Status/Comand	see description				
1.5	**21074**	R/W	7078		Max differentials condenser min/week		1	250		1
1.5	**21075**	R/W	7078		Status/Comand	see description				
1.5	**21076**	R/W	7080		Max differentials evaporator max/week		1	250		1
1.5	**21077**	R/W	7080		Status/Comand	see description				
1.5	**21078**	R/W	7082		Max differentials evaporator min/week		1	250		1
1.5	**21079**	R/W	7082		Status/Comand	see description				
1.5	**21080**	R/W	7153		Pumping off refrigerant	x 0: Off 1: On	0	1		1
1.5	**21081**	R/W	7202		Commissioning heat pump	x 0: Off 1: Heating mode 2: Cooling mode	0	2		1
1.5	**21082**	R/W	7207		Output selection heat pump modulating		0	100	%	1
1.5	**21083**	R/W	7212		Output selection heat pump multistage	x 0: Off 1: Compressor 1 2: Compressor 2 3: Compressor 1+2	0	3		1
1.5	**21084**	R/W	7223		Disable heat pump	x 0: Inactive 1: Active	0	1		1
1.5	**21085**	R/W	7226		Monitoring heat pump	x 0: On 1: Critical only	0	1		1
1.5	**21086**	R/W			User Reset	x 0: No 1: Yes	0	1		1
1.5	**21087**	R/W	2956		dT cooling down end evapor		-10	10	°C	1/64
1.5	**21088**	R/W	2956		Status/Comand	see description				

1.5	**21089**	R			Emerson RCC Controler, Operating mode	x 0: Off 1: Cooling 2: Heating 3: Standby 4: Manual	0	4		1
1.5	**21090**	R			Amitime HP Controler, Operating mode	x 0: Standby 1: Cooling 2: Heating 3: Hot water 4: Defrost 5: Base function mode 256: Test standby 257: Test cooling 258: Test heating	0	4		1
1.6	**21091**	R/W			Supervision pressure switch source	1: None 2: With source operation x 3: According to heat source	1	3		1
1.6	**21092**	R/W			Supervision pressure switch source intermed circ	x 1: None 2: With source operation	1	2		1
1.6	**21093**	R/W			El compr. power at source temp 1 and flow temp 1		0	600		1/100
1.6	**21094**	R/W			El compr. power at source temp 1 and flow temp 2		0	600		1/100
1.6	**21095**	R/W			El compr. power at source temp 2 and flow temp 1		0	600		1/100
1.6	**21096**	R/W			El compr. power at source temp 2 and flow temp 2		0	600		1/100
1.6	**21097**	R/W			OT limit compressor power		-25	35	°C	1/64
1.6	**21098**	R/W			Status/Comand	see description				
1.6	**21099**	R/W			Minimum compressor power below OT limit		0	100	%	1
1.6	**21100**	R/W			Minimum compressor power over OT limit		0	100	%	1
1.6	**21101**	R/W			Source protection with substitute sensor	x 0: No 1: Yes	0	1		1
1.6	**21102**	R/W			Supervision external superheat controller	x 1: None 2: With compr operation	1	2		1
1.6	**21103**	R/W			Repetition error 529/530: Superheat controller		0	50		1
1.6	**21104**	R/W			Status/Comand	see description				
	0x7400...0x77FF	BL		Energy meter						
1.0	**29696**	R	3110		Heat delivered		0	9999999	kWh	1
1.0	29697					(32 Bit Data)				
1.0	**29698**	R	3110		Status/Comand	see description				
1.0	**29699**	R	3113		Energy brought in		0	3500000	kWh	1
1.0	29700					(32 Bit Data)				
1.0	**29701**	R	3113		Status/Comand	see description				
1.0	**29702**	R	3116		Performance factor		0	10		1/100
1.0	**29703**	R	3116		Status	see description				
1.0	**29704**	R	3120		Yearly perf factor 1		0	10		1/100
1.0	**29705**	R	3120		Status	see description				
1.0	**29706**	R	3120		Fixed day 1	Year	100	199	Year	1
1.0	**29707**	R	3120			Month	1	12	Month	1
1.0	**29708**	R	3120			Day	1	31	Day	1
1.0	**29709**	R	3120		Status	see description				
1.0	**29710**	R	3121		Heat delivered heating 1		0	9999999	kWh	1
1.0	29711					(32 Bit Data)				
1.0	**29712**	R	3121		Status	see description				
1.0	**29713**	R	3122		Heat delivered DHW 1		0	9999999	kWh	1
1.0	29714					(32 Bit Data)				
1.0	**29715**	R	3122		Status	see description				
1.0	**29716**	R	3124		Energy brought in heating 1		0	3500000	kWh	1
1.0	29717					(32 Bit Data)				
1.0	**29718**	R	3124		Status	see description				
1.0	**29719**	R	3125		Energy brought in DHW 1		0	3500000	kWh	1
1.0	29720					(32 Bit Data)				
1.0	**29721**	R	3125		Status	see description				
1.0	**29722**	R	3127		Yearly perf factor 2		0	10	h:m	1/100
1.0	**29723**	R	3127		Status	see description				
1.0	**29724**	R	3127		Fixed day 2	Year	100	199	Year	1
1.0	**29725**	R	3127			Month	1	12	Month	1
1.0	**29726**	R	3127			Day	1	31	Day	1
1.0	**29727**	R	3127		Status	see description				
1.0	**29728**	R	3128		Heat delivered heating 2		0	9999999	kWh	1
1.0	29729					(32 Bit Data)				
1.0	**29730**	R	3128		Status	see description				
1.0	**29731**	R	3129		Heat delivered DHW 2		0	9999999	kWh	1
1.0	29732					(32 Bit Data)				
1.0	**29733**	R	3129		Status	see description				
1.0	**29734**	R	3131		Energy brought in heating 2		0	3500000	kWh	1
1.0	29735					(32 Bit Data)				
1.0	**29736**	R	3131		Status	see description				
1.0	**29737**	R	3132		Energy brought in DHW 2		0	3500000	kWh	1
1.0	29738					(32 Bit Data)				
1.0	**29739**	R	3132		Status	see description				
1.0	**29740**	R	3134		Yearly perf factor 3		0	10	h:m	1/100
1.0	**29741**	R	3134		Status	see description				
1.0	**29742**	R	3134		Fixed day 3	Year	100	199	Year	1
1.0	**29743**	R	3134			Month	1	12	Month	1
1.0	**29744**	R	3134			Day	1	31	Day	1
1.0	**29745**	R	3134		Status	see description				
1.0	**29746**	R	3135		Heat delivered heating 3		0	9999999	kWh	1
1.0	29747					(32 Bit Data)				
1.0	**29748**	R	3135		Status	see description				
1.0	**29749**	R	3136		Heat delivered DHW 3		0	9999999	kWh	1
1.0	29750									
1.0	**29751**	R	3136		Status	see description				
1.0	**29752**	R	3138		Energy brought in heating 3		0	3500000	kWh	1
1.0	29753					(32 Bit Data)				
1.0	**29754**	R	3138		Status	see description				

1.0	**29755**	R	3139		Energy brought in DHW 3		0	3500000	kWh	1
1.0	29756					(32 Bit Data)				
1.0	**29757**	R	3139		Status	see description				
1.0	**29758**	R	3141		Yearly perf factor 4		0	10	h:m	1/100
1.0	**29759**	R	3141		Status	see description				
1.0	**29760**	R	3141		Fixed day 4	Year	100	199	Year	1
1.0	**29761**	R	3141			Month	1	12	Month	1
1.0	**29762**	R	3141			Day	1	31	Day	1
1.0	**29763**	R	3141		Status	see description				
1.0	**29764**	R	3142		Heat delivered heating 4		0	9999999	kWh	1
1.0	29765					(32 Bit Data)				
1.0	**29766**	R	3142		Status	see description				
1.0	**29767**	R	3143		Heat delivered DHW 4		0	9999999	kWh	1
1.0	29768					(32 Bit Data)				
1.0	**29769**	R	3143		Status	see description				
1.0	**29770**	R	3145		Energy brought in heating 4		0	3500000	kWh	1
1.0	29771					(32 Bit Data)				
1.0	**29772**	R	3145		Status	see description				
1.0	**29773**	R	3146		Energy brought in DHW 4		0	3500000	kWh	1
1.0	29774					(32 Bit Data)				
1.0	**29775**	R	3146		Status	see description				
1.0	**29776**	R	3148		Yearly perf factor 5		0	10		1/100
1.0	**29777**	R	3148		Status	see description				
1.0	**29778**	R	3148		Fixed day 5	Year	100	199	Year	1
1.0	**29779**	R	3148			Month	1	12	Month	1
1.0	**29780**	R	3148			Day	1	31	Day	1
1.0	**29781**	R	3148		Status	see description				
1.0	**29782**	R	3149		Heat delivered heating 5		0	9999999	kWh	1
1.0	29783					(32 Bit Data)				
1.0	**29784**	R	3149		Status	see description				
1.0	**29785**	R	3150		Heat delivered DHW 5		0	9999999	kWh	1
1.0	29786					(32 Bit Data)				
1.0	**29787**	R	3150		Status	see description				
1.0	**29788**	R	3152		Energy brought in heating 5		0	3500000	kWh	1
1.0	29789					(32 Bit Data)				
1.0	**29790**	R	3152		Status	see description				
1.0	**29791**	R	3153		Energy brought in DHW 5		0	3500000	kWh	1
1.0	29792					(32 Bit Data)				
1.0	**29793**	R	3153		Status	see description				
1.0	**29794**	R	3155		Yearly perf factor 6		0	10		1/100
1.0	**29795**	R	3155		Status	see description				
1.0	**29796**	R	3155		Fixed day 6	Year	100	199	Year	1
1.0	**29797**	R	3155			Month	1	12	Month	1
1.0	**29798**	R	3155			Day	1	31	Day	1
1.0	**29799**	R	3155		Status	see description				
1.0	**29800**	R	3156		Heat delivered heating 6		0	9999999	kWh	1
1.0	29801					(32 Bit Data)				
1.0	**29802**	R	3156		Status	see description				
1.0	**29803**	R	3157		Heat delivered DHW 6		0	9999999	kWh	1
1.0	29804					(32 Bit Data)				
1.0	**29805**	R	3157		Status	see description				
1.0	**29806**	R	3159		Energy brought in heating 6		0	3500000	kWh	1
1.0	29807					(32 Bit Data)				
1.0	**29808**	R	3159		Status	see description				
1.0	**29809**	R	3160		Energy brought in DHW 6		0	3500000	kWh	1
1.0	29810					(32 Bit Data)				
1.0	**29811**	R	3160		Status	see description				
1.0	**29812**	R	3162		Yearly perf factor 7		0	10	h:m	1/100
1.0	**29813**	R	3162		Status	see description				
1.0	**29814**	R	3162		Fixed day 7	Year	100	199	Year	1
1.0	**29815**	R	3162			Month	1	12	Month	1
1.0	**29816**	R	3162			Day	1	31	Day	1
1.0	**29817**	R	3162		Status	see description				
1.0	**29818**	R	3163		Heat delivered heating 7		0	9999999	kWh	1
1.0	29819					(32 Bit Data)				
1.0	**29820**	R	3162		Status	see description				
1.0	**29821**	R	3164		Heat delivered DHW 7		0	9999999	kWh	1
1.0	29822					(32 Bit Data)				
1.0	**29823**	R	3164		Status	see description				
1.0	**29824**	R	3166		Energy brought in heating 7		0	3500000	kWh	1
1.0	29825					(32 Bit Data)				
1.0	**29826**	R	3166		Status	see description				
1.0	**29827**	R	3167		Energy brought in DHW 7		0	3500000	kWh	1
1.0	29828					(32 Bit Data)				
1.0	**29829**	R	3167		Status	see description				
1.0	**29830**	R	3169		Yearly perf factor 8		0	10	h:m	1/100
1.0	**29831**	R	3169		Status	see description				
1.0	**29832**	R	3169		Fixed day 8	Year	100	199	Year	1
1.0	**29833**	R	3169			Month	1	12	Month	1
1.0	**29834**	R	3169			Day	1	31	Day	1
1.0	**29835**	R	3169		Status	see description				
1.0	**29836**	R	3170		Heat delivered heating 8		0	9999999	kWh	1
1.0	29837					(32 Bit Data)				
1.0	**29838**	R	3170		Status	see description				
1.0	**29839**	R	3171		Heat delivered DHW 8		0	9999999	kWh	1
1.0	29840					(32 Bit Data)				
1.0	**29841**	R	3171		Status	see description				
1.0	**29842**	R	3173		Energy brought in heating 8		0	3500000	kWh	1
1.0	29843					(32 Bit Data)				
1.0	**29844**	R	3173		Status	see description				
1.0	**29845**	R	3174		Energy brought in DHW 8		0	3500000	kWh	1
1.0	29846					(32 Bit Data)				
1.0	**29847**	R	3174		Status	see description				
1.0	**29848**	R	3176		Yearly perf factor 9		0	10	h:m	1/100
1.0	**29849**	R	3176		Status	see description				
1.0	**29850**	R	3176		Fixed day 9	Year	100	199	Year	1

1.0	**29851**	R	3176			Month	1	12	Month	1
1.0	**29852**	R	3176			Day	1	31	Day	1
1.0	**29853**	R	3176		Status	see description				
1.0	**29854**	R	3177		Heat delivered heating 9		0	9999999	kWh	1
1.0	29855					(32 Bit Data)				
1.0	**29856**	R	3177		Status	see description				
1.0	**29857**	R	3178		Heat delivered DHW 9		0	9999999	kWh	1
1.0	29858					(32 Bit Data)				
1.0	**29859**	R	3178		Status	see description				
1.0	**29860**	R	3180		Energy brought in heating 9		0	3500000	kWh	1
1.0	29861					(32 Bit Data)				
1.0	**29862**	R	3180		Status	see description				
1.0	**29863**	R	3181		Energy brought in DHW 9		0	3500000	kWh	1
1.0	29864					(32 Bit Data)				
1.0	**29865**	R	3181		Status	see description				
1.0	**29866**	R	3183		Yearly perf factor 10		0	10	h:m	1/100
1.0	**29867**	R	3183		Status	see description				
1.0	**29868**	R	3183		Fixed day 10	Year	100	199	Year	1
1.0	**29869**	R	3183			Month	1	12	Month	1
1.0	**29870**	R	3183			Day	1	31	Day	1
1.0	**29871**	R	3183		Status	see description				
1.0	**29872**	R	3184		Heat delivered heating 10		0	9999999	kWh	1
1.0	29873					(32 Bit Data)				
1.0	**29874**	R	3184		Status	see description				
1.0	**29875**	R	3185		Heat delivered DHW 10		0	9999999	kWh	1
1.0	29876					(32 Bit Data)				
1.0	**29877**	R	3185		Status	see description				
1.0	**29878**	R	3187		Energy brought in heat 10		0	3500000	kWh	1
1.0	29879					(32 Bit Data)				
1.0	**29880**	R	3187		Status	see description				
1.0	**29881**	R	3188		Energy brought in DHW 10		0	3500000	kWh	1
1.0	29882					(32 Bit Data)				
1.0	**29883**	R	3188		Status	see description				
1.5	**29884**	R/W	3090		Pulse count heat	x 0: None 1: With input H1 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**29885**	R/W	3092		Pulse unit heat	x 0: None 1: kWh 2: Liter	0	2		1
1.5	**29886**	R/W	3093		Pulse value heat numer		1	1000		1
1.5	**29887**	R/W	3094		Pulse value heat denom		1	1000		1
1.5	**29888**	R/W	3095		Flow measurement heat	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**29889**	R/W	3097		Flow heating		10	60000	l/h	1
1.5	**29890**	R/W	3097		Status/Comand	see description				
1.5	**29891**	R/W	3098		Flow DHW		10	60000	l/h	1
1.5	**29892**	R/W	3098		Status/Comand	see description				
1.5	**29893**	R/W	3100		Pulse count energy	x 0: None 1: With input H1 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**29894**	R/W	3102		Pulse unit energy	x 0: None 1: kWh 2: --- inadmissable setting --- 3: m3	0	3		1
1.5	**29895**	R/W	3103		Pulse value energy numer		1	1000		1
1.5	**29896**	R/W	3104		Pulse value energy denom		1	1000		1
1.5	**29897**	R/W	3106		Mean gas energy content		1	100	kWh/m3	1/10
1.5	**29898**	R/W	3108		Electrical source output		0.01	10	kW	1/100
1.5	**29899**	R/W	3108		Status	see description				
1.5	**29900**	R/W	3109		Count el imm heater flow	x 0: None 1: Heat delivered 2: Energy brought in 3: Both	0	3		1
1.5	**29901**	R	3112		Source heat absorbed		0	3500000		1
1.5	29902					(32 Bit Data)				
1.5	**29903**	R	3112		Status	see description				
1.5	**29904**	R/W	3119		Fixed day yearly perf fact		1	12	Month	1

1.5	**29905**	R/W	3119		Fixed day yearly perf fact		1	31	Day	1
1.5	**29906**	R	3123		Refrigeration delivered 1		0	9999999	kWh	1
1.5	29907					(32 Bit Data)				
1.5	**29908**	R	3123		Status	see description				
1.5	**29909**	R	3126		Energy brought in cooling 1		0	3500000	kWh	1
1.5	29910					(32 Bit Data)				
1.5	**29911**	R	3126		Status	see description				
1.5	**29912**	R	3130		Refrigeration delivered 2		0	9999999	kWh	1
1.5	29913					(32 Bit Data)				
1.5	**29914**	R	3130		Status	see description				
1.5	**29915**	R	3133		Energy brought in cooling 2		0	3500000	kWh	1
1.5	29916					(32 Bit Data)				
1.5	**29917**	R	3133		Status	see description				
1.5	**29918**	R	3137		Refrigeration delivered 3		0	9999999	kWh	1
1.5	29919					(32 Bit Data)				
1.5	**29920**	R	3137		Status	see description				
1.5	**29921**	R	3140		Energy brought in cooling 3		0	3500000	kWh	1
1.5	29922					(32 Bit Data)				
1.5	**29923**	R	3140		Status	see description				
1.5	**29924**	R	3144		Refrigeration delivered 4		0	9999999	kWh	1
1.5	29925					(32 Bit Data)				
1.5	**29926**	R	3144		Status	see description				
1.5	**29927**	R	3147		Energy brought in cooling 4		0	3500000	kWh	1
1.5	29928					(32 Bit Data)				
1.5	**29929**	R	3147		Status	see description				
1.5	**29930**	R	3151		Refrigeration delivered 5		0	9999999	kWh	1
1.5	29931					(32 Bit Data)				
1.5	**29932**	R	3151		Status	see description				
1.5	**29933**	R	3154		Energy brought in cooling 5		0	3500000	kWh	1
1.5	29934					(32 Bit Data)				
1.5	**29935**	R	3154		Status	see description				
1.5	**29936**	R	3158		Refrigeration delivered 6		0	9999999	kWh	1
1.5	29937					(32 Bit Data)				
1.5	**29938**	R	3158		Status	see description				
1.5	**29939**	R	3161		Energy brought in cooling 6		0	3500000	kWh	1
1.5	29940					(32 Bit Data)				
1.5	**29941**	R	3161		Status	see description				
1.5	**29942**	R	3165		Refrigeration delivered 7		0	9999999	kWh	1
1.5	29943					(32 Bit Data)				
1.5	**29944**	R	3165		Status	see description				
1.5	**29945**	R	3168		Energy brought in cooling 7		0	3500000	kWh	1
1.5	29946					(32 Bit Data)				
1.5	**29947**	R	3168		Status	see description				
1.5	**29948**	R	3172		Refrigeration delivered 8		0	9999999	kWh	1
1.5	29949					(32 Bit Data)				
1.5	**29950**	R	3172		Status	see description				
1.5	**29951**	R	3175		Energy brought in cooling 8		0	3500000	kWh	1
1.5	29952					(32 Bit Data)				
1.5	**29953**	R	3175		Status	see description				
1.5	**29954**	R	3179		Refrigeration delivered 9		0	9999999	kWh	1
1.5	29955					(32 Bit Data)				
1.5	**29956**	R	3179		Status	see description				
1.5	**29957**	R	3182		Energy brought in cooling 9		0	3500000	kWh	1
1.5	29958					(32 Bit Data)				
1.5	**29959**	R	3182		Status	see description				
1.5	**29960**	R	3186		Refrigeration delivered 10		0	9999999	kWh	1
1.5	29961					(32 Bit Data)				
1.5	**29962**	R	3186		Status	see description				
1.5	**29963**	R	3189		Energy brought in cooling 10		0	3500000	kWh	1
1.5	29964					(32 Bit Data)				
1.5	**29965**	R	3189		Status	see description				
1.5	**29966**	R/W	3190		Reset fixed day storage	x 0: No 1: Yes	0	1		1
1.5	**29967**	R/W	3192		Count el imm heater DHW	x 0: None 1: Heat delivered 2: Energy brought in 3: Both	0	3		1
1.5	**29968**	R/W	3193		Count el imm heater buffer	x 0: None 1: Heat delivered 2: Energy brought in 3: Both	0	3		1
1.5	**29969**	R/W	3195		Electric pump power heating		0.01	10	kW	1/100
1.5	**29970**	R/W	3195		Status/Comand	see description				
1.5	**29971**	R/W	3196		Electric pump power DHW		0.01	10	kW	1/100
1.5	**29972**	R/W	3196		Status/Comand	see description				
1.5	**29973**	R/W	3250		Pulse count source	x 0: None 1: With input H1 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**29974**	R/W	3252		Pulse unit source	x 0: None 1: kWh 2: Liter	0	2		1
1.5	**29975**	R/W	3253		Pulse value source numer		1	1000		1
1.5	**29976**	R/W	3254		Pulse value source denom		1	1000		1

1.5	**29977**	R/W	3255		Flow measurement source	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**29978**	R/W	3257		Flow source		10	60000	l/h	1
1.5	**29979**	R/W	3257		Status/Comand	see description				
1.5	**29980**	R/W	3260		Antifreeze source	x 1: Wert 470; 0 2: Ethylenglycol 3: Propylenglycol 4: Mixture Ethylen- and Propylenglycol	1	4		1
1.5	**29981**	R/W	3261		Antifreeze concentr source		1	100	%	1
1.5	**29982**	R/W	3264		Energy price high-tariff		1	1000		1
1.5	**29983**	R/W	3264		Status/Comand	see description				
1.5	**29984**	R/W	3265		Energy price low-tariff/smart grid wish		1	1000		1
1.5	**29985**	R/W	3265		Status/Comand	see description				
1.5	**29986**	R/W	3266		Energy price smart grid imposed		1	1000		1
1.5	**29987**	R/W	3266		Status/Comand	see description				
1.5	**29988**	R/W	3267		Energy price with alternative source		1	1000		1
1.5	**29989**	R/W	3267		Status/Comand	see description				
1.6	**29990**	R/W	3197		Electric power compressor		0.01	10	kW	1/100
1.6	**29991**	R/W	3197		Status/Comand	see description				
	0x7800...0x7BFF	BL		Supplementary source						
1.0	**30720**	R/W	3700		Release below outside temp		-50	50	°C	1/64
1.0	**30721**	R/W	3700		Status/Comand	see description				
1.0	**30722**	R/W	3701		Release above outside temp		-50	50	°C	1/64
1.0	**30723**	R/W	3701		Status/Comand	see description				
1.0	**30724**	R	8586		Suppl source setpoint		0	140	°C	1/64
1.0	**30725**	R	8586		Status/Comand	see description				
1.0	**30726**	R	8022		State supplementary source	see description: status codes	0	1000		1
1.6	**30727**	R/W	3690		Setpoint incr main source		0	60	°C	1/64
1.3	**30728**	R/W	3705		Supplementary source overrun time		0	120	min	1
1.3	**30729**	R/W	3720		Supplementary source switching integral		1	500	°C*min	1
1.3	**30730**	R/W	3720		Status/Comand	see description				
1.3	**30731**	R/W	3722		Supplementary source switching diff off		0	20	°C	1/64
1.3	**30732**	R/W	3723		Supplementary source locking time		1	120	min	1
1.3	**30733**	R/W	3723		Status/Comand	see description				
1.5	**30734**	R/W	3691		Ouput limit main source		1	100	%	1
1.5	**30735**	R/W	3691		Status/Comand	see description				
1.5	**30736**	R/W	3692		Suppl source with DHW charging	0: Locked 1: Substitute x 2: Complement 3: Instantly 4: First 5: Alone	0	5		1
1.5	**30737**	R/W	3694		OT limit with DHW charging	0: Disregard x 1: Note	0	1		1
1.5	**30738**	R/W	3710		Suppl source setpoint min		0	80	°C	1/64
1.5	**30739**	R/W	3710		Status/Comand	see description				
1.5	**30740**	R/W	3718		Supplementary source release integral		1	500	°C*min	1
1.5	**30741**	R/W	3718		Status/Comand	see description				
1.5	**30742**	R/W	3719		Supplementary source reset integral		1	500	°C*min	1
1.5	**30743**	R/W	3719		Status/Comand	see description				
1.5	**30744**	R/W	3725		Suppl source control sensor	x 1: None 2: Buffer sensor B4	1	2		1
1.5	**30745**	R/W	3750		Producer type	0: Other 1: Solid fuel boiler 2: Heat pump x 3: Oil/gas boiler	0	3		1
1.5	**30746**	R/W	3755		Delay lockout position		1	40	min	1
1.5	**30747**	R/W	3755		Status/Comand	see description				
1.5	**30748**	R/W			Switching differential ouput limit main source		1	100	%	1
1.5	**30749**	R/W			Use of supplementary source	x 0: Supplementary 1: Hybrid	0	1		
1.5	**30750**	R/W			Flow temperature hybrid source	x 1: None 2: Mean value flow temp HP/boiler temp 3: Flow temp heat pump 4: Boiler temp	1	4		
1.5	**30751**	R/W			Pump hybrid source	x 0: Separately 1: Boiler pump Q1 2: Condenser pump Q9	0	2		
1.5	**30752**	R	8585		Control temperature		0	140	°C	1/64
1.5	**30753**	R	8585		Status	see description				
1.5	**30754**	R			Status heat demand (K27)	x 0: Off 1: On	0	1		
1.5	**30755**	R			Status	see description				
1.5	**30756**	R			State suppl source control (K32)	x 0: Off 1: On	0	1		
1.5	**30757**	R			Status	see description				
1.6	**30758**	R/W	3695		Supplementary source release with DHW charging	x 0: According to release 1: With load only 2: With load or heating	0	2		
1.6	**30759**	R/W	3696		Supplementary source lock with DHW charging	x 0: With end of charging 1: No heating and B3 hot 2: Sensor B3 hot	0	2		
1.6	**30760**	R/W	3697		Supplementary source with DHW push	x 0: Off 1: On	0	1		
1.6	**30761**	R/W	3698		Supplementary source with warmer/cooler function	x 0: Off 1: On	0	1		

1.6	**30762**	R/W	3704		Supplementary source with heat generation lock	x 0: Off 1: On DHW 2: On	0	2		
1.6	**30763**	R/W	3711		Supplementary source setpoint maximum		0	140	°C	1/64
1.6	**30764**	R/W	3712		Setpoint chimney sweep		0	80	°C	1/64
1.6	**30765**	R/W			Neutral zone switching integral		0	20	°C	1/64
1.6	**30766**	R/W	8590		Hours run suppl source		0	199'999	h	1/3600
1.6	30767					(32 Bit Data)				
	0x7C00...0x7FFF	BL		Solid fuel boiler						
1.0	**31744**	R/W	8570		Hours run solid fuel boiler		0	199'999	h	1/3600
1.0	31745					(32 Bit Data)				
1.0	**31746**	R	8560		Solid fuel boiler temp		0	140	°C	1/64
1.0	**31747**	R	8560		Status	see description				
1.0	**31748**	R	8561		Solid fuel boiler setpoint		0	140	°C	1/64
1.0	**31749**	R	8561		Status	see description				
1.0	**31750**	R	8563		Solid fuel boiler return temp		0	140	°C	1/64
1.0	**31751**	R	8563		Status	see description				
1.0	**31752**	R	8008		State solid fuel boiler	see description: status codes	0	1000		1
1.3	**31753**	R/W	4110		Min solid fuel boiler setpoint		8	120	°C	1/64
1.3	**31754**	R/W	4130		Temp differential on solid fuel boiler		1	40	°C	1/64
1.5	**31755**	R/W	4102		Solid fuel boiler locks other producers	0: Off x 1: On	0	1		1
1.5	**31756**	R/W	4103		Solid fuel boiler charg prio DHW stor tank	x 0: Off 1: On	0	1		1
1.5	**31757**	R/W	4114		Temperature stroke min		0	40	°C	1/64
1.5	**31758**	R/W	4134		Solid fuel boiler connection DHW stor tank	x 0: None 1: With sensor B3 2: With sensor B31 3: With sensor B3 and B31	0	3		1
1.5	**31759**	R/W	4135		Solid fuel boiler temp setp DHW charg	x 1: Wert 853; 0 2: Storage tank setpoint 3: Boiler temp setpoint min	1	3		1
1.5	**31760**	R/W	4136		Solid fuel boiler DHW charging with Q3	0: No x 1: Yes	0	1		1
1.5	**31761**	R/W	4137		Solid fuel boiler connection buffer	0: None 1: With B4 2: With B42/B41 x 3: With B4 and B42/B41	0	3		1
1.5	**31762**	R/W	4138		Solid fuel boiler temp setp buffer charg	x 1: Wert 853; 0 2: Storage tank setpoint 3: Boiler temp setpoint min	1	3		1
1.5	**31763**	R/W	4140		Pump overrun time solid fuel boiler		0	120	min	1
1.5	**31764**	R/W	4141		Overtemperature drop solid fuel boiler		60	140	°C	1/64
1.5	**31765**	R/W	4153		Return temp limitation		8	95	°C	1/64
1.5	**31766**	R/W	4158		Flow influence to boiler return control	x 0: Off 1: On	0	1		1
1.5	**31767**	R/W	4163		Actuator running time return temp limitation		30	650	s	1
1.5	**31768**	R/W	4164		P-band (Xp) return temp limitation		1	100	°C	1/64
1.5	**31769**	R/W	4165		Integral action time (Tn) return temp limitation		10	650	s	1
1.5	**31770**	R/W	4170		Frost protection for plant solid fuel boiler	x 0: Off 1: On	0	1		1
1.5	**31771**	R/W	4190		Solid fuel boiler residual heat fct dur max		5	60	min	1
1.5	**31772**	R/W	4190		Status/Comand	see description				
1.5	**31773**	R/W	4192		Solid fuel boiler residual heat fct trigg	x 0: Once 1: Several times	0	1		1
1.5	**31774**	R/W	4201		Solid fuel boiler pump speed min		0	100	%	1
1.5	**31775**	R/W	4202		Solid fuel boiler pump speed max		0	100	%	1
1.5	**31776**	R/W	4203		Solid fuel boiler pump speed P-band XP		1	100	°C	1/64
1.5	**31777**	R/W	4204		Solid fuel boiler pump speed Tn		1	650	s	1
1.5	**31778**	R	8564		Solid fuel boiler return setp		0	140	°C	1/64
1.5	**31779**	R	8568		Speed solid fuel boiler pump		0	100	%	1
1.5	**31780**	R	8568		Status	see description				
1.5	**31781**	R			Status solar pump ext. Exchanger K9	x 0: Off 1: On	0	1		1
1.5	**31782**	R			Status	see description				
1.5	**31783**	R			Status solar actuator buffer (K8)	x 0: Off 1: On	0	1		1
1.5	**31784**	R			Status	see description				
1.5	**31785**	R			Status solar actuator pool (K18)	x 0: Off 1: On	0	1		1
1.5	**31786**	R			Status	see description				
	0x8000...0x83FF	BL		Solar						
1.0	**32768**	R/W	3810		Temp diff on		0	40	°C	1/64
1.0	**32769**	R/W	3811		Temp diff off		0	40	°C	1/64
1.0	**32770**	R/W	3812		Charg temp min DHW st tank		8	95	°C	1/64
1.0	**32771**	R/w	3812		Status/Comand	see description				
1.0	**32772**	R/W	3813		Temp diff on buffer		0	40	°C	1/64
1.0	**32773**	R/W	3813		Status/Comand	see description				
1.0	**32774**	R/W	3814		Temp diff off buffer		0	40	°C	1/64
1.0	**32775**	R/W	3814		Status/Comand	see description				
1.0	**32776**	R/W	3815		Charging temp min buffer		8	95	°C	1/64
1.0	**32777**	R/W	3815		Status/Comand	see description				
1.0	**32778**	R/W	3816		Temp diff on swi pool		0	40	°C	1/64
1.0	**32779**	R/W	3816		Status/Comand	see description				
1.0	**32780**	R/W	3817		Temp diff off swi pool		0	40	°C	1/64
1.0	**32781**	R/W	3817		Status/Comand	see description				
1.0	**32782**	R/W	3818		Charging temp min swi pool		8	95	°C	1/64
1.0	**32783**	R/W	3818		Status/Comand	see description				
1.0	**32784**	R	8510		Collector temp 1		-28	350	°C	1/64
1.0	**32785**	R	8510		Status	see description				
1.0	**32786**	R	8519		Solar flow temp		-28	350	°C	1/64
1.0	**32787**	R	8519		Status	see description				
1.0	**32788**	R	8520		Solar return temp		-28	350	°C	1/64
1.0	**32789**	R	8520		Status	see description				
1.0	**32790**	R	8526		24-hour yield solar energy		0	999.9	kWh	1/10
1.0	**32791**	R	8526		Status	see description				

1.5	**32792**	R/W	8527		Total yield solar energy		0	199999	kWh	1/10
	32793					(32 Bit Data)				
1.0	**32794**	R	8527		Status/Comand	see description				
1.0	**32795**	R/W	8530		Hours run solar yield		0	199'999	h	1/3600
1.0	32796					(32 Bit Data)				
1.0	**32797**	R/W	8531		Hours run collect overtemp		0	199'999	h	1/3600
1.0	32798					(32 Bit Data)				
1.0	**32799**	R	8547		Collector temp 2		-28	350	°C	1/64
1.0	**32800**	R	8547		Status	see description				
1.0	**32801**	R	8007		State solar	see description: status codes	0	1000		1
1.5	**32802**	R/W	3822		Charging priority storage	0: None x 1: DHW storage tank 2: Buffer	0	2		1
1.5	**32803**	R/W	3825		Charging time relative priority		2	60	min	1
1.5	**32804**	R/W	3825		Status/Comand	see description				
1.5	**32805**	R/W	3826		Wait time relative priority		1	40	min	1
1.5	**32806**	R/W	3827		Wait time parallel operation		0	40	min	1
1.5	**32807**	R/W	3827		Status/Comand	see description				
1.5	**32808**	R/W	3828		Start delay secondary pump		0	600	s	1
1.5	**32809**	R/W	3830		Collector Start function		5	60	min	1
1.5	**32810**	R/W	3830		Status/Comand	see description				
1.5	**32811**	R/W	3831		Min collector pump running time		5	120	s	1
1.5	**32812**	R/W	3832		Collector Start function on		00:00	23:50	h:m	1/60
1.5	**32813**	R/W	3833		Collector Start function off		00:00	23:50	h:m	1/60
1.5	**32814**	R/W	3834		Collector Start function gradient		1	20	min/°C	1
1.5	**32815**	R/W	3834		Status/Comand	see description				
1.5	**32816**	R/W	3835		Min collector temp start fct		0	30	°C	1/64
1.5	**32817**	R/W	3835		Status/Comand	see description				
1.5	**32818**	R/W	3840		Collector frost protection temp		-20	5	°C	1/64
1.5	**32819**	R/W	3840		Status/Comand	see description				
1.5	**32820**	R/W	3850		Collector overtemperature protection		30	350	°C	1/64
1.5	**32821**	R/W	3850		Status/Comand	see description				
1.5	**32822**	R/W	3860		Evaporation temperature of heat carrier		60	350	°C	1/64
1.5	**32823**	R/W	3860		Status/Comand	see description				
1.5	**32824**	R/W	3862		Impact evaporation superv	x 0: On own collector pump 1: On both collector pumps	0	1		1
1.5	**32825**	R/W	3870		Pump speed min solar		0	100	%	1
1.5	**32826**	R/W	3871		Pump speed max solar		0	100	%	1
1.5	**32827**	R/W	3872		Pump speed P-band XP solar		1	100	°C	1/64
1.5	**32828**	R/W	3873		Pump speed Integral action time Tn solar		1	650	s	1
1.5	**32829**	R/W	3880		Type of antifreeze added	x 1: Wert 470; 0 2: Ethylenglycol 3: Propylenglycol 4: Mixture Ethylen- and Propylenglycol	1	4		1
1.5	**32830**	R/W	3881		Antifreeze concentration		1	100	%	1
1.5	**32831**	R/W	3884		Volumetric flow solar pump		10	1500	l/h	1
1.5	**32832**	R/W	3884		Status/Comand	see description				
1.5	**32833**	R/W	3886		Pulse count yield	x 0: None 1: With input H1 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3 12: With input H31 13: With input H32 14: With input H33	0	14		1
1.5	**32834**	R/W	3887		Pulse unit yield	x 0: None 1: kWh 2: Liter	0	2		1
1.5	**32835**	R/W	3888		Pulse value yield numer		1	1000		1
1.5	**32836**	R/W	3889		Pulse value yield denom		1	1000		1
1.5	**32837**	R/W	3891		Flow measurement yield	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**32838**	R/W	3896		Readj solar flow sensor B63		-20	20	°C	1/64
1.5	**32839**	R/W	3897		Readj solar return sensor B64		-20	20	°C	1/64
1.5	**32840**	R	8499		Status collector pump 1 (Q5)	x 0: Off 1: On	0	1		1
1.5	**32841**	R	8499		Status	see description				
1.5	**32842**	R	8505		Speed collector pump 1		0	100	%	1
1.5	**32843**	R	8505		Status	see description				
1.5	**32844**	R	8506		Speed solar pump ext. exchanger		0	100	%	1
1.5	**32845**	R	8506		Status	see description				
1.5	**32846**	R	8507		Speed solar pump buffer		0	100	%	1
1.5	**32847**	R	8507		Status	see description				
1.5	**32848**	R	8508		Speed solar pump pool		0	100	%	1
1.5	**32849**	R	8508		Status	see description				
1.5	**32850**	R/W	8511		Collector temp max actual value 1 (B6)		-28	350	°C	1/64
1.5	**32851**	R	8511		Status	see description				
1.5	**32852**	R/W	8512		Collector temp min actual value 1 (B6)		-28	350	°C	1/64
1.5	**32853**	R	8512		Status	see description				

1.5	**32854**	R	8513		Temp differential collector 1/DHW		-168	350	°C	1/64
1.5	**32855**	R	8513		Status	see description				
1.5	**32856**	R	8514		Temp differential collector 1/buffer		-168	350	°C	1/64
1.5	**32857**	R	8514		Status	see description				
1.5	**32858**	R	8515		Temp differential collector 1/pool		-168	350	°C	1/64
1.5	**32859**	R	8515		Status	see description				
1.5	**32860**	R	8521		Solar throughput		0	65535	l/min	1/10
1.5	**32861**	R	8521		Status	see description				
1.5	**32862**	R	8542		Status collector pump 2 (Q16)	x 0: Off 1: On	0	1		1
1.5	**32863**	R	8542		Status	see description				
1.5	**32864**	R	8543		Speed collector pump 2		0	100	%	1
1.5	**32865**	R	8543		Status	see description				
1.5	**32866**	R/W	8548		Collector temp max actual value 2 (B61)		-28	350	°C	1/64
1.5	**32867**	R	8548		Status	see description				
1.5	**32868**	R/W	8549		Collector temp min actual value 2 (B61)		-28	350	°C	1/64
1.5	**32869**	R	8549		Status	see description				
1.5	**32870**	R	8550		Temp differential collector 2/DHW		-168	350	°C	1/64
1.5	**32871**	R	8550		Status	see description				
1.5	**32872**	R	8551		Temp differential collector 2/buffer		-168	350	°C	1/64
1.5	**32873**	R	8551		Status	see description				
1.5	**32874**	R	8552		Temp differential collector 2/pool		-168	350	°C	1/64
1.5	**32875**	R	8552		Status	see description				
1.5	**32876**	R			Status solar pump ext. Exchanger K9	x 0: Off 1: On	0	1		1
1.5	**32877**	R			Status	see description				
1.5	**32878**	R			Status solar actuator buffer (K8)	x 0: Off 1: On	0	1		1
1.5	**32879**	R			Status	see description				
1.5	**32880**	R			Status solar actuator pool (K18)	x 0: Off 1: On	0	1		1
1.5	**32881**	R			Status	see description				
	0x8800..0x8BFF	BL		Cascade						
1.0	**34816**	R	8100		Priority source 1		0	16		1
1.0	**34817**	R	8101		State source 1	x 0: Missing 1: Faulty 2: Manual control active 3: Heat generation lock active 4: Chimney sweep funct active 5: Temporarily unavailable 6: Outside temp limit active 7: Not released 8: Released	0	8		1
1.0	**34818**	R	8102		Priority source 2		0	16		1
1.0	**34819**	R	8103		State source 2	x 0: Missing …. 8: Released	0	8		1
1.0	**34820**	R	8104		Priority source 3		0	16		1
1.0	**34821**	R	8105		State source 3	x 0: Missing …. 8: Released	0	8		1
1.0	**34822**	R	8106		Priority source 4		0	16		1
1.0	**34823**	R	8107		State source 4	x 0: Missing …. 8: Released	0	8		1
1.0	**34824**	R	8108		Priority source 5		0	16		1
1.0	**34825**	R	8109		State source 5	x 0: Missing …. 8: Released	0	8		1
1.0	**34826**	R	8110		Priority source 6		0	16		1
1.0	**34827**	R	8111		State source 6	x 0: Missing …. 8: Released	0	8		1
1.0	**34828**	R	8112		Priority source 7		0	16		1
1.0	**34829**	R	8113		State source 7	x 0: Missing …. 8: Released	0	8		1
1.0	**34830**	R	8114		Priority source 8		0	16		1
1.0	**34831**	R	8115		State source 8	x 0: Missing …. 8: Released	0	8		1
1.0	**34832**	R	8116		Priority source 9		0	16		1
1.0	**34833**	R	8117		State source 9	x 0: Missing …. 8: Released	0	8		1
1.0	**34834**	R	8118		Priority source 10		0	16		1
1.0	**34835**	R	8119		State source 10	x 0: Missing …. 8: Released	0	8		1
1.0	**34836**	R	8120		Priority source 11		0	16		1
1.0	**34837**	R	8121		State source 11	x 0: Missing …. 8: Released	0	8		1
1.0	**34838**	R	8122		Priority source 12		0	16		1
1.0	**34839**	R	8123		State source 12	x 0: Missing …. 8: Released	0	8		1
1.0	**34840**	R	8124		Priority source 13		0	16		1
1.0	**34841**	R	8125		State source 13	x 0: Missing …. 8: Released	0	8		1
1.0	**34842**	R	8126		Priority source 14		0	16		1
1.0	**34843**	R	8127		State source 14	x 0: Missing …. 8: Released	0	8		1
1.0	**34844**	R	8128		Priority source 15		0	16		1

1.0	**34845**	R	8129		State source 15	x 0: Missing …. 8: Released	0	8		1
1.0	**34846**	R	8130		Priority source 16		0	16		1
1.0	**34847**	R	8131		State source 16	x 0: Missing …. 8: Released	0	8		1
1.0	**34848**	R	8138		Cascade flow temp		0	140	°C	1/64
1.0	**34849**	R	8138		Status	see description				
1.0	**34850**	R	8139		Cascade flow temp setp		0	140	°C	1/64
1.0	**34851**	R	8139		Status	see description				
1.0	**34852**	R	8150		Source seq ch'over current		0	990	h	1
1.0	**34853**	R	8150		Status	see description				
1.3	**34854**	R/W	3530		Release limit producer sequence		0	500	°C*min	1
1.3	**34855**	R/W	3531		Reset limit producer sequence		0	500	°C*min	1
1.3	**34856**	R/W	3533		Switch-on delay lag heat source		0	120	min	1
1.5	**34857**	R/W	3510		Cascade control strategy	1: None x 2: Late on, late off 3: Early on, late off 4: According to buffer temperature	1	4		1
1.5	**34858**	R/W	3511		Power range, lower limit (Pmin)		0	100	%	1
1.5	**34859**	R/W	3512		Power range, upper limit (Pmax)		0	100	%	1
1.5	**34860**	R/W	3514		Switching sequence	1: None x 2: Serial, last stage released 3: Parallel, release last stage	1	3		1
1.5	**34861**	R/W	3516		Maximum number of producer forced charging		1	16		1
1.5	**34862**	R/W	3517		Max source force charg OT		-20	15	°C	1/64
1.5	**34863**	R/W	3517		Status/Comand	see description				
1.5	**34864**	R/W	3518		Number of sources defrosting allowed		1	100	%	1
1.5	**34865**	R/W	3522		Release integral source sequence, cooling		1	200	°C*min	1
1.5	**34866**	R/W	3523		Reset integral source sequence, cooling		1	200	°C*min	1
1.5	**34867**	R/W	3525		Switch-on delay source sequence, cooling		0	20	min	1
1.5	**34868**	R/W	3538		Substitute common flow temp	0: None x 1: Max prod value 2: Internal prod value 3: Median prod value	0	3		1
1.5	**34869**	R/W	3540		Time to automatic producer sequence switching		10	990	h	1
1.5	**34870**	R/W	3540		Status/Comand	see description				
1.5	**34871**	R/W	3541		Exclude at automatic producer sequence switching	x 0: none 1: First producer 2: Last producer 3: First and last producer	0	3		1
1.5	**34872**	R/W	3542		Source sequence cooling, mirrored	0: No x 1: Yes	0	1		1
1.5	**34873**	R/W	3544		Leading producer	x 1: Wert 686; 0 2: Producer 2 3: Producer 3 4: Producer 4 5: Producer 5 6: Producer 6 7: Producer 7 8: Producer 8 9: Producer 9 10: Producer 10 11: Producer 11 12: Producer 12 13: Producer 13 14: Producer 14 15: Producer 15 16: Producer 16	1	16		1
1.5	**34874**	R	3544		Status	see description				
1.5	**34875**	R/W	3590		Min temp differential hydraulic balancing		0	20	°C	1/64
1.5	**34876**	R/W	3590		Status/Comand	see description				
1.5	**34877**	R/W			Neutral zone heating cascade		1	10	°C	1/64
1.5	**34878**	R/W			Neutral zone cooling cascade		1	20	°C	1/64
1.5	**34879**	R/W	5840		Solar actuating device	x 1: No charging request 2: Diverting valve	1	2		1
1.5	**34880**	R/W	5841		External solar exchanger	x 1: None 2: DHW storage tank 3: Buffer storage tank	1	3		1
1.5	**34881**	R			Priority cooling source 1		0	16		1
1.5	**34882**	R			Priority cooling source 2		0	16		1
1.5	**34883**	R			Priority cooling source 3		0	16		1
1.5	**34884**	R			Priority cooling source 4		0	16		1
1.5	**34885**	R			Priority cooling source 5		0	16		1
1.5	**34886**	R			Priority cooling source 6		0	16		1
1.5	**34887**	R			Priority cooling source 7		0	16		1
1.5	**34888**	R			Priority cooling source 8		0	16		1
1.5	**34889**	R			Priority cooling source 9		0	16		1
1.5	**34890**	R			Priority cooling source 10		0	16		1
1.5	**34891**	R			Priority cooling source 11		0	16		1
1.5	**34892**	R			Priority cooling source 12		0	16		1
1.5	**34893**	R			Priority cooling source 13		0	16		1
1.5	**34894**	R			Priority cooling source 14		0	16		1
1.5	**34895**	R			Priority cooling source 15		0	16		1
1.5	**34896**	R			Priority cooling source 16		0	16		1
1.5	**34897**	R	8140		Cascade return temp actual value		0	140	°C	1/64
1.5	**34898**	R	8140		Status	see description				
1.5	**34899**	R	8141		Cascade return temp actual setpoint		0	140	°C	1/64
1.5	**34900**	R	8141		Status	see description				
1.5	**34901**	R	8144		Cooling cascade flow temp		0	140	°C	1/64
1.5	**34902**	R	8144		Status	see description				
1.5	**34903**	R	8145		Cooling casc flow temp setp		0	140	°C	1/64
1.5	**34904**	R	8145		Status	see description				
1.5	**34905**	R	8155		Time up to auto ch'over source sequence cooling		0	990	h	1
1.5	**34906**	R	8155		Status	see description				

1.5	**34907**	R			State cascade pump (Q25)	x 0: Off 1: On	0	1		1
1.5	**34908**	R			Status	see description				
1.5	**34909**	R/W	3533		Switch-on delay DHW		0	120	min	1
1.6	**34910**	R			Switching sequence actual		0	255		1
1.6	**34911**	R			Heating cascade sequence		0	255		1
1.6	**34912**	R			Sequence cooling cascade current		0	255		1
1.6	**34913**	R			Number of cooling sources		0	255		1
1.6	**34914**	R			Number of sources with active cooling		0	255		1
1.6	**34915**	R			Number of sources with passive cooling		0	255		1
1.6	**34916**	R			Number of cooling sources with optimum energy		0	255		1
1.6	**34917**	R			Common cooling	x 0: None 1: Common 1 2: Common 2	0	2		1
	0x8C00..0x8FFF	BL		General functions						
1.0	**35840**	R/W	5570		Temp diff on dT contr 1		0	40	°C	1/64
1.0	**35841**	R/W	5571		Temp diff off dT contr 1		0	40	°C	1/64
1.0	**35842**	R/W	5572		On temp min dT contr 1		-30	120	°C	1/64
1.0	**35843**	R/W	5580		Temp diff on dT contr 2		0	40	°C	1/64
1.0	**35844**	R/W	5581		Temp diff off dT contr 2		0	40	°C	1/64
1.0	**35845**	R/W	5582		On temp min dT contr 2		-30	120	°C	1/64
1.0	**35846**	R/W	6110		Time constant building		0	50	h	1
1.0	**35847**	R	8565		Flue gas temp		0	350	°C	1/64
1.0	**35848**	R	8565		Status	see description				
1.5	**35849**	R/W	8567		Flue gas temp max		0	350	°C	1/64
1.0	**35850**	R	8567		Status	see description				
1.0	**35851**	R	8700		Outside temp		-50	50	°C	1/64
1.0	**35852**	R	8700		Status	see description				
1.5	**35853**	R/W	8701		Outside temp min		-50	50	°C	1/64
1.5	**35854**	R/W	8702		Outside temp max		-50	50	°C	1/64
1.0	**35855**	R/W	8703		Outside temp attenuated		-50	50	°C	1/64
1.0	**35856**	R	8704		Outside temp composite		-50	50	°C	1/64
1.0	**35857**	R/W	7150		Simulation outside temp		-50	50	°C	1/64
1.0	**35858**	R/W	7150		Status/Comand	see description				
1.0	**35859**	R/W	5600		Air dehumidifier	x 0: Off 1: On	0	1		1
1.0	**35860**	R/W	5602		Air dehumidifier r.h. on		0	100	%	1
1.0	**35861**	R/W	5603		Air dehumidifier r.h. SD		2	50	%	1
1.0	**35862**	R/W	6710		Reset alarm relay	x 0: No 1: Yes	0	1		1
1.0	**35863**	R/W	7120		Economy mode	x 0: Off 1: On	0	1		1
1.0	**35864**	R/W	7120		Status/Comand	see description				
1.0	**35865**	R/W	7141		Emergency operation	x 0: Off 1: On	0	1		1
1.5	**35866**	R/W	7119		Eco function	x 0: Locked 1: Released	0	1		1
1.5	**35867**	R/W	7142		Backup operation function type	x 1: Wert 504; 0 2: Automatically	1	2		1
1.5	**35868**	R/W	5573		Sensor 1 dT controller 1	0: None 1: Buffer sensor B4 2: Buffer sensor B41 3: Collector sensor B6 4: DHW sensor B31 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: DHW circulating sensor B39 10: Swimming pool sensor B13 11: Collector sensor 2 B61 12: --- inadmissable setting --- 13: --- inadmissable setting --- 14: Buffer sensor B42 15: Segment flow sensor B10 16: Cascade return sensor B70 x 17: Special temp sensor 1 18: Special temp sensor 2 19: DHW sensor B3 20: HP flow sensor B21 21: HP return sensor B71 22: --- inadmissable setting --- 23: Outside temp sensor B9 24: Source inlet sensor B91 25: Source outl sens B92/B84 26: Room sensor B5 27: --- inadmissable setting --- 28: Room sensor B52 29: --- inadmissable setting --- 30: Room sensor B53 31: --- inadmissable setting --- 32: Flue gas temp sensor B8 33: Solid fuel boiler sensor B22 34: Solid fuel return sensor B72 35: --- inadmissable setting --- 36: --- inadmissable setting --- 37: --- inadmissable setting ---	0	38		1

1.5	**35869**	R/W	5574		Sensor 2 dT controller 1	0: None 1: Buffer sensor B4 2: Buffer sensor B41 3: Collector sensor B6 4: DHW sensor B31 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: DHW circulating sensor B39 10: Swimming pool sensor B13 11: Collector sensor 2 B61 12: --- inadmissable setting --- 13: --- inadmissable setting --- 14: Buffer sensor B42 15: Segment flow sensor B10 16: Cascade return sensor B70 17: Special temp sensor 1 x 18: Special temp sensor 2 19: DHW sensor B3 20: HP flow sensor B21 21: HP return sensor B71 22: --- inadmissable setting --- 23: Outside temp sensor B9 24: Source inlet sensor B91 25: Source outl sens B92/B84 26: Room sensor B5 27: --- inadmissable setting --- 28: Room sensor B52 29: --- inadmissable setting --- 30: Room sensor B53 31: --- inadmissable setting --- 32: Flue gas temp sensor B8 33: Solid fuel boiler sensor B22 34: Solid fuel return sensor B72 35: --- inadmissable setting --- 36: --- inadmissable setting --- 37: --- inadmissable setting ---	0	38		1
1.5	**35870**	R/W	5575		On time min dT contr 1		0	250	s	1
1.5	**35871**	R/W	5577		Pump/valve kick K21	0: Off x 1: On	0	1		1
1.5	**35872**	R/W	5583		Sensor 1 dT controller 2	0: None 1: Buffer sensor B4 2: Buffer sensor B41 3: Collector sensor B6 4: DHW sensor B31 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: DHW circulating sensor B39 10: Swimming pool sensor B13 11: Collector sensor 2 B61 12: --- inadmissable setting --- 13: --- inadmissable setting --- 14: Buffer sensor B42 15: Segment flow sensor B10 16: Cascade return sensor B70 x 17: Special temp sensor 1 18: Special temp sensor 2 19: DHW sensor B3 20: HP flow sensor B21 21: HP return sensor B71 22: --- inadmissable setting --- 23: Outside temp sensor B9 24: Source inlet sensor B91 25: Source outl sens B92/B84 26: Room sensor B5 27: --- inadmissable setting --- 28: Room sensor B52 29: --- inadmissable setting --- 30: Room sensor B53 31: --- inadmissable setting --- 32: Flue gas temp sensor B8 33: Solid fuel boiler sensor B22 34: Solid fuel return sensor B72 35: --- inadmissable setting --- 36: --- inadmissable setting --- 37: --- inadmissable setting ---	0	38		1

1.5	**35873**	R/W	5584		Sensor 2 dT controller 2	0: None 1: Buffer sensor B4 2: Buffer sensor B41 3: Collector sensor B6 4: DHW sensor B31 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: DHW circulating sensor B39 10: Swimming pool sensor B13 11: Collector sensor 2 B61 12: --- inadmissable setting --- 13: --- inadmissable setting --- 14: Buffer sensor B42 15: Segment flow sensor B10 16: Cascade return sensor B70 17: Special temp sensor 1 x 18: Special temp sensor 2 19: DHW sensor B3 20: HP flow sensor B21 21: HP return sensor B71 22: --- inadmissable setting --- 23: Outside temp sensor B9 24: Source inlet sensor B91 25: Source outl sens B92/B84 26: Room sensor B5 27: --- inadmissable setting --- 28: Room sensor B52 29: --- inadmissable setting --- 30: Room sensor B53 31: --- inadmissable setting --- 32: Flue gas temp sensor B8 33: Solid fuel boiler sensor B22 34: Solid fuel return sensor B72 35: --- inadmissable setting --- 36: --- inadmissable setting --- 37: --- inadmissable setting ---	0	38		1
1.5	**35874**	R/W	5585		On time min dT contr 2		0	250	s	1
1.5	**35875**	R/W	5587		Pump/valve kick K22	0: Off x 1: On	0	1		1
1.5	**35876**	R/W	5606		Release air dehumidifier	x 1: Wert 682; 0 2: Time program heating circuit 3: Time program 5	1	3		1
1.5	**35877**	R/W	5608		Air dehumidiefier acquisition air r.h.	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**35878**	R/W			Outside air temp control	0: Off 1: Summer only 2: Winter only x 3: Summer and Winter	0	3		1
1.5	**35879**	R/W			Outside air temp control below outside temp		-20	20	°C	1/64
1.5	**35880**	R/W			Outside air temp control, temp diff		-20	20	°C	1/64
1.5	**35881**	R/W			Outside air temp control, on time min		0	255	min	1
1.5	**35882**	R/W			Outside air temp control, off time min		0	255	min	1
1.5	**35883**	R	8723		Relative air humidity		0	100	%	1
1.5	**35884**	R	8723		Status	see description				
1.5	**35885**	R			State air dehumidifier (K29)	x 0: Off 1: On	0	1		1
1.5	**35886**	R			Status	see description				
1.5	**35887**	R			State alarm relay (K10)	x 0: Off 1: On	0	1		1
1.5	**35888**	R			Status	see description				
1.5	**35889**	R			Status time program 5 relais (K13)	x 0: Off 1: On	0	1		1
1.5	**35890**	R			Status	see description				
1.5	**35891**	R			Status delta-T controller 1 K21	x 0: Off 1: On	0	1		1
1.5	**35892**	R			Status	see description				
1.5	**35893**	R			Status delta-T controller 2 K22	x 0: Off 1: On	0	1		1
1.5	**35894**	R			Status	see description				
1.5	**35895**	R/W	7121		End economy mode	x 1: Wert 504; 0 2: Automatically	1	2		1
1.6	**35896**	R/W	5578		Off temp max dT contr 1		-30	120	°C	1/64
1.6	**35897**	R/W	5578		Status/Comand	see description				
1.6	**35898**	R/W	5588		Off temp max dT contr 2		-30	120	°C	1/64
1.6	**35899**	R/W	5588		Status/Comand	see description				
1.6	**35900**	R/W			Displ event message electr immers heater	x 0: No 1: Yes	0	1		1
1.6	**35901**	R/W	7130		Chimney sweep function	x 0: Off 1: On	0	1		1
1.6	**35902**	R/W	7154		Release without source protection		0	240	h	1
	0x9000...0x93FF	BL		Configuration						
1.5	**36864**	R/W	5700		Plant diagram selection		1	24		1
1.5	**36865**	R/W	5700		Status/Comand	see description				
1.5	**36866**	R			Plant diagram selection validity	x 0: Changed 1: Unchanged	0	1		1
1.6	**36867**	R/W	5890		Relay output QX1	0..83 (see user manual)	0	83		1

1.6	**36868**	R/W	5891		Relay output QX2	0..83 (see user manual)	0	83		1
1.6	**36869**	R/W	5892		Relay output QX3	0..83 (see user manual)	0	83		1
1.6	**36870**	R/W	5894		Triac output ZX4 / Relay output QX4	0..83 (see user manual)	0	83		1
1.6	**36871**	R/W	5895		Relay output QX5	0..83 (see user manual)	0	83		1
1.6	**36872**	R/W	5896		Triac output ZX6 / Relay output QX6	0..83 (see user manual)	0	83		1
1.6	**36873**	R/W	5897		Relay output QX7	0..83 (see user manual)	0	83		1
1.6	**36874**	R/W	5898		Relay output QX8	0..83 (see user manual)	0	83		1
1.6	**36875**	R/W	5899		Relay output QX9	0..83 (see user manual)	0	83		1
1.6	**36876**	R/W	5900		Relay output QX10	0..83 (see user manual)	0	83		1
1.6	**36877**	R/W	5901		Relay output QX11	0..83 (see user manual)	0	83		1
1.6	**36878**	R/W	5902		Relay output QX12	0..83 (see user manual)	0	83		1
1.6	**36879**	R/W	5903		Relay output QX13	0..83 (see user manual)	0	83		1
1.5	**36880**	R/W	5909		Function output ZX4-Mod	0..35 (see user manual)	0	35		1
1.5	**36881**	R/W	5930		Sensor input BX1	0..45 (see user manual)	0	45		1
1.5	**36882**	R/W	5931		Sensor input BX2	0..45 (see user manual)	0	45		1
1.5	**36883**	R/W	5932		Sensor input BX3	0..42 (see user manual)	0	42		1
1.5	**36884**	R/W	5933		Sensor input BX4	0..42 (see user manual)	0	42		1
1.5	**36885**	R/W	5934		Sensor input BX5	0..34 (see user manual)	0	34		1
1.5	**36886**	R/W	5935		Sensor input BX6	0..34 (see user manual)	0	34		1
1.5	**36887**	R/W	5936		Sensor input BX7	0..42 (see user manual)	0	42		1
1.5	**36888**	R/W	5937		Sensor input BX8	0..42 (see user manual)	0	42		1
1.5	**36889**	R/W	5938		Sensor input BX9	0..42 (see user manual)	0	42		1
1.5	**36890**	R/W	5939		Sensor input BX10	0..42 (see user manual)	0	42		1
1.5	**36891**	R/W	5940		Sensor input BX11	0..42 (see user manual)	0	42		1
1.5	**36892**	R/W	5941		Sensor input BX12	0..42 (see user manual)	0	42		1
1.5	**36893**	R/W	5942		Sensor input BX13	0..45 (see user manual)	0	45		1
1.5	**36894**	R/W	5943		Sensor input BX14	0..45 (see user manual)	0	45		1
1.5	**36895**	R/W	5950		Input H1 function selection	0..61 (see user manual)	0	61		1
1.5	**36896**	R/W	5951		Type of contact H1	0: normal closed x 1: normal opened	0	1		1
1.5	**36897**	R/W	5953		Input value 1 H1		0	1000		1/10
1.5	**36898**	R/W	5954		Function value 1 H1		-100	500		1/10
1.5	**36899**	R/W	5955		Input value 2 H1		0	1000		1/10
1.5	**36900**	R/W	5956		Function value 2 H1		-100	500		1/10
1.5	**36901**	R/W	5957		Temperature sensor H1	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**36902**	R/W	5960		Input H3 function selection	0..61 (see user manual)	0	61		1
1.5	**36903**	R/W	5961		Type of contact H3	0: normal closed x 1: normal opened	0	1		1
1.5	**36904**	R/W	5963		Input value 1 H3		0	1000		1/10
1.5	**36905**	R/W	5964		Function value1 H3		-100	500		1/10
1.5	**36906**	R/W	5965		Input value 2 H3		0	1000		1/10
1.5	**36907**	R/W	5966		Function value 2 H3		-100	500		1/10
1.5	**36908**	R/W	5967		Temperature sensor H3	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.6	**36909**	R/W	5980		Function input EX1	0..30 (see user manual)	0	30		1
1.5	**36910**	R/W	5981		Operating action input EX1	0: normal closed x 1: normal opened	0	1		1
1.6	**36911**	R/W	5982		Function input EX2	0..30 (see user manual)	0	30		1
1.5	**36912**	R/W	5983		Operating action input EX2	0: normal closed x 1: normal opened	0	1		1
1.6	**36913**	R/W	5984		Function input EX3	0..30 (see user manual)	0	30		1
1.5	**36914**	R/W	5985		Operating action input EX3	0: normal closed x 1: normal opened	0	1		1
1.6	**36915**	R/W	5986		Function input EX4	0..30 (see user manual)	0	30		1

1.5	**36916**	R/W	5987		Operating action input EX4	0: normal closed x 1: normal opened	0	1		1
1.6	**36917**	R/W	5988		Function input EX5	0..30 (see user manual)	0	30		1
1.5	**36918**	R/W	5989		Operating action input EX5	0: normal closed x 1: normal opened	0	1		1
1.6	**36919**	R/W	5990		Function input EX6	0..30 (see user manual)	0	30		1
1.5	**36920**	R/W	5991		Operating action input EX6	0: normal closed x 1: normal opened	0	1		1
1.6	**36921**	R/W	5992		Function input EX7	0..30 (see user manual)	0	30		1
1.5	**36922**	R/W	5993		Operating action input EX7	0: normal closed x 1: normal opened	0	1		1
1.6	**36923**	R/W	5996		Function input EX9	0..30 (see user manual)	0	30		1
1.6	**36924**	R/W	5997		Function input EX10	0..30 (see user manual)	0	30		1
1.6	**36925**	R/W	5998		Function input EX11	0..30 (see user manual)	0	30		1
1.5	**36926**	R/W	5999		Operating action input EX9	x 0: normal closed 1: normal opened	0	1		1
1.5	**36927**	R/W	6000		Operating action input EX10	x 0: normal closed 1: normal opened	0	1		1
1.5	**36928**	R/W	6001		Operating action input EX11	x 0: normal closed 1: normal opened	0	1		1
1.5	**36929**	R/W	6014		Function mixing valve group 1	1: None x 2: Heating circuit 1 3: Heating circuit 2 4: Heating circuit 3 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: Primary contr/system pump 8: DHW primary controller 9: Instantaneous DHW heater 10: --- inadmissable setting --- 11: Cooling circuit 1 12: Heating circ/cooling circ 1 13: --- inadmissable setting --- 14: Ret temp contr sol fuel boil 15: --- inadmissable setting --- 16: Cooling circuit 2 17: Heating circ/cooling circ 2 18: Cooling circuit 3 19: Heating circ/cooling circ 3 20: DHW interm circuit controller	1	20		1
1.5	**36930**	R/W	6014		Function mixing valve group 1	1: None x 2: Heating circuit 1 3: Heating circuit 2 4: Heating circuit 3 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: Primary contr/system pump 8: DHW primary controller 9: Instantaneous DHW heater 10: --- inadmissable setting --- 11: Cooling circuit 1 12: Heating circ/cooling circ 1 13: --- inadmissable setting --- 14: Ret temp contr sol fuel boil 15: --- inadmissable setting --- 16: Cooling circuit 2 17: Heating circ/cooling circ 2 18: Cooling circuit 3 19: Heating circ/cooling circ 3 20: DHW interm circuit controller	1	20		1
1.5	**36931**	R/W	6070		Function output UX1	0..35 (see user manual)	0	35		1
1.5	**36932**	R/W	6071		Signal logic output UX1	x 0: Standard 1: Inverted	0	1		1
1.5	**36933**	R/W	6072		Signal output UX1	x 0: 0..10V 1: PWM	0	1		1
1.5	**36934**	R/W	6075		Temperature value 10V UX1		5	130	°C	1/64
1.5	**36935**	R/W	6076		Output voltage UX1		0	10	V	1/10
1.5	**36936**	R/W	6078		Function output UX2	0..35 (see user manual)	0	35		1
1.5	**36937**	R/W	6079		Signal logic output UX2	x 0: Standard 1: Inverted	0	1		1
1.5	**36938**	R/W	6080		Signal output UX2	x 0: 0..10V 1: PWM	0	1		1
1.5	**36939**	R/W	6084		Temperature value 10V UX2		5	130	°C	1/64
1.5	**36940**	R/W	6087		Output voltage UX2		0	10	V	1/10
1.5	**36941**	R/W	6089		Function output UX3	0..30 (see user manual)	0	30		1
1.5	**36942**	R/W	6090		Signal logic output UX3	x 0: Standard 1: Inverted	0	1		1
1.5	**36943**	R/W	6091		Signal output UX3	x 0: 0..10V 1: PWM	0	1		1
1.5	**36944**	R/W	6094		Temperature value 10V UX		5	130	°C	1/64
1.5	**36945**	R/W	6095		Output voltage UX3		0	10	V	1/10
1.5	**36946**	R/W	6096		Sensor type device	x 1: Wert 594; 0 2: NTC 5k	1	2		1
1.5	**36947**	R/W	6097		Sensor type collector	x 1: Wert 595; 0 2: Pt 1000	1	2		1
1.5	**36948**	R/W	6098		Measured value corr collector sensor 1 (B6)		-20	20	°C	1/64
1.5	**36949**	R/W	6099		Measured value corr collector sensor 2 (B61)		-20	20	°C	1/64
1.5	**36950**	R/W	6100		Outside temp sensor measuring correction		-3	3	°C	1/64
1.5	**36951**	R/W	6101		Sensor type flue gas temperature	x 1: Wert 595; 0 2: Pt 1000	1	2		1
1.5	**36952**	R/W	6102		Measured value corr flue gas sensor (B8)		-20	20	°C	1/64
1.5	**36953**	R/W	6104		Sensor type solar flow/return	x 1: Wert 595; 0 2: Pt 1000	1	2		1
1.5	**36954**	R/W	6105		Sensor type heat pump flow/return	x 1: Wert 595; 0 2: Pt 1000	1	2		1

1.5	**36955**	R/W	6106		Sensor type source inlet/outlet	x 1: Wert 595; 0 2: Pt 1000	1	2		1
1.5	**36956**	R/W	6110		Building time constant		0	50	h	1
1.5	**36957**	R/W	6114		Setp compensation Xp		1	100	°C	1/64
1.5	**36958**	R/W	6115		Setp compensation Tn		10	650	s	1
1.5	**36959**	R/W	6116		Time constant setpoint compensation		0	14	min	1
1.5	**36960**	R/W	6117		Central setpoint shift		1	100	°C	1/64
1.5	**36961**	R/W	6117		Status/Comand	see description				
1.5	**36962**	R/W	6118		Setpoint reduction delay		1	200	K/min	1
1.5	**36963**	R/W	6118		Status/Comand	see description				
1.5	**36964**	R/W	6119		Central setp compens cooling		-20	-1	°C	1/64
1.5	**36965**	R/W	6119		Status/Comand	see description				
1.5	**36966**	R/W	6120		Frost protection for the plant	0: Off x 1: On	0	1		1
1.5	**36967**	R/W	6123		Restart lock pumps		0	600	s	1
1.5	**36968**	R/W	6123		Status/Comand	see description				
1.5	**36969**	R/W	6140		Water pressure max		0	10	bar	1/10
1.5	**36970**	R/W	6140		Status/Comand	see description				
1.5	**36971**	R/W	6141		Water pressure min		0	10	bar	1/10
1.5	**36972**	R/W	6141		Status/Comand	see description				
1.5	**36973**	R/W	6142		Water pressure critical min		0	10	bar	1/10
1.5	**36974**	R/W	6142		Status/Comand	see description				
1.5	**36975**	R/W	6148		Static press supervision 1	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**36976**	R/W	6150		Water pressure 2 max		0	10	bar	1/10
1.5	**36977**	R/W	6150		Status/Comand	see description				
1.5	**36978**	R/W	6151		Water pressure 2 min		0	10	bar	1/10
1.5	**36979**	R/W	6151		Status/Comand	see description				
1.5	**36980**	R/W	6152		Water pressure 2 critical min		0	10	bar	1/10
1.5	**36981**	R/W	6152		Status/Comand	see description				
1.5	**36982**	R/W	6154		Static press supervision 2	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**36983**	R/W	6180		Water pressure 3 max		0	10	bar	1/10
1.5	**36984**	R/W	6180		Status/Comand	see description				
1.5	**36985**	R/W	6181		Water pressure 3 min		0	10	bar	1/10
1.5	**36986**	R/W	6181		Status/Comand	see description				
1.5	**36987**	R/W	6182		Water pressure 3 critical min		0	10	bar	1/10
1.5	**36988**	R/W	6182		Status/Comand	see description				
1.5	**36989**	R/W	6184		Static press supervision 3	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**36990**	R/W	6200		Store sensor	x 0: No 1: Yes	0	1		1
1.5	**36991**	R/W	6201		Delete sensors	x 0: No 1: Yes	0	1		1
1.5	**36992**	R/W	6204		Store parameter	x 0: No 1: Yes	0	1		1
1.5	**36993**	R/W	6205		Reset parameter	x 0: No 1: Yes	0	1		1
1.5	**36994**	R/W	6212		Control number heat generation 1		0	199999		1
1.5	**36995**	R/W	6213		Control number heat generation 2		0	199999		1
1.5	**36996**	R/W	6215		Control number storage tank		0	199999		1
1.5	**36997**	R/W	6217		Control number heating circuits		0	199999		1
1.5	**36998**	R/W	6290		Acquisition room temperature 1	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1

1.5	**36999**	R/W	6291		Acquisition room temperature 2	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**37000**	R/W	6292		Acquisition room temperature 3	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**37001**	R/W	6293		Room 1 r.h. measurement	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**37002**	R/W	6294		Room 2 r.h. measurement	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**37003**	R/W	6295		Room 3 r.h. measurement	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3	0	11		1
1.5	**37004**	R/W	6296		Acquisition room air quality 1	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3 12: With input H31 13: With input H32 14: With input H33	0	14		1
1.5	**37005**	R/W	6297		Acquisition room air quality 2	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3 12: With input H31 13: With input H32 14: With input H33	0	14		1

1.5	**37006**	R/W	6298		Acquisition room air quality 3	x 0: None 1: With input H1 2: With input H2 module 1 3: With input H2 module 2 4: With input H2 module 3 5: With input H21 module 1 6: With input H21 module 2 7: With input H21 module 3 8: With input H22 module 1 9: With input H22 module 2 10: With input H22 module 3 11: With input H3 12: With input H31 13: With input H32 14: With input H33	0	14		1
1.5	**37007**	R/W	6331		PWM period electric flow		0	999	s	1
1.5	**37008**	R/W	6332		PWM Ausschaltzeit Elektro-Vorlauf Modulation		0	999	s	1
1.5	**37009**	R/W	6333		PWM Einschaltzeit Elektro-Vorlauf Modulation		0	999	s	1
1.5	**37010**	R/W	6334		PWM delay electric flow 2		0	100	s	1
1.5	**37011**	R/W	6345		Code Commissioning		0	99999		1
1.5	**37012**	R/W	6346		Code Engineer		0	99999		1
1.5	**37013**	R/W	6347		Code OEM		0	99999		1
1.5	**37014**	R/W	6348		Code OEM 2		0	99999		1
1.5	**37015**	R/W	6358		Voltage output GX1	x 2: Off	2	2		1
1.5	**37016**	R/W	6362		Polynomial coeff 0 heat UX		-1000	1000		1
1.5	**37017**	R/W	6363		Polynomial coeff 1 heat UX		-1000	1000		1
1.5	**37018**	R/W	6364		Polynomial coeff 2 heat UX		-1000	1000		1
1.5	**37019**	R/W	6365		Polynomial coeff 3 heat UX		-1000	1000		1
1.5	**37020**	R/W	6366		Polynomial coeff 0 cool UX		-1000	1000		1
1.5	**37021**	R/W	6367		Polynomial coeff 1 cool UX		-1000	1000		1
1.5	**37022**	R/W	6368		Polynomial coeff 2 cool UX		-1000	1000		1
1.5	**37023**	R/W	6369		Polynomial coeff 3 cool UX		-1000	1000		1
1.6	**37024**	R/W	6371		Relay output QX31	0..83 (see user manual)	0	83		1
1.6	**37025**	R/W	6372		Relay output QX32	0..83 (see user manual)	0	83		1
1.6	**37026**	R/W	6373		Relay output QX33	0..83 (see user manual)	0	83		1
1.6	**37027**	R/W	6374		Triac output ZX34 / Relay output QX34	0..83 (see user manual)	0	83		1
1.6	**37028**	R/W	6375		Relay output QX35	0..83 (see user manual)	0	83		1
1.5	**37029**	R/W	6384		Function output ZX34-Mod	0..35 (see user manual)	0	35		1
1.5	**37030**	R/W	6391		Sensor input BX31	0..42 (see user manual)	0	42		1
1.5	**37031**	R/W	6392		Sensor input BX32	0..42 (see user manual)	0	42		1
1.5	**37032**	R/W	6393		Sensor input BX33	0..42 (see user manual)	0	42		1
1.5	**37033**	R/W	6394		Sensor input BX34	0..42 (see user manual)	0	42		1
1.5	**37034**	R/W	6395		Sensor input BX35	0..42 (see user manual)	0	42		1
1.5	**37035**	R/W	6396		Sensor input BX36	0..42 (see user manual)	0	42		1
1.5	**37036**	R/W	6400		Function input H31	0..61 (see user manual)	0	61		1
1.5	**37037**	R/W	6401		Contact type H31	0: normal closed x 1: normal opened	0	1		1
1.5	**37038**	R/W	6403		Input value 1 H31		0	1000		1/10
1.5	**37039**	R/W	6404		Funct value 1 H31		-100	500		1/10
1.5	**37040**	R/W	6405		Input value 2 H31		0	1000		1/10
1.5	**37041**	R/W	6406		Funct value 2 H31		-100	500		1/10
1.5	**37042**	R/W	6407		Temperature sensor H31	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**37043**	R/W	6410		Function input H32	0..61 (see user manual)	0	61		1
1.5	**37044**	R/W	6411		Contact type H32	0: normal closed x 1: normal opened	0	1		1
1.5	**37045**	R/W	6413		Input value 1 H32		0	1000		1/10
1.5	**37046**	R/W	6414		Funct value 1 H32		-100	500		1/10
1.5	**37047**	R/W	6415		Input value 2 H32		0	1000		1/10
1.5	**37048**	R/W	6416		Funct value 2 H32		-100	500		1/10

1.5	**37049**	R/W	6417		Temperature sensor H32	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**37050**	R/W	6420		Function input H33	0..61 (see user manual)	0	61		1
1.5	**37051**	R/W	6421		Contact type H33	0: normal closed x 1: normal opened	0	1		1
1.5	**37052**	R/W	6423		Input value 1 H33		0	1000		1/10
1.5	**37053**	R/W	6424		Funct value 1 H33		-100	500		1/10
1.5	**37054**	R/W	6425		Input value 2 H33		0	1000		1/10
1.5	**37055**	R/W	6426		Funct value 2 H33		-100	500		1/10
1.5	**37056**	R/W	6455		Function mixing valve group 31	1..20 (see user manual)	1	20		1
1.5	**37057**	R/W	6470		Function output WX31	x 0: None 1: Expansion valve evapor V81 2: Expansion valve EVI V82	0	2		1
	0x9400..0x97FF	BL		Device						
1.0	**37888**	R/W	7700		Relay test	x 0: No test 1: Everything off 2: Relay output QX1 3: Relay output QX2 4: Relay output QX3 5: Output QX4/ZX4 6: Relay output QX5 7: Relay output QX6 8: Relay output QX7 9: Relay output QX8 10: Relay output QX9 11: Relay output QX10 12: Relay output QX11 13: Relay output QX12 14: Relay output QX13 15: Relay output QX31 16: Relay output QX32 17: Relay output QX33 18: Relay output QX34 19: Relay output QX35 20: Relay output QX21 module 1 21: Relay output QX22 module 1 22: Relay output QX23 module 1 23: Relay output QX21 module 2 24: Relay output QX22 module 2 25: Relay output QX23 module 2 26: Relay output QX21 module 3 27: Relay output QX22 module 3 28: Relay output QX23 module 3	0	28		1
1.0	**37889**	R/W	7710		Output test UX1		0	100	%	1
1.0	**37890**	R/W	7710		Status/Comand	see description				
1.0	**37891**	R	7711		Output signal UX1		0	10 100	V %	1/100
1.0	**37892**	R	7711		Status	see description				
1.0	**37893**	R	7711		Unit	0..3: reserved 4: Voltage V 5: PWM %	0	5	V	1/10
1.0	**37894**	R/W	7716		Output test UX2		0	100	%	1
1.0	**37895**	R/W	7716		Status/Comand	see description				
1.0	**37896**	R	7717		Output signal UX2		0	10 100	V %	1/100
1.0	**37897**	R	7717		Status	see description				
1.0	**37898**	R	7717		Unit	0..3: reserved 4: Voltage V 5: PWM %	0	5		1/10
1.0	**37899**	R/W	7724		Output test UX3		0	100	%	1
1.0	**37900**	R/W	7724		Status	see description				
1.0	**37901**	R	7725		Output signal UX3		0	10 100	V %	1/100
1.0	**37902**	R	7725		Status	see description				
1.0	**37903**	R	7725		Unit	0..3: reserved 4: Voltage V 5: PWM %	0	5		1/10
1.0	**37904**	R/W	7780		Output test UX21 module 1		0	100	%	1
1.0	**37905**	R/W	7780		Status/Comand	see description				
1.0	**37906**	R	7781		Output signal UX21 module 1		0	10 100	V %	1/100
1.0	**37907**	R	7781		Status	see description				
1.0	**37908**	R	7781		Unit	0..3: reserved 4: Voltage V 5: PWM %	0	5		1/10
1.0	**37909**	R/W	7782		Output test UX22 module 1		0	100	%	1

1.0	**37910**	R/W	7782		Status/Comand	see description				
1.0	**37911**	R	7783		Output signal UX22 module 1		0	10 100	V %	1/100
1.0	**37912**	R	7783		Status	see description				
1.0	**37913**	R	7783		Unit	0..3: reserved 4: Voltage V 5: PWM %	0	5		1/10
1.0	**37914**	R/W	7784		Output test UX21 module 2		0	100	%	1
1.0	**37915**	R/W	7784		Status/Comand	see description				
1.0	**37916**	R	7785		Output signal UX21 module 2		0	10 100	V %	1/100
1.0	**37917**	R	7785		Status	see description				
1.0	**37918**	R	7785		Unit	0..3: reserved 4: Voltage V 5: PWM %	0	5		1/10
1.0	**37919**	R/W	7786		Output test UX22 module 2		0	100	%	1
1.0	**37920**	R/W	7786		Status/Comand	see description				
1.0	**37921**	R	7787		Output signal UX22 module 2		0	10 100	V %	1/100
1.0	**37922**	R	7787		Status	see description				
1.0	**37923**	R	7787		Unit	0..3: reserved 4: Voltage V 5: PWM %	0	5		1/10
1.0	**37924**	R/W	7788		Output test UX21 module 3		0	100	%	1
1.0	**37925**	R/W	7788		Status/Comand	see description				
1.0	**37926**	R	7789		Output signal UX21 module 3		0	10 100	V %	1/100
1.0	**37927**	R	7789		Status	see description				
1.0	**37928**	R	7789		Unit	0..3: reserved 4: Voltage V 5: PWM %	0	5		1/10
1.0	**37929**	R/W	7790		Output test UX22 module 3		0	100	%	1
1.0	**37930**	R/W	7790		Status/Comand	see description				
1.0	**37931**	R	7791		Output signal UX22 module 3		0	10 100	V %	1/100
1.0	**37932**	R	7791		Status	see description				
1.0	**37933**	R	7791		Unit	0..3: reserved 4: Voltage V 5: PWM %	0	5		1/10
1.0	**37934**	R/W	7796		Output test WX21 module 1		0	100	%	1
1.0	**37935**	R/W	7796		Status/Comand	see description				
1.0	**37936**	R	7797		Pos step motor WX21 mod 1		0	65535		1
1.0	**37937**	R	7797		Status	see description				
1.0	**37938**	R/W	7798		Output test WX21 module 2		0	100	%	1
1.0	**37939**	R/W	7798		Status/Comand	see description				
1.0	**37940**	R	7799		Pos step motor WX21 mod 2		0	65535		1
1.0	**37941**	R	7799		Status	see description				
1.0	**37942**	R/W	7800		Output test WX21 module 3		0	100	%	1
1.0	**37943**	R/W	7800		Status/Comand	see description				
1.0	**37944**	R	7801		Pos step motor WX21 mod 3		0	65535		1
1.0	**37945**	R	7801		Status	see description				
1.0	**37946**	R/W	7965		Output test WX31		0	100	%	1
1.0	**37947**	R/W	7965		Status/Comand	see description				
1.0	**37948**	R	7966		Pos stepper motor WX31		0	65535		1
1.0	**37949**	R	7966		Status	see description				
1.0	**37950**	R/W	7705		Mod setp ZX6 relay test		0	100	%	1
1.0	**37951**	R	7708		Modulation signal ZX6		0	100	%	1
1.0	**37952**	R	7708		Status	see description				
1.0	**37953**	R/W	7969		Mod setp ZX34 relay test		0	100	%	1
1.0	**37954**	R	7970		Modulation signal ZX34		0	100	%	1
1.0	**37955**	R	7970		Status	see description				
1.0	**37956**	R/W	7705		Mod setp ZX4 relay test		0	100	%	1
1.0	**37957**	R	7708		Modulation signal ZX4		0	100	%	1
1.0	**37958**	R	7708		Status	see description				
1.5	**37959**	R	9005		Water pressure 1		-100	500	bar	1/10
1.5	**37960**	R	9005		Status	see description				
1.5	**37961**	R	9006		Water pressure 2		-100	500	bar	1/10
1.5	**37962**	R	9006		Status	see description				
1.5	**37963**	R	9009		Water pressure 3		-100	500	bar	1/10
1.5	**37964**	R	9009		Status	see description				
1.5	**37965**	R	9016		Special temperature 1		0	140	°C	1/64
1.5	**37966**	R	9016		Status	see description				
1.5	**37967**	R	9017		Special temperature 2		0	140	°C	1/64
1.5	**37968**	R	9017		Status	see description				
1.6	**37969**	R	9018		Special temperature 3		0	140	°C	1/64
1.6	**37970**	R	9018		Status	see description				
1.6	**37971**	R	9019		Special temperature 4		0	140	°C	1/64
1.6	**37972**	R	9019		Status	see description				
1.6	**37973**	R	9020		Special temperature 5		0	140	°C	1/64
1.6	**37974**	R	9020		Status	see description				
1.6	**37975**	R	9021		Special temperature 6		0	140	°C	1/64
1.6	**37976**	R	9021		Status	see description				
1.6	**37977**	R	9022		Special temperature 7		0	140	°C	1/64
1.6	**37978**	R	9022		Status	see description				
1.6	**37979**	R	9023		Special temperature 8		0	140	°C	1/64
1.6	**37980**	R	9023		Status	see description				
				Device Register reserve						
1.0	**38000**	R	7804		Sensor temp BX1		-28	350	°C	1/64
1.0	**38001**	R	7804		Status	see description				
1.0	**38002**	R	7805		Sensor temp BX2		-28	350	°C	1/64
1.0	**38003**	R	7805		Status	see description				
1.0	**38004**	R	7806		Sensor temp BX3		-28	350	°C	1/64
1.0	**38005**	R	7806		Status	see description				
1.0	**38006**	R	7807		Sensor temp BX4		-28	350	°C	1/64
1.0	**38007**	R	7807		Status	see description				
1.0	**38008**	R	7808		Sensor temp BX5		-28	350	°C	1/64

1.0	**38009**	R	7808		Status	see description				
1.0	**38010**	R	7809		Sensor temp BX6		-28	350	°C	1/64
1.0	**38011**	R	7809		Status	see description				
1.0	**38012**	R	7810		Sensor temp BX7		-28	350	°C	1/64
1.0	**38013**	R	7810		Status	see description				
1.0	**38014**	R	7811		Sensor temp BX8		-28	350	°C	1/64
1.0	**38015**	R	7811		Status	see description				
1.0	**38016**	R	7812		Sensor temp BX9		-28	350	°C	1/64
1.0	**38017**	R	7812		Status	see description				
1.0	**38018**	R	7813		Sensor temp BX10		-28	350	°C	1/64
1.0	**38019**	R	7813		Status	see description				
1.0	**38020**	R	7814		Sensor temp BX11		-28	350	°C	1/64
1.0	**38021**	R	7814		Status	see description				
1.0	**38022**	R	7815		Sensor temp BX12		-28	350	°C	1/64
1.0	**38023**	R	7815		Status	see description				
1.0	**38024**	R	7816		Sensor temp BX13		-28	350	°C	1/64
1.0	**38025**	R	7816		Status	see description				
1.0	**38026**	R	7817		Sensor temp BX14		-28	350	°C	1/64
1.0	**38027**	R	7817		Status	see description				
1.0	**38028**	R	7830		Sensor temp BX21 module 1		-28	350	°C	1/64
1.0	**38029**	R	7830		Status	see description				
1.0	**38030**	R	7831		Sensor temp BX22 module 1		-28	350	°C	1/64
1.0	**38031**	R	7831		Status	see description				
1.0	**38032**	R	7832		Sensor temp BX21 module 2		-28	350	°C	1/64
1.0	**38033**	R	7832		Status	see description				
1.0	**38034**	R	7833		Sensor temp BX22 module 2		-28	350	°C	1/64
1.0	**38035**	R	7833		Status	see description				
1.0	**38036**	R	7834		Sensor temp BX21 module 3		-28	350	°C	1/64
1.0	**38037**	R	7834		Status	see description				
1.0	**38038**	R	7835		Sensor temp BX22 module 3		-28	350	°C	1/64
1.0	**38039**	R	7835		Status	see description				
1.0	**38040**	R	7973		Sensor temp BX31		-28	350	°C	1/64
1.0	**38041**	R	7973		Status	see description				
1.0	**38042**	R	7974		Sensor temp BX32		-28	350	°C	1/64
1.0	**38043**	R	7974		Status	see description				
1.0	**38044**	R	7975		Sensor temp BX33		-28	350	°C	1/64
1.0	**38045**	R	7975		Status	see description				
1.0	**38046**	R	7976		Sensor temp BX34		-28	350	°C	1/64
1.0	**38047**	R	7976		Status	see description				
1.0	**38048**	R	7977		Sensor temp BX35		-28	350	°C	1/64
1.0	**38049**	R	7977		Status	see description				
1.0	**38050**	R	7978		Sensor temp BX36		-28	350	°C	1/64
1.0	**38051**	R	7978		Status	see description				
				Device Register reserve						
1.0	**38100**	R	7844		Input signal H1		0	2^32		1/10
1.0	38101					(32 Bit Data)				
1.0	**38102**	R	7844		Status	see description				
1.0	**38103**	R	7844		Unit	x 0: None 1: Closed (ooo), Open (---) 2: Pulse 3: Frequency Hz 4: Voltage V	0	4		1/10
1.0	**38104**	R	7845		Input signal H2 module 1		0	2^32		1/10
1.0	38105					(32 Bit Data)				
1.0	**38106**	R	7845		Status	see description				
1.0	**38107**	R	7845		Unit	x 0: None ... 4: Voltage V	0	4		1/10
1.0	**38108**	R	7845		Input signal H21 module 1		0	2^32		1/10
1.0	38109					(32 Bit Data)				
1.0	**38110**	R	7845		Status	see description				
1.0	**38111**	R	7845		Unit	x 0: None ... 4: Voltage V	0	4		1/10
1.0	**38112**	R	7846		Input signal H22 module 1		0	2^32		1/10
1.0	38113					(32 Bit Data)				
1.0	**38114**	R	7846		Status	see description				
1.0	**38115**	R	7846		Unit	x 0: None ... 4: Voltage V	0	4		1/10
1.0	**38116**	R	7847		Input signal H2 module 2		0	2^32		1
1.0	38117					(32 Bit Data)				
1.0	**38118**	R	7847		Status	see description				
1.0	**38119**	R	7847		Unit	x 0: None ... 4: Voltage V	0	4		1
1.0	**38120**	R	7847		Input signal H21 module 2		0	2^32		1
1.0	38121					(32 Bit Data)				
1.0	**38122**	R	7847		Status	see description				
1.0	**38123**	R	7847		Unit	x 0: None ... 4: Voltage V	0	4		1
1.0	**38124**	R	7848		Input signal H22 module 2		0	2^32	V	1/10
1.0	38125					(32 Bit Data)				
1.0	**38126**	R	7848		Status	see description				
1.0	**38127**	R	7848		Unit	x 0: None ... 4: Voltage V	0	4	V	1/10
1.0	**38128**	R	7849		Input signal H2 module 3		0	2^32		1
1.0	38129					(32 Bit Data)				
1.0	**38130**	R	7849		Status	see description				
1.0	**38131**	R	7849		Unit	x 0: None ... 4: Voltage V	0	4		1
1.0	**38132**	R	7849		Input signal H21 module 3		0	2^32		1
1.0	38133					(32 Bit Data)				

1.0	**38134**	R	7849		Status	see description				
1.0	**38135**	R	7849		Unit	x 0: None ... 4: Voltage V	0	4		1
1.0	**38136**	R	7850		Input signal H22 module 3		0	2^32	Hz	1/10
1.0	38137					(32 Bit Data)				
1.0	**38138**	R	7850		Status	see description				
1.0	**38139**	R	7850		Unit	x 0: None ... 4: Voltage V	0	4	Hz	1/10
1.0	**38140**	R	7858		Input signal H3		0	2^32		1/10
1.0	38141					(32 Bit Data)				
1.0	**38142**	R	7858		Status	see description				
1.0	**38143**	R	7858		Unit	x 0: None ... 4: Voltage V	0	4		1/10
1.0	**38144**	R	7989		Input signal H31		0	2^32		1/10
1.0	38145					(32 Bit Data)				
1.0	**38146**	R	7989		Status	see description				
1.0	**38147**	R	7989		Unit	x 0: None ... 4: Voltage V	0	4		1/10
1.0	**38148**	R	7994		Input signal H32		0	2^32		1/10
1.0	38149					(32 Bit Data)				
1.0	**38150**	R	7994		Status	see description				
1.0	**38151**	R	7994		Unit	x 0: None ... 4: Voltage V	0	4		1/10
1.0	**38152**	R	7999		Input signal H33		0	2^32		1/10
1.0	38153					(32 Bit Data)				
1.0	**38154**	R	7999		Status	see description				
1.0	**38155**	R	7999		Unit	x 0: None ... 4: Voltage V	0	4		1/10
1.0	**38156**	R	7728		Defrosting DI6	x 0: Off 1: On	0	1		1
1.0	**38157**	R	7728		Status/Comand	see description				
1.0	**38158**	R	7729		Error/alarm message DI7	x 0: Off 1: On	0	255		1
1.0	**38159**	R	7729		Status/Comand	see description				
1.0	**38160**	R	7911		Input EX1	x 0: 0V 1: 230V	0	1		1
1.0	**38161**	R	7911		Status/Comand	see description				
1.0	**38162**	R	7912		Input EX2	x 0: 0V 1: 230V	0	1		1
1.0	**38163**	R	7912		Status/Comand	see description				
1.0	**38164**	R	7913		Input EX3	x 0: 0V 1: 230V	0	1		1
1.0	**38165**	R	7913		Status/Comand	see description				
1.0	**38166**	R	7914		Input EX4	x 0: 0V 1: 230V	0	1		1
1.0	**38167**	R	7914		Status/Comand	see description				
1.0	**38168**	R	7915		Input EX5	x 0: 0V 1: 230V	0	1		1
1.0	**38169**	R	7915		Status/Comand	see description				
1.0	**38170**	R	7916		Input EX6	x 0: 0V 1: 230V	0	1		1
1.0	**38171**	R	7916		Status/Comand	see description				
1.0	**38172**	R	7917		Input EX7	x 0: 0V 1: 230V	0	1		1
1.0	**38173**	R	7917		Status/Comand	see description				
1.0	**38174**	R	7919		Input EX9	x 0: 0V 1: 230V	0	1		1
1.0	**38175**	R	7919		Status/Comand	see description				
1.0	**38176**	R	7945		Input EX10	x 0: 0V 1: 230V	0	1		1
1.0	**38177**	R	7945		Status/Comand	see description				
1.0	**38178**	R	7946		Input EX11	x 0: 0V 1: 230V	0	1		1
1.0	**38179**	R	7946		Status/Comand	see description				
1.0	**38180**	R	7950		Input EX21 module 1	x 0: 0V 1: 230V	0	1		1
1.0	**38181**	R	7950		Status/Comand	see description				
1.0	**38182**	R	7951		Input EX21 module 2	x 0: 0V 1: 230V	0	1		1
1.0	**38183**	R	7951		Status/Comand	see description				
1.0	**38184**	R	7952		Input EX21 module 3	x 0: 0V 1: 230V	0	1		1
1.0	**38185**	R	7952		Status/Comand	see description				
				Device Register reserve						
1.0	**38400**	R	7721		Heating mode D1	x 0: Off 1: On	0	1		1
1.0	**38401**	R	7721		Status	see description				
1.0	**38402**	R	7722		Cooling mode D2	x 0: Off 1: On	0	1		1
1.0	**38403**	R	7722		Status	see description				
1.0	**38404**	R	7723		Heat pump D3	x 0: Off 1: On	0	1		1
1.0	**38405**	R	7723		Status	see description				
1.0	**38406**	R	9031		Relay output QX1	x 0: Off 1: On	0	1		1
1.0	**38407**	R	9031		Status	see description				
1.0	**38408**	R	9032		Relay output QX2	x 0: Off 1: On	0	1		1
1.0	**38409**	R	9032		Status	see description				

1.0	**38410**	R	9033		Relay output QX3	x 0: Off 1: On	0	1		1
1.0	**38411**	R	9033		Status	see description				
1.0	**38412**	R	9034		Triac output ZX4/Relay output QX4	x 0: Off 1: On	0	1		1
1.0	**38413**	R	9034		Status	see description				
1.0	**38414**	R	9035		Relay output QX5	x 0: Off 1: On	0	1		1
1.0	**38415**	R	9035		Status	see description				
1.0	**38416**	R	9036		Triac output ZX6 / Relay output QX6	x 0: Off 1: On	0	1		1
1.0	**38417**	R	9036		Status	see description				
1.0	**38418**	R	9037		Relay output QX7	x 0: Off 1: On	0	1		1
1.0	**38419**	R	9037		Status	see description				
1.0	**38420**	R	9038		Relay output QX8	x 0: Off 1: On	0	1		1
1.0	**38421**	R	9038		Status	see description				
1.0	**38422**	R	9039		Relay output QX9	x 0: Off 1: On	0	1		1
1.0	**38423**	R	9039		Status	see description				
1.0	**38424**	R	9040		Relay output QX10	x 0: Off 1: On	0	1		1
1.0	**38425**	R	9040		Status	see description				
1.0	**38426**	R	9041		Relay output QX11	x 0: Off 1: On	0	1		1
1.0	**38427**	R	9041		Status	see description				
1.0	**38428**	R	9042		Relay output QX12	x 0: Off 1: On	0	1		1
1.0	**38429**	R	9042		Status	see description				
1.0	**38430**	R	9043		Relay output QX13	x 0: Off 1: On	0	1		1
1.0	**38431**	R	9043		Status	see description				
1.0	**38432**	R	9050		Relay output QX21 module 1	x 0: Off 1: On	0	1		1
1.0	**38433**	R	9050		Status	see description				
1.0	**38434**	R	9051		Relay output QX22 module 1	x 0: Off 1: On	0	1		1
1.0	**38435**	R	9051		Status	see description				
1.0	**38436**	R	9052		Relay output QX23 module 1	x 0: Off 1: On	0	1		1
1.0	**38437**	R	9052		Status	see description				
1.0	**38438**	R	9053		Relay output QX21 module 2	x 0: Off 1: On	0	1		1
1.0	**38439**	R	9053		Status	see description				
1.0	**38440**	R	9054		Relay output QX22 module 2	x 0: Off 1: On	0	1		1
1.0	**38441**	R	9054		Status	see description				
1.0	**38442**	R	9055		Relay output QX23 module 2	x 0: Off 1: On	0	1		1
1.0	**38443**	R	9055		Status	see description				
1.0	**38444**	R	9056		Relay output QX21 module 3	x 0: Off 1: On	0	1		1
1.0	**38445**	R	9056		Status	see description				
1.0	**38446**	R	9057		Relay output QX22 module 3	x 0: Off 1: On	0	1		1
1.0	**38447**	R	9057		Status	see description				
1.0	**38448**	R	9058		Relay output QX23 module 3	x 0: Off 1: On	0	1		1
1.0	**38449**	R	9058		Status	see description				
1.0	**38450**	R	9071		Relay output QX31	x 0: Off 1: On	0	1		1
1.0	**38451**	R	9071		Status	see description				
1.0	**38452**	R	9072		Relay output QX32	x 0: Off 1: On	0	1		1
1.0	**38453**	R	9072		Status	see description				
1.0	**38454**	R	9073		Relay output QX33	x 0: Off 1: On	0	1		1
1.0	**38455**	R	9073		Status	see description				
1.0	**38456**	R	9074		Triac output ZX34 / Relay output QX34	x 0: Off 1: On	0	1		1
1.0	**38457**	R	9074		Status	see description				
1.0	**38458**	R	9075		Relay output QX35	x 0: Off 1: On	0	1		1
1.0	**38459**	R	9075		Status	see description				
				Device Register reserve						
1.0	**38600**	R	6586		Partial diagram heat pump		0	255		1
1.0	**38601**	R	6590		Partial diagram solar collector		0	255		1
1.0	**38602**	R	6593		Partial diagram dhw storage		0	255		1
1.0	**38603**	R	6592		Partial diagram buffer		0	255		1
1.0	**38604**	R	6570		Partial diagram heat circuit 1		0	255		1
1.0	**38605**	R	6571		Partial diagram cooling circuit 1		0	255		1
1.0	**38606**	R	6572		Partial diagram heat circuit 2		0	255		1
1.0	**38607**	R	6573		Partial diagram cooling circuit 2		0	255		1
1.0	**38608**	R	6574		Partial diagram heat circuit 2		0	255		1
1.0	**38609**	R	6575		Partial diagram cooling circuit 3		0	255		1
1.0	**38610**	R	6583		Partial diagram converter		0	255		1
1.0	**38611**	R	6591		Partial diagram solid fuel boiler		0	255		1
1.0	**38612**	R	6582		Partial diagram swimming pool		0	255		1
1.0	**38613**	R	6588		Partial diagram hydraulic balancing		0	255		1
1.0	**38614**	R	6594		Partial diagram instantaneous heater		0	255		1
1.0	**38615**	R	6579		Partial diagram Consumer circuit 1		0	255		1
1.0	**38616**	R	6580		Partial diagram Consumer circuit 2		0	255		1
1.0	**38617**	R	6581		Partial diagram Consumer circuit 3		0	255		1
1.0	**38618**	R	6589		Cascade status	0: Inactiv 1: Active	0	255		1

1.0	**38619**	R	6587		Partial diagram suppl source		0	255		1
1.5	**38620**	R	6576		Partial diagram ventilation 1		0	255		1
1.5	**38621**	R	6577		Partial diagram ventilation 2		0	255		1
1.5	**38622**	R	6578		Partial diagram ventilation 3		0	255		1
1.5	**38623**	R	6584		Partial diagram converter 2		0	255		1
1.5	**38624**	R			LPB interface available	0: No x 1: Yes	0	1		1
1.5	**38625**	R			Modbus interface available	0: No x 1: Yes	0	1		1
	0x9800..0x9BEF	BL		Device block 2						
1.0	**38912**	R	6220		Software version		0.0	99		1/10
1.0	**38913**	R	6221		Development index		0	65535		1
1.0	**38914**	R			Modbus Object List Version		0.0	65535		1/10
1.0	**38915**	R	6222		Device hours run		0	199'999	h	1/3600
1.0	38916					(32 Bit Data)				
1.5	**38917**	R	6228		Bootloader version		0	65535		1/10
1.5	**38918**	R	6229		Eeprom version		0	65535		1/10
				Device Register reserve						
1.0	**38928**	R	6800		History 1	Year	100	199	Year	1
1.0	**38929**	R	6800			Month	1	12	Month	1
1.0	**38930**	R	6800			Day	1	31	Day	1
1.0	**38931**	R	6800			Hour	0	23	h	1
1.0	**38932**	R	6800			Minute	0	59	m	1
1.0	**38933**	R	6800		Status	see description				
1.0	**38934**	R	6801		Error code 1	ErrorCode	0	65535		1
1.0	**38935**	R	6801		Status	see description				
1.0	**38936**	R	6802		History 2	Year	100	199	Year	1
1.0	**38937**	R	6802			Month	1	12	Month	1
1.0	**38938**	R	6802			Day	1	31	Day	1
1.0	**38939**	R	6802			Hour	0	23	h	1
1.0	**38940**	R	6802			Minute	0	59	m	1
1.0	**38941**	R	6802		Status	see description				
1.0	**38942**	R	6803		Error code 2	ErrorCode	0	65535		1
1.0	**38943**	R	6803		Status	see description				
1.0	**38944**	R	6804		History 3	Year	100	199	Year	1
1.0	**38945**	R	6804			Month	1	12	Month	1
1.0	**38946**	R	6804			Day	1	31	Day	1
1.0	**38947**	R	6804			Hour	0	23	h	1
1.0	**38948**	R	6804			Minute	0	59	m	1
1.0	**38949**	R	6804		Status	see description				
1.0	**38950**	R	6805		Error code 3	ErrorCode	0	65535		1
1.0	**38951**	R	6805		Status	see description				
1.0	**38952**	R	6806		History 4	Year	100	199	Year	1
1.0	**38953**	R	6806			Month	1	12	Month	1
1.0	**38954**	R	6806			Day	1	31	Day	1
1.0	**38955**	R	6806			Hour	0	23	h	1
1.0	**38956**	R	6806			Minute	0	59	m	1
1.0	**38957**	R	6806		Status	see description				
1.0	**38958**	R	6807		Error code 4	ErrorCode	0	65535		1
1.0	**38959**	R	6807		Status	see description				
1.0	**38960**	R	6808		History 5	Year	100	199	Year	1
1.0	**38961**	R	6808			Month	1	12	Month	1
1.0	**38962**	R	6808			Day	1	31	Day	1
1.0	**38963**	R	6808			Hour	0	23	h	1
1.0	**38964**	R	6808			Minute	0	59	m	1
1.0	**38965**	R	6808		Status	see description				
1.0	**38966**	R	6809		Error code 5	ErrorCode	0	65535		1
1.0	**38967**	R	6809		Status	see description				
1.0	**38968**	R	6810		History 6	Year	100	199	Year	1
1.0	**38969**	R	6810			Month	1	12	Month	1
1.0	**38970**	R	6810			Day	1	31	Day	1
1.0	**38971**	R	6810			Hour	0	23	h	1
1.0	**38972**	R	6810			Minute	0	59	m	1
1.0	**38973**	R	6810		Status	see description				
1.0	**38974**	R	6811		Error code 6	ErrorCode	0	65535		1
1.0	**38975**	R	6811		Status	see description				
1.0	**38976**	R	6812		History 7	Year	100	199	Year	1
1.0	**38977**	R	6812			Month	1	12	Month	1
1.0	**38978**	R	6812			Day	1	31	Day	1
1.0	**38979**	R	6812			Hour	0	23	h	1
1.0	**38980**	R	6812			Minute	0	59	m	1
1.0	**38981**	R	6812		Status	see description				
1.0	**38982**	R	6813		Error code 7	ErrorCode	0	65535		1
1.0	**38983**	R	6813		Status	see description				
1.0	**38984**	R	6814		History 8	Year	100	199	Year	1
1.0	**38985**	R	6814			Month	1	12	Month	1
1.0	**38986**	R	6814			Day	1	31	Day	1
1.0	**38987**	R	6814			Hour	0	23	h	1
1.0	**38988**	R	6814			Minute	0	59	m	1
1.0	**38989**	R	6814		Status	see description				
1.0	**38990**	R	6815		Error code 8	ErrorCode	0	65535		1
1.0	**38991**	R	6815		Status	see description				
1.0	**38992**	R	6816		History 9	Year	100	199	Year	1
1.0	**38993**	R	6816			Month	1	12	Month	1
1.0	**38994**	R	6816			Day	1	31	Day	1
1.0	**38995**	R	6816			Hour	0	23	h	1
1.0	**38996**	R	6816			Minute	0	59	m	1
1.0	**38997**	R	6816		Status	see description				
1.0	**38998**	R	6817		Error code 9	ErrorCode	0	65535		1
1.0	**38999**	R	6817		Status	see description				
1.0	**39000**	R	6818		History 10	Year	100	199	Year	1
1.0	**39001**	R	6818			Month	1	12	Month	1
1.0	**39002**	R	6818			Day	1	31	Day	1
1.0	**39003**	R	6818			Hour	0	23	h	1
1.0	**39004**	R	6818			Minute	0	59	m	1
1.0	**39005**	R	6818		Status	see description				

1.0	**39006**	R	6819		Error code 10	ErrorCode	0	65535		1
1.0	**39007**	R	6819		Status	see description				
1.0	**39008**	R/W	6820		Reset history	x 0: No 1: Yes	0	1		1
				Device Register reserve						
1.0	**39040**	R	6700		Error Message	ErrorCode	0	65535		1
1.0	**39041**	R			Error Prio	priority	0	65535		
1.0	**39042**	R			Service Message	ServiceCode	0	65535		
1.0	**39043**	R			Error Prio	priority	0	65535		
1.0	**39044**	R			Info Sonderbetrieb	Bit7: Special opreration active Bit0..6: Special operation: 0= Normal (no special opreration) 1= Manual operation 2= SLT test 3= Chimney sweep function 4= Controller stop 5= Combustion optimization low-fire 6= Combustion optimization high-fire 7= Emergency operation 8= Output test 9= Simulation outside temp 10= Alternative energy mode 11= Commissioning function 12= Deareation function 13= Dry fire function 14= Eco opertation 15= Initializing 16= DHW Push	0	255		
1.5	**39045**	R			Responsibility for message	x 0: No display of responsibility 1: Only display phone no 2: Service 3: Customer service 4: Installer 5: Janitor 6: Administration 7: Refrigeration engineer 8: Hotline	0	8		1
1.5	**39046**	R			Telephone responsibility for message		0	255		1
1.5	**39047**	R					0	255		1
1.5	**39048**	R					0	255		1
1.5	**39049**	R					0	255		1
1.5	**39050**	R					0	255		1
1.5	**39051**	R					0	255		1
1.5	**39052**	R					0	255		1
1.5	**39053**	R					0	255		1
1.5	**39054**	R					0	255		1
1.5	**39055**	R					0	255		1
1.5	**39056**	R					0	255		1
1.5	**39057**	R					0	255		1
1.5	**39058**	R					0	255		1
1.5	**39059**	R					0	255		1
1.5	**39060**	R					0	255		1
1.5	**39061**	R					0	255		1
1.5	**39062**	R			Responsibility for message	x 0: No display of responsibility 1: Only display phone no 2: Service 3: Customer service 4: Installer 5: Janitor 6: Administration 7: Refrigeration engineer 8: Hotline	0	8		1
1.5	**39063**	R			Telephone responsibility for message		0	255		1
1.5	**39064**	R					0	255		1
1.5	**39065**	R					0	255		1
1.5	**39066**	R					0	255		1
1.5	**39067**	R					0	255		1
1.5	**39068**	R					0	255		1
1.5	**39069**	R					0	255		1
1.5	**39070**	R					0	255		1
1.5	**39071**	R					0	255		1
1.5	**39072**	R					0	255		1
1.5	**39073**	R					0	255		1
1.5	**39074**	R					0	255		1
1.5	**39075**	R					0	255		1
1.5	**39076**	R					0	255		1
1.5	**39077**	R					0	255		1
1.5	**39078**	R					0	255		1
				Device Register reserve						
1.5	**39100**	R	8050		Time stamp status history entry 1	Year	100	199	Year	1
1.5	**39101**	R	8050			Month	1	12	Month	1
1.5	**39102**	R	8050			Day	1	31	Day	1
1.5	**39103**	R	8050			Hour	0	23	h	1
1.5	**39104**	R	8050			Minute	0	59	m	1
1.5	**39105**	R	8050		Status	see description				
1.5	**39106**	R	8051		Status code history entry 1	StatusCode	0	65535		1
1.5	**39107**	R	8051		Status	see description				
1.5	**39108**	R	8052		Time stamp status history entry 2	Year	100	199	Year	1
1.5	**39109**	R	8052			Month	1	12	Month	1
1.5	**39110**	R	8052			Day	1	31	Day	1
1.5	**39111**	R	8052			Hour	0	23	h	1
1.5	**39112**	R	8052			Minute	0	59	m	1
1.5	**39113**	R	8052		Status	see description				
1.5	**39114**	R	8053		Status code history entry 2	StatusCode	0	65535		1
1.5	**39115**	R	8053		Status	see description				
1.5	**39116**	R	8054		Time stamp status history entry 3	Year	100	199	Year	1

1.5	**39117**	R	8054			Month	1	12	Month	1
1.5	**39118**	R	8054			Day	1	31	Day	1
1.5	**39119**	R	8054			Hour	0	23	h	1
1.5	**39120**	R	8054			Minute	0	59	m	1
1.5	**39121**	R	8054		Status	see description				
1.5	**39122**	R	8055		Status code history entry 3	StatusCode	0	65535		1
1.5	**39123**	R	8055		Status	see description				
1.5	**39124**	R	8056		Time stamp status history entry 4	Year	100	199	Year	1
1.5	**39125**	R	8056			Month	1	12	Month	1
1.5	**39126**	R	8056			Day	1	31	Day	1
1.5	**39127**	R	8056			Hour	0	23	h	1
1.5	**39128**	R	8056			Minute	0	59	m	1
1.5	**39129**	R	8056		Status	see description				
1.5	**39130**	R	8057		Status code history entry 4	StatusCode	0	65535		1
1.5	**39131**	R	8057		Status	see description				
1.5	**39132**	R	8058		Time stamp status history entry 5	Year	100	199	Year	1
1.5	**39133**	R	8058			Month	1	12	Month	1
1.5	**39134**	R	8058			Day	1	31	Day	1
1.5	**39135**	R	8058			Hour	0	23	h	1
1.5	**39136**	R	8058			Minute	0	59	m	1
1.5	**39137**	R	8058		Status	see description				
1.5	**39138**	R	8059		Status code history entry 5	StatusCode	0	65535		1
1.5	**39139**	R	8059		Status	see description				
1.5	**39140**	R	8060		Time stamp status history entry 6	Year	100	199	Year	1
1.5	**39141**	R	8060			Month	1	12	Month	1
1.5	**39142**	R	8060			Day	1	31	Day	1
1.5	**39143**	R	8060			Hour	0	23	h	1
1.5	**39144**	R	8060			Minute	0	59	m	1
1.5	**39145**	R	8060		Status	see description				
1.5	**39146**	R	8061		Status code history entry 6	StatusCode	0	65535		1
1.5	**39147**	R	8061		Status	see description				
1.5	**39148**	R	8062		Time stamp status history entry 7	Year	100	199	Year	1
1.5	**39149**	R	8062			Month	1	12	Month	1
1.5	**39150**	R	8062			Day	1	31	Day	1
1.5	**39151**	R	8062			Hour	0	23	h	1
1.5	**39152**	R	8062			Minute	0	59	m	1
1.5	**39153**	R	8062		Status	see description				
1.5	**39154**	R	8063		Status code history entry 7	StatusCode	0	65535		1
1.5	**39155**	R	8063		Status	see description				
1.5	**39156**	R	8064		Time stamp status history entry 8	Year	100	199	Year	1
1.5	**39157**	R	8064			Month	1	12	Month	1
1.5	**39158**	R	8064			Day	1	31	Day	1
1.5	**39159**	R	8064			Hour	0	23	h	1
1.5	**39160**	R	8064			Minute	0	59	m	1
1.5	**39161**	R	8064		Status	see description				
1.5	**39162**	R	8065		Status code history entry 8	StatusCode	0	65535		1
1.5	**39163**	R	8065		Status	see description				
1.5	**39164**	R	8066		Time stamp status history entry 9	Year	100	199	Year	1
1.5	**39165**	R	8066			Month	1	12	Month	1
1.5	**39166**	R	8066			Day	1	31	Day	1
1.5	**39167**	R	8066			Hour	0	23	h	1
1.5	**39168**	R	8066			Minute	0	59	m	1
1.5	**39169**	R	8066		Status	see description				
1.5	**39170**	R	8067		Status code history entry 9	StatusCode	0	65535		1
1.5	**39171**	R	8067		Status	see description				
1.5	**39172**	R	8068		Time stamp status history entry 10	Year	100	199	Year	1
1.5	**39173**	R	8068			Month	1	12	Month	1
1.5	**39174**	R	8068			Day	1	31	Day	1
1.5	**39175**	R	8068			Hour	0	23	h	1
1.5	**39176**	R	8068			Minute	0	59	m	1
1.5	**39177**	R	8068		Status	see description				
1.5	**39178**	R	8069		Status code history entry 10	StatusCode	0	65535		1
1.5	**39179**	R	8069		Status	see description				
1.5	**39180**	R/W	8070		Reset history	x 0: No 1: Yes	0	1		1
		BL		Service/special operation						
1.5	**39200**	R/W	7167		Commissioning Wizard	0: Off x 1: On	0	1		1
1.5	**39201**	R/W	7168		Production test wizard	0: Off x 1: On	0	1		1
1.5	**39202**	R/W	7180		Text responsibility 1	x 0: No display of responsibility 1: Only display phone no 2: Service 3: Customer service 4: Installer 5: Janitor 6: Administration 7: Refrigeration engineer 8: Hotline	0	8		1
1.5	**39203**	R/W	7181		Telephone responsibility 1		0	255		1
1.5	**39204**	R/W					0	255		1
1.5	**39205**	R/W					0	255		1
1.5	**39206**	R/W					0	255		1
1.5	**39207**	R/W					0	255		1
1.5	**39208**	R/W					0	255		1
1.5	**39209**	R/W					0	255		1
1.5	**39210**	R/W					0	255		1
1.5	**39211**	R/W					0	255		1
1.5	**39212**	R/W					0	255		1
1.5	**39213**	R/W					0	255		1
1.5	**39214**	R/W					0	255		1
1.5	**39215**	R/W					0	255		1
1.5	**39216**	R/W					0	255		1
1.5	**39217**	R/W					0	255		1
1.5	**39218**	R/W					0	255		1

1.5	**39219**	R/W	7182		Text responsibility 2	x 0: No display of responsibility 1: Only display phone no 2: Service 3: Customer service 4: Installer 5: Janitor 6: Administration 7: Refrigeration engineer 8: Hotline	0	8		1
1.5	**39220**	R/W	7183		Telephone responsibility 2		0	255		1
1.5	**39221**	R/W					0	255		1
1.5	**39222**	R/W					0	255		1
1.5	**39223**	R/W					0	255		1
1.5	**39224**	R/W					0	255		1
1.5	**39225**	R/W					0	255		1
1.5	**39226**	R/W					0	255		1
1.5	**39227**	R/W					0	255		1
1.5	**39228**	R/W					0	255		1
1.5	**39229**	R/W					0	255		1
1.5	**39230**	R/W					0	255		1
1.5	**39231**	R/W					0	255		1
1.5	**39232**	R/W					0	255		1
1.5	**39233**	R/W					0	255		1
1.5	**39234**	R/W					0	255		1
1.5	**39235**	R/W					0	255		1
1.5	**39236**	R/W	7184		Text responsibility 3	x 0: No display of responsibility 1: Only display phone no 2: Service 3: Customer service 4: Installer 5: Janitor 6: Administration 7: Refrigeration engineer 8: Hotline	0	8		1
1.5	**39237**	R/W	7185		Telephone responsibility 3		0	255		1
1.5	**39238**	R/W					0	255		1
1.5	**39239**	R/W					0	255		1
1.5	**39240**	R/W					0	255		1
1.5	**39241**	R/W					0	255		1
1.5	**39242**	R/W					0	255		1
1.5	**39243**	R/W					0	255		1
1.5	**39244**	R/W					0	255		1
1.5	**39245**	R/W					0	255		1
1.5	**39246**	R/W					0	255		1
1.5	**39247**	R/W					0	255		1
1.5	**39248**	R/W					0	255		1
1.5	**39249**	R/W					0	255		1
1.5	**39250**	R/W					0	255		1
1.5	**39251**	R/W					0	255		1
1.5	**39252**	R/W					0	255		1
1.5	**39253**	R/W	7186		Text responsibility 4	x 0: No display of responsibility 1: Only display phone no 2: Service 3: Customer service 4: Installer 5: Janitor 6: Administration 7: Refrigeration engineer 8: Hotline	0	8		1
1.5	**39254**	R/W	7187		Telephone responsibility 4		0	255		1
1.5	**39255**	R/W					0	255		1
1.5	**39256**	R/W					0	255		1
1.5	**39257**	R/W					0	255		1
1.5	**39258**	R/W					0	255		1
1.5	**39259**	R/W					0	255		1
1.5	**39260**	R/W					0	255		1
1.5	**39261**	R/W					0	255		1
1.5	**39262**	R/W					0	255		1
1.5	**39263**	R/W					0	255		1
1.5	**39264**	R/W					0	255		1
1.5	**39265**	R/W					0	255		1
1.5	**39266**	R/W					0	255		1
1.5	**39267**	R/W					0	255		1
1.5	**39268**	R/W					0	255		1
1.5	**39269**	R/W					0	255		1
1.5	**39270**	R/W	7188		Text responsibility 5	x 0: No display of responsibility 1: Only display phone no 2: Service 3: Customer service 4: Installer 5: Janitor 6: Administration 7: Refrigeration engineer 8: Hotline	0	8		1
1.5	**39271**	R/W	7189		Telephone responsibility 5		0	255		1
1.5	**39272**	R/W					0	255		1
1.5	**39273**	R/W					0	255		1
1.5	**39274**	R/W					0	255		1
1.5	**39275**	R/W					0	255		1
1.5	**39276**	R/W					0	255		1
1.5	**39277**	R/W					0	255		1
1.5	**39278**	R/W					0	255		1
1.5	**39279**	R/W					0	255		1
1.5	**39280**	R/W					0	255		1
1.5	**39281**	R/W					0	255		1
1.5	**39282**	R/W					0	255		1

1.5	**39283**	R/W					0	255		1
1.5	**39284**	R/W					0	255		1
1.5	**39285**	R/W					0	255		1
1.5	**39286**	R/W					0	255		1
	0x9BF0..0x9FFF	BL		Device block 3						
1.0	**39920**	R/W			Clock time and Date	Year	100	199	Year	1
1.0	**39921**	R/W			Clock time and Date	Month	1	12	Month	1
1.0	**39922**	R/W			Clock time and Date	Day	1	31	Day	1
1.0	**39923**	R/W			Clock time and Date	Hour	0	23	h	1
1.0	**39924**	R/W			Clock time and Date	Minute	0	59	min	1
1.0	**39925**	R/W			Clock time and Date	Second	0	59	s	1
1.5	**39926**	R/W			Clock time and Date	Day of week	1	7	Day	1
1.5	**39927**	R/W	5		Start of summertime		1	12	Month	1
1.5	**39928**	R/W	5		Start of summertime		1	31	Day	1
1.5	**39929**	R/W	6		End of summertime		1	12	Month	1
1.5	**39930**	R/W	6		End of summertime		1	31	Day	1
		BL		Time prog heating circuit 1						
1.0	**39940**	R/W	501, 502		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39941**	R/W	503, 504		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39942**	R/W	505, 506		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39943**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39944**	R/W	501, 502		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39945**	R/W	503, 504		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39946**	R/W	505, 506		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39947**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39948**	R/W	501, 502		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39949**	R/W	503, 504		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39950**	R/W	505, 506		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39951**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39952**	R/W	501, 502		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39953**	R/W	503, 504		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39954**	R/W	505, 506		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39955**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39956**	R/W	501, 502		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39957**	R/W	503, 504		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39958**	R/W	505, 506		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39959**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39960**	R/W	501, 502		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39961**	R/W	503, 504		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39962**	R/W	505, 506		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39963**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39964**	R/W	501, 502		Sunday 1st phase on	H-Byte: phase on	00:00	24:00	h:m	10min

					Sunday 1st phase off	L-Byte: phase off	00:00	24:00		
1.0	**39965**	R/W	503, 504		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39966**	R/W	505, 506		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39967**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39968**	R/W	516		Default values	x 0: No 1: Yes	0	1		1
		BL		Time prog heating circuit 2						
1.0	**39980**	R/W	521, 522		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39981**	R/W	523, 524		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39982**	R/W	525, 526		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39983**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39984**	R/W	521, 522		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39985**	R/W	523, 524		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39986**	R/W	525, 526		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39987**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39988**	R/W	521, 522		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39989**	R/W	523, 524		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39990**	R/W	525, 526		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39991**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39992**	R/W	521, 522		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39993**	R/W	523, 524		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39994**	R/W	525, 526		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39995**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**39996**	R/W	521, 522		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39997**	R/W	523, 524		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39998**	R/W	525, 526		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**39999**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40000**	R/W	521, 522		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40001**	R/W	523, 524		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40002**	R/W	525, 526		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40003**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40004**	R/W	521, 522		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40005**	R/W	523, 524		Sunday 2nd phase on	H-Byte: phase on	00:00	24:00	h:m	10min

					Sunday 2nd phase off	L-Byte: phase off	00:00	24:00		
1.0	**40006**	R/W	525, 526		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40007**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40008**	R/W	536		Default values	x 0: No 1: Yes	0	1		1
		BL		Time program 3/HC3						
1.0	**40040**	R/W	541, 542		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40041**	R/W	543, 544		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40042**	R/W	545, 546		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40043**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40044**	R/W	541, 542		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40045**	R/W	543, 544		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40046**	R/W	545, 546		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40047**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40048**	R/W	541, 542		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40049**	R/W	543, 544		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40050**	R/W	545, 546		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40051**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40052**	R/W	541, 542		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40053**	R/W	543, 544		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40054**	R/W	545, 546		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40055**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40056**	R/W	541, 542		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40057**	R/W	543, 544		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40058**	R/W	545, 546		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40059**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40060**	R/W	541, 542		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40061**	R/W	543, 544		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40062**	R/W	545, 546		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40063**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40064**	R/W	541, 542		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40065**	R/W	543, 544		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40066**	R/W	545, 546		Sunday 3rd phase on	H-Byte: phase on	00:00	24:00	h:m	10min

					Sunday 3rd phase off	L-Byte: phase off	00:00	24:00		
1.0	**40067**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40068**	R/W	556		Default values	x 0: No 1: Yes	0	1		1
		BL		Time program 4 / DHW						
1.0	**40080**	R/W	561, 562		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40081**	R/W	563, 564		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40082**	R/W	565, 566		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40083**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40084**	R/W	561, 562		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40085**	R/W	563, 564		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40086**	R/W	565, 566		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40087**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40088**	R/W	561, 562		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40089**	R/W	563, 564		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40090**	R/W	565, 566		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40091**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40092**	R/W	561, 562		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40093**	R/W	563, 564		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40094**	R/W	565, 566		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40095**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40096**	R/W	561, 562		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40097**	R/W	563, 564		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40098**	R/W	565, 566		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40099**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40100**	R/W	561, 562		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40101**	R/W	563, 564		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40102**	R/W	565, 566		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40103**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40104**	R/W	561, 562		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40105**	R/W	563, 564		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40106**	R/W	565, 566		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min

1.0	**40107**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40108**	R/W	576		Default values	x 0: No 1: Yes	0	1		1
		BL		Time program 5						
1.0	**40140**	R/W	601, 602		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40141**	R/W	603, 604		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40142**	R/W	605, 606		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40143**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40144**	R/W	601, 602		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40145**	R/W	603, 604		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40146**	R/W	605, 606		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40147**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40148**	R/W	601, 602		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40149**	R/W	603, 604		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40150**	R/W	605, 606		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40151**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40152**	R/W	601, 602		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40153**	R/W	603, 604		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40154**	R/W	605, 606		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40155**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40156**	R/W	601, 602		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40157**	R/W	603, 604		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40158**	R/W	605, 606		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40159**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40160**	R/W	601, 602		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40161**	R/W	603, 604		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40162**	R/W	605, 606		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40163**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40164**	R/W	601, 602		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40165**	R/W	603, 604		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.0	**40166**	R/W	605, 606		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min

1.0	**40167**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.0	**40168**	R/W	616		Default values	x 0: No 1: Yes	0	1		1
		BL		Time prog cooling circuit 1						
1.6	**40180**	R/W	471, 472		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40181**	R/W	473, 474		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40182**	R/W	475, 476		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40183**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40184**	R/W	471, 472		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40185**	R/W	473, 474		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40186**	R/W	475, 476		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40187**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40188**	R/W	471, 472		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40189**	R/W	473, 474		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40190**	R/W	475, 476		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40191**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40192**	R/W	471, 472		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40193**	R/W	473, 474		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40194**	R/W	475, 476		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40195**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40196**	R/W	471, 472		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40197**	R/W	473, 474		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40198**	R/W	475, 476		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40199**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40200**	R/W	471, 472		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40201**	R/W	473, 474		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40202**	R/W	475, 476		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40203**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40204**	R/W	471, 472		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40205**	R/W	473, 474		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40206**	R/W	475, 476		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min

1.6	**40207**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40208**	R/W	479		Default values	x 0: No 1: Yes	0	1		1
		BL	Time prog cooling circuit 2							
1.6	**40240**	R/W	481, 482		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40241**	R/W	483, 484		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40242**	R/W	485, 486		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40243**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40244**	R/W	481, 482		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40245**	R/W	483, 484		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40246**	R/W	485, 486		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40247**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40248**	R/W	481, 482		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40249**	R/W	483, 484		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40250**	R/W	485, 486		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40251**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40252**	R/W	481, 482		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40253**	R/W	483, 484		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40254**	R/W	485, 486		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40255**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40256**	R/W	481, 482		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40257**	R/W	483, 484		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40258**	R/W	485, 486		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40259**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40260**	R/W	481, 482		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40261**	R/W	483, 484		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40262**	R/W	485, 486		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40263**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40264**	R/W	481, 482		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40265**	R/W	483, 484		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40266**	R/W	485, 486		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min

1.6	**40267**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40268**	R/W	489		Default values	x 0: No 1: Yes	0	1		1
		BL	Time prog cooling circuit 3							
1.6	**40280**	R/W	491, 492		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40281**	R/W	493, 494		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40282**	R/W	495, 496		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40283**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40284**	R/W	491, 492		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40285**	R/W	493, 494		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40286**	R/W	495, 496		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40287**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40288**	R/W	491, 492		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40289**	R/W	493, 494		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40290**	R/W	495, 496		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40291**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40292**	R/W	491, 492		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40293**	R/W	493, 494		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40294**	R/W	495, 496		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40295**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40296**	R/W	491, 492		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40297**	R/W	493, 494		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40298**	R/W	495, 496		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40299**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40300**	R/W	491, 492		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40301**	R/W	493, 494		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40302**	R/W	495, 496		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40303**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40304**	R/W	491, 492		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40305**	R/W	493, 494		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.6	**40306**	R/W	495, 496		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min

1.6	**40307**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.6	**40308**	R/W	499		Default values	x 0: No 1: Yes	0	1		1
		BL		Holidays heating circuit 1						
1.0	**40400**	R/W	642		Holidays Start 1	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40401**	R/W	642		Status/Comand	see description				
1.0	**40402**	R/W	643		Holidays Ende 1	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40403**	R/W	643		Status/Comand	see description				
1.0	**40404**	R/W	642		Holidays Start 2	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40405**	R/W	642		Status/Comand	see description				
1.0	**40406**	R/W	643		Holidays Ende 2	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40407**	R/W	643		Status/Comand	see description				
1.0	**40408**	R/W	642		Holidays Start 3	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40409**	R/W	642		Status/Comand	see description				
1.0	**40410**	R/W	643		Holidays Ende 3	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40411**	R/W	643		Status/Comand	see description				
1.0	**40412**	R/W	642		Holidays Start 4	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40413**	R/W	642		Status/Comand	see description				
1.0	**40414**	R/W	643		Holidays Ende 4	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40415**	R/W	643		Status/Comand	see description				
1.0	**40416**	R/W	642		Holidays Start 5	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40417**	R/W	642		Status/Comand	see description				
1.0	**40418**	R/W	643		Holidays Ende 5	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40419**	R/W	643		Status/Comand	see description				
1.0	**40420**	R/W	642		Holidays Start 6	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40421**	R/W	642		Status/Comand	see description				
1.0	**40422**	R/W	643		Holidays Ende 6	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40423**	R/W	643		Status/Comand	see description				
1.0	**40424**	R/W	642		Holidays Start 7	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40425**	R/W	642		Status/Comand	see description				
1.0	**40426**	R/W	643		Holidays Ende 7	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40427**	R/W	643		Status/Comand	see description				
1.0	**40428**	R/W	642		Holidays Start 8	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40429**	R/W	642		Status/Comand	see description				
1.0	**40430**	R/W	643		Holidays Ende 8	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40431**	R/W	643		Status/Comand	see description				
1.0	**40432**	R/W	648		Holidays Operating level	x 0: Frost protection 1: Reduced	0	1		1
		BL		Holidays heating circuit 2						
1.0	**40440**	R/W	652		Holidays Start 1	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40441**	R/W	652		Status/Comand	see description				
1.0	**40442**	R/W	653		Holidays Ende 1	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40443**	R/W	653		Status/Comand	see description				
1.0	**40444**	R/W	652		Holidays Start 2	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40445**	R/W	652		Status/Comand	see description				
1.0	**40446**	R/W	653		Holidays Ende 2	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40447**	R/W	653		Status/Comand	see description				
1.0	**40448**	R/W	652		Holidays Start 3	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40449**	R/W	652		Status/Comand	see description				
1.0	**40450**	R/W	653		Holidays Ende 3	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40451**	R/W	653		Status/Comand	see description				
1.0	**40452**	R/W	652		Holidays Start 4	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40453**	R/W	652		Status/Comand	see description				
1.0	**40454**	R/W	653		Holidays Ende 4	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40455**	R/W	653		Status/Comand	see description				
1.0	**40456**	R/W	652		Holidays Start 5	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40457**	R/W	652		Status/Comand	see description				
1.0	**40458**	R/W	653		Holidays Ende 5	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40459**	R/W	653		Status/Comand	see description				
1.0	**40460**	R/W	652		Holidays Start 6	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40461**	R/W	652		Status/Comand	see description				
1.0	**40462**	R/W	653		Holidays Ende 6	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1

1.0	**40463**	R/W	653		Status/Comand	see description				
1.0	**40464**	R/W	652		Holidays Start 7	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40465**	R/W	652		Status/Comand	see description				
1.0	**40466**	R/W	653		Holidays Ende 7	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40467**	R/W	653		Status/Comand	see description				
1.0	**40468**	R/W	652		Holidays Start 8	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40469**	R/W	652		Status/Comand	see description				
1.0	**40470**	R/W	653		Holidays Ende 8	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40471**	R/W	653		Status/Comand	see description				
1.0	**40472**	R/W	658		Holidays Operating level	x 0: Frost protection 1: Reduced	0	1		1
		BL		Holidays heating circuit 3						
1.0	**40480**	R/W	662		Holidays Start 1	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40481**	R/W	662		Status/Comand	see description				
1.0	**40482**	R/W	663		Holidays Ende 1	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40483**	R/W	663		Status/Comand	see description				
1.0	**40484**	R/W	662		Holidays Start 2	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40485**	R/W	662		Status/Comand	see description				
1.0	**40486**	R/W	663		Holidays Ende 2	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40487**	R/W	663		Status/Comand	see description				
1.0	**40488**	R/W	662		Holidays Start 3	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40489**	R/W	662		Status/Comand	see description				
1.0	**40490**	R/W	663		Holidays Ende 3	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40491**	R/W	663		Status/Comand	see description				
1.0	**40492**	R/W	662		Holidays Start 4	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40493**	R/W	662		Status/Comand	see description				
1.0	**40494**	R/W	663		Holidays Ende 4	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40495**	R/W	663		Status/Comand	see description				
1.0	**40496**	R/W	662		Holidays Start 5	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40497**	R/W	662		Status/Comand	see description				
1.0	**40498**	R/W	663		Holidays Ende 5	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40499**	R/W	663		Status/Comand	see description				
1.0	**40500**	R/W	662		Holidays Start 6	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40501**	R/W	662		Status/Comand	see description				
1.0	**40502**	R/W	663		Holidays Ende 6	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40503**	R/W	663		Status/Comand	see description				
1.0	**40504**	R/W	662		Holidays Start 7	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40505**	R/W	662		Status/Comand	see description				
1.0	**40506**	R/W	663		Holidays Ende 7	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40507**	R/W	663		Status/Comand	see description				
1.0	**40508**	R/W	662		Holidays Start 8	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40509**	R/W	662		Status/Comand	see description				
1.0	**40510**	R/W	663		Holidays Ende 8	H-Byte: Month L-Byte: Day	1 1	12 31	Month Day	1
1.0	**40511**	R/W	663		Status/Comand	see description				
1.0	**40512**	R/W	668		Holidays Operating level	x 0: Frost protection 1: Reduced	0	1		1
		BL		Time program ventilation 1						
1.5	**40520**	R/W	581, 582		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40521**	R/W	583, 584		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40522**	R/W	585, 586		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40523**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40524**	R/W	581, 582		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40525**	R/W	583, 584		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40526**	R/W	585, 586		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40527**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40528**	R/W	581, 582		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40529**	R/W	583, 584		Wednesday 2nd phase on	H-Byte: phase on	00:00	24:00	h:m	10min

					Wednesday 2nd phase off	L-Byte: phase off	00:00	24:00		
1.5	**40530**	R/W	585, 586		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40531**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40532**	R/W	581, 582		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40533**	R/W	583, 584		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40534**	R/W	585, 586		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40535**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40536**	R/W	581, 582		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40537**	R/W	583, 584		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40538**	R/W	585, 586		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40539**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40540**	R/W	581, 582		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40541**	R/W	583, 584		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40542**	R/W	585, 586		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40543**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40544**	R/W	581, 582		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40545**	R/W	583, 584		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40546**	R/W	585, 586		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40547**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40548**	R/W	589		Standard values TSP	x 0: No 1: Yes	0	1		1
		BL		Time program ventilation 2						
1.5	**40560**	R/W	591, 592		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40561**	R/W	593, 594		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40562**	R/W	595, 596		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40563**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40564**	R/W	591, 592		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40565**	R/W	593, 594		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40566**	R/W	595, 596		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40567**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40568**	R/W	591, 592		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40569**	R/W	593, 594		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40570**	R/W	595, 596		Wednesday 3rd phase on	H-Byte: phase on	00:00	24:00	h:m	10min

					Wednesday 3rd phase off	L-Byte: phase off	00:00	24:00		
1.5	**40571**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40572**	R/W	591, 592		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40573**	R/W	593, 594		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40574**	R/W	595, 596		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40575**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40576**	R/W	591, 592		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40577**	R/W	593, 594		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40578**	R/W	595, 596		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40579**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40580**	R/W	591, 592		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40581**	R/W	593, 594		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40582**	R/W	595, 596		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40583**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40584**	R/W	591, 592		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40585**	R/W	593, 594		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40586**	R/W	595, 596		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40587**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40588**	R/W	599		Standard values TSP	x 0: No 1: Yes	0	1		1
		BL		Time program ventilation 3						
1.5	**40600**	R/W	621, 622		Monday 1st phase on Monday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40601**	R/W	623, 624		Monday 2nd phase on Monday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40602**	R/W	625, 626		Monday 3rd phase on Monday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40603**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40604**	R/W	621, 622		Tuesday 1st phase on Tuesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40605**	R/W	623, 624		Tuesday 2nd phase on Tuesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40606**	R/W	625, 626		Tuesday 3rd phase on Tuesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40607**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40608**	R/W	621, 622		Wednesday 1st phase on Wednesday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40609**	R/W	623, 624		Wednesday 2nd phase on Wednesday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40610**	R/W	625, 626		Wednesday 3rd phase on Wednesday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min

1.5	**40611**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40612**	R/W	621, 622		Thursday 1st phase on Thursday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40613**	R/W	623, 624		Thursday 2nd phase on Thursday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40614**	R/W	625, 626		Thursday 3rd phase on Thursday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40615**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40616**	R/W	621, 622		Friday 1st phase on Friday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40617**	R/W	623, 624		Friday 2nd phase on Friday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40618**	R/W	625, 626		Friday 3rd phase on Friday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40619**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40620**	R/W	621, 622		Saturday 1st phase on Saturday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40621**	R/W	623, 624		Saturday 2nd phase on Saturday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40622**	R/W	625, 626		Saturday 3rd phase on Saturday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40623**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40624**	R/W	621, 622		Sunday 1st phase on Sunday 1st phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40625**	R/W	623, 624		Sunday 2nd phase on Sunday 2nd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40626**	R/W	625, 626		Sunday 3rd phase on Sunday 3rd phase off	H-Byte: phase on L-Byte: phase off	00:00 00:00	24:00 24:00	h:m	10min
1.5	**40627**	R/W			Status / Comand Switching phase status	Bit 0:1st phase on inactive Bit 1:1st phase off inactive Bit 2:2nd phase on inactive Bit 3:2nd phase off inactive Bit 4:3rd phase on inactive Bit 5:3rd phase off inactive Bit6-15: Unused				
1.5	**40628**	R/W	629		Standard values TSP	x 0: No 1: Yes	0	1		1
		BL		Local Process Bus						
1.5	**40640**	R/W	6600		Device address		0	16		1
1.5	**40641**	R/W	6601		Segment address		0	14		1
1.5	**40642**	R/W	6604		LPB power supply function selection	0: Off x 1: Automatic	0	1		1
1.5	**40643**	R/W	6605		LPB power supply status	0: Off x 1: On	0	1		1
1.5	**40644**	R/W	6610		Display system message	0: No x 1: Yes	0	1		1
1.5	**40645**	R/W	6612		Alarm delay		2	60	min	1
1.5	**40646**	R/W	6612		Status/Comand	see description				
1.5	**40647**	R/W	6620		Central switch-over working area	0: Segment x 1: System	0	1		1
1.5	**40648**	R/W	6621		Summer/winter changeover automatic	x 0: Local 1: Central	0	1		1
1.5	**40649**	R/W	6623		Operating mode changeover	0: Local x 1: Central	0	1		1
1.5	**40650**	R/W	6625		Dhw allocation	0: All heating-/cooling circuits local 1: All heating-/cooling circuits within segment x 2: All heating-/cooling circuits within system	0	2		1
1.5	**40651**	R/W	6627		Cool demand	0: Local x 1: Central	0	1		1
1.5	**40652**	R/W	6630		Cascade master	1: Off x 2: Automatically	1	2		1
1.5	**40653**	R/W	6632		Outside temp limit external source accept	0: No x 1: Yes	0	1		1
1.5	**40654**	R/W	6640		Clock time source	x 0: Autonomous clock in the controller 1: From bus: slave without remote setting 2: From bus: slave with remote setting 3: Controller is the clock time master	0	3		1
	0xA400..0xA7FF	BL		**Process Signals (Bridging Solution, for additional features and more detailed information see special Document)**						
1.0	**41984** **...** **42055**	-	-		reserved - see special Document					
1.0	**41984**	R			TempAnfoEMxt	Value	0	140	°C	1/64

1.0	41985					Attribute	0	65535		
1.0	41986					Prio	0	16		
1.0	41987					Lrel	0	100	%	1
1.0	41988					AttributeExt	0	65535		
1.0	not used									
1.0	**41990**	R/W			StatEExt	Attribute	0	65535		
1.0	41991					LeistRel	0	100	%	1
1.0	41992					LeistAbs	0	65535	kWh	1/10
1.0	41993					BetStd	0	65535	h	1
1.0	41994					AttributeExt	0	65535		
1.0	not used									
1.0	not used									
1.0	**41997**	R/W			ProzSperrErz	H-Byte: c8Value L-Byte: c8Attribut	0 0	100 255	%	1
1.0	**41998**	R/W			ProzZwangErz	H-Byte: c8Value L-Byte: c8Attribut	0 0	100 255	%	1
1.0	**41999**	R			TempAnfoKuehlEMxt	Wert	0	140	°C	1/64
1.0	42000					Attribute	0	65535		
1.0	not used									
1.0	not used									
1.0	**42005**	R/W			StatEEKuehl	Attribute	0	65535		
1.0	not used									
1.0	not used									
1.0	**42016**	W			TempAnfo (Timeout 11 minutes)	Heating request temperature (Value)	0	140	°C	1/64
1.0	42017					Heating request control (Attribute): 0: Heat request off 1025: Heat request on	0	65535		
1.0	**42018**	R			StatEM	Heating state (Attribute) Bit0= Heating generator available Bit1= ... Bit2= Heating generator fault Bit3= ... Bit4= Heating generator looked permanently Bit5= Heating generator looked temporarily Bit6..8 = ... Bit9= Forced heat draw demand Bit10..14= ... Bit15= Defrost mode	0	65535		
1.0	42019					Heating generator relative output (LeistRel) 0: Generator off 1: Generator pump on >1: Output of generator	0	100	%	1
1.0	42020					Heating generator installed output (LeistAbs)	0	65535	kWh	1/10
1.0	**42021**	R			ProzSperrEM	H-Byte: c8Value L-Byte: c8Attribut	0 0	100 255	%	1
1.0	**42022**	R			ProzZwangEM	H-Byte: c8Value L-Byte: c8Attribut	0 0	100 255	%	1
1.0	**42023**	R			StatVM	Attribute				
1.0	**42024**	R			ProzSperrVM	H-Byte: c8Value L-Byte: c8Attribut	0 0	100 255	%	1
1.0	**42025**	R			ProzZwangVM	Wert Attribut	0 0	100 255	%	1
1.0	not used									
1.0	not used									
1.0	**42032**	W			TempAnfoKuehl (Timeout 11 minutes)	Cooling request temperature (Value)	0	140	°C	1/64
1.0	42033					Cooling request control (Attribute): 0: Cooling request off 65: Cooling request for common 1 on 129: Cooling request for common 2 on	0	65535		
1.0	**42034**	R			StatEMKuehl	Cooling state (Attribute) Bit0= Cooling generator/common available Bit1= Common 1 is actual cooling Bit2= Common 2 is actual cooling Bit3= Common 1 closed / no cooling Bit4= Common 2 closed / no cooling Bit5= ... Bit6= Cooling generator fault Bit7= Cooling generator looked permanently Bit8= Cooling generator looked temporarily Bit9= ... Bit10..15: not used	0	65535		
1.0	**42035**	R			StatVMKuehl	Attribute	0	65535		
1.0	not used									
1.0	not used									
1.0	**42048**	R/W			TempErzWert	Value	0	140	°C	1/64
1.0	42049				Status	see description				
1.0	**42050**	R			TempSchiVor	Value	0	140	°C	1/64
1.0	42051				Status	see description				
1.0	**42052**	R			TempPuffer	Value	0	140	°C	1/64
1.0	42053				Status	see description				
1.0	**42054**	R/W			TempAuss	Value	-50	50	°C	1/64
1.0	42055				Status	see description				
1.0	**42056**	R/W			Switch-on command heat pump See "Swi-on command HP stage x" in the manual	0: Control 1: Off 2: Stage1 3: Stage1 and 2	0	3		1
1.5	**42057**	W			TempRaumWert 1	Value	0	30	°C	1/64
1.5	42058				Status	see description				
1.5	**42059**	W			TempRaumWert 2	Value	0	30	°C	1/64
1.5	42060				Status	see description				
1.5	**42061**	W			TempRaumWert 3	Value	0	30	°C	1/64
1.5	42062				Status	see description				
	0xA800…0xA9FF	BL		Modbus 1						
1.5	**43008**	R/W	6651		Modbus Slaveadress		1	247		1

1.5	**43009**	R/W	6651		Status/Comand	see description				
1.5	**43010**	R/W	6652		Modbus baud rate		0	8		1
1.5	**43011**	R/W	6653		Modbus parity	x 0: Even 1: Odd 2: None	0	2		1
1.5	**43012**	R/W	6654		Modbus stop bit		1	2		1
1.5	**43013**	R/W			Output test Modbus Port 1		0	100	%	1
1.5	**43014**	R/W			Status/Comand	see description				
1.5	**43015**	R/W			Output test Modbus Port 2		0	100	%	1
1.5	**43016**	R/W			Status/Comand	see description				
1.5	**43017**	R/W			Output test Modbus Port 3		0	100	%	1
1.5	**43018**	R/W			Status/Comand	see description				
1.5	**43019**	R/W			Output test Modbus Port 4		0	100	%	1
1.5	**43020**	R/W			Status/Comand	see description				
1.5	**43021**	R/W			Output test Modbus Port 5		0	100	%	1
1.5	**43022**	R/W			Status/Comand	see description				
1.5	**43023**	R/W			Output test Modbus Port 6		0	100	%	1
1.5	**43024**	R/W			Status/Comand	see description				
1.5	**43025**	R/W			Output test Modbus Port 7		0	100	%	1
1.5	**43026**	R/W			Status/Comand	see description				
1.5	**43027**	R/W			Output test Modbus Port 8		0	100	%	1
1.5	**43028**	R/W			Status/Comand	see description				
	43029			Reserved						
	43030			Reserved						
1.5	**43031**	R/W	6660		Modbus Slave address port 1		1	247		1
1.5	**43032**	R/W	6660		Status/Comand	see description				
1.5	**43033**	R/W	6665		Modbus Slave address port 2		1	247		1
1.5	**43034**	R/W	6665		Status/Comand	see description				
1.5	**43035**	R/W	6670		Modbus Slave address port 3		1	247		1
1.5	**43036**	R/W	6670		Status/Comand	see description				
1.5	**43037**	R/W	6675		Modbus Slave address port 4		1	247		1
1.5	**43038**	R/W	6675		Status/Comand	see description				
1.5	**43039**	R/W	6680		Modbus Slave address port 5		1	247		1
1.5	**43040**	R/W	6680		Status/Comand	see description				
1.5	**43041**	R/W	6685		Modbus Slave address port 6		1	247		1
1.5	**43042**	R/W	6685		Status/Comand	see description				
1.5	**43043**	R/W	6690		Modbus Slave address port 7		1	247		1
1.5	**43044**	R/W	6690		Status/Comand	see description				
1.5	**43045**	R/W	6695		Modbus Slave address port 8		1	247		1
1.5	**43046**	R/W	6695		Status/Comand	see description				
	43047			Reserved						
	43048			Reserved						
1.5	**43049**	R/W	6661		Modbus Device port 1	x 0: None 1: OEM 2: Pump Grundfos 3: Pump Wilo 4: Fan Ebm-papst 5: Inverter Invertek	0	5		1
1.5	**43050**	R/W	6666		Modbus Device port 2	x 0: None 1: OEM 2: Pump Grundfos 3: Pump Wilo 4: Fan Ebm-papst 5: Inverter Invertek	0	5		1
1.5	**43051**	R/W	6671		Modbus Device port 3	x 0: None 1: OEM 2: Pump Grundfos 3: Pump Wilo 4: Fan Ebm-papst 5: Inverter Invertek	0	5		1
1.5	**43052**	R/W	6676		Modbus Device port 4	x 0: None 1: OEM 2: Pump Grundfos 3: Pump Wilo 4: Fan Ebm-papst 5: Inverter Invertek	0	5		1
1.5	**43053**	R/W	6681		Modbus Device port 5	x 0: None 1: OEM 2: Pump Grundfos 3: Pump Wilo 4: Fan Ebm-papst 5: Inverter Invertek	0	5		1
1.5	**43054**	R/W	6686		Modbus Device port 6	x 0: None 1: OEM 2: Pump Grundfos 3: Pump Wilo 4: Fan Ebm-papst 5: Inverter Invertek	0	5		1
1.5	**43055**	R/W	6691		Modbus Device port 7	x 0: None 1: OEM 2: Pump Grundfos 3: Pump Wilo 4: Fan Ebm-papst 5: Inverter Invertek	0	5		1
1.5	**43056**	R/W	6696		Modbus Device port 8	x 0: None 1: OEM 2: Pump Grundfos 3: Pump Wilo 4: Fan Ebm-papst 5: Inverter Invertek	0	5		1
	43057			Reserved						
	43058			Reserved						
1.5	**43059**	R/W	6662		Modbus Function port 1	0..81 (see user manual)	0	81		1
1.5	**43060**	R/W	6667		Modbus Function port 2	0..81 (see user manual)	0	81		1
1.5	**43061**	R/W	6672		Modbus Function port 3	0..81 (see user manual)	0	81		1
1.5	**43062**	R/W	6677		Modbus Function port 4	0..81 (see user manual)	0	81		1

1.5	**43063**	R/W	6682		Modbus Function port 5	0..81 (see user manual)	0	81		1
1.5	**43064**	R/W	6687		Modbus Function port 6	0..81 (see user manual)	0	81		1
1.5	**43065**	R/W	6692		Modbus Function port 7	0..81 (see user manual)	0	81		1
1.5	**43066**	R/W	6697		Modbus Function port 8	0..81 (see user manual)	0	81		1
	43067			Reserved						
	43068			Reserved						
1.5	**43069**	R			Output state Modbus Port 1		0	65335		1
1.5	**43070**	R			Status	see description				
1.5	**43071**	R			Output state Modbus Port 2		0	65335		1
1.5	**43072**	R			Status	see description				
1.5	**43073**	R			Output state Modbus Port 3		0	65335		1
1.5	**43074**	R			Status	see description				
1.5	**43075**	R			Output state Modbus Port 4		0	65335		1
1.5	**43076**	R			Status	see description				
1.5	**43077**	R			Output state Modbus Port 5		0	65335		1
1.5	**43078**	R			Status	see description				
1.5	**43079**	R			Output state Modbus Port 6		0	65335		1
1.5	**43080**	R			Status	see description				
1.5	**43081**	R			Output state Modbus Port 7		0	65335		1
1.5	**43082**	R			Status	see description				
1.5	**43083**	R			Output state Modbus Port 8		0	65335		1
1.5	**43084**	R			Status	see description				
	43085			Reserved						
	43086			Reserved						
1.5	**43087**	R			Output signal Modbus Port 1		0	65335		1
1.5	**43088**	R			Status	see description				
1.5	**43089**	R			Output signal Modbus Port 2		0	65335		1
1.5	**43090**	R			Status	see description				
1.5	**43091**	R			Output signal Modbus Port 3		0	65335		1
1.5	**43092**	R			Status	see description				
1.5	**43093**	R			Output signal Modbus Port 4		0	65335		1
1.5	**43094**	R			Status	see description				
1.5	**43095**	R			Output signal Modbus Port 5		0	65335		1
1.5	**43096**	R			Status	see description				
1.5	**43097**	R			Output signal Modbus Port 6		0	65335		1
1.5	**43098**	R			Status	see description				
1.5	**43099**	R			Output signal Modbus Port 7		0	65335		1
1.5	**43100**	R			Status	see description				
1.5	**43101**	R			Output signal Modbus Port 8		0	65335		1
1.5	**43102**	R			Status	see description				
	43103			Reserved						
	43104			Reserved						
1.5	**43105**	R			Input signal Modbus Port 1		0	65335		1
1.5	**43106**	R			Status	see description				
1.5	**43107**	R			Input signal Modbus Port 2		0	65335		1
1.5	**43108**	R			Status	see description				
1.5	**43109**	R			Input signal Modbus Port 3		0	65335		1
1.5	**43110**	R			Status	see description				
1.5	**43111**	R			Input signal Modbus Port 4		0	65335		1
1.5	**43112**	R			Status	see description				
1.5	**43113**	R			Input signal Modbus Port 5		0	65335		1
1.5	**43114**	R			Status	see description				
1.5	**43115**	R			Input signal Modbus Port 6		0	65335		1
1.5	**43116**	R			Status	see description				
1.5	**43117**	R			Input signal Modbus Port 7		0	65335		1
1.5	**43118**	R			Status	see description				
1.5	**43119**	R			Input signal Modbus Port 8		0	65335		1
1.5	**43120**	R			Status	see description				
	43121			Reserved						
	43122			Reserved						
	0xB000…0xB3FF	BL		Config extension module						
1.5	**45056**	R/W	7300		Function extension module 1	0: None x 1: Multifunctional 2: Heating circuit 1 3: Heating circuit 2 4: Heating circuit 3 5: --- inadmissable setting --- 6: Solar DHW 7: Primary contr/system pump 8: DHW primary controller 9: Instantaneous DHW heater 10: --- inadmissable setting --- 11: Cooling circuit 1 12: Heating circ/cooling circ 1 13: Solid fuel boiler 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: Cooling circuit 2 17: Heating circ/cooling circ 2 18: Cooling circuit 3 19: Heating circ/cooling circ 3 20: DHW interm circuit controller	0	20		1
1.6	**45057**	R/W	7301		Relay output QX21 module 1	0..83 (see user manual)	0	83		1
1.6	**45058**	R/W	7302		Relay output QX22 module 1	0..83 (see user manual)	0	83		1
1.6	**45059**	R/W	7303		Relay output QX23 module 1	0..83 (see user manual)	0	83		1
1.5	**45060**	R/W	7307		Sensor input BX21 module 1	0..45 (see user manual)	0	45		1
1.5	**45061**	R/W	7308		Sensor input BX22 module 1	0..45 (see user manual)	0	45		1
1.5	**45062**	R/W	7311		Function input H2 module 1	0..61 (see user manual)	0	61		1
1.5	**45063**	R/W	7312		Contact type H2 module 1	0: normal closed x 1: normal opened	0	1		1
1.5	**45064**	R/W	7314		Voltage value 1 H2 module 1		0	10	V	1/10
1.5	**45065**	R/W	7315		Funct value 1 H2 module 1		-100	500		1/10
1.5	**45066**	R/W	7316		Voltage value 2 H2 module 1		0	10	V	1/10
1.5	**45067**	R/W	7317		Funct value 2 H2 module 1		-100	500		1/10

1.5	**45068**	R/W	7318		Temp sensor H2 module 1	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**45069**	R/W	7321		Function input H21 module 1	0..61 (see user manual)	0	61		1
1.5	**45070**	R/W	7322		Contact type H21 module 1	0: normal closed x 1: normal opened	0	1		1
1.5	**45071**	R/W	7324		Input value 1 H21 module 1		0	1000		1/10
1.5	**45072**	R/W	7325		Function value 1 H21 module 1		-100	500		1/10
1.5	**45073**	R/W	7326		Input value 2 H21 module 1		0	1000		1/10
1.5	**45074**	R/W	7327		Function value 2 H21 module 1		-100	500		1/10
1.5	**45075**	R/W	7328		Temp sensor H21 module 1	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**45076**	R/W	7331		Function input H22 module 1	0..61 (see user manual)	0	61		1
1.5	**45077**	R/W	7332		Contact type H22 module 1	0: normal closed x 1: normal opened	0	1		1
1.5	**45078**	R/W	7334		Input value 1 H22 module 1		0	1000		1/10
1.5	**45079**	R/W	7335		Function value 1 H22 module 1		-100	500		1/10
1.5	**45080**	R/W	7336		Input value 2 H22 module 1		0	1000		1/10
1.5	**45081**	R/W	7337		Function value 2 H22 module 1		-100	500		1/10
1.5	**45082**	R/W	7338		Temp sensor H22 module 1	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**45083**	R/W	7341		Voltage output GX21 module 1	x 1: Off 2: 12 Volt	1	2		1
1.6	**45084**	R/W	7342		Function input EX21 Modul 1	0..30 (see user manual)	0	30		1
1.5	**45085**	R/W	7343		Operating action input EX21 Modul 1	0: normal closed x 1: normal opened	0	1		1
1.5	**45086**	R/W	7348		Function output UX21 module 1	0..35 (see user manual)	0	35		1
1.5	**45087**	R/W	7349		Signal logic output UX21 module 1	x 0: Standard 1: Inverted	0	1		1
1.5	**45088**	R/W	7350		Signal output UX21 module 1	x 0: 0..10V 1: PWM	0	1		1
1.5	**45089**	R/W	7354		Temp value 10V UX21 module 1		5	130	°C	1/64
1.5	**45090**	R/W	7355		Function output UX22 module 1	0..35 (see user manual)	0	35		1
1.5	**45091**	R/W	7356		Signal logic output UX22 module 1	x 0: Standard 1: Inverted	0	1		1
1.5	**45092**	R/W	7357		Signal output UX22 module 1	x 0: 0..10V 1: PWM	0	1		1

1.5	**45093**	R/W	7361		Temp value 10V UX22 module 1		5	130	°C	1/64
1.5	**45094**	R/W	7362		Function output WX21 module 1	x 0: None 1: Expansion valve evapor V81 2: Expansion valve EVI V82	0	2		1
1.5	**45095**	R/W			Operating mode WX21 module 1	x 0: Halbschritt 1: Vollschritt 1-phasig	0	1		1
1.5	**45096**	R/W			Rotating direction WX21 module 1	0: Standard x 1: Inverted	0	1		1
1.5	**45097**	R/W			Step rate WX21 module 1		30	300		1
1.5	**45098**	R/W			Number of steps WX21 module 1		0	6400		1
1.5	**45099**	R/W			Steps at setpoint 0% WX21 module 1		0	6400		1
1.5	**45100**	R/W			Steps at setpoint 100% WX21 module 1		0	6400		1
1.5	**45101**	R/W			Steps overdrive WX21 module 1		0	6400		1
1.5	**45102**	R/W			Calibration WX21 module 1		0	255	h	1
1.5	**45103**	R/W			Status/Comand	see description				
1.5	**45104**	R/W	7375		Function extension module 2	0: None x 1: Multifunctional 2: Heating circuit 1 3: Heating circuit 2 4: Heating circuit 3 5: --- inadmissable setting --- 6: Solar DHW 7: Primary contr/system pump 8: DHW primary controller 9: Instantaneous DHW heater 10: --- inadmissable setting --- 11: Cooling circuit 1 12: Heating circ/cooling circ 1 13: Solid fuel boiler 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: Cooling circuit 2 17: Heating circ/cooling circ 2 18: Cooling circuit 3 19: Heating circ/cooling circ 3 20: DHW interm circuit controller	0	20		1
1.6	**45105**	R/W	7376		Relay output QX21 module 2	0..83 (see user manual)	0	83		1
1.6	**45106**	R/W	7377		Relay output QX22 module 2	0..83 (see user manual)	0	83		1
1.6	**45107**	R/W	7378		Relay output QX23 module 2	0..83 (see user manual)	0	83		1
1.5	**45108**	R/W	7382		Sensor input BX21 module 2	0..45 (see user manual)	0	45		1
1.5	**45109**	R/W	7383		Sensor input BX22 module 2	0..45 (see user manual)	0	45		1
1.5	**45110**	R/W	7386		Function input H2 module 2	0..61 (see user manual)	0	61		1
1.5	**45111**	R/W	7387		Contact type H2 module 2	0: normal closed x 1: normal opened	0	1		1
1.5	**45112**	R/W	7389		Voltage value 1 H2 module 2		0	10	V	1/10
1.5	**45113**	R/W	7390		Funct value 1 H2 module 2		-100	500		1/10
1.5	**45114**	R/W	7391		Voltage value 2 H2 module 2		0	10	V	1/10
1.5	**45115**	R/W	7392		Funct value 2 H2 module 2		-100	500		1/10
1.5	**45116**	R/W	7393		Temp sensor H2 module 2	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**45117**	R/W	7396		Function input H21 module 2	0..61 (see user manual)	0	61		1
1.5	**45118**	R/W	7397		Contact type H21 module 2	0: normal closed x 1: normal opened	0	1		1
1.5	**45119**	R/W	7399		Input value 1 H21 module 2		0	1000		1/10
1.5	**45120**	R/W	7400		Function value 1 H21 module 2		-100	500		1/10
1.5	**45121**	R/W	7401		Input value 2 H21 module 2		0	1000		1/10
1.5	**45122**	R/W	7402		Function value 2 H21 module 2		-100	500		1/10

1.5	**45123**	R/W	7403		Temp sensor H21 module 2	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**45124**	R/W	7406		Function input H22 module 2	0..61 (see user manual)	0	61		1
1.5	**45125**	R/W	7407		Contact type H22 module 2	0: normal closed x 1: normal opened	0	1		1
1.5	**45126**	R/W	7409		Input value 1 H22 module 2		0	1000		1/10
1.5	**45127**	R/W	7410		Function value 1 H22 module 2		-100	500		1/10
1.5	**45128**	R/W	7411		Input value 2 H22 module 2		0	1000		1/10
1.5	**45129**	R/W	7412		Function value 2 H22 module 2		-100	500		1/10
1.5	**45130**	R/W	7413		Temp sensor H22 module 2	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**45131**	R/W	7416		Voltage output GX21 module 2	x 1: Off 2: 12 Volt	1	2		1
1.6	**45132**	R/W	7417		Function input EX21 Modul 2	0..30 (see user manual)	0	30		1
1.5	**45133**	R/W	7418		Operating action input EX21 Modul 2	0: normal closed x 1: normal opened	0	1		1
1.5	**45134**	R/W	7423		Function output UX21 module 2	0..35 (see user manual)	0	35		1
1.5	**45135**	R/W	7424		Signal logic output UX21 module 2	x 0: Standard 1: Inverted	0	1		1
1.5	**45136**	R/W	7425		Signal output UX21 module 2	x 0: 0..10V 1: PWM	0	1		1
1.5	**45137**	R/W	7429		Temp value 10V UX21 module 2		5	130	°C	1/64
1.5	**45138**	R/W	7430		Function output UX22 module 2	0..35 (see user manual)	0	35		1
1.5	**45139**	R/W	7431		Signal logic output UX22 module 2	x 0: Standard 1: Inverted	0	1		1
1.5	**45140**	R/W	7432		Signal output UX22 module 2	x 0: 0..10V 1: PWM	0	1		1
1.5	**45141**	R/W	7436		Temp value 10V UX22 module 2		5	130	°C	1/64
1.5	**45142**	R/W	7437		Function output WX21 module 2	x 0: None 1: Expansion valve evapor V81 2: Expansion valve EVI V82	0	2		1
1.5	**45143**	R/W			Operating mode WX21 module 2	x 0: Halbschritt 1: Vollschritt 1-phasig	0	1		1
1.5	**45144**	R/W			Rotating direction WX21 module 2	0: Standard x 1: Inverted	0	1		1
1.5	**45145**	R/W			Step rate WX21 module 2		30	300		1
1.5	**45146**	R/W			Number of steps WX21 module 2		0	6400		1
1.5	**45147**	R/W			Steps at setpoint 0% WX21 module 2		0	6400		1
1.5	**45148**	R/W			Steps at setpoint 100% WX21 module 2		0	6400		1
1.5	**45149**	R/W			Steps overdrive WX21 module 2		0	6400		1
1.5	**45150**	R/W			Calibration WX21 module 2		0	255	h	1
1.5	**45151**	R/W			Status/Comand	see description				

1.5	**45152**	R/W	7450		Function extension module 3	0: None x 1: Multifunctional 2: Heating circuit 1 3: Heating circuit 2 4: Heating circuit 3 5: --- inadmissable setting --- 6: Solar DHW 7: Primary contr/system pump 8: DHW primary controller 9: Instantaneous DHW heater 10: --- inadmissable setting --- 11: Cooling circuit 1 12: Heating circ/cooling circ 1 13: Solid fuel boiler 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: Cooling circuit 2 17: Heating circ/cooling circ 2 18: Cooling circuit 3 19: Heating circ/cooling circ 3 20: DHW interm circuit controller	0	20		1
1.6	**45153**	R/W	7451		Relay output QX21 module 3	0..83 (see user manual)	0	83		1
1.6	**45154**	R/W	7452		Relay output QX22 module 3	0..83 (see user manual)	0	83		1
1.6	**45155**	R/W	7453		Relay output QX23 module 3	0..83 (see user manual)	0	83		1
1.5	**45156**	R/W	7457		Sensor input BX21 module 3	0..45 (see user manual)	0	45		1
1.5	**45157**	R/W	7458		Sensor input BX22 module 3	0..45 (see user manual)	0	45		1
1.5	**45158**	R/W	7461		Function input H2 module 3	0..61 (see user manual)	0	61		1
1.5	**45159**	R/W	7462		Contact type H2 module 3	0: normal closed x 1: normal opened	0	1		1
1.5	**45160**	R/W	7464		Voltage value 1 H2 module 3		0	10	V	1/10
1.5	**45161**	R/W	7465		Funct value 1 H2 module 3		-100	500		1/10
1.5	**45162**	R/W	7466		Voltage value 2 H2 module 3		0	10	V	1/10
1.5	**45163**	R/W	7467		Funct value 2 H2 module 3		-100	500		1/10
1.5	**45164**	R/W	7468		Temp sensor H2 module 3	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**45165**	R/W	7471		Function input H21 module 3	0..61 (see user manual)	0	61		1
1.5	**45166**	R/W	7472		Contact type H21 module 3	0: normal closed x 1: normal opened	0	1		1
1.5	**45167**	R/W	7474		Input value 1 H21 module 3		0	1000		1/10
1.5	**45168**	R/W	7475		Function value 1 H21 module 3		-100	500		1/10
1.5	**45169**	R/W	7476		Input value 2 H21 module 3		0	1000		1/10
1.5	**45170**	R/W	7477		Function value 2 H21 module 3		-100	500		1/10
1.5	**45171**	R/W	7478		Temp sensor H21 module 3	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**45172**	R/W	7481		Function input H22 module 3	0..61 (see user manual)	0	61		1
1.5	**45173**	R/W	7482		Contact type H22 module 3	0: normal closed x 1: normal opened	0	1		1
1.5	**45174**	R/W	7484		Input value 1 H22 module 3		0	1000		1/10
1.5	**45175**	R/W	7485		Function value 1 H22 module 3		-100	500		1/10
1.5	**45176**	R/W	7486		Input value 2 H22 module 3		0	1000		1/10
1.5	**45177**	R/W	7487		Function value 2 H22 module 3		-100	500		1/10

1.5	**45178**	R/W	7488		Temp sensor H22 module 3	x 0: None 1: --- inadmissable setting --- 2: --- inadmissable setting --- 3: --- inadmissable setting --- 4: --- inadmissable setting --- 5: --- inadmissable setting --- 6: --- inadmissable setting --- 7: --- inadmissable setting --- 8: --- inadmissable setting --- 9: --- inadmissable setting --- 10: --- inadmissable setting --- 11: --- inadmissable setting --- 12: Solar flow sensor B63 13: Solar return sensor B64 14: --- inadmissable setting --- 15: --- inadmissable setting --- 16: --- inadmissable setting --- 17: --- inadmissable setting --- 18: --- inadmissable setting --- 19: --- inadmissable setting --- 20: HP flow sensor B21 21: HP return sensor B71	0	21		1
1.5	**45179**	R/W	7491		Voltage output GX21 module 3	x 1: Off 2: 12 Volt	1	2		1
1.6	**45180**	R/W	7492		Function input EX21 Modul 3	0..30 (see user manual)	0	30		1
1.5	**45181**	R/W	7493		Operating action input EX21 Modul 3	0: normal closed x 1: normal opened	0	1		1
1.5	**45182**	R/W	7498		Function output UX21 module 3	0..35 (see user manual)	0	35		1
1.5	**45183**	R/W	7499		Signal logic output UX21 module 3	x 0: Standard 1: Inverted	0	1		1
1.5	**45184**	R/W	7500		Signal output UX21 module 3	x 0: 0..10V 1: PWM	0	1		1
1.5	**45185**	R/W	7504		Temp value 10V UX21 module 3		5	130	°C	1/64
1.5	**45186**	R/W	7505		Function output UX22 module 3	0..35 (see user manual)	0	35		1
1.5	**45187**	R/W	7506		Signal logic output UX22 module 3	x 0: Standard 1: Inverted	0	1		1
1.5	**45188**	R/W	7507		Signal output UX22 module 3	x 0: 0..10V 1: PWM	0	1		1
1.5	**45189**	R/W	7511		Temp value 10V UX22 module 3		5	130	°C	1/64
1.5	**45190**	R/W	7512		Function output WX21 module 3	x 0: None 1: Expansion valve evapor V81 2: Expansion valve EVI V82	0	2		1
1.5	**45191**	R/W			Operating mode WX21 module 3	x 0: Halbschritt 1: Vollschritt 1-phasig	0	1		1
1.5	**45192**	R/W			Rotating direction WX21 module 3	0: Standard x 1: Inverted	0	1		1
1.5	**45193**	R/W			Step rate WX21 module 3		30	300		1
1.5	**45194**	R/W			Number of steps WX21 module 3		0	6400		1
1.5	**45195**	R/W			Steps at setpoint 0% WX21 module 3		0	6400		1
1.5	**45196**	R/W			Steps at setpoint 100% WX21 module 3		0	6400		1
1.5	**45197**	R/W			Steps overdrive WX21 module 3		0	6400		1
1.5	**45198**	R/W			Calibration WX21 module 3		0	255	h	1
1.5	**45199**	R/W			Status/Comand	see description				

Error Codes (2 Byte Value)

Englisch	Deutsch
0:No error	0:Kein Fehler
1:	1:
2:	2:
3:	3:
4:	4:
5:	5:
6:	6:
7:	7:
8:	8:
9:	9:
10:Outside sensor	10:Aussenfühler
11:Solar sensor	11:Sonnenfühler
12:Wind sensor	12:Windfühler
13:	13:
14:	14:
15:	15:
16:	16:
17:	17:
18:	18:
19:	19:
20:Boiler sensor 1	20:Kesselfühler 1
21:	21:
22:Boiler sensor 2	22:Kesselfühler 2
23:	23:
24:	24:
25:Boiler sensor solid fuel	25:Kesselfühler Feststoff
26:Common flow sensor	26:Gem Vorlauffühler
27:Common flow sensor 2	27:Schienenvorlauffühler 2
28:Flue gas temp sensor	28:Abgasfühler
29:	29:
30:Flow sensor 1	30:Vorlauffühler 1
31:Flow sensor cooling 1	31:Vorlauffühler Kühlen 1
32:Flow sensor 2	32:Vorlauffühler 2
33:Flow sensor HP	33:Vorlauffühler WP
34:Condenser sensor	34:Kondensatorfühler
35:Source inlet sensor	35:Quellen-Eintrittsfühler
36:Hot-gas sensor 1	36:Heissgasfühler 1
37:Hot-gas sensor 2	37:Heissgasfühler 2
38:Flow sensor prim contr	38:Vorlauffühler Vorregler
39:Evaporator sensor	39:Verdampferfühler
40:Return sensor 1	40:Rücklauffühler 1
41:	41:
42:Return sensor 2	42:Rücklauffühler 2
43:Return sensor solid fuel	43:Rücklauffühler Feststoff
44:Return sensor HP	44:Rücklauffühler WP
45:Source outlet sensor	45:Quellen-Austrittsfühler
46:Return sensor cascade	46:Rücklauffühler Kaskade
47:Common return sensor	47:Gem Rücklauffühler
48:Refrigerant sensor liquid	48:Kältemittelfühler flüssig
49:	49:
50:DHW sensor 1	50:Trinkwasserfühler 1
51:	51:
52:DHW sensor 2	52:Trinkwasserfühler 2
53:	53:
54:DHW flow sensor	54:TWW-Vorlauffühler
55:St tank 2 DHW sens 1	55:Speicher 2 TWW-Fühler 1
56:St tank 2 DHW sens 2	56:Speicher 2 TWW-Fühler 2
57:DHW circulation sensor	57:TWW Zirkulationsfühler
58:DHW thermostat	58:Trinkwasserthermostat
59:	59:
60:Room sensor 1	60:Raumfühler 1
61:Room unit 1	61:Raumgerät 1
62:Room unit 1 type	62:Raumgerät 1 Typ
63:	63:
64:Room unit 1 bus interr	64:Raumgerät 1 Busunterbr

65:Room sensor 2	65:Raumfühler 2
66:Room unit 2	66:Raumgerät 2
67:Room unit 2 type	67:Raumgerät 2 Typ
68:Room sensor 3	68:Raumfühler 3
69:Room unit 2 bus interr	69:Raumgerät 2 Busunterbr
70:Storage tank sensor 1	70:Pufferspeicherfühler 1
71:Storage tank sensor 2	71:Pufferspeicherfühler 2
72:Storage tank sensor 3	72:Pufferspeicherfühler 3
73:Collector sensor 1	73:Kollektorfühler 1
74:Collector sensor 2	74:Kollektorfühler 2
75:Bypass sensor	75:Bypassfühler
76:Special sensor 1	76:Sonderfühler 1
77:Air pressure sensor	77:Luftdruckfühler
78:Water pressure sensor	78:Wasserdruckfühler
79:Brine sensor	79:Solefühler
80:LPB no communication	80:LPB keine Kommunikation
81:LPB short-circuit/comm	81:LPB Kurzschluss/Komm
82:LPB address collision	82:LPB Adresskollision
83:BSB short-circuit	83:BSB Kurzschluss
84:BSB address collision	84:BSB Adresskollision
85:BSB Radio communication	85:BSB Funkkommunikation
86:PPS short-circuit	86:PPS Kurzschluss
87:PPS 2 short-circuit	87:PPS 2 Kurzschluss
88:PPS no communication	88:PPS keine Kommunikation
89:	89:
90:Data loss in RAM	90:Datenverlust im RAM
91:Data loss in EEPROM	91:Datenverlust im EEPROM
92:Device electronics error	92:Elektronikfehler im Gerät
93:Change battery	93:Batterie wechseln
94:Battery memory card	94:Batterie Speicherkarte
95:Time of day invalid	95:Uhrzeit ungültig
96:Minor SW failure	96:Kleiner SW Fehler
97:SW or HW failure	97:SW oder HW Fehler
98:Extension module 1	98:Erweiterungsmodul 1
99:Extension module 2	99:Erweiterungsmodul 2
100:2 clock time masters	100:Zwei Uhrzeitmaster
101:Par clock time source	101:Par Uhrzeitlieferant
102:Clock without backup	102:Uhr Gangreserve fehlt
103:Communication failure	103:Kommunikationsfehler
104:	104:
105:Maintenance message	105:Wartungsmeldung
106:Source temp too low	106:Quellentemp zu tief
107:Hot-gas compressor 1	107:Heissgas Verdichter 1
108:Hot-gas compressor 2	108:Heissgas Verdichter 2
109:Boiler temp supervision	109:Kesseltemp-Überwach
110:Lockout SLT	110:Störabschaltung STB
111:Shutdown limit thermost	111:Sicherh'abschalt TW
112:Lockout flue gas SLT	112:Störabschalt AbgasSTB
113:Safety shutd flue gas	113:Sicherh'abschalt Abgas
114:Shutd flue gas thermo	114:Abgastherm ausgelöst
115:Shutd flue gas sensor	115:Abgasfühler angespr
116:Shutd flue gas sensor	116:Abgasfühler abgesch
117:Water pressure too high	117:Wasserdruck zu hoch
118:Water pressure too low	118:Wasserdruck zu niedrig
119:Shutd water press swi	119:W'druckschalt ausgelöst
120:Fl temp prectrl too low	120:Vorl'tempVorreg zu tief
121:Flow temp HC1	121:Vorlauftemperatur HK1
122:Flow temp HC2	122:Vorlauftemperatur HK2
123:Flow temp DHW too low	123:Vorl'temp TWW zu tief
124:Boiler temp too low	124:Kesseltemp zu tief
125:Boiler temp too high	125:Kesseltemp zu hoch
126:DHW charg temp	126:TWW Ladetemperatur
127:Legionella temp	127:Legionellentemperatur
128:Loss of flame in op	128:Flamm'ausfall in Betrieb
129:Wrong air supply	129:Falsche Luftversorgung
130:Flue gas temp too high	130:Abgastemp zu hoch
131:Burner lockout	131:Brennerstörung

132:Safety shutdown	132:Sicherheitsabschaltung
133:Safety time exceeded	133:Sicherh'zeit überschritt
134:Common fault HP	134:Sammelstörung WP
135:Brine circuit	135:Solekreislauf
136:Press refrig circuit HP	136:Druck Kältekreislauf WP
137:No HP	137:WP fehlt
138:No control sensor HP	138:Regelfühler WP fehlt
139:	139:
140:LPB address not valid	140:LPB Adresse unzulässig
141:LPB config not consist	141:LPB Konfig inkonsistent
142:No device on LPB	142:Fehlendes Gerät am LPB
143:	143:
144:	144:
145:PPS wrong device type	145:PPS falscher Gerätetyp
146:Configuration error	146:Fühler/Stellglied Konfig
147:BMU not connected	147:BMU nicht ang'schlossen
148:Incompatible LBP unit	148:Inkompatibles LBP-Gerät
149:Configuration FPF	149:Konfiguration FPF
150:BMU	150:BMU
151:BMU internal	151:BMU intern
152:Parameterization	152:Parametrierung
153:Unit locked	153:Gerät manuell verriegelt
154:Plausibility criterion	154:Plausibilitätskriterium
155:Reset locked	155:Entriegelung blockiert
156:	156:
157: Boiler flow thermostat	157: Kesselvorl. Thermost.
158:Condensate	158:Kondensat
159:	159:
160:Fan speed threshold	160:Gebläsedrehzahlschwelle
161:Max fan speed	161:Max Gebläsedrehzahl
162:Air pressure switch	162:Luftdruckwächter
163:Modulation valve	163:Modulationsventil
164:Flow press switch HC	164:Ström'druckwächter HK
165:Priority circuit	165:Vorrangumschaltung
166:Air pressure switch	166:Luftdruckwächter
167:Heating output limits	167:Heizleistungsgrenzen
168:	168:
169:Sitherm Pro system	169:Sitherm Pro System
170:	170:
171:Alarm contact 1 active	171:Alarmkontakt 1 aktiv
172:Alarm contact 2 active	172:Alarmkontakt 2 aktiv
173:Alarm contact 3 active	173:Alarmkontakt 3 aktiv
174:Alarm contact 4 active	174:Alarmkontakt 4 aktiv
175:Error out FPF active	175:Fehlerausgang FPF aktiv
176:Water press 2 too high	176:Wasserdruck 2 zu hoch
177:Water press 2 too low	177:Wasserdruck 2 niedrig
178:Limit thermostat HC1	178:Temperaturwächter HK1
179:Limit thermostat HC2	179:Temperaturwächter HK2
180:Chimney sweep function	180:Schornsteinfegerfkt
181:Controller stop function	181:Regler-Stopp-Funktion
182:Sitherm Pro drift test	182:Sitherm Pro Drifttest
183:Parameter setting mode	183:Parametriermodus
184:Modem function	184:Modemfunktion
185:Floor curing function	185:Estrich-Funktion
186:Configuration input	186:Konfiguration Eingang
187:Configuration output	187:Konfiguration Ausgang
188:	188:Erzeugersperre aktiv
189:	189:
190:	190:
191:SLT has tripped	191:STB hat ausgelöst
192:	192:
193:Start prevention	193:Startverhinderung
194:	194:
195:Water refill time	195:Wassernachfülldauer
196:Water refill time/week	196:Wassernachfüll'/Woche
197:	197:
198:	198:

199:	199:
200:Fire/smoke alarm	200:Feuer-/Rauch-Alarm
201:Frost alarm	201:Frost-Alarm
202:Supply air sensor	202:Zuluftfühler
203:Airflow alarm	203:Strömungs-Alarm
204:Fan overload	204:Ventilator Überlast
205:Pump/electric fault	205:Pumpen/Elektrostörung
206:Chiller	206:Kältemaschine
207:Fault cooling circuit	207:Störung Kühlkreis
208:Flow supervision	208:Strömungs Überwachung
209:Fault heating circuit	209:Störung Heizkreis
210:Fault SYNERGYR	210:Störung SYNERGYR
211:Fault solid fuel boiler	211:Störung Feststoffkess
212:Internal comm failure	212:Fehler intern Komm
213:Safety / blocking chain	213:Sicherh' od Sperrkette
214:Engine supervision	214:Motorüberwachung
215:Fan, Valve fault	215:Gebläse/Luftuml'vent
216:Boiler fault	216:Störung Kessel
217:Sensor fault	217:Fühler Fehler
218:Pressure supervision	218:Drucküberwachung
219:	219:Störung Trinkwasser
220:AUX 1 alarm	220:AUX 1 Alarm
221:AUX 2 alarm	221:AUX 2 Alarm
222:Hi-press on HP op	222:HD bei WP-Betrieb
223:Hi-press on start HC	223:HD bei Start HK
224:Hi-press on start DHW	224:HD bei Start TWW
225:Low-pressure	225:Niederdruck
226:Compressor 1 overlaod	226:Verdichter 1 Überlast
227:Compressor 2 overlaod	227:Verdichter 2 Überlast
228:Flow swi heat source	228:Ström'wächter W'quelle
229:Press swi heat source	229:Druckwächter W'quelle
230:Source pump overload	230:Quellenpumpe Überlast
231:Sensor B101	231:Fühler B101
232:Sensor B102	232:Fühler B102
233:Sensor B103	233:Fühler B103
234:Sensor B104	234:Fühler B104
235:Sensor B105	235:Fühler B105
236:Sensor B106	236:Fühler B106
237:Sensor B107	237:Fühler B107
238:Sensor B108	238:Fühler B108
239:Sensor B109	239:Fühler B109
240:	240:
241:Flow sensor yield	241:Vorlauffühler Ertrag
242:Return sensor yield	242:Rücklauffühler Ertrag
243:Swimming pool sensor	243:Schwimmbadfühler
244:Fault source cascade	244:Störung Erz'kaskade
245:	245:
246:	246:
247:Defrost fault	247:Abtaustörung
248:	248:
249:	249:
250:	250:
251:	251:
252:	252:
253:Error cause ambiguous	253:Fehl'ursache nicht eind
254:Unknown error code	254:Unbek Fehlercode
255:See other error list	255:Siehe weitere Fehlerliste
256:Heat exch thermostat	256:Wärmetau. Thermostat
257:Casing sensor	257:Gehäusetemp Fühler
258:Casing overtemp	258:Gehäuse Übertemp
259:CJC sensor	259:Kaltstellenkomp Fühler
260:Flow sensor 3	260:Vorlauffühler 3
261:Loss of flame Eng bu	261:Flam'ausfall Stirl'br
262:Loss of fl' Supp bu	262:Flam'ausfall Zus'br
263:Eng bu BCU failure	263:Fehler Stirling FA
264:Supp bu BCU failure	264:Fehler Zusatzbr FA
265:BCU failure	265:FA Ausfall

266:fan fault	266:Fehler Gebläse
267:Fan calibration	267:Kalib'fehler Gebläse
268:Spool valve fault	268:Luftumlenkventil Fehler
269:Spool valve calib	269:Kalib'fehl Luftuml'ventil
270:Exc temp diff h' exch	270:Temp diff W'tauscher
271:Diff'pressure too high	271:Diff'druck zu gross
272:Diff'pressure too low	272:Diff'druck zu klein
273:Conf'fault pres'sensor	273:Konf'fehler DruckSens
274:Zero flow protection	274:Strömungssicherung
275:Zero flow aft deaer	275:Durchfl'mangel n' Entl
276:Zero flow	276:Durchfl'mangel
277:Zero flow DHW	277:Durchflu'mangel TW
278:Max temp rise	278:Max Temp'anstieg
279:Stirl manifold thermo	279:Stirl' Ansaugthermostat
280:Inner iron overtemp	280:Inneres Eisen Übertemp
281:Dyn absorber tripped	281:Dyn Abs Anschlag
282:G83/ENS/GIM	282:G83/ENS
283:Altern' overc trip	283:Alternat Überstrom
284:WCS overtemp	284:WCS Übertemp
285:Alternat SC	285:Alternat Kurzschl
286:Eng head overtemp	286:Stirling Kopf Übertemp
287:Eng head undertemp	287:Stirling Kopf Untertemp
288:Regenerat overtemp	288:Regenerator Übertemp
289:WCS overt + inner iron	289:WCS Übertemp+ In'Eisen
290:WCS overt + DA	290:WCS Übertemp + DA
291:WCS overt + G83	291:WCS Übertemp + G83
292:WCS overt + Alt	292:WCS Übertemp + Alt
293:WCS overt + SC	293:WCS Übertemp+ KS
294:WCS + eng head overt	294:WCS + Kopf Übertemp
295:WCS + eng head undert	295:WCS + Kopf Untertemp
296:WCS overt + Reg	296:WCS Übertemp + Reg
297:	297:
298:False flame Eng bu	298:Falsche Flamme Sti'bren
299:False flame Supp bu	299:Falsche Flamme Zus'bren
300:Eng head undert SW	300:S'Kopf Untertemp SW
301:Eng head overt SW	301:S'Kopf Übertemp SW
302:Eng head t'couple diff	302:S'Kopf T/C Differenz
303:Eng head t'couple cont	303:S'Kopf T/C Regelung
304:Eng head t' coupl lim	304:S'Kopf T/C Überw
305:Eng under current	305:Altern minimum Strom
306:Black start failure	306:Netz'ausf Start Fehler
307:Engine stall	307:Generator blockiert
308:Stop resistor integrity	308:Stop Widerstand Test
309:Power fail detection	309:Netzausfall Detektion
310:Power mon comm fail	310:Leist'zähler Kom'fehler
311:EGC comm failure	311:Kom'fehler Gen'steu.
312:Bl' start fail' pump en	312:Inselbet'start Pumpe
313:Bl' start fail' PSU sw	313:Inselbet'start Stromver.
314:Bl' start fail' batt sw	314:Inselbet'start Batterie
315:Bl' start fail socket en	315:Inselbet'start N'anschl
316:Grid voltage OOR	316:Netzspannung Überw.
317:Grid frequency OOR	317:Netzfrequenz Überw.
318:GSM comm failure	318:Kom'fehler Netzmodul
319:Check configuration	319:Konfiguration prüfen
320:DHW charging sensor	320:TWW Ladefühler
321:DHW outlet sensor	321:TWW Zapffühler
322:Water press 3 too high	322:Wasserdruck 3 zu hoch
323:Water press 3 too low	323:Wasserdruck 3 niedrig
324:BX same sensors	324:BX gleiche Fühler
325:BX/e'module same sens	325:BX/E'mod gleiche Fühler
326:BX/m'grp same sens	326:BX/M'gru gleiche Fühler
327:E'module same funct	327:E'modul gleiche Funktion
328:Mix group same funct	328:Misch'gruppe gleiche Fkt
329:E'mod/m'grp same funct	329:E'mod/M'gru gleiche Fkt
330:BX1 no function	330:BX1 keine Funktion
331:BX2 no function	331:BX2 keine Funktion
332:BX3 no function	332:BX3 keine Funktion

333:BX4 no function	333:BX4 keine Funktion
334:BX5 no function	334:BX5 keine Funktion
335:BX21 no function	335:BX21 keine Funktion
336:BX22 no function	336:BX22 keine Funktion
337:B1 no function	337:B1 keine Funktion
338:B12 no function	338:B12 keine Funktion
339:Coll pump Q5 missing	339:Kollektorpumpe Q5 fehlt
340:Coll pump Q16 missing	340:Kollekt'pumpe Q16 fehlt
341:Coll sensor B6 missing	341:Kollekt'fühler B6 fehlt
342:Solar DHW B31missing	342:Solar TWW B31 fehlt
343:Solar integration missing	343:Solareinbindung fehlt
344:Solar buffer K8 missing	344:Solar Puffer K8 fehlt
345:Sol swi pool K18 missing	345:Solar Sch'bad K18 fehlt
346:Boiler pump Q10 missing	346:Kesselpumpe Q10 fehlt
347:Solid fuel boil comp sens	347:Fest'kessel Vergl'fühler
348:Solid fuel boil addr err	348:Fest'kess Adressfehler
349:Buff valve Y15 missing	349:Puffer'ventil Y15 fehlt
350:Buffer address error	350:Puffer Adressfehler
351:Prim/sys pump addr err	351:Vor/Zu'pu Adressfehler
352:Pr'less header addr err	352:hyd'Weiche Adressfehler
353:Casc sens B10 missing	353:Kaskad'fühler B10 fehlt
354:Special sensor 2	354:Sonderfühler 2
355:3-ph curr asymmetric	355:Drehstrom asymmetrisch
356:Flow switch consumers	356:Ström'wächter Verb
357:Flow temp cooling 1	357:Vorlauftemp Kühlkreis 1
358:Soft starter	358:Sanftanlasser
359:Div valve cool Y21 miss	359:Uml'vent Kühl Y21 fehlt
360:Proc rev va Y22 miss	360:Prozessum'v Y22 fehlt
361:Source sens B91 miss	361:Quellen'fühler B91 fehlt
362:Source sens B92 miss	362:Quellen'fühler B92 fehlt
363:Compr sens B84 miss	363:Verd'fühler B84 fehlt
364:Cool system HP wrong	364:Kühlsystem WP falsch
365:Inst heater Q34 miss	365:Durchl'erhitz Q34 fehlt
366:Room temp sensor Hx	366:Raumtemp'fühler Hx
367:Room humidity sens Hx	367:Raumfeuchtefühler Hx
368:Flow temp setp readjHx	368:Vorlaufsollwertkorr Hx
369:External	369:Extern
370:Thermodynamic source	370:Thermodynam Erzeuger
371:Flow temp HC3	371:Vorlauftemperatur HK3
372:Limit thermostat HC3	372:Temperaturwächter HK3
373:Extension module 3	373:Erweiterungsmodul 3
374:Sitherm Pro calculation	374:Sitherm Pro Berechnung
375:BV stepper motor	375:BV Schrittmotor
376:Drift test limit value	376:Drifttest Grenzwert
377:Drift test prevented	377:Drifttest verhindert
378:Repetition internal	378:Repetition intern
379:Repetition extran light	379:Repetition Fremdlicht
380:Repetition flame	380:Repetition Flamme
381:Repetition startup	381:Repetition Anlauf
382:Repetition speed	382:Repetition Drehzahl
383:No Repetition	383:Keine Repetition
384:Extraneous ligth	384:Fremdlicht
385:Mains undervoltage	385:Netzunterspannung
386:Fan speed tolerance	386:Gebläsedrehzahltoleranz
387:Air pressure tolerance	387:Luftdrucktoleranz
388:DHW sensor no function	388:TWW Fühl' keine Funktion
389:	389:
390:	390:
391:Room controller 1	391:Raumregler 1
392:Room controller 2	392:Raumregler 2
393:Room controller 3	393:Raumregler 3
394:Eng Bu BCU Com fail	394:Keine Komm Stirling FA
395:Supp Bu BCU Com fail	395:Keine Komm Zus'br FA
396:Eng head t'c' cont integ	396:S'Kopf T/C Reg Plausib
397:Eng head t'c' cont rise	397:S'Kopf T/C Reg Anstieg
398:Eng head t'c' lim integ	398:S'Kopf T/C Üb Plausib
399:Eng head t'c' lim rise	399:S'Kopf T/C Üb Anstieg

400: Flow dir heat gen	400: Ström'richt Wärmeerz
401:EGC ARL relay defect	401:EGC ARL Relais defekt
402:EGC ext electr missing	402:EGC keine Speisung
403:EGC Dumpload failure	403:EGC Lastwider. defekt
404:EGC Stab Res failure	404:EGC Stab.Wid. defekt
405:EGC ADC SEG OOR	405:EGC ADC SEG OOR
406:EGC Backdumpl failure	406:EGC Sich.Wid. defekt
407:EGC Backdumpl failure	407:EGC Sich.Wid. defekt
408:EGC Backdumpl failure	408:EGC Sich.Wid. defekt
409:Wrong EGC comm data	409:Falsche EGC Kommunik.
410:EGC eng signal failure	410:EGC Gen. Signal Fehler
411:EGC Backdumpl active	411:EGC Sich.Wid. Betrieb
412:EGC Backdumpl active	412:EGC Sich.Wid. Betrieb
413:EGC Backdumpl active	413:EGC Sich.Wid. Betrieb
414:EGC Backdumpl active	414:EGC Sich.Wid. Betrieb
415:Eng frequency low	415:Generatorfrequenz tief
416:Eng unable to start	416:Gen. Start unmöglich
417:Eng RPV sensor	417:Generator RPV Sensor
418:Eng RPV overtemp	418:Gen. RPV Übertemp.
419:Cooling water	419:Kühlwasser
420:Operation overtemp	420:Betrieb Übertemperatur
421:Temp diff h'ex eng bu	421:T'diff W'tau Stirl'br
422:State BCU Eng bu incon	422:Sta BCU Sti'br widers
423:State BCU Supp bu inco	423:Sta BCU Zus'br widers
424:Rep loss flame Eng bu	424:Rep. Flam'ausf Stirl'br
425:Rep. loss of fl' Supp bu	425:Rep. Flam'ausf Zus'br
426:Check flue gas damper	426:Rückmeld' Abgasklappe
427:Config flue gas damper	427:Konfig Abgasklappe
428:Boiler flow Eng bu	428:Kess'durchfluss Stirl'br
429:Dyn water pres too high	429:Dyn W'druck zu hoch
430:Dyn water pres too low	430:Dyn W'druck zu niedrig
431:Primary exch sensor	431:Primärtauscherfühler
432:Function ground missing	432:Funktionserde fehlt
433:Heat exch temp	433:Wärmetauschertemp
434:EGC, no link to grid	434:EGC, nicht an Netz ange
435:EGC, ARL in lock state	435:EGC, ARL verriegelt
436:EGC, supply feedb discr	436:EGC, Speisungsüberw
437:	437:
438:Bus conflict LPB/BSB	438:Buskonflikt LPB/BSB
439:Bus module not detect	439:Busmodul nicht erkannt
440:	440:
441:BX31 no function	441:BX31 keine Funktion
442:BX32 no function	442:BX32 keine Funktion
443:BX33 no function	443:BX33 keine Funktion
444:BX34 no function	444:BX34 keine Funktion
445:BX35 no function	445:BX35 keine Funktion
446:BX36 no function	446:BX36 keine Funktion
447:BX6 no function	447:BX6 keine Funktion
448:No messag receiver 1	448:Kein Meld'empfänger 1
449:No messag receiver 2	449:Kein Meld'empfänger 2
450:No messag receiver 3	450:Kein Meld'empfänger 3
451:No messag receiver 4	451:Kein Meld'empfänger 4
452:HX1 no function	452:HX1 keine Funktion
453:HX3 no function	453:HX3 keine Funktion
454:HX31 no function	454:HX31 keine Funktion
455:HX32 no function	455:HX32 keine Funktion
456:HX33 no function	456:HX33 keine Funktion
457:BX7 no function	457:BX7 keine Funktion
458:Instant WH sensor	458:Durchl'erhitzerfühler
459:	459:
460:	460:
461:Return sensor 3	461:Rücklauffühler 3
462:BX8 no function	462:BX8 keine Funktion
463:BX9 no function	463:BX9 keine Funktion
464:BX10 no function	464:BX10 keine Funktion
465:BX11 no function	465:BX11 keine Funktion
466:BX12 no function	466:BX12 keine Funktion

467:BX13 no function	467:BX13 keine Funktion
468:BX14 no function	468:BX14 keine Funktion
469:HX21 no function	469:HX21 keine Funktion
470:HX22 no function	470:HX22 keine Funktion
471:HX2 no function	471:HX2 keine Funktion
472:Flow sensor cooling 2	472:Vorlauffühler Kühlen 2
473:Flow sensor cooling 3	473:Vorlauffühler Kühlen 3
474:Flow temp cooling 2	474:Vorlauftemp Kühlkreis 2
475:Flow temp cooling 3	475:Vorlauftemp Kühlkreis 3
476:Suction gas sensor	476:Sauggasfühler
477:Evapor press sensor	477:Verdampf'druck Sensor
478:HX/e'module same sens	478:HX/E'mod gleich Sensor
479:No refrigerant selected	479:Kein Kältemittel gewählt
480:Suction gas sensor EVI	480:Sauggasfühler EVI
481:Evap press sensor EVI	481:Verd'druck Sensor EVI
482:Evapor temp sensor EVI	482:Verdampfungsfühler EVI
483:Soft starter 2	483:Sanftanlasser 2
484:Div valve cool Y45 miss	484:Uml'vent Kühl Y45 fehlt
485:Div valve cool Y46 miss	485:Uml'vent Kühl Y46 fehlt
486:No EI receiver 1	486:Kein EI Empfänger 1
487:No EI receiver 2	487:Kein EI Empfänger 2
488:Condens press sensor	488:Kondensat'druck Sensor
489:Cascade master miss	489:Kaskadenmaster fehlt
490:Cascade source miss	490:Kaskade Erzeuger fehlt
491:Max evaporation temp	491:Max Verdampfungstemp
492:K2/modulat incompatible	492:K2/Modulat inkompatibel
493:Outside air sensor	493:Aussenluftfühler
494:Outside air Q17 missing	494:Aussenluft' Q17 fehlt
495:Modbus no comm'cation	495:Modbus keine Kommunik'
496:Flow sw source int circ	496:Strömw Quellenzw'kreis
497:Pres sw sourc int circ	497:Druckw Quellenzw'kreis
498:Air quality sensor Hx	498:Luftqualitätfühler Hx
499:External source missing	499:Externe Quelle fehlt
500:Modbus configuration	500:Modbus Konfiguration
501:Suction gas sensor 2	501:Sauggasfühler 2
502:Sourc int circ flow sens	502:Quellenzw' Vorl'fühler
503:Sourc int circ ret sens	503:Quellenzw' Rückl'fühler
504:Pres diff proc reversal	504:Druckdiff Proz'umkehr
505:Expansion valve evap	505:Exp'ventil Verdampfer
506:Suppl source missing	506:Zusatzerzeuger fehlt
507:Hi-press compr 2 in op	507:HD Verd 2 bei Betrieb
508:Hi-pr compr 2 start HC	508:HD Verd 2 bei Start HK
509:Hi-pr compr 2 st DHW	509:HD Verd 2 Start TWW
510:Low-press compr 2	510:Niederdruck Verd 2
511:Leg temp circ pipe	511:Legionellentemp Zirk'leit
512:No trend receiver 1	512:Kein Trend Empfänger 1
513:No trend receiver 2	513:Kein Trend Empfänger 2
514:Admin password	514:Admin Passwort
515:Flow switch suppl sourc	515:Ström'wächter Zus'erz
516:Heat pump missing	516:Wärmepumpe fehlt

Status Codes (2 Byte Value)

#	Englisch	Deutsch
0	---	---
1	SLT has tripped	STB angesprochen
2	Fault	Störung
3	Limiter has tripped	Wächter angesprochen
4	Manual control active	Handbetrieb aktiv
5	Chim sweep fct, high-fire	Schornsteinfegerfkt,Volllast
6	Chim sweep fct, low-fire	Schornsteinfegerfkt,Teillast
7	Chimney sweep funct active	Schornsteinfegerfkt aktiv
8	Locked, manual	Gesperrt, manuell
9	Locked, automatic	Gesperrt, automatisch
10	Locked	Gesperrt
11	Protective start	Anfahrentlastung
12	Protective start, low-fire	Anfahrentlastung, Teillast
13	Return limitation	Rücklaufbegrenzung
14	Return limitation, low-fire	Rücklaufbegrenzung, Teillast
15	Released	Freigegeben
16	Released, low-fire	Freigegeben, Teillast
17	Overrun active	Nachlauf aktiv
18	In operation	In Betrieb
19	Released	Freigegeben
20	Min limitation	Minimalbegrenzung
21	Min limitation, low-fire	Minimalbegrenzung, Teillast
22	Min limitation active	Minimalbegrenzung aktiv
23	Frost prot plant active	Anlagefrostschutz aktiv
24	Frost protection active	Frostschutz aktiv
25	Off	Aus
26	Emergency operation	Notbetrieb
27	Locked, externally	Gesperrt, extern
28	Limit source temp min	Begr Quellentemp Min
29	High-press in HP mode	HD bei WP-Betrieb
30	Flow switch heat source	Ström'wächter W'quelle
31	Press switch heat source	Druckwächter W'quelle
32	Limit hot-gas compr1	Begr Heissgas Verdichter 1
33	Limit hot-gas compr2	Begr Heissgas Verdichter 2
34	Limit switch-off temp max	Begr Ausschalttemp Max
35	Compr off time min active	Verd'stillstandzeit Min aktiv
36	Compens surplus heat	Kompensat Wärmeüberschuss
37	Limitation time active	Begrenzungszeit aktiv
38	Compr run time min active	Verd'laufzeit Min aktiv
39	Compensation heat deficit	Kompensation Wärmedefizit
40	Limit diff condens max	Begr Spreiz Kondens Max
41	Limit diff condens min	Begr Spreiz Kondens Min
42	Limit diff evap max	Begr Spreiz Verda Max
43	Limit diff evap min	Begr Spreiz Verda Min
44	Compr and electric on	Verdichter und Elektro ein
45	Compressors 1 and 2 on	Verdichter 1 und 2 Ein
46	Compressor 1 on	Verdichter 1 Ein
47	Compressor 2 on	Verdichter 2 Ein
48	Frost protection HP	Frostschutz Wärmepumpe
49	Flow active	Vorlauf aktiv
50	Released, evap ready	Freigegeben, Verd bereit
51	No request	Keine Anforderung
52	Frost prot collector active	Kollektorfrostschutz aktiv
53	Recooling active	Rückkühlung aktiv
54	Max st tank temp reached	Max Speichertemp erreicht
55	Evaporation prot active	Verdampfungsschutz aktiv
56	Overtemp prot active	Überhitzschutz aktiv
57	Max charging temp reached	Max Ladetemp erreicht
58	Charging DHW	Ladung Trinkwasser
59	Charging buffer	Ladung Pufferspeicher
60	Charging swimming pool	Ladung Schwimmbad
61	Min charg temp not reached	Min Ladetemp nicht erreicht
62	Temp diff insufficient	Temp'differenz ungenügend
63	Radiation insufficient	Einstrahlung ungenügend
64	El charg, emergency mode	Ladung Elektro, Notbetrieb

65	El charg, source protection	Ladung Elektro, Quell'schutz
66	Charg el imm heater	Ladung Elektroeinsatz
67	Forced charging active	Zwangsladung aktiv
68	Partial charging active	Teilladung aktiv
69	Charging active	Ladung aktiv
70	Charged, max st tank temp	Geladen, max Speichertemp
71	Charged, max charging temp	Geladen, max Ladetemp
72	Charged, forced temp	Geladen, Zwanglad Solltemp
73	Charged, required temp	Geladen, Solltemperatur
74	Part charged, required temp	Teilgeladen, Solltemperatur
75	Charged	Geladen
76	Cold	Kalt
77	Recooling via collector	Rückkühlung via Kollektor
78	Recooling via heat gen/HCs	Rückkühlung via Erz/Hk's
79	Discharging prot active	Entladeschutz aktiv
80	Charg time limitation active	Ladezeitbegrenzung aktiv
81	Charging locked	Ladung gesperrt
82	Charging lock active	Ladesperre aktiv
83	Forced, max st tank temp	Zwang, max Speichertemp
84	Forced, max charging temp	Zwang, max Ladetemperatur
85	Forced, legionella setp	Zwang, Legionellensollwert
86	Forced, nominal setp	Zwang, Nennsollwert
87	El charging, legionella setp	Ladung Elektro, Leg'sollwert
88	El charging, nominal setp	Ladung Elektro, Nennsollwert
89	El charging, reduced setp	Ladung Elektro, Red'sollwert
90	El charging, frost prot setp	Ladung Elektro,Fros'sollwert
91	El imm heater released	Elektroeinsatz freigegeben
92	Push, legionella setp	Push, Legionellensollwert
93	Push, nominal setp	Push, Nennsollwert
94	Push active	Push aktiv
95	Charging, legionella setp	Ladung, Legionellensollwert
96	Charging, nominal setp	Ladung, Nennsollwert
97	Charging, reduced setp	Ladung, Reduziertsollwert
98	Charged, legionella temp	Geladen, Legio'temperatur
99	Charged, nominal temp	Geladen, Nenntemperatur
100	Charged, reduced temp	Geladen, Reduz'temperatur
101	Frost prot room active	Raumfrostschutz aktiv
102	Floor curing function active	Estrichfunktion aktiv
103	Restricted, boiler protection	Eingeschränkt, Kesselschutz
104	Restricted, DHW priority	Eingeschränkt, TWW-Vorrang
105	Restricted, buffer	Eingeschränkt, Puffer
106	Heating mode restricted	Heizbetrieb eingeschränkt
107	Forced draw buffer	Zwangsabnahme Puffer
108	Forced draw DHW	Zwangsabnahme TWW
109	Forced draw source	Zwangsabnahme Erzeuger
110	Forced draw	Zwangsabnahme
111	Opt start ctrl+boost heating	Einschaltopt+Schnellaufheiz
112	Optimum start control	Einschaltoptimierung
113	Boost heating	Schnellaufheizung
114	Comfort heating mode	Heizbetrieb Komfort
115	Optimum stop control	Ausschaltoptimierung
116	Reduced heating mode	Heizbetrieb Reduziert
117	Frost protection flow active	Vorlauffrostschutz aktiv
118	Summer operation	Sommerbetrieb
119	24-hour Eco active	Tages-Eco aktiv
120	Setback reduced	Absenkung Reduziert
121	Setback frost protection	Absenkung Frostschutz
122	Room temp limitation	Raumtemp'begrenzung
123	SLT test active	STB-Test aktiv
124	Charging restricted	Ladung eingeschränkt
125	Defrost active	Abtauen aktiv
126	Dripping	Abtropfen
127	Active cooling mode	Aktiver Kühlbetrieb
128	Passive cooling mode	Passiver Kühlbetrieb
129	Cooling down evaporator	Abkühlen Verdampfer
130	Preheating for defrost	Vorwärmen für Abtauen
131	Electric charging defrost	Ladung Elektro, Abtauen

132	Forced defrost active	Zwangsabtauen aktiv
133	Dewpoint monitor active	Taupunktwächter aktiv
134	Cooling limit OT active	Kühlgrenze TA aktiv
135	Locking time after heating	Sperrdauer nach Heizen
136	Flow temp setp incr hygro	Vorlaufsollw'anhebung Hygro
137	Heating mode	Heizbetrieb
138	Cooling mode off	Kühlbetrieb aus
139	Limit switch-off temp min	Begr Ausschalttemp. Min
140	Heating off/cooling locked	Heizen Aus/Kühlen gesperrt
141	Boiler frost prot active	Kesselfrostschutz aktiv
142	Recooling via DHW/HCs	Rückkühlung via TWW/Hk's
143	Charged, min charging temp	Geladen, Min Ladetemp
144	Cooling mode restricted	Kühlbetrieb eingeschränkt
145	Limit swi-off temp max cool	Begr Aus'temp max Kühlen
146	Cooling mode locked	Kühlbetrieb gesperrt
147	Hot	Warm
148	Cooling mode ready	Kühlbetrieb bereit
149	Protection mode cooling	Schutzbetrieb Kühlen
150	Cooling mode Comfort	Kühlbetrieb Komfort
151	Charg DHW+buffer+swi pool	Lad'ng TWW+Puffer+Sch'bad
152	Charging DHW+buffer	Ladung Trinkwasser+Puffer
153	Charging DHW+swi pool	Ladung Trinkwasser+Sch'bad
154	Charging buffer+swi pool	Ladung Puffer+Schwimmbad
155	Heating mode source	Heizbetrieb Erzeuger
156	Heated, max swi pool temp	Geheizt, max Schw'badtemp
157	Heated, setpoint source	Geheizt, Sollwert Erzeuger
158	Heated, setpoint solar	Geheizt, Sollwert Solar
159	Heated	Geheizt
160	Heating mode solar off	Heizbetrieb Solar Aus
161	Heating mode source off	Heizbetrieb Erzeuger Aus
162	Heating mode off	Heizbetrieb Aus
163	Assisted firing active	Anfeuerungshilfe aktiv
164	Electric charging, forced	Ladung Elektro, Zwang
165	Electric charging, substitute	Ladung Elektro, Ersatz
166	In operation for HC	In Betrieb für Heizkreis
167	In part load op for HC	In Teillastbetrieb für HK
168	In operation for DHW	In Betrieb für Trinkwasser
169	In part load op for DHW	In Teillastbetrieb für TWW
170	In op for HC, DHW	In Betrieb für HK,TWW
171	In part load op for HC, DHW	In Teillastbetrieb für HK.TWW
172	Locked, solid fuel boiler	Gesperrt, Feststoffkessel
173	Released for HC, DHW	Freigegeben für HK,TWW
174	Released for DHW	Freigegeben für TWW
175	Released for HC	Freigegeben für HK
176	Locked, outside temp	Gesperrt, Aussentemperatur
177	Limit flow min dewpoint	Begr Vorlauf min Taupunkt
178	Limit flow min OT	Begr Vorlauf min TA
179	Flow limit reached	Vorlaufgrenze erreicht
180	3-ph current asymmetric	Drehstrom asymmetrisch
181	Low-pressure	Niederdruck
182	Fan overload	Ventilator Überlast
183	Compressor 1 overload	Verdichter 1 Überlast
184	Compressor 2 overload	Verdichter 2 Überlast
185	Source pump overload	Quellenpumpe Überlast
186	Flow switch consumers	Ström'wächter Verbraucher
187	Operation limit OT min	Einsatzgrenze TA Min
188	Operation limit OT max	Einsatzgrenze TA Max
189	Limit source temp min water	Begr Quellentemp Min Wasser
190	Limit source temp min brine	Begr Quellentemp Min Sole
191	Limit source temp max	Begr Quellentemp Max
192	Forced defrost compressor	Zwangsabtauen Verdichter
193	Forced defrost fan	Zwangsabtauen Ventilator
194	Defrost with compressor	Abtauen mit Verdichter
195	Defrost with fan	Abtauen mit Ventilator
196	Limit source temp min cooling	Begr Quellentemp Min Kühlen
197	Electric on	Elektro Ein
198	Locked, Economy mode	Gesperrt, Ökobetrieb

199	Consumption	Zapfbetrieb
200	Ready	Bereit
201	Standby charging	Bereitschaftsladung
202	Frost prot cooling active	Frostschutz Kühlen aktiv
203	Full charging active	Durchladung aktiv
204	Locked, heating mode	Gesperrt, Heizbetrieb
205	Locked, source	Gesperrt, Erzeuger
206	Locked, buffer	Gesperrt, Puffer
207	Comp run time min activ,cool	Verd'laufzeit Min aktiv, Kühl
208	Compr 1 and 2 on, cooling	Verd' 1 und 2 ein, Kühlbetr
209	Compr 1 on, cooling mode	Verdichter 1 ein,Kühlbetrieb
210	Compr 2 on, cooling mode	Verdichter 2 ein,Kühlbetrieb
211	Lockout position	Störstellung
212	Start prevention	Startverhinderung
213	Shutdown	Ausserbetriebsetzung
214	Safety time	Sicherheitszeit
215	Startup	Inbetriebsetzung
216	Standby	Standby
217	Home run	Heimlauf
218	Prepurge	Vorlüften
219	Postpurge	Nachlüften
220	Controller stop active	Reglerstopp aktiv
221	Keep hot mode on	Warmhaltebetrieb ein
222	Keep hot mode active	Warmhaltebetrieb aktiv
223	Frost prot instant WH	Frostschutz Durchl'erhitzer
224	Ignition	Zünden
225	Settling time	Einschwingzeit
226	Exotic gas operation	Exotengasbetrieb
227	Drift test active	Drifttest aktiv
228	Special operation	Sonderbetrieb
229	Setting mode	Einstellbetrieb
230	Indiv boiler setting active	Exemplareinstellung aktiv
231	Start man drift test	Start manueller Drifttest
232	Flue gas temp, switch-off	Abgastemp, Abschaltung
233	Flue gas temp, output red	Abgastemp, Leist'begrenzung
234	Flue gas temp too high	Abgastemperatur zu hoch
235	Water pressure too low	Wasserdruck zu niedrig
236	Party function active	Partyfunktion aktiv
237	Transfer, legionella setpoint	Umladung, Legionellensollwert
238	Transfer, nominal setpoint	Umladung, Nennsollwert
239	Transfer, reduced setpoint	Umladung, Reduziertsollwert
240	Transfer active	Umladung aktiv
241	Residual heat usage	Restwärmenutzung
242	Restratification active	Umschichtung aktiv
243	Keep hot mode released	Warmhaltebetrieb freigegeb'
244	Source released	Erzeuger freigegeben
245	SLT limits output	STB begrenzt Leistung
246	Mains undervoltage	Netzunterspannung
247	Temp drop protection active	Unterkühlschutz aktiv
248	Continuous pump operation	Pumpendauerlauf
249	Charg opt energy, nominal	Ladung opt Energie, Nenn
250	Charg opt energy, legio	Ladung opt Energie, Legio
251	Charg opt energy EU, nom	Ladung opt Energie EW, Nenn
252	Charg opt energy EU, legio	Ladung opt Energie EW, Legio
253	Flow too low	Durchfluss gering
254	Pumping off refrig, man	Kältemittel abpumpen, Manuell
255	Collective state 255	Sammelzustand 255
256	Pumping off refrigerant	Kältemittel abpumpen
257	Start delay defrost	Startverzögerung Abtauen
258	Compressor locked	Verdichter gesperrt
259	Locked, source temp max	Gesperrt, Quellentemp Max
260	Locked, source temp min	Gesperrt, Quellentemp Min
261	Locked, return temp max	Gesperrt, Rücklauftemp Max
262	Locked, return temp min	Gesperrt, Rücklauftemp Min
263	Locked, flow temp max	Gesperrt, Vorlauftemp Max
264	Locked, flow temp min	Gesperrt, Vorlauftemp Min
265	Locked, cond temp max	Gesperrt, Kondens'temp Max

266	Locked, evap temp min	Gesperrt, Verdamp'temp Min
267	Locked, hot-gas temp max	Gesperrt, Heissgastemp Max
268	Limitation evap temp min	Begr Verdampfungstemp Min
269	Limitation cond temp max	Begr Kondensationstemp Max
270	Limitation evap temp max	Begr Verdampfungstemp Max
271	El imm heater locked	Elektroeinsatz gesperrt
272	Hi-temp charging active	Hochtemperaturladung aktiv
273	Fault soft starter 1	Störung Sanftanlasser 1
274	Fault soft starter 2	Störung Sanftanlasser 2
275	Flow switch source int circ	Ström'wächt Quellenzw'kreis
276	Press switch source int circ	Druckwächt Quellenzw'kreis
277	Air quality control	Luftqualitätsregelung
278	Humidity limitation	Feuchtebegrenzung
279	Ventilation switch	Lüftungsschalter
280	Night cooling	Nachtkühlung
281	Stage 1	Stufe 1
282	Stage 2	Stufe 2
283	Stage 3	Stufe 3
284	Boost ventilation	Stosslüften
285	Cooling mode Reduced	Kühlbetrieb Reduziert
286	Increase Reduced	Anhebung Reduziert
287	Increase Protection	Anhebung Schutzbetrieb
288	Locking time after cooling	Sperrdauer nach Kühlen
289	Limit pres diff proc revers	Begr Druckdiff Proz'umkehr
290	Low-pressure compressor 2	Niederdruck Verdichter 2
291	High-press compr 2 in op	HD Verdicher 2 bei Betrieb
292	Automatic operation	Automatischer Betrieb
293	Manual operation	Manueller Betrieb
294	Disabled, COP min	Gesperrt, Leistungszahl Min
295	Disabled, energy price	Gesperrt, Energiepreis
296	Passive cool mode disabled	Passiver Kühlbetr gesperrt
297	Flow switch suppl source	Ström'wächter Zus'erzeuger
298	Warmer function active	Wärmerfunktion aktiv
299	Cooler function active	Kälterfunktion aktiv
300	Adverse wind funct active	Gegenwindfunktion aktiv

Modbus General Description	**(Default value bold)**
Connector	3-pole Screw terminal (A+, B-, REF)
Interface type	RS485
Termination	termination resistor selectable with DIP Switch
Modbus Version (modbus.org)	Modbus Application Protocol Specification V1.1b
	Modbus over Serial Line V1.02
Modbus Mode	RTU
Modbus Role	Slave
Slave Address	**1**...247
Baud rate	Configurable 1'200, 2'400, 4'800, 9'600, **19'200**, 38'400, 57'600, 76'800, 115'200
Start bit	1
Data bit	8
Stop bit	**1**/2
Parity	**Even**/Odd/None
Modbus function codes	0x03 Read Holdingregisters
	0x06 Write Single Register (not for structured data types)
	0x10 Write multiple Register
Broadcast	not supported
Data type	Always 2 Byte per Register Signed /Unsigned 16bit & 32bit (32 bit in 2 Registers) Structured Data
Coding	Most significant first
Telegramm Length	max 44 Data byte
Response Timeout	300 ms
Parameter ACS7xx	[6651] Slave address
	[6652] Baud rate
	[6653] Parity
	[6654] Stop bit
Read/Write acces by registers	**only bold register can be read/written.** **Non bold Register must be read/written at same time with the previous (bold) register**

General Comments about Date Values

Year (8Bit Value)	1900-1999 -> 000...099 2000-2099 -> 100...199
Month	1 = January ... 12 = December
Hour	0...24
Minute	0...59
Second	0...59
Day	1...31
NY (No Year)	NY (No Year) = 0 year figure valid NY (No Year) = 1 year figure blank
ND (No Date)	ND (No Date) = 0 month / day valid ND (No Date) = 1 month / day
NW (No Week)	NW (No Week) = 0 weekday valid NW (No Week) = 1 weekday blank
NT (No Time)	NT (No Time) = 0 time of day valid NT (No Time) = 1 time of day
SUTI	SUTI = 0 standard time SUTI = 1 summer time

Time prog example

Switching program from 06:10h to 22:00h (Resolution 10min)

Monday 1st phase on	06:10h	-->	H-Byte: phase on	37
Monday 1st phase off	22:00h	-->	L-Byte: phase off	132

Status/Command

Description	Comment
Differs on selected action (read= status or write= command)	
Command is an **enumeration type** and not a Bit set (in contrast to STATUS). This means that only one Command can be delivered with each write access.	
Status: (Read) -> Bitwise	
Bit0:ObjectUnused	DP not used by device application (inactive; out of operation) 'ObjectUnused' = true (=1) indicates that the data point is inactive
Bit1:SensorShortCircuit	Short-circuit of sensor (only relevant together with DeviceFailure) 'SensorShortCircuit' = true (=1) indicates that the DeviceFailure is a short-circuit of the sensor. This STATUS Bit cannot be influenced via Write Command
Bit2:Overriden	Data point in override mode (Not used for Modbus) 'Overridden' = true (=1) indicates that the data point has been overridden with 'Override' Command. With 'Override'-incapable data points, this Bit is always 0.
Bit3: Reserved	
Bit4: Reserved	
Bit5: Reserved	
Bit6:DeviceFailure	Device-internal fault (e.g. A/D converter) with impact on data point 'DeviceFailure' = true (=1) indicates a fault of the device with its impact on the data point (e.g. faulty sensor, faulty A/D converter). This STATUS Bit cannot be influenced via Write Command
Bit7: Reserved	Always 0
Comand: (Write) -> Values in decimal	
0: Release (Release of an overridden data)	Not used for Modbus
1: Write (Normal write access)	Mandatory for write operation!
2: Override (Access with override right)	Not used for Modbus
3: Reserved	
4: Reserved	
5: SetOutOfService (Puts data points out of operation)	used especially to deactivate setting values and the associated application functions
6: ResetOutOfService (Puts data points into operation)	used especially to activate setting values and the associated application functions
>7: Reserved	