



Crimping Information for Aluminum Compression Connectors

Compact, Connectors Class B, C, Flex Class G, H, I, K, M & DLO Copper and Aluminum Conductors

OEC USA INC.

ALUMINUM
Rev. 01 Date: 8/25/25

Tooling Selection Chart With Die-less Crimping Tools (Range Taking)

Lug Size	Approved Cu Wire Classes								Range Taking (Applicable Wire Range)	Color	Burndy PAT444S	Greenlee HK12ID & EK12IDL	Milwaukee 2877-22
	B	C	G	H	I	K	M	DLO					
	AWG	AWG	AWG						AWG				
8	8	8	8	8	8	8	8	8	-	Blue	Die-less	Die-less	Die-less
6	6	6	6	6	6	6	-	6	6 - 8	Gray			
4	4	4	-	-	-	-	-	-	4 - 6	Green			
2	2	2	4	4	4	4	4	4	2 - 6	Pink			
1	1	1	2	2	2	2	2	2	1 - 6	Gold			
1/0	1/0	1/0	1	1	1	1	1	1	1/0 - 6	Tan			
2/0	2/0	2/0	1/0	1/0	1/0	1/0	1/0	1/0	2/0 - 4	Olive			
3/0	3/0	3/0	2/0	2/0	2/0	2/0	2/0	2/0	3/0 - 2	Ruby			
4/0	4/0	4/0	3/0	3/0	3/0	3/0	3/0	3/0	4/0 - 1	White			
250	250	250	4/0	4/0	4/0	4/0	4/0	4/0	250 - 1/0	Red			
300	300	300	250	250	-	-	-	-	300 - 2/0	Blue			
350	350	350	250	250	250	250	250	262	350 - 3/0	Brown			
400	400	400	300	300	300	300	300	313	400 - 4/0	Green			
500	500	500	350	350	350	350	350	373	500 - 250	Pink			
600	600	600	400	400	400	400	400	444	600 - 250	Black			
700	700	700	500	500	500	500	500	535	700 - 250	Purple			
750	750	750	600	600	600	-	600	646	750 - 500	Yellow			
800	800	800	-	-	-	-	-	-	-	White			
900	900	900	-	-	-	-	-	-	-	Gray			
1000	1000	1000	750	750	750	-	-	777	1000 - 750	Brown			



- 1) Select the proper lug or splice connector for the size of cable being installed, ensuring that the size matches the description in the table below.
- 2) Strip the insulation from the cable to a length so that the stripped area of the cable can be completely inserted into and fill the barrel of the lug or splice.
Carefully strip the insulation from the cable without nicking the strands.
- 3) Wire brush the stripped portion of the cable to remove oxide films.
- 4) The stripped portion of the conductor must be clean and inserted completely into the connector barrel.
- 5) Using the tool and die combination specified in the table below, install 2 crimps, leaving a space of 1/8 inch minimum between successive crimps.



Tooling Selection Chart With Die Set Crimping Tools

Lug Size	Compact Class B,C Aluminum and Copper Conductor		Flex Class G,H,I,K Conductor	Flex Class M Conductor	DLO Locomotive	Color	Burndy Y35, Y39, Y46,Y750, PAT750, PAT750LI	Burndy Tool Y35, Y39, Y750, PAT750, PAT750LI with Ilco Die Set	Greenlee HK1240 & EK1240LI	Milwaukee 2779-22	Panduit CT2931 & CT2940
	AWG	AWG	AWG	AWG	AWG						
8	8	8	8	8	-	Blue	U8CABT	ILD-374	KA12-8	49-16-U008	-
6	6	6	6	-	-	Gray	U6CABT	ILD-346	KA12-6	49-16-U006	CD920-4
4	4	4	-	-	-	Green	U4CABT	ILD-375	KA12-4	49-16-U004	CD920-1
2	2	2	4	4	-	Pink	U2CABT	ILD-348	KA12-2	49-16-U002	CD920-1/0
1	1	1	2	2	2	Gold	U1CABT	ILD-471	KA12-1	49-16-U001	CD920-2/0
1/0	1/0	1/0	1	1	1	Tan	U25ART	ILD-296	KA12-1/0	49-16-U01A	CD920-3/0
2/0	2/0	2/0	1/0	1/0	1/0	Olive	U26ART	ILD-297	KA12-2/0	49-16-U02A	CD920-4/0
3/0	3/0	3/0	2/0	2/0	2/0	Ruby	U27ART	ILD-467	KA12-3/0	49-16-U03A	CD920-250
4/0	4/0	4/0	3/0	3/0	3/0	White	U28ART	ILD-298	KA12-4/0	49-16-U04A	CD920-300
250	250	250	4/0	4/0	4/0	Red	U29ART	ILD-324	KA12-250	49-16-U250	CD920-350
300	300	300	250	-	-	Blue	U30ART	ILD-470	KA12-300	49-16-U300	CD920-400
350	350	350	250	250	262	Brown	U31ART	ILD-299	KA12-350	49-16-U350	CD920-500
400	400	400	300	300	313	Green	U32ART	ILD-472	KA12-400	49-16-U400	-
500	500	500	350	350	373	Pink	U34ART	ILD-300	KA12-500	49-16-U500	CD920-500A
600	600	600	400	400	444	Black	U36ART	ILD-473	KA12-600	49-16-U600	CD920-750
700	700	700	500	500	535	Purple	-	-	-	-	-
750	750	750	600	600	646	Yellow	U39ART-2	ILD-936	KA12-750	49-16-U750	CD920-750A
1000	1000	1000	750	-	777	Brown	S44ART-4	-	-	-	CD920-1000A