

PDU Address (Offset)	Logical Address	Description	Allowable Function Code(s)	Notes
Coils				
0	1	No Operation	0x01, 0x05	Placeholder for future use
Discrete Inputs				
0	10001	VOC Alarm	0x02	VOC threshold exceeded
1	10002	Min Ambient Temperature Alarm	0x02	Min ambient temp. threshold exceeded
2	10003	Max Ambient Temperature Alarm	0x02	Max ambient temp. threshold exceeded
3	10004	Humidity Alarm	0x02	Humidity threshold exceeded
Input Registers				
0	30001	VOC Index	0x04	Current VOC level
1	30002	Ambient Temperature	0x04	Current temperature
2	30003	Humidity Level	0x04	Current humidity
3	30004	VOC Alarm Count	0x04	Number of VOC alarms
4	30005	Min Ambient Temp. Alarm Count	0x04	Number of min temperature alarms
5	30006	Max Ambient Temp. Alarm Count	0x04	Number of max temperature alarms
6	30007	Humidity Alarm Count	0x04	Number of humidity alarms
Holding Registers				
0	40001	Sensors Sampling Interval	0x03, 0x06, 0x10	Interval in milliseconds
1	40002	Max VOC Index Alarm Threshold	0x03, 0x06, 0x10	Threshold for VOC alarm
2	40003	Max Ambient Temp Alarm Threshold	0x03, 0x06, 0x10	Threshold for max temperature alarm
3	40004	Min Ambient Temp Alarm Threshold	0x03, 0x06, 0x10	Threshold for min temperature alarm
4	40005	Max Humidity Alarm Threshold	0x03, 0x06, 0x10	Threshold for humidity alarm

Function Code	Description
1	Read Coils
2	Read Discrete Inputs
3	Read Holding Registers
4	Read Input Registers
5	Write Single Coil
6	Write Single Holding Register
15	Write Multiple Coils
16	Write Multiple Holding Registers