

Phase 0 print, measure and scan protocol

For producing the physical sample set that Phase 0 measures against **Status** Procedure. Every design decision it refers to is settled elsewhere. **Read with** docs/PHASE0-BRIEF.md section 4, DESIGN.md section 21, SAMPLE-NOTES.md

0. What this is for, and what it is not

Phase 0a proved that the renderer and the analyser agree with each other. They agree in a world with no paper, no ink and no scanner, which is exactly the world where agreement is easy. Phase 0 asks the only question that matters after that: does the agreement survive contact with a printer.

This protocol produces the evidence, it does not judge the printer. A print that comes out at 99.6 percent of nominal is not a failure. The whole point of the fiducial scheme is that the software measures what actually landed on the paper and reports it, so scale error is data rather than damage. What this protocol is looking for is the difference between a print that is slightly off, which is normal and absorbed, and a print that is grossly off because something in the print path silently rescaled it, which is not.

There is one thing here that genuinely is a gate, and it is not a measurement: **every sheet must be scanned before it is shot.** A clean scan and a shot scan of the same physical sheet is the input pair that render-and-difference needs at Phase 1, and it cannot be reconstructed later. Once a sheet has holes in it, the clean version of that exact sheet is gone forever.

1. Equipment

Required.

- A printer that takes Letter paper. Any consumer inkjet or laser is fine.
- Digital calipers reading to 0.01 mm, with jaws of at least 150 mm. Vernier calipers work but are slower and harder to read on a printed edge.
- A flatbed scanner. The existing corpus came from one and its behaviour is already characterised in section 8.
- A phone camera that can save an unresized original.
- Plain white printer paper, ordinary weight. Do not use photo paper, card, or anything coated.

Optional.

- A steel rule 200 mm or longer, for the spans that exceed the calipers.

- Plotter access for the roll sheet. If you do not have it, skip that item and say so in the notes rather than substituting something else.
- Buff or tinted stock, one sheet, if you have any. The paper knockout is tested against stock colour in the software already, but seeing it on real tinted paper is worth one sheet.

Not required and not wanted. Do not use a target backer, a staple gun, or anything else at this stage. Nothing gets shot until section 10.

2. Before you print, verify the files

Claude Code renders the print set into `out/` along with a one-page index. Open the index first and check that the file list matches section 4 of this document. Then open `out/GL-CF25-LTR.pdf` in a PDF viewer and look at it at 100 percent zoom.

You are looking for four things, and all four are visual rather than measured.

1. **Twenty-five bulls in a five by five grid, plus a row of three below it.** The bottom row is the sighter row and it sits further from the grid than the grid rows sit from each other.
2. **Four square QR codes, one near each page corner.**
3. **Small black squares scattered between the bulls.** These are the fiducial markers. There should be thirty-four of them on this sheet. You do not need to count them now, but they should be obviously present and obviously square.
4. **Nothing overlapping anything.** No marker touching a ring, no code touching a bull.

If any of those four is wrong, stop. That is a renderer fault and printing it wastes paper and time.

3. Printer settings, and the traps

This is the part where the run gets ruined, and it gets ruined silently. Work through it once, carefully, and then leave the settings alone for the whole run.

Open the PDF in a real PDF viewer, not a browser. Adobe Acrobat Reader, or whatever desktop PDF application you use. Browser print dialogs hide the scaling control or rename it, and Chrome in particular defaults to a "Fit to printable area" behaviour that is exactly the thing this protocol exists to prevent.

In the print dialog, find the page scaling control and set it to 100 percent. Depending on the application it is called one of:

- "Actual size" in Adobe Acrobat Reader. This is the correct choice there. Do not choose "Fit", "Shrink oversized pages" or "Custom scale".
- "Scale: 100" or "Custom Scale: 100%" elsewhere.

- In Chrome or Edge, "Scale" set to "Default" is **not** the same as 100 percent. Change it to "Custom" and type 100.

Turn off every automatic fitting option. The names vary by driver. Look for and disable anything called fit to page, fit to printable area, shrink to fit, scale to paper size, borderless, or expand to fill. Any one of these applies a scale factor of roughly 94 to 97 percent without telling you.

Set the paper size to Letter, 8.5 by 11 inches. Not A4. If the driver offers both Letter and "Letter (borderless)", choose plain Letter.

Set orientation to portrait.

Set print quality to normal or better. Draft mode on an inkjet thins the ink and can break up the fiducial markers, which are only 4.0 mm square. High quality is fine and slower. Do not use any "economy" or "toner save" mode.

Set colour handling to whatever your printer does natively. The built-in sheets are black only, so mono is fine. If your printer composites black from colour inks, that is worth knowing and worth noting, because it changes how the artwork subtracts at Phase 1.

Turn off duplex. Every sheet is single sided.

Turn off any "auto rotate and centre" option if the driver offers one. It usually does no harm, but it moves the artwork relative to the paper edge and there is no reason to introduce a variable.

Print one copy of `GL-CF25-LTR.pdf` and stop there. Do not print the whole set yet. Section 5 tells you what to do with that first sheet, and if the settings are wrong you will have wasted one sheet rather than fifteen.

4. The print list

Print these only after the first sheet has passed section 5.

#	File	Copies	Scale	Notes
1	GL-CF25-LTR.pdf	3	100%	The reference sheet. One stays clean forever as a control
2	GL-CF25-LTR-D-blank.pdf	1	100%	Load block with captions, nothing filled in
3	GL-CF25-LTR-D-filled.pdf	1	100%	Same definition, load data printed, instance code present
4	GL-CF25-LTR-96.pdf	1	100%	Already scaled in the file. Print at 100 percent, not at 96.2
5	GL-LR300-T-tile1.pdf to tile4.pdf	1 each	100%	The four sheets of the 2 by 2 assembly
6	GL-LR300-R36.pdf	1	100%	Plotter only. Skip if you do not have one
7	GL-CF25-LTR.pdf on buff stock	1	100%	Optional. Only if you have tinted paper

Item 4 is the one people get wrong. The 96.2 percent sheet is deliberately mis-scaled, and the mis-scaling is baked into the PDF. You print it at 100 percent like everything else. If you also set the printer to 96.2 percent you get 92.5 percent and a fixture that tests nothing anybody planned.

Items 2 and 3 must produce identical geometry. That is conformance test 27 and it is worth confirming with your own eyes: hold the two sheets up to a window, one on top of the other, and every bull, marker and code should sit exactly on top of its twin. Only the contents of the block at the bottom differ.

Write on each sheet in pencil, in the top margin, as it comes out of the printer: the file name, the date, and a sequence number. Do this immediately. Fifteen sheets of nearly identical black rings become indistinguishable within about ninety seconds. Pencil rather than pen, in the margin rather than anywhere near a bull or a marker.

5. Measurement

5.1 Why you are measuring at all

Two reasons, and neither of them is quality control on your printer.

To catch a gross scale error. Fit-to-page produces roughly 94 to 96 percent, which is a 4 to 6 percent error. On the measurement below that is 4.5 to 6.8 mm, which you cannot miss. This check exists to catch that, not to catch 0.3 percent.

To have a physical ground truth for the software's reported scale. DESIGN.md section 9 has the application report the print scale it detected. Comparing that number against a caliper measurement of the same sheet is how you find out whether the reported scale is trustworthy.

This is the more valuable of the two reasons and it is why the numbers get written down rather than merely checked.

5.2 The like-edge rule, which matters more than the caliper does

Ink spreads. A printed black disc is very slightly larger than the disc in the file, by an amount called dot gain that depends on the printer, the ink and the paper. On a consumer inkjet it is commonly 0.05 to 0.15 mm on each edge.

This means **measuring the outside diameter of a ring gives you the true diameter plus two dot gains**, and it will read over 25.4 mm every time. That is not an error and it is not something to correct for.

The way round it is to measure **like edge to like edge**: the left edge of one ring to the left edge of another ring. Both edges are displaced outward by the same dot gain, in the same direction, so the gain cancels exactly and what you measure is the true centre-to-centre distance. This is the single most useful measuring habit in this document.

left edge to left edge	outside to outside
gain cancels, exact	gain adds twice, reads high
$ \text{-----} 114.0 \text{ -----} $ $(\#\#) \quad (\#\#) \quad (\#\#) \quad (\#\#)$	$ \text{-----} 139.4 + 2g \text{ -----} $ $(\#\#) \quad (\#\#) \quad (\#\#) \quad (\#\#)$

5.3 What to measure on GL-CF25-LTR

Take the first printed sheet. Lay it flat on a hard surface. Measure each of these and write the result down.

#	What	Nominal	Gross-error threshold
A	Top row, leftmost bull left edge to fourth bull left edge	114.0 mm	Anything outside 113.0 to 115.0 mm
B	Left column, top bull top edge to fourth bull top edge	114.0 mm	Anything outside 113.0 to 115.0 mm
C	Any single ring, outside diameter	25.4 mm plus dot gain	Anything outside 25.3 to 25.8 mm
D	Two adjacent bulls, like edge to like edge	38.0 mm	Anything outside 37.7 to 38.3 mm
E	Last scoring row to sighter row, like edge to like edge	45.6 mm	Anything outside 45.2 to 46.0 mm

Measurements A and B are the important pair. Measurement C is there to give you a dot-gain figure, which is genuinely useful later, and it is the one that will read high. Do not treat C reading 25.55 mm as a problem; record it as your printer's dot gain of 0.075 mm per edge and move on.

If A and B are both inside the thresholds, the print path is honest and you can print the rest of the set.

If A or B is low by 4 to 6 percent, roughly 108 to 110 mm, then a fit-to-page setting is still on somewhere. Go back to section 3 and work through it again. The likeliest culprits, in order, are: printing from a browser, an "Actual size" versus "Fit" radio button that reset itself, and a driver-level fit option under a properties or advanced button that the application's own dialog does not show.

If A and B disagree with each other by more than about 0.5 mm, the printer is scaling the two axes differently. That is unusual but real, especially on inkjets where the paper feed direction and the head travel direction are different mechanisms. Note it, because the software should detect it as separate x and y scale factors, and that is now a specific thing to check rather than a surprise.

If A and B are off by less than 1 percent, that is normal and you do nothing about it. Write the numbers down and carry on. That is exactly the error the fiducials exist to measure.

5.4 What to measure on the other sheets

Do not repeat the full set. One measurement each is enough, because you are confirming that nothing changed between sheets rather than re-characterising the printer.

Sheet	Measure	Nominal
GL-CF25-LTR-D blank	Top row, first to fourth bull, like edge	114.0 mm
GL-CF25-LTR-D filled	Same	114.0 mm, and identical to the blank
GL-CF25-LTR-96	Top row, first to fourth bull, like edge	109.7 mm
Any GL-LR300-T tile	The two columns, like edge to like edge	101.6 mm
GL-LR300-R36	Two adjacent bulls in a row, like edge	101.6 mm

The 96.2 percent sheet is the one that proves the fixture is real. 114.0 times 0.962 is 109.7 mm. If it measures 114.0 you printed the wrong file. If it measures about 105.5 you scaled it twice.

5.5 Recording

Create `scans/phase0/MEASUREMENTS.md` and write the numbers into it as you go, one block per sheet, in this shape:

```
## GL-CF25-LTR, sheet 1 of 3
Printed 2026-09-14, HP OfficeJet 8025, plain paper, normal quality, mono
A top row, 1st to 4th, left edge to left edge 113.92 mm
B left column, 1st to 4th, top edge to top edge 113.88 mm
C ring outside diameter 25.53 mm
D adjacent bulls, like edge 37.98 mm
E scoring to sighter, like edge 45.57 mm
Derived: x scale 0.99930, y scale 0.99895, dot gain about 0.065 mm per edge
```

Fill in your actual printer model. It matters, because the whole point of measurement 2 in docs/FIDUCIAL-DECISION.md section 10 is to find the dot-gain floor on your actual printer rather than on a printer in a paper.

6. Scanning

6.1 Settings

- **Resolution: scan every sheet twice, once at 600 DPI and once at 300 DPI.** Both are needed. The 600 DPI scan is the reference and the 300 DPI scan is what most users will actually produce.
- **Colour mode: colour, 24 bit,** even though the sheets are black only. A colour scan can be converted to grayscale later and the reverse is not true, and the chroma residual work in DESIGN.md section 11 needs colour.
- **File format: PNG or TIFF.** Not JPEG. JPEG artefacts sit exactly on the ring edges that everything downstream measures. The existing corpus is JPEG and that is a limitation of the existing corpus, not a precedent.
- **Turn off every automatic correction.** Specifically: auto crop, auto deskew, auto colour correction, auto contrast, auto exposure, descreen, dust removal, sharpening, and any "text enhancement" or "document mode". Every one of these alters edge positions or invents pixels. Scan raw and flat.
- **Turn off any multi-page or PDF output mode.** One image file per scan.

6.2 Placement

Place the sheet squarely against the scanner's registration corner, artwork face down, and close the lid fully. Do not weight it, and do not press on the glass.

Deliberate skew is not needed here. The off-axis case is covered by the photograph in section 7, and a scanner that has been given a skewed sheet plus an auto-deskew you forgot to turn off produces a result nobody can interpret.

6.3 The thing that will catch you out

Your scanner does not capture the whole page. This is already measured and recorded in SAMPLE-NOTES.md : the existing 600 DPI scans are 4958 by 6458 pixels, which is 8.263 by 10.763

inches, against a page that is 8.5 by 11. Roughly 0.24 inches of width and 0.24 inches of height are missing.

The corner QR codes start 12.0 mm, or 0.47 inches, in from the page edge, so they survive comfortably. The outermost fiducial markers can sit as close as 6.0 mm, or 0.24 inches, from the edge, and those are right on the boundary of what your scanner keeps.

So, **after the first 600 DPI scan, before you scan anything else, check the marker count.** Open the image and look at all four edges. `GL-CF25-LTR` carries thirty-four markers. If the edge markers are cut off or missing, that is your scanner cropping, not a printing fault and not a detector fault, and it needs to be known before fourteen more scans are made the same way.

If markers are being lost, note it precisely, in pixels from each edge, and tell me. There are several ways to handle it and the right one depends on how much is going.

6.4 Naming

```
scans/phase0/<sheet>_<state>_<dpi>.png  
  
GL-CF25-LTR_clean_600.png  
GL-CF25-LTR_clean_300.png  
GL-CF25-LTR-96_clean_600.png  
GL-LR300-T-tile1_clean_600.png
```

Use `clean` now. The same sheets scanned after shooting become `shot`, which is what makes the pair obvious to anything that reads the directory.

7. The photograph

`SAMPLE-NOTES.md` records that the existing corpus has **no genuine off-axis photograph at all**, and that the distortion fitting in `DESIGN.md` section 11 cannot be validated without one. This is the single most valuable new sample in the whole run, because it is the only one that tests a code path nothing has ever tested.

Take at least one, of `GL-CF25-LTR`, `clean`.

- **Unresized camera original.** Not a screenshot, not shared through a messaging app, not exported from a photo editor. Get the file off the phone by cable or by a method that preserves the original bytes. The corpus already contains a messaging-app-downscaled image and it is there as a degraded-input test, not as a substitute for the real thing.
- **Handheld, from normal standing distance**, roughly the distance you would naturally hold a phone from a target pinned to a wall. Do not brace it, do not use a tripod. The point is to capture what a user will actually produce.
- **Deliberately off-axis.** Stand to one side and above, so the sheet appears as a clear trapezoid rather than a rectangle. Something in the region of twenty to thirty degrees off perpendicular. If it looks square in the viewfinder, move.

- **The whole sheet in frame**, with a little margin around it. All four corner codes must be visible.
- **No flash**. Ordinary indoor or window light. Flash produces a specular hotspot on the paper that is its own separate problem and not the one being tested here.
- **Pin or tape it to a wall**. Photographing a sheet lying on a table adds a fold or a curl that confuses the question.

Take three or four and keep them all. They cost nothing and the failure modes of handheld photographs are not visible on a phone screen.

```
scans/phase0/GL-CF25-LTR_clean_photo1.jpg
```

Also worth one photograph of a tile, since the tile carries only nine markers and the photograph path is where nine markers is most likely to be too few.

8. Order of operations

This order exists because two of the steps are irreversible.

1. Print `GL-CF25-LTR`, one copy.
2. Measure it, section 5.3.
3. If the measurements pass, print the rest of the set. If not, fix the print path and start again at step 1.
4. Measure one span on each remaining sheet, section 5.4.
5. Write `scans/phase0/MEASUREMENTS.md`.
6. **Scan every sheet clean**, at 600 and at 300, section 6.
7. Check the marker count on the first 600 DPI scan before continuing, section 6.3.
8. Photograph, section 7.
9. Write the `SAMPLE-NOTES.md` entries, section 9.
10. Stop. Tell me the numbers before anything gets shot.

Step 6 comes before any shooting and there is no way to go back and do it later. Once a sheet has holes, its clean scan cannot be made.

Keep one copy of `GL-CF25-LTR` clean and unshot, permanently. File it somewhere flat. It is the control sheet, and in six months when something is behaving oddly it is the only physical object that can tell you whether the target changed or the software did.

9. Writing the notes

`SAMPLE-NOTES.md` documents the existing corpus well, and the new material should not be worse. Add a `scans/phase0/` section with one row per file and, above it, a short block recording the conditions everything shares: printer make and model, paper, quality setting, scanner make and model, scanner software and version, and the date.

The reason to record the scanner software version is that scanner drivers change their default processing between versions, and a scan that suddenly looks different a year from now is otherwise unexplainable.

10. What happens after this, and what not to do yet

Phase 0 runs against these clean scans and this photograph. Its gate is registration residual under one thousandth of an inch across the whole page, on both the scan and the photograph, plus correct detection of the deliberately mis-scaled print. The measurements you wrote down in section 5 are what the reported scale gets checked against.

Do not shoot anything until Phase 0 has run. Not because shooting breaks anything, but because if the registration work turns up a reason to change the sheet, you want to find that out before there are fifteen shot targets of the old design and a temptation to keep them.

Do not write on the sheets beyond the pencil note in the top margin. No X marks, no arrows, no load data in the block by hand. That comes later and it is a Phase 1 concern.

Do not fold them. Flat storage, in a folder or a box. Paper is a developable surface and a homography absorbs a fold better than you would expect, per `DESIGN.md` section 6, but there is no reason to spend that margin before the baseline exists.