

Cheat Sheets

OPTICAL POWER LEVELS AT ONT

	<u>Alcatel BPON</u>	<u>Tellabs BPON</u>	<u>Motorola</u>
1550 nm BPON	-9 to +1dBm	-9 to +1dBm	-9 to +2dBm
1490 nm BPON	-26 to -10dBm	-26 to -11dBm	-26 to -11
1310 nm BPON	0 to +4dBm	0 to +4dBm	0 to +4

All Manufactures with GPON

1550nm	-9dBm to +1dBm
1490nm	-27dBm to -10dBm
1310nm	0 to +4dBm

dBm = decibels relative to *milliwatts*

RF power @ ONT.....+7dBmV to +35dBmV

(-20dBmV or greater = no RF signal)

RF power @ GBS and STB

..... -6 to +13dBmV

dBmV = decibels relative to one *millivolt*

dBm = decibels relative to one *milliwatt*

Carrier channels 2 thru 135 = 57MHz to 861MHz

Carrier to Noise Ratio (C/N)

..... 45 dB or greater is ideal