

Rockchip Solutions DDR SDRAM Support List

Ver 2.65

2025/3/17

NOTICE

Symbol	Description
✓	Fully Tested and Mass production
T/A	Sample Tested and Applicable, Applicable and Ready for Mass Production
S/A	The Samples have Passed the Compatibility Test. Customer should do the PVT(Production/Process Verification Test) before Mass Production to confirm.
N/A	Not Applicable
Empty	Not be evaluated

◆ ALL SYMBOL ✓ T/A S/A only applies to samples submitted for verification, which means that no customers have reported any problems so far, but it does not mean that there will be no problems in the future.

◆ For DDR products on this list, Rockchip only conducts compatibility testing and cannot guarantee that there will be no problems during mass production. Please do the PVT(Production/Process Verification Test) before Mass Production to confirm.

- ◆ The DRAM Part Number usually consists of two parts divided by '-', the first part contains memory type, density, organization, package, and the second part usually means data rate. It should be noticed that some vendors like ESMT, RAYSON, CXMT, BIWIN, Kingston, Foresee, Goldkey, the second part contains other important information. We don't care about the part represented of data rate.
- ◆ Rockchip platform can support all the chips that match the first part of Part Number which marks 'v', 'T/A' or 'S/A', and do not need to care the second part. If you want your system running more effective, you may need to find out the exact data rate in DRAM datasheet and config in kernel menuconfig.
- ◆ Please copy the Rockchip reference design model of DRAM area PCB Layout directly without any modification and follow the PCB layout rules from Rockchip. Contact information: fae@rock-chips.com
- ◆ THIS DOCUMENT IS PROVIDED “AS IS”. ROCKCHIP ELECTRONICS CO., LTD. (“ROCKCHIP”) DOES NOT PROVIDE ANY WARRANTY OF ANY KIND, EXPRESSED, IMPLIED OR OTHERWISE, WITH RESPECT TO THE ACCURACY, RELIABILITY, COMPLETENESS, MERCHANTABILITY, FITNESS FOR ANY PARTICULAR PURPOSE OR NON-INFRINGEMENT OF ANY REPRESENTATION, INFORMATION AND CONTENT IN THIS DOCUMENT. THIS DOCUMENT IS FOR REFERENCE ONLY. THIS DOCUMENT MAY BE UPDATED OR CHANGED WITHOUT ANY NOTICE AT ANY TIME DUE TO THE UPGRADES OF THE PRODUCT OR ANY OTHER REASONS.
- ◆ EVERY TIMES UPDATE WILL BE HIGHLIGHTED BY YELLOW.
- ◆ For DDR products on this list, except for specially marked products, they can be used without software modification under normal circumstances.
- ◆ For DDR products on this list, each platform corresponds to each testing separately and the test results of different platforms cannot be referenced.

◆ Application Note:

[1] Because lack of Address pin A15 in package, following SoCs do not support the 512M*8 DDR3: RK2906-6, RK2906-8, RK3066.

[2] Only support for RK3128.

[3] The DRAM's VDD and VDDQ should powered by 1.5V when it used on these SoCs.

[4] It can work stably on RK3399 with loader version `rk3399_ddr_XXXMHz_v1.22.bin` and trust version `rk3399_bl31_v1.28.elf`, or the later version than all above. On RK3399pro, loader should be updated to `rk3399pro_ddr_XXXMHz_v1.22.bin`, trust version should be updated to `rk3399pro_bl31_v1.28.elf`. Or the later version than all above.

[5] Only after week code 1937 (means 2019, week 37th) can be used, the product with early week code may cause system crash or unstable.



week code

[6] The DDR must be boot from 400MHz, please use `XXXX_ddr_400MHz_vX.XX.bin` to merge loader.

[7] On RK3568/RK3566, loader should be updated to `rk3568_ddr_XXXMHz_v1.09.bin` / `rk3566_ddr_XXXMHz_v1.09.bin` or later version.


[8] Only after week code 2101 (means 2021, week 01th) can be used, the product with early week code may cause system crash or unstable.



week code


[9] Only after week code 2118 (the third row, first four numbers means 2021, week 18th) can be used, the product with early week code may cause system crash or unstable.

week code



[10] Only after week code 022 (the fourth row, first three numbers means 2020, week 22th) can be used, the product with early week code may cause system crash or unstable.

week code




[11] For LPDDR4 and LPDDR4X unified product, platform only approve LPDDR4 mode, not guarantee LPDDR4X mode can work stably. So VDDQ must provide 1.1V not 0.6V.

[12] For LPDDR4X mode, the DDR bin need update to V1.13 or later version on RK3568 and RK3566.

[13] Only after week code 201 (the fourth row, first three numbers means 2022, week 2nd) can be used, the product with early week code may cause crash.

week code



[14] At the speed of 4266Mbps, it exists unfixable issues. The maximum frequency of this product is limited to 3733.

[15] On RV1126/RV1109, the performance of LPDDR4/LPDDR4X is not enough, please use it after evaluation.

[16] It can't work normally between 400MHz-625MHz and DTS cannot use this frequency band.

[17] On RK3588, the DDR bin should be updated to `rk3588_ddr_lp4_2112MHz_lp5_2736MHz_v1.10.bin` or later version, the bl31 should be updated to `rk3588_bl31_v1.37.elf` or later version.

[18] We tested samples like below, the left picture below may showed a boot error and the right picture below passes the test.

FAIL



PASS



[19] The DDR bin need update to V1.04 or later version on RK3576.

[20] Products produced only after week code 2328 (picture below the third row, the last four numbers means 2024, week 11th) are marked as **S/A**. Products produced before week code 2328 are marked as **N/A**. There is a problem with using the product before the 28th week in the year 2023 in the client application, and it cannot be worked.



[21] Please use the template which DDR3_A15 has a link to the DDR chip.

[22] The auto self-refresh function, frequency conversion feature, and standby wake-up function need to be disabled before use. See <https://redmine.rock-chips.com/boards/6/topics/274>

[23] Products produced with week code 2333, 2409, 2417, 2419, 2427, 2431 (picture below the third row, the first four numbers means 2023, week 33rd) are non-compliant with requirements.



[24] Please update the ddr.bin to v1.23 or the later version, **the CA_ODT pin of the DDR component must be pulled up to VDD2, which need modify PCB layout.**

[25] On RK3588, the DDR bin should be updated to rk3588_ddr_lp4_2112MHz_lp5_2736MHz_v1.18.bin or later version, on RK3576 the DDR bin should be updated to rk3576_ddr_lp4_2112MHz_lp5_2736MHz_v1.06.bin or later version.

[26] For some DDR products whose frequencies are lower than the maximum frequency of the platform, it is necessary to modify the frequency to a matching one by yourself. Refer to "修改DDR bin文件" in the "Rockchip_Developer_Guide_DDR_CN" or "Modify the DDR bin file" in "Rockchip_Developer_Guide_DDR_EN".

◆ Revision History

Revision No.	History	Date
2.00	ORG.	2012.12.24
2.25	Add some supporting messages	2017.03.30
2.26	Add some supporting messages	2017.05.24
2.27	Add some supporting messages	2017.07.05
2.28	Add some supporting messages	2017.08.24
2.29	Add some supporting messages	2017.11.24
2.30	Add some supporting messages	2018.01.24
2.31	Add some supporting messages	2018.03.26
2.32	Add some supporting messages	2018.05.25
2.34	Add some supporting messages	2018.10.17
2.35	Add some supporting messages	2018.12.11
2.36	Add some supporting messages	2019.01.21
2.37	Add some supporting messages	2019.03.11
2.38	Add some supporting messages	2019.05.15
2.39	Add some supporting messages	2019.07.19
2.40	Add some supporting messages	2019.09.30
2.41	Add some supporting messages	2019.11.25
2.42	Add some supporting messages, switch column order of product name.	2020.03.30
2.43	Add some supporting messages	2020.06.16
2.44	Add some supporting messages, modify IMD256M16R4ABD8LY , IMD512M16R4AZD8JY , H9HCNNBNPUMLHR , H9CCNNN8JTMLAR , H9CKNNNBPTMRLR , H9CKNNNCPTMRPR to N/A. Add "Product Status".	2020.09.02
2.45	Add some supporting messages, change the order of manufacture.	2020.11.17
2.46	Add some supporting messages	2021.01.29
2.47	Add some supporting messages	2021.04.16
2.48	Add some supporting messages	2021.07.20
2.49	Modify T/A of K4U8E3S4AD-MG** , NT6AP256T32AV , NT6AP512T32AV to N/A on RV1126/RV1109, fill Samsung and Nanya LPDDR4X on RV1126/RV1109 with N/A.	2021.07.23
2.50	Add some supporting messages, add note [8][9][10][11].	2021.10.22
2.51	Add some supporting messages	2022.01.17
2.52	Add some supporting messages, change note [12][13].	2022.04.01
2.53	Add some supporting messages, add note [14], modify T/A of K4U6E3S4AA-MG** , K4UHE3D4AB-MG** , K4UBE3D4AA-MG** to N/A on RK3588, modify T/A of NCLDXC1MJ512M32 , FLXC2002G-N2 , RS512M32LM4D2BDS-53BT , QN4LPD512M32M-32H to N/A on RK3399, modify T/A of FLXC4004G-26 , GE8062666ND to N/A on RK3568.	2022.05.30
2.54	Add note [15][16], change note [4], modify T/A of M15T1G1664A-DEBG2C to N/A on RV1126/RV1109, T/A of RS2G32LF4D4BDT-53BT to N/A on RK3588.	2022.08.18
2.55	Change T/A of H9HCNNNBKUMLXR to N/A on RK3399, T/A of EM6HC16EWBH-09H to N/A on all platforms. Delete parts of verison history.	2022.12.05
2.56	Change T/A of NCLDXC1MG256M32 to N/A on all platforms. Add note [17].	2023.04.07
2.57	Add some supporting messages, modify note[14] and part of HYNIX NANYA KINGSTON product to S/A, change T/A of BWSR8X32H2A-32G-X to N/A.	2023.11.22
2.58	Add some supporting messages	2023.12.05
2.59	Add some supporting messages,modify S/A of NT6AN512T32AV , T/A of RS1G32LF4D2BDS-53BT , K3LKCKC0BM-MG** to N/A.	2024.04.23
2.60	Add some supporting messages,modify N/A of K3LKCKC0BM-MG** to T/A.	2024.04.30
2.61	Add some supporting messages, modify S/A of Gd82B32MJ0-41M2 to N/A.	2024.06.05
2.62	Add some supporting messages	2024.09.03
2.63	Modify T/A of NT6AP512T32BL on RK3568/3562/3566 to N/A.	2024.09.05
2.64	Add some supporting messages, modify T/A of CXDQ3BFAM-CQ-A , CXDQ3BFAM-CJ-A , CXDQ3BFAM-IJ-A to S/A.	2024.11.28
2.65	Add some supporting messages, modify T/A of IS43QR16256B-083RBLI , NT5AD512M16C4 , A3F8GH40BBF-MC , N2AD8G16C4-JR , D5116AN9CXGXN to N/A, modify S/A of DD4N08GBCDSO2-C2 , DS4D82FBFCENY , KAD4N3M46GUT , GSD08GHGB6-S3L3C , BI4D8G1666-DL1 , BI4D8G1666-DL2 to N/A.	2025.03.17

See Infocenter, <https://redmine.rock-chips.com/documents/49>, for access to the latest support list.

Consumer

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK3218	RK3576	RK3528	RK3562	RK3508/ RK3588S/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3328H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3328A/ RK3328B/RK3329/ PX5	RK2908/ RK2918	RK2928/ RK3028A/ RK3128-PX3-SE	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188-PX3	与RK兼容情况			
																						CPU_RAM	NPU_RAM										
Micron	MT47H64M16HR-25	EOL	1G bit	64M×16	DDR2	84ball																									✓		
	MT41J128M8JP-15E-G (D9MNL)		1G bit	128M×8	DDR3	78ball																									✓		
	MT41K128M8DA-107-J (D9RDL)		1G bit	128M×8	DDR3L	78ball																									✓		
	MT41K64M16TW-107-J (D9SFT)		1G bit	64M×16	DDR3L	96ball										T/A																T/A	
	MT41J128M16HA-15E-D (D9LGG)		2G bit	128M×16	DDR3	96ball																									✓		
	MT41J256M8HX-15E-D (D9LGK)		2G bit	256M×8	DDR3	78ball																			T/A					✓	T/A	T/A	
	MT41K256M8DA-125-K (D9PSH)		2G bit	256M×8	DDR3L	78ball																			T/A				✓	T/A	T/A	T/A	
	MT41K256M8DA-125-M (D9PFJ)		2G bit	256M×8	DDR3L	78ball																			T/A				✓	T/A	T/A	T/A	
	MT41K128M16HA-15E-D (D9LJM)		2G bit	128M×16	DDR3L	96ball																							✓				
	MT41K128M16T-125-K (D9PTK)		2G bit	128M×16	DDR3L	96ball									T/A	T/A									T/A				✓	T/A	T/A	T/A	
	MT41K128M16T-107-K (D9PSZ)		2G bit	128M×16	DDR3L	96ball									T/A							T/A			T/A				✓	T/A	T/A	T/A	
	MT41K512M8RH-125-E (D9QBJ)		4G bit	512M×8	DDR3L	78ball																				T/A							
	MT41K512M8RG-107-N (D9RVX)		4G bit	512M×8	DDR3L	78ball																											
	MT41K512M8DA-107-P (D9SGQ)		4G bit	512M×8	DDR3L	78ball																											
	MT41K256M16RE-15E-D (D9PBF)		4G bit	256M×16	DDR3L	96ball																								✓			
	MT41K256M16HA-125-E (D9PXV)		4G bit	256M×16	DDR3L	96ball																								✓			
	MT41K256M16LY-107-N (D9SDD)		4G bit	256M×16	DDR3L	96ball									T/A	T/A														✓	T/A	T/A	T/A
	MT41K256M16TW-107-P (D9SHD)		4G bit	256M×16	DDR3L	96ball									T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A				
	MT41K256M16TW-107 IT-P (D9SHG)		4G bit	256M×16	DDR3L	96ball																											
	MT41K512M16HA-125-A (D9STQ)	EOL	8G bit	512M×16	DDR3L	96ball													✓														
	MT41K512M16HA-107-A (D9SDQ)	EOL	8G bit	512M×16	DDR3L	96ball																											
	MT41K512M16V-107T1-P (D9ZWN)		8G bit	512M×16	DDR3L	96ball																											
	MT40A256M16GE-083E-B (D9TGO)	EOL	4G bit	256M×16	DDR4	96ball																											
	MT40A256M16GE-075E-B (D9TGS)	EOL	4G bit	256M×16	DDR4	96ball																											
	MT40A512M16TB-062E-J (D9WWP)	EOL	8G bit	512M×16	DDR4	96ball																											
	MT40A512M16Y-083E-B (D9TRK)		8G bit	512M×16	DDR4	96ball																											
	MT40A512M16TB-062E-E (D9BPK)		8G bit	512M×16	DDR4	96ball																											
	MT40A512M16LY-062E-E (D9WEJ)	EOL	8G bit	512M×16	DDR4	96ball																											
	MT40A1G16WBU-083E-B (D9TPH)	EOL	16G bit	1024M×16	DDR4	96ball																											
	MT40A1G16KD-062E-E (D9ZFW)	EOL	16G bit	1024M×16	DDR4	96ball																											
	MT40A1G16TB-062E-F (D8CX)		16G bit	1024M×16	DDR4	96ball																											
	MT40A2G16SKL-062E-B (D9XQF)		32G bit	2048M×16	DDR4	96ball																											
Micron	MT42L128M32D1GU-25 WT-A (Z9QHQ)		4G bit	128M×32	LPDDR2	134ball																											
	MT42L256M16D1GU-18 WT-A (D9RLT)		4G bit	256M×16	LPDDR2	134ball																											
	MT42L128M64D2LL-25 WT-A (D9QOQ)		8G bit	128M×32×2Ch	LPDDR2	216ball																											
	MT53L256M32D1PE-107 WT-B (D9SRZ)		8G bit	256M×32	LPDDR3	178ball																											
	MT53L512M32D2PF-107 WT-B (D9SSF)		16G bit	512M×32	LPDDR3	178ball																											
	MT53E128M16D1DS-046 WT-A (D9WXT)		2G bit	128M×16	LPDDR4/LPDDR4X	200ball																											

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3566/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3508/ RK3508S	RK3228H1	RK3599	RK3328	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3229/ PX5	RK2908/ RK2918	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3108/PX3	与RK兼容情况
																			CPU_RAM	NPU_RAM							
Samsung	K4T1G164QE		1G bit	64M*16	DDR2	84ball																	✓				
	K4B1G0846G		1G bit	128M*8	DDR3	78ball															T/A		✓				T/A
	K4B1G1646L-C**		1G bit	64M*16	DDR3	96ball								T/A	T/A												
	K4B1G1646L-Y**		1G bit	64M*16	DDR3L	96ball								T/A	T/A								✓				
	K4B2G0846C		2G bit	256M*8	DDR3	78ball																		✓			
	K4B2G0846E-Y**		2G bit	256M*8	DDR3L	78ball																T/A					T/A
	K4B2G1646C		2G bit	128M*16	DDR3	96ball																					
	K4B2G1646E		2G bit	128M*16	DDR3	96ball																					
	K4B2G1646Q		2G bit	128M*16	DDR3	96ball																					
	K4B2G1646Q		2G bit	128M*16	DDR3	96ball																					
	K4B2G1646E-Y**		2G bit	128M*16	DDR3L	96ball									T/A	T/A					T/A			T/A	T/A	T/A	T/A
	K4B4G0846E-C**		4G bit	512M*8	DDR3	78ball																					
	K4B4G1646B-C**		4G bit	256M*16	DDR3	96ball																					
	K4B4G1646Q-Y**	EOL	4G bit	256M*16	DDR3L	96ball										T/A	T/A		✓	T/A	T/A			✓	T/A	T/A	T/A
	K4B4G1646D-Y**		4G bit	256M*16	DDR3L	96ball											T/A	T/A		✓	T/A	T/A					
	K4B4G1646D-C**	EOL	4G bit	256M*16	DDR3	96ball																					
	K4W4G1646Q-C**		4G bit	256M*16	DDR3	96ball																					
	K4B4G1646E-Y**		4G bit	256M*16	DDR3L	96ball																					
	K4B4G1646E-C**		4G bit	256M*16	DDR3	96ball				T/A	T/A		T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A	T/A					T/A	T/A
	K4B8G1646D-Y**	EOL	8G bit	512M*16	DDR3L	96ball																					
	K4A4G165WE-BC**	EOL	4G bit	256M*16	DDR4	96ball																					
	K4A4G165WF-BC**	EOL	4G bit	256M*16	DDR4	96ball					T/A		T/A	T/A	T/A												
	K4A4G165WG-BC**		4G bit	256M*16	DDR4	96ball																					
	K4A8G085WC-BC**		8G bit	1024M*8	DDR4	78ball																					
	K4A8G165WB-BC**	EOL	8G bit	512M*16	DDR4																						

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H1	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1806/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3229/ PX5	RK2906/ RK2918	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3	与RK兼容情况		
Nanya	NT5TU32M16CG-3C		512M bit	32M×16	DDR2	84ball									T/A												✓					
	NT5TU32M16RG		512M bit	32M×16	DDR2	84ball									T/A																	
	NT5TU64M16H8G		1G bit	64M×16	DDR2	84ball									T/A																	
	NT5CB64M16GP		1G bit	64M×16	DDR3	96ball	T/A		T/A						T/A											T/A						
	NT5CC64M16GP		1G bit	64M×16	DDR3L	96ball									T/A																	
	NT5CB128MRDN		1G bit	128M×8	DDR3	96ball																					✓					
	NT5CC128MRDN		1G bit	128M×8	DDR3L	78ball																		T/A			✓				T/A	
	NT5CB128MRFN		1G bit	128M×8	DDR3	78ball																		T/A							T/A	
	NT5CC128MRGN		1G bit	128M×8	DDR3L	78ball																									T/A	
	NT5CB256MRGN		2G bit	256M×8	DDR3	78ball																			T/A		✓	T/A	T/A	T/A	T/A	
	NT5CB256MBIN		2G bit	256M×8	DDR3	78ball																			T/A		✓	T/A	T/A	T/A	T/A	
	NT5CB256MBFN		2G bit	256M×8	DDR3	78ball																			T/A		✓	T/A	T/A	T/A	T/A	
	NT5CB256MBIN		2G bit	256M×8	DDR3	78ball									T/A	T/A		T/A	T/A	T/A						T/A		✓	T/A	T/A	T/A	
	NT5CC256MBIN		2G bit	256M×8	DDR3L	78ball									T/A	T/A		T/A	T/A	T/A							T/A				T/A	
	NT5CB128M16BP		2G bit	128M×16	DDR3	96ball																			T/A		✓	T/A	T/A	T/A	T/A	
	NT5CB128M16HP		2G bit	128M×16	DDR3	96ball																			T/A			T/A			T/A	
	NT5CC128M16BP		2G bit	128M×16	DDR3L	96ball																					✓					
	NT5CB128M16GP		2G bit	128M×16	DDR3	96ball																					✓					
	NT5CC128M16GP	EOL	2G bit	128M×16	DDR3L	96ball									T/A										T/A		✓	T/A	T/A	T/A	T/A	
	NT5CB128M16BP	EOL	2G bit	128M×16	DDR3	96ball									T/A	T/A			T/A	T/A					T/A	T/A					T/A	
	NT5CB128M16JR		2G bit	128M×16	DDR3	96ball			T/A						T/A	T/A										T/A					T/A	
	NT5CC128M16JR		2G bit	128M×16	DDR3L	96ball	T/A		T/A						T/A	T/A	T/A		T/A	T/A	T/A		T/A	T/A	T/A						T/A ^(H)	
	NT5CB512MBIN		4G bit	512M×8	DDR3	78ball									T/A	T/A		T/A	T/A	T/A												
	NT5CB512MBDN		4G bit	512M×8	DDR3	78ball									T/A	T/A		T/A	T/A	T/A												
	NT5CC512MBIN		4G bit	512M×8	DDR3L	78ball									T/A	T/A		T/A	T/A	T/A												
	NT5CC512MBDN		4G bit	512M×8	DDR3L	78ball									T/A	T/A		T/A	T/A	T/A												
	NT5CB256M16BP		4G bit	256M×16	DDR3	96ball																					✓	T/A	T/A	T/A	T/A	
	NT5CB256M16CP	EOL	4G bit	256M×16	DDR3	96ball																										
	NT5CB256M16DP	EOL	4G bit	256M×16	DDR3	96ball																										
	NT5CB256M16EP		4G bit	256M×16	DDR3	96ball									T/A	T/A	T/A	T/A	T/A	T/A		T/A				T/A						
	NT5CC256M16CP	EOL	4G bit	256M×16	DDR3L	96ball									T/A	T/A	T/A	T/A	T/A	T/A		T/A				T/A						
	NT5CC256M16EP	EOL	4G bit	256M×16	DDR3L	96ball									T/A	T/A	T/A	T/A	T/A	T/A		T/A				T/A						
	NT5CC256M16ER		4G bit	256M×16	DDR3L	96ball	T/A								T/A	T/A	T/A	T/A	T/A	T/A		T/A				T/A						
	NT5CB256M16ER		4G bit	256M×16	DDR3	96ball	T/A		T/A	T/A		T/A	T/A																			
	NT5AD256M16B2	EOL	4G bit	256M×16	DDR4	96ball										T/A					T/A		T/A									
	NT5AD256M16D4	EOL	4G bit	256M×16	DDR4	96ball										T/A					T/A		T/A									
	NT5AD256M16E4		4G bit	256M×16	DDR4	96ball			T/A	T/A		T/A	T/A																			
	NT5AD512M16A4	EOL	8G bit	512M×16	DDR4	96ball																										
	NT5AD512M16C4		8G bit	512M×16	DDR4	96ball																										
	NT5AD512M16G4	EOL	8G bit	512M×16	DDR4	96ball																										
	NT6TL128M32AQ		4G bit	128M×32	LPDDR2	168ball																			T/A						T/A	
	NT6TL256F32AI		8G bit	256M×32	LPDDR2	134ball																			T/A						T/A	
	NT6TL256T32AI		8G bit	256M×32	LPDDR2	134ball																			T/A						T/A	
	NT6TL256T32AQ		8G bit	256M×32	LPDDR2	168ball																			T/A						T/A	
	NT6CL128M32BM		4G bit	128M×32	LPDDR3	178ball																			T/A							
	NT6CL128M32CM		4G bit	128M×32	LPDDR3	178ball																										
	NT6CL128M32DM		4G bit	128M×32	LPDDR3	178ball																										
	NT6CL256T32CM		8G bit	256M×32	LPDDR3	178ball																										
	NT6CL256T32BM		8G bit	256M×32	LPDDR3	178ball																										
	NT6CL256M32AM		8G bit	256M×32	LPDDR3	178ball																										
	NT6CL512T32AM		16G bit	512M×32	LPDDR3	178ball																										
	NT6CL256T32AQ		8G bit	256M×32	LPDDR3	168ball																										
	NT6AN256T32AV		8G bit	256M×32	LPDDR4	200ball																										
	NT6AN512T32AV		16G bit	512M×32	LPDDR4	200ball																										
	NT6AN1024F32AV		32G bit	1024M×32	LPDDR4	200ball																										
	NT6AP256T32AV		8G bit	256M×32	LPDDR4X	200ball			T/A																							
	NT6AP256T32BV		8G bit	256M×32	LPDDR4X	200ball																										
	NT6AP512T32BV		16G bit	512M×32	LPDDR4X	200ball																										
	NT6AP512T32AV		16G bit	512M×32	LPDDR4X	200ball																										
	NT6AP512T32BL		16G bit	512M×32	LPDDR4X	200ball																										
	NT6AP1024F32BV		32G bit	1024M×32	LPDDR4X	200ball																										

兼容性好

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3229 /PX5	RK2908/ RK2918	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036G/ RK3126	RK3066/RK3066A/ PX3/RK3168/ RK3188/PX3	与RK兼容情况
																					CPU_RAM	NPU_RAM								
CXMT	CXDQ2BFAMCG	EOL	4G bit	256M×16	DDR4	96ball							T/A	T/A				T/A ^[9]												
	CXDQ1BFAMCG		8G bit	512M×16	DDR4	96ball							T/A	T/A				T/A ^[9]												
	CXDQ1BFAMCQ-A	EOL	8G bit	512M×16	DDR4	96ball																								
	CXDQ1BFAMCJA	EOL	8G bit	512M×16	DDR4	96ball			S/A ^[28]				S/A ^[28]	N/A				N/A	S/A ^[28]	N/A	N/A		N/A							
	CXDQ4BFAMCJ-M		16G bit	1024M×16	DDR4	96ball							S/A ^[28]	S/A ^[28]				N/A	N/A	N/A	N/A									
	CXDB3ABAM-MK		8G bit	256M×32	LPDDR4/LPDDR4X	200ball							T/A ^[70]	T/A ^[70]								T/A								
	CXDB3ABAM-MK-A		8G bit	256M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A ^[70]	T/A	T/A	T/A				T/A												
	CXDB4ABAM-MK		16G bit	512M×32	LPDDR4/LPDDR4X	200ball				T/A ^[70]	T/A ^[70]	T/A ^[70]	T/A ^[70]	T/A ^[70]				T/A												
	CXDB4CBAM-MK-A		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A ^[70]	T/A	T/A	S/A ^[10]				T/A												
	CXDB4CBAM-ML-A		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A ^[70]	T/A	T/A	S/A ^[10]				T/A												
	CXDB4CCAM-MJ		16G bit	512M×32	LPDDR4/LPDDR4X	200ball				T/A	T/A ^[70]	T/A	T/A					T/A												
	CXDBBCCBM-MK-B		24G bit	768M×32	LPDDR4/LPDDR4X	200ball			T/A		T/A	T/A ^[70]	T/A	T/A																
	CXDBSCCAM-MK		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball					T/A ^[70]	T/A	T/A ^[70]	T/A ^[70]																
	CXDBSCCAM-ML		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						N/A																		
	CXDBSCCBM-M*-A		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	S/A	T/A ^[70]	S/A	S/A																
	CXDBSCBAM-MA-B		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A	T/A	T/A	T/A	N/A															
	CXDBSCCDM-MA-M		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball			T/A		T/A	T/A	T/A	T/A																
	CXDBSCCDM-MA-M		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			T/A		T/A	T/A ^[70]	T/A	T/A																
	CXDBSCCBM-MA-A		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball					T/A	T/A	T/A	T/A																
	CXDBDCCCM-MA-M		96G bit	36G×32	LPDDR4/LPDDR4X	200ball																								
	CXDB7CCDM-MA-M		128G bit	4G×32	LPDDR4/LPDDR4X	200ball			T/A ^[29]				T/A ^[29]	T/A ^[29]																
	CXDCDCBM-MT-M		48G bit	1536M×32	LPDDR5/LPDDR5X	315ball			T/A																					
	CXDCDIEDM-MT-M		96G bit	1536M×64	LPDDR5	496ball						N/A																		
GigaDevice/XCMemory	GDP1BFLM-CB		2G bit	128M×16	DDR3L	96ball				T/A				T/A	T/A															
	GDP1BFLM-CA		2G bit	128M×16	DDR3L	96ball						T/A	T/A																	
	GDP1BFLA-C*		2G bit	128M×16	DDR3L	96ball		T/A		N/A	T/A		T/A	T/A	T/A															
	GDP2BFLM-C*		4G bit	256M×16	DDR3L	96ball		T/A		T/A		T/A	T/A	T/A	T/A															
	GDP3BELM-CB		8G bit	512M×16	DDR3L	96ball		T/A		N/A	N/A	N/A	N/A																	
	GDQ2BFAA-CE		4G bit	256M×16	DDR4	96ball			N/A										T/A	T/A	N/A		N/A							
	GDQ2BFAA-CQ		4G bit	256M×16	DDR4	96ball			N/A	S/A ^[28]		S/A ^[28]	S/A ^[28]	S/A ^[28]				N/A	S/A ^[28]	S/A ^[28]	N/A		N/A							
	GDQ2BFAA-CJ		4G bit	256M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A				N/A	N/A	N/A	N/A		N/A							
	GDQ3BFAM-CJ		8G bit	512M×16	DDR4	96ball					T/A	T/A	T/A	T/A																
	GD84CBQM-MK		16G bit	512M×32	LPDDR4/LPDDR4X	200ball				T/A	T/A	T/A	T/A	T/A																
	GD84CBQM-M*		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A	T/A	T/A	T/A	T/A																
	GD84CBQM-ML		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A		T/A	T/A	T/A	T/A																
	GD8SCCQ-N-ML		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A		T/A	T/A	T/A	T/A																
JHCC	CA484G16V-F9**C		4G bit	256M×16	DDR4	96ball					T/A ^[9]		T/A ^[9]	T/A ^[9]	T/A															
	CA488G16V-F9**C		8G bit	512M×16	DDR4	96ball					T/A		T/A	T/A	T/A															
ESMT	M14D1G1664A-1.8BG2S		1G bit	64M×16	DDR2	84ball																								
	M15T1G1664A-DEBG2C		1G bit	64M×16	DDR3L	96ball									N/A	T/A														
	M15T1G1664A-DEBG2CS		1G bit	64M×16	DDR3L	96ball																								
	M15T1G1664A-EFBG2S		1G bit	64M×16	DDR3L	96ball																								
	M15T1G1664A-DEBG2S		1G bit	64M×16	DDR3L	96ball																								
	M15T2G16128A-DEBG2L		2G bit	128M×16	DDR3L	96ball													N/A	N/A										
	M15T2G16128A-DEBG2LS	EOL	2G bit	128M×16	DDR3L	96ball																								
	M15T2G16128A-DEBG2R		2G bit	128M×16	DDR3L	96ball																								
	M15T2G16128A-DEBG2D		2G bit	128M×16	DDR3L	96ball																								
	M15T4G16256A-DEBG2L	EOL	4G bit	256M×16	DDR3L	96ball																								
	M15F4G16256A-DEBG2L	EOL	4G bit	256M×16	DDR3	96ball									N/A	N/A			N/A	N/A	N/A									
	M15T4G16256A-DEBG2R	EOL	4G bit	256M×16	DDR3L	96ball																								
	M15T4G16256A-DEBG2G	EOL	4G bit	256M×16	DDR3L	96ball																								
	M15T4G16256A-DEBG2S		4G bit	256M×16	DDR3L	96ball																								
	M15T4G16256A-DEBG2P		4G bit	256M×16	DDR3L	96ball				T/A																				
	M16U4G16256A-KJBG		4G bit	256M×16	DDR4	96ball																								
	M16U4G16256A-QLBG		4G bit	256M×16	DDR4	96ball																								
	M16U4G16256A-QLBG2Z		4G bit	256M×16	DDR4	96ball																								
	M16U8G16512A-NLBG2W		8G bit	512M×16	DDR4	96ball																								
	M16U8G16512A-NLBG2C		8G bit	512M×16	DDR4	96ball																								
	M56Z8G32256A-SMBIG		8G bit	256M×32	LPDDR4	200ball																								
	M56Z8G32256A-SMBYIG		8G bit	256M×32	LPDDR4/LPDDR4X	200ball				N/A	N/A		N/A	N/A																
	M56Z16G32512A-TNBYG2D		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A		T/A	T/A	T/A	T/A																
UniC	SCB15H1G160CF-13K		1G bit	64M×16	DDR3	96ball																								
	SCB15H1G160AF-13K		1G bit	64M×16	DDR3	96ball																								
	SCB13H1G160EF-11M		1G bit	64M×16	DDR3L	96ball				</																				

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3229/ PX5	RK2908/ RK2918	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3	与RK兼容情况
																					CPU_RAM	NPU_RAM								
SCSemicon	HXB18T1G160AF-25D		1G bit	64M*16	DDR2	84ball																								256M16在RK3066，RK31xx平台上需要添加定额相关补丁。并且对参考层完整性要求较高，需要严格遵照我们的布板要求布板。
	HXB18T2G160AF-25D		2G bit	128M*16	DDR2	84ball																								
	HXB15H2G080BF-15H		2G bit	256M*8	DDR3	78ball																								
	HXB15H2G160CF-13K		2G bit	128M*16	DDR3	96ball																								
	HXB15H4G080BF-15H		4G bit	512M*8	DDR3	78ball																								
	HXB15H4G160BF-15H		4G bit	256M*16	DDR3	96ball																								
Winbond	W9751G0KB-25		512M bit	32M*16	DDR2	84ball																								
	W9751G6NB-25		512M bit	32M*16	DDR2	84ball																								
	W971G06SB-18		1G bit	64M*16	DDR2	84ball																								
	W931G06KB-12		1G bit	64M*16	DDR3	96ball																								
	W831G06MB-12	EOL	1G bit	64M*16	DDR3	96ball																								
	W831G6NB-12		1G bit	64M*16	DDR3L	96ball																								
	W831G09RB-11		1G bit	64M*16	DDR3L	96ball	T/A																							
	W632G06KB-15		2G bit	128M*16	DDR3	96ball																								
	W632G06NB-12		2G bit	128M*16	DDR3	96ball				N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	
	W632G06NB-09		2G bit	128M*16	DDR3L	96ball																								
	W632G06QB-09		2G bit	128M*16	DDR3L	96ball																								
	W632G06RB-09		2G bit	128M*16	DDR3L	96ball																								
	W634G06QB-11		4G bit	256M*16	DDR3L	96ball																								
	W634G06QB-09		4G bit	256M*16	DDR3L	96ball																								
	W634G06RB-09		4G bit	256M*16	DDR3L	96ball																								
	W634G06RB-11		4G bit	256M*16	DDR3L	96ball																								
	W634G06RB-09		4G bit	256M*16	DDR3L	96ball																								
	W634G06RB-11		4G bit	256M*16	DDR3L	96ball																								
	W638G06QB-111		8G bit	512M*16	DDR3L	96ball																								
	W638G06QB-09		8G bit	512M*16	DDR3L	96ball																								
	W664G06RB-06		4G bit	256M*16	DDR4	96ball																								
	W66BL6NBUIAFI		2G bit	128M*16	LPDDR4	200ball																								
	W66P2R0QAGJ		8G bit	256M*32	LPDDR4/LPDDR4X	200ball																								
Etron Tech	EM68B16C/WPA-25H		512M bit	32M*16	DDR2	84ball																								
	EM68B16C/WQK-18H		512M bit	32M*16	DDR2	84ball																								
	EM68B16C/WQH-18H		512M bit	32M*16	DDR2	84ball																								
	EM6GC16EWKG-12H		1G bit	64M*16	DDR3	96ball																								
	EM6GC16EWKE-12H	EOL	2G bit	128M*16	DDR3	96ball																								
	EM6GC16EWXD-12H	EOL	2G bit	128M*16	DDR3	96ball																								
	EM6GD16EWKG-12H	EOL	2G bit	128M*16	DDR3	96ball																								
	EM6GD16EWXF-12H	EOL	EOL	128M*16	DDR3	96ball																								
	EM6GD16EWBH-12H		2G bit	128M*16	DDR3	96ball																								
	EM6HC16EWBH-09H		2G bit	128M*16	DDR3L	96ball				N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	
	EM6GE16EWSB-15H		4G bit	256M*16	DDR3	96ball																								
	EM6GE08EWSC-12H		4G bit	512M*8	DDR3	96ball																								
	EM6GE16EWXC-12H		4G bit	256M*16	DDR3	96ball																								
	EM6HE16EWXD-12H	EOL	4G bit	256M*16	DDR3L	96ball																								
	EM6GE16EWXD-10H	EOL	4G bit	256M*16	DDR3	96ball																								
	EM6GE16EWSF-12H	EOL	4G bit	256M*16	DDR3	96ball																								
	EM6HE16EWSF-12H	EOL	4G bit	256M*16	DDR3L	96ball																								
	EM6HE16EWAKG-10H		4G bit	256M*16	DDR3L	96ball																								
	EM6HE16EWAKG-09H		4G bit	256M*16	DDR3L	96ball																								
	EM6GE16EWAKG-10H		4G bit	256M*16	DDR3	96ball																								
	EM6HF16EBXB-10ESH		8G bit	512M*16	DDR3L	96ball																								
	EM6HF16EBXB-09SH		8G bit	512M*16	DDR3L	96ball																								
	EM6OE16NWAKA-08H		4G bit	256M*16	DDR4	96ball																								
	EM6OE16NWB-62H		4G bit	256M*16	DDR4	96ball																								
	EM6OE16NWB-07H		4G bit	256M*16	DDR4	96ball																								
	EM6OF16NWB-62H		8G bit	512M*16	DDR4	96ball																								
	EM6OF16NWB-62H		8G bit	512M*16	DDR4	96ball																								
	EM6PH32MVAJA-46SH		32G bit	1024M*32	LPDDR4	200ball																								
Zentel	A3R12E40DBF-AH		512M bit	32M*16	DDR2	84ball																								
	A3T1GF40CBF-HP		1G bit	64M*16	DDR3	96ball																								
	A3T1GF40CBF-GM		1G bit	64M*16	DDR3	96ball																								
	A3T2GF40BBF-GM		2G bit	128M*16	DDR3	96ball																								
	A3T2GF40CBF-HP		2G bit	128M*16	DDR3	96ball																								
	A3T4GF40BBF-HP		4G bit	256M*16	DDR3	96ball																								
	A3T4GF40ABF-GM		4G bit	256M*16	DDR3	96ball																								
	A3T8GF33BBF-GM**		8G bit	1G*8	DDR3	78ball																								
	A3T8GF33BBF-HP**		8G bit	1G*8	DDR3	78ball																								
	A3F4GH40CBF-WD		4G bit	256M*16	DDR4	96ball																								
	A3F8GH40BBF-KD		8G bit	512M*16	DDR4	96ball																								

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3229/ PX5	RK2906/ RK2918	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3	与RK兼容情况			
																						CPU_RAM	NPU_RAM										
nPM	PMF810816CBR-GRDN		1G bit	64M×16	DDR2	84ball									T/A																		
	PMF510816ABR-GRDN		1G bit	64M×16	DDR3	96ball																				√							
	PMF410816EBR-MBDN		1G bit	64M×16	DDR3L	96ball								T/A																			
	PMF511816ABR-GRDN		2G bit	128M×16	DDR3	96ball																				√							
	PMF511816DBR-KADN		2G bit	128M×16	DDR3	96ball																	T/A							T/A			
	PMF411816HBR-NC DN		2G bit	128M×16	DDR3L	96ball								T/A																			
	PMF412816HBR-KADN		4G bit	256M×16	DDR3L	96ball													T/A	T/A													
	PMF512816BHR-KADN		4G bit	256M×16	DDR3	96ball																											
	PMF512816DBR-KADN		4G bit	256M×16	DDR3	96ball																											
	PMF512816HBR-KADN		4G bit	256M×16	DDR3	96ball																											
	PMF512816HBR-NC DN		4G bit	256M×16	DDR3	96ball								T/A																			
	τ Memory	PMF412816FBR-KADN		4G bit	256M×16	DDR3L	96ball																										
TMF41G6EBR-MBDN			1G bit	64M×16	DDR3L	96ball										T/A																	
TMF42G6HBR-MBDN			2G bit	128M×16	DDR3L	96ball	T/A																										
TMF42G6HBR-NC DN			2G bit	128M×16	DDR3L	96ball				T/A			T/A	T/A																			
TMF54G6HBR-KADN			4G bit	256M×16	DDR3	96ball																											
TMF54G6HBR-NC DN			4G bit	256M×16	DDR3	96ball					T/A			T/A	T/A																		
TDG64G6DB-KC NN			4G bit	256M×16	DDR4	96ball																											
TDG68G6CB-KC NN		8G bit	512M×16	DDR4	96ball																												
ISSI	IS43TR16640B-125KBL		1G bit	64M×16	DDR3	96ball									T/A																		
	IS43TR16128C-125KBL		2G bit	128M×16	DDR3	96ball									T/A																		
	IS43TR16512BL-125KBL1		8G bit	512M×16	DDR3L	96ball											T/A																
Essencore	ISTQ4G63EFR		4G bit	256M×16	DDR3	96ball										T/A				T/A	T/A												
	EL38NMMAA1-PBER		8G bit	256M×32	LPDDR3	178ball																											
	EL4BPMBBB1-S4ER		16G bit	512M×32	LPDDR4	200ball																											
SPECTEK	PE918-15E (PRN256M8V79DG8GQF-15E)		2G bit	256M×8	DDR3	78ball																					T/A		T/A	T/A	T/A	T/A	
	PE936-15E (PRN256M8V89CG8GQF-15E)		2G bit	256M×8	DDR3	78ball																					N/A		T/A	T/A	T/A	N/A	
	PEB08-15E (PRN512M8V80AG8RHF-15E)		4G bit	512M×8	DDR3	78ball																					T/A			T/A	T/A	T/A ^[9]	
	PEB15-15E (PRN256M16V80AG8GPF-15E)		4G bit	256M×16	DDR3	96ball																					T/A			T/A	T/A	T/A	
	PEB16-15E (PRM256M16V80AG8GPF-15E)		4G bit	256M×16	DDR3	96ball																					T/A			T/A	T/A	T/A	
	PEB17 (SUU256M16V90BG8LY-125TP)		4G bit	256M×16	DDR3	96ball																									N/A		
	PEB39 (SUU256M16V90BG8LY-125TP)		4G bit	256M×16	DDR3	96ball										T/A																	
	PEB29 (PRN256M16V00HG8GNF-125)		4G bit	256M×16	DDR3	96ball									T/A																		
	Z9QHJG (SM128MX32U80MD1L GU-25FT)		4G bit	128M×32	LPDDR2	96ball																										T/A	
	PB047 (SS256M32V01MD1LPF-107BT)		8G bit	256M×32	LPDDR3	178ball											N/A	N/A	N/A	N/A	N/A												
	PB008 (SM512M322E0FD4LHL)		16G bit	512M×32	LPDDR3	178ball																											
	PS006 (SU256M32201MD1BNP)		8G bit	256M×32	LPDDR4	200ball																											
	PS007 (SU512M32201MD2BNP)		16G bit	512M×32	LPDDR4	200ball																											
	(PS086) SU256M64200MD4DKN)		16G bit	256M×64	LPDDR4	366ball																											
	PS004 (SM512M64291MD4BNK)		32G bit	512M×64	LPDDR4	366ball																											
	PS035 (SU512M64201MD4BNK)		32G bit	512M×64	LPDDR4	366ball																											
	PS013 (SM512M64201MD4BNK)		32G bit	512M×64	LPDDR4	366ball																											
	PU031 (SM768M64Y4BMD4FZU-UT)		48G bit	768M×64	LPDDR5/LPDDR5X	496ball																											
	PU055 (SM1G64Y42MD4FZV-UT)		64G bit	1G×64	LPDDR5/LPDDR5X	496ball																											
	PU032 (SM1536M64Y4BMD8FCL-UT)		96G bit	1536M×64	LPDDR5/LPDDR5X	496ball																											
	PU054 (SM2G64Y42MD8FCL-UT)		128G bit	2G×64	LPDDR5/LPDDR5X	496ball																											

MICRON子品牌，
兼容性良好

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3229/ PX5	RK2906/ RK2918	RK1928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3030/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3	与RK兼容情况		
																						CPU_RAM	SPU_RAM									
eLixir	N2CB2G16JR-FL		2G bit	128M*16	DDR3	96ball				T/A		T/A	T/A																			
	N2CB4G16ER-FL		4G bit	256M*16	DDR3	96ball				T/A		T/A	T/A																			
	N2AD4G16E4-JR		4G bit	256M*16	DDR4	96ball			S/A	T/A		T/A	T/A	T/A					T/A													
	N2AD8G16C4-JR		8G bit	512M*16	DDR4	96ball				N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A			N/A								
MIRA	P3R1GE4CF-G8E		1G bit	64M*16	DDR2	84ball																					√					
	P3R1GE3FG-G8E		1G bit	128M*8	DDR2	84ball																					√					
	P2P2GF4ALF-GGN		2G bit	128M*16	DDR3	96ball									T/A												T/A					
	P2P2GF4ALF-GJS		2G bit	128M*16	DDR3	96ball									T/A	T/A																
	P3P4GF3BLF-GGN		4G bit	512M*8	DDR3	78ball																							T/A	N/A	N/A	
	P3P4GF4BLF-GGN		4G bit	256M*16	DDR3	96ball				N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	P3P4GF4BLF-GJS		4G bit	256M*16	DDR3	96ball				N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	P3P4GF4DMF-GJS		4G bit	256M*16	DDR3	96ball									T/A		T/A		T/A	T/A	T/A											
	P5M4GK4CMF-GMX		4G bit	256M*16	DDR4	96ball																T/A		T/A								
Kingston	D1216ECMDXGJD		2G bit	128M*16	DDR3L	96ball									T/A					T/A	T/A											
	D5128EETBPGGBU		4G bit	512M*8	DDR3	78ball																										
	D2516EC4BXGGB	EOL	4G bit	256M*16	DDR3L	96ball										T/A ^[9]												T/A ^[9]				
	D2516ECMDXGJD		4G bit	256M*16	DDR3L	96ball										T/A	T/A	T/A										T/A				
	D2516C4BXGJD		4G bit	256M*16	DDR3	96ball																										
	B5116ECMDXGJD		8G bit	512M*16	DDR3L	96ball																										
	D2516ACPCXGRK	EOL	4G bit	256M*16	DDR4	96ball					T/A		T/A	T/A	T/A					T/A	T/A											
	D2516AN9EXGXN		4G bit	256M*16	DDR4	96ball			S/A	T/A		T/A	T/A	T/A						T/A												
	D5116AH8CXGUM		8G bit	512M*16	DDR4	96ball				T/A		T/A	T/A	T/A																		
	D5116AN9CXGXN		8G bit	512M*16	DDR4	96ball					N/A	N/A		N/A	N/A	N/A		N/A	N/A	N/A	N/A											
	D2532LA3WLGJA		8G bit	256M*32	LPDDR3	178ball																										
	D2532LA6MLGJA		8G bit	256M*32	LPDDR3	178ball																										
	D0811LN2ALGJA		8G bit	256M*32	LPDDR3	178ball										T/A																
	KB25AADL3E08G		8G bit	512M*16	LPDDR3	178ball																										
	C1612LN2ALGJA		8G bit	512M*16	LPDDR3	178ball																										
	D2516PC1CDG1PLR	EOL	8G bit	256M*32	LPDDR4	200ball																										
	B1621PC6FDGUKR	EOL	16G bit	512M*32	LPDDR4	200ball				T/A ^[9]	N/A	T/A ^[9]	T/A ^[9]	S/A ^[9]						N/A												
	Q5116PH1MDGPAR	EOL	16G bit	512M*32	LPDDR4	200ball				N/A		N/A	N/A	N/A	N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	B5116PH3MDGPAR	EOL	16G bit	512M*32	LPDDR4	200ball									S/A ^[9]	N/A																
	B1621XH5ADGTR	EOL	16G bit	512M*32	LPDDR4X	200ball						S/A ^[9]	T/A ^[9]	S/A ^[9]																		
	B1621XH6BDGTAR	EOL	16G bit	512M*32	LPDDR4X	200ball						S/A		S/A																		
	B1621XH7CDGUAR		16G bit	512M*32	LPDDR4X	200ball						T/A ^[9]																				
	B2421XC4FDGTR	EOL	24G bit	768M*32	LPDDR4X	200ball				T/A		T/A	T/A	N/A						N/A												
	B3221XC5GDGTR	EOL	32G bit	1024M*32	LPDDR4X	200ball				T/A ^[9]		T/A ^[9]	T/A ^[9]	N/A						N/A												
	Q3222XH6BDGUAR	EOL	32G bit	1024M*32	LPDDR4X	200ball						T/A ^[9]	S/A	S/A																		

256M16 in RK3066... RK31xx platform requires supplementing related pins, and for reference layer integrity requirements are relatively high, need to strictly follow our board requirements.

256M16在RK3066、RK31xx平台上需要添加定频相关补丁。并且对参考层完整性要求较高，需要严格遵照我们的布板要求布板。

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H1	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3229/ PX5	RK2906/ RK2918	RK3926/ RK3028A/ RK3128/PX3-SE	RK3926/RK3026/ RK3030/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3	与RK兼容情况
																					CPU_RAM	NPU_RAM								
FORESEE	F60C1A0002-M6		2G bit	128M×16	DDR3L	96ball								T/A	T/A					T/A		T/A								
	F60C1A0004-M7		4G bit	256M×16	DDR3L	96ball								T/A	T/A					T/A		T/A								
	F62C1A0004-M5		4G bit	256M×16	DDR4	96ball				T/A			T/A	T/A						T/A		T/A								
	FD4V10004-22		4G bit	256M×16	DDR4	96ball														T/A		T/A								
	FD45116ZSA062C		8G bit	512M×16	DDR4	96ball														T/A										
	MD4C10004-N93R		4G bit	256M×16	DDR4	96ball			T/A	T/A			T/A	T/A	T/A															
	MD4C1001G-N43R		8G bit	512M×16	DDR4	96ball				T/A			T/A	T/A	T/A					T/A		T/A								
	MD4C1002G-W43R		16G bit	1024M×16	DDR4	96ball			T/A	T/A			T/A	T/A	T/A					T/A										
	NCLD3B1128M32		4G bit	128M×32	LPDDR3	178ball														T/A										
	NCLD3B2256M32		8G bit/ 2ev	256M×32	LPDDR3	178ball																								
	NCLD4C1MA256M32	EOL	8G bit	256M×32	LPDDR4	200ball																								
	NCLDXC1MG256M32		8G bit	256M×32	LPDDR4/LPDDR4X	200ball				N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A
	FLAC2001G-D9		8G bit	256M×32	LPDDR4	200ball							S/A ^[9]																	
	FLXC2002G-N2		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A ^[10]			T/A ^[10]	T/A ^[10]	S/A ^{[10]98}			N/A				N/A									
	FLXC2002G-26		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A ^[10]			T/A ^[10]	T/A ^[10]	S/A ^{[10]98}																
	FLXC2002G-C4		16G bit	512M×32	LPDDR4X	200ball				T/A			T/A																	
	NCLD4C2MA512M32	EOL	16G bit	512M×32	LPDDR4	200ball																								
	NCLDXC1MC512M32		16G bit	512M×32	LPDDR4/LPDDR4X	200ball																								
	NCLDXC1MJ512M32		16G bit	512M×32	LPDDR4/LPDDR4X	200ball				N/A	N/A	N/A	N/A	N/A	N/A	N/A														
	FLXC1002G-N1		16G bit	512M×32	LPDDR4/LPDDR4X	200ball										N/A														
	FLXC2002G-W6		16G bit	512M×32	LPDDR4/LPDDR4X	200ball				T/A			T/A																	
	FLXC2003G-49		24G bit	768M×32	LPDDR4/LPDDR4X	200ball				T/A			T/A	T/A	N/A															
	FLXC4003G-W7		24G bit	768M×32	LPDDR4/LPDDR4X	200ball				N/A		T/A ^[10]	N/A	N/A																
	FLXC4004G-26		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				N/A			N/A	N/A	N/A															
	FLXC2004G-N1		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			T/A		T/A		T/A	T/A																
	FLXC4004G-W6		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				N/A		T/A ^[10]	N/A	N/A																
	FLXC4004G-61		32G bit	1024M×32	LPDDR4X	200ball			T/A																					
	FLXC2004G-30		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball							S/A ^[10]																	
	FLXC4006G-20		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball			T/A			N/A	N/A	N/A																
	FLXC4006G-63		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball						N/A																		
	FLXC4006G-64		48G bit	1536M×32	LPDDR4X	200ball			N/A		N/A	N/A	N/A	N/A																
	FLXC4006G-49		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball			T/A		T/A	T/A	T/A	T/A																
	FLXC8008G-61		64G bit	2048M×32	LPDDR4X	200ball				T/A			T/A																	
	FLXC4008G-30		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball				T/A		T/A	T/A	T/A																
	FLXW4008G-P1		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball				T/A			T/A																	
	FLSP4004G-N5		32G bit	1024M×32	LPDDR5	315ball						N/A																		
	FLSP2004G-60		32G bit	1024M×32	LPDDR5	315ball						T/A																		
	FLSP4006G-62		48G bit	1536M×32	LPDDR5	315ball						N/A																		
	FLSP4008G-60		64G bit	2048M×32	LPDDR5	315ball						S/A																		
BIWIN	BWPD03X16A9B-04Gb		4G bit	256M×16	DDR3L	96ball								T/A	N/A															
	BWSD3X16N8B-04Gb		4G bit	256M×16	DDR3L	96ball								T/A																
	BWND3X16J8B-04Gb		4G bit	256M×16	DDR3L	96ball																								
	BWSD04X16A9B-04Gb		4G bit	256M×16	DDR4	96ball						T/A	T/A	T/A																
	BW52L256M32D1PF		8G bit	256M×32	LPDDR3	178ball																								
	BW52L512M32D2PF		16G bit	512M×32	LPDDR3	178ball																								
	BWMD4X32H2A-08Gb	EOL	8G bit	256M×32	LPDDR4	200ball																								
	BWMECX32H2A-08Gb	EOL	8G bit	256M×32	LPDDR4	200ball								S/A ^[10]																
	BWMD4X32H2A-16Gb	EOL	16G bit	512M×32	LPDDR4	200ball																								
	BWME9X32H2A-16Gb		16G bit	512M×32	LPDDR4	200ball																								
	BWMEYX32H2A-16Gb		16G bit	512M×32	LPDDR4	200ball																								
	BWME9X32H2A-16Gb-X		16G bit	512M×32	LPDDR4X	200ball				T/A			T/A	T/A	S/A ^[10]															
	BWMZAX32H2A-16G-X		16G bit	512M×32	LPDDR4/LPDDR4X	200ball				S/A		T/A ^[10]	S/A	S/A																
	BWMZEX32H2A-16G-X		16G bit	512M×32	LPDDR4/LPDDR4X	200ball						T/A	T/A ^[10]	T/A	T/A															
	BWSRX32H2A-16G-X		16G bit	512M×32	LPDDR4X	200ball						T/A		T/A	T/A															
	BWSRX32H2A-16G-X		16G bit	512M×32	LPDDR4X	200ball						T/A		T/A	T/A															
	BWCC2X32N2A-16G-X		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			T/A	T/A		T/A ^[10]	T/A	T/A																
	BWME4X32H2A-24Gb-X		24G bit	768M×32	LPDDR4X	200ball						T/A		T/A	T/A	N/A														
	BWMEXX32H2A-24Gb-X		24G bit	768M×32	LPDDR4X	200ball						N/A		T/A ^[10]	N/A	N/A														
	BWMEIX32H2A-24G-X		24G bit	768M×32	LPDDR4/LPDDR4X	200ball						T/A		T/A	T/A															
	BWMEDX32H2A-32Gb-X		32G bit	1024M×32	LPDDR4X	200ball						T/A ^[11]		T/A ^[11]	T/A ^[11]	N/A														
	BWSRX32H2A-32G-X	EOL	32G bit	1024M×32	LPDDR4X	200ball			N/A	N/A		T/A ^[10]	N/A	N/A	N/A															
	BWSRX32H2A-32G-X		32G bit	1024M×32	LPDDR4X	200ball						T/A		T/A	T/A															
	BWMZAX32H2A-32Gb-X		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						T/A		T/A ^[10]																

16

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3328H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/ RK3328B/RK3229/ PX5	RK2908/ RK2918	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3	与RK兼容情况			
ICMAX	IMD128M16R32Z8LY		2G bit	128M*16	DDR3L	96ball													S/A	S/A													
	IMD256M16R30HG8GNF-107		4G bit	256M*16	DDR3	96ball								S/A			S/A		N/A	N/A		S/A											
	IMD256M16R324J8LY		4G bit	256M*16	DDR3L	96ball								S/A			S/A		S/A	S/A		S/A		S/A									
	IMD512M16R31JA8GGPF		8G bit	512M*16	DDR3	96ball											S/A					S/A											
	IMD256M16R4AABD8LY		4G bit	256M*16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A		
	IMD256M16R4ZAD8TB		4G bit	256M*16	DDR4	96ball								S/A																			
	IMD512M16R4DBD8LY		8G bit	512M*16	DDR4	96ball								S/A																			
	IMD512M16R4AZD8JY		8G bit	512M*16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	
	IMD512M16R4FCD8TB		8G bit	512M*16	DDR4	96ball														N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	
	IMH256M32Z1D1DNP		8G bit	256M*32	LPDDR4	200ball									S/A (PL)			S/A			S/A												
IMH512M32H2D2ENA		16G bit	512M*32	LPDDR4X	200ball							S/A (PL)	S/A	S/A								S/A											
IMH512M32Z2D2ENP		16G bit	512M*32	LPDDR4/LPDDR4X	200ball					S/A		S/A	S/A																				
TMTIC	TN4G16D3CSEP-EK		4G bit	256M*16	DDR3	96ball											S/A					S/A											
	TN8G16D4DS44-GZ		8G bit	512M*16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A									
	TM8G32MD4LSA1-4H		8G bit	256M*32	LPDDR4	200ball											S/A					S/A											
	TH16G32MD4LQM1-4H		16G bit	512M*32	LPDDR4	200ball											N/A					N/A											
Goldkey	GH4061600HRL-1833		4G bit	256M*16	DDR3L	96ball										S/A			S/A	S/A	S/A												
	GE4062666HD		4G bit	256M*16	DDR4	96ball								S/A																			
	GE8062666ND		8G bit	512M*16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A			N/A									
	GE8062400HD-1833		8G bit	512M*16	DDR4	96ball																											
	L4D32HT1-06242		32G bit	1024M*32	LPDDR4	200ball				N/A		N/A	N/A									S/A											
Eorex	EM47DM1688SBA		2G bit	128M*16	DDR3	96ball																						N/A					
	EM47EM0888SBA-150		2G bit	256M*8	DDR3	78ball																		S/A			S/A	N/A	N/A	N/A	S/A		
	EM47EM1688SBA-150		4G bit	256M*16	DDR3	96ball																					S/A						
	EM47EM1688SBB-150A		4G bit	256M*16	DDR3	96ball																							S/A	S/A	S/A		
	EM47FM0888SBA-150		4G bit	512M*8	DDR3	78ball																							S/A	S/A			
	EM47FM0888SBA-150A		4G bit	512M*8	DDR3	78ball																							S/A	S/A			
	EM47FM3288MBA-125		8G bit	256M*32	DDR3	136ball																			S/A					S/A			
	EM49FM1688PBA-075		8G bit	512M*16	DDR4	96ball							S/A							S/A											S/A		
EM45FM3288LBA-187F		16Gb/2Channel	256M*32*2Ch	LPDDR2	220ball																			S/A						N/A			
axeme	H2A301G1656BC6C		1G bit	64M*16	DDR2	84ball									S/A	N/A	N/A	N/A	N/A	N/A		N/A		N/A	N/A			N/A	N/A	N/A	N/A		
	H2A401G1666BFBC		1G bit	64M*16	DDR3	96ball									S/A																		
	H2A402G1666BFBC		2G bit	128M*16	DDR3	96ball																							S/A	S/A			
	H2A404G1666CFMC		4G bit	256M*16	DDR3	96ball										S/A		S/A	S/A	S/A													
	H2A404G0866CD8C		4G bit	512M*8	DDR3	78ball																			S/A						S/A		
Sinker	SNB2816S21PS13		2G bit	128M*16	DDR3L	96ball									S/A																		
	SNB5616S21PS13		4G bit	256M*16	DDR3L	96ball									S/A				S/A	S/A													
ProMOS	V59C1G01168QBASXJ25		1G bit	64M*16	DDR2	84ball										N/A	N/A	N/A	N/A	N/A		N/A		N/A	N/A		✓	N/A	N/A	N/A	N/A		
	V73CAG01808RAJ19		1G bit	128M*8	DDR3	78ball																						✓					
	V59C1G02168QB		2G bit	128M*16	DDR2	84ball										N/A	N/A	N/A	N/A	N/A		N/A		N/A	N/A		✓	N/A	N/A	N/A	N/A		

台湾颗粒厂商，
兼容性较好

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H1	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3229 /PX5	RK2906/ RK2918	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3	与RK兼容情况
																						CPU_RAM	NPU_RAM							
QCHIP	QN3B128M16H-13A		2G bit	128M*16	DDR3	96ball									S/A									S/A						
	QN3R256M16M-16G		4G bit	256M*16	DDR3	96ball																								
	QN4A256M16M-26G		4G bit	256M*16	DDR4	96ball							S/A																	
	QN4A512M16M-24E		8G bit	512M*16	DDR4	96ball							S/A						S/A											
	QN4LPD512M32M-32H		16G bit	512M*32	LPDDR4	200ball											N/A					N/A								
	QN4LPD512M32S-32I		16G bit	512M*32	LPDDR4	200ball																	N/A							
	QN4LPD512M32T-37I		16G bit	512M*32	LPDDR4X	200ball						S/A P0											N/A							
	QN4LPD1GM32T-42I		32G bit	1024M*32	LPDDR4X	200ball			S/A			S/A																		
	QN4LPXD1GM32SP-32H		32G bit	1024M*32	LPDDR4/LPDDR4X	200ball			S/A			S/A		N/A																
	QN4XLP32GM16H-42I		32G bit	1024M*32	LPDDR4X	200ball			S/A			S/A																		
	QN4LPXD1536M32SP-32H		48G bit	1536M*32	LPDDR4/LPDDR4X	200ball					S/A		S/A	S/A																
QN4XLP64GM16H-42J		64G bit	2048M*32	LPDDR4X	200ball					N/A		N/A	N/A																	
XINCUN	XCCB128M16FP-EKNAH		2G bit	128M*16	DDR3	96ball														S/A										
	XCCC128M16FP-EKNAB		2G bit	128M*16	DDR3L	96ball																		S/A						
	XCCC256M16FP-EKNAY		4G bit	256M*16	DDR3L	96ball																		S/A						
	XCCB256M16DP-EKNAH		4G bit	256M*16	DDR3	96ball														S/A										
	XCCC256M16EP-EKNAY		4G bit	256M*16	DDR3L	96ball																		S/A			S/A			
HIKSEMI	HSED4HB04G-JD3		4G bit	256M*16	DDR4	96ball							S/A																	
	HSED4HB08G-JD4		8G bit	512M*16	DDR4	96ball				S/A		S/A	S/A																	
	HSEL4XA2G-HD8		16G bit	512M*32	LPDDR4X	200ball					S/A P0	S/A	S/A																	
	HSEL4XFA4G-CA9M		32G bit	1024M*32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A																	
	HSEL4XFA4G-HD9		32G bit	1024M*32	LPDDR4X	200ball			S/A			S/A	S/A	S/A																
DBTC	DS4D82FBFCENY		8G bit	512M*16	DDR4	96ball				N/A	N/A		N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A							
	DS4D162FBFCENY		16G bit	1024M*16	DDR4	96ball							S/A																	
	DL4008E2FSC2GHHY		8G bit	256M*32	LPDDR4	200ball							S/A																	
	DL4X16E3FDEE2GHHY		16G bit	512M*32	LPDDR4X	200ball						S/A	S/A																	
	DL4X16E3FSEE2GMR		16G bit	512M*32	LPDDR4X	200ball				S/A	N/A	S/A	S/A																	
	DL4X32E3CQEE2GCX		32G bit	1024M*32	LPDDR4/LPDDR4X	200ball				N/A		N/A	N/A																	
KEYMOS	KL4X162BD-C2B		16G bit	512M*32	LPDDR4X	200ball					N/A	N/A	N/A	N/A																
	KL4X322BQ-C7B		32G bit	1024M*32	LPDDR4X	200ball					N/A	N/A	N/A	N/A																
Netsol	S5RG2G20CMS-MGCJ		32G bit	512M*64	LPDDR4	360ball											N/A					N/A								
MT.MOSET	ED3E25608CE-P9		2G bit	256M*8	DDR3	78ball																		S/A		S/A	S/A	N/A	S/A	
sMART	S4B2G0846C-HYH9		2G bit	256M*8	DDR3	78ball																		S/A					S/A	巴西颗粒，国内用的不多
	S4B2G0846D-HYK0		2G bit	256M*8	DDR3	78ball																		S/A				S/A		

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588C	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3329 /PX5	RK2906/ RK2918	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036G/ RK3126	RK3066/RK3066A/ PX3/RK3168/ RK3188/PX3	与RK兼容情况
																						CPU_RAM	NPU_RAM							
WINS	VP5TQ1G0835-F9		1G bit	128M×8	DDR3	78ball																				✓				
	VP5TQ2G1635FFP-F9		2G bit	128M×16	DDR3	96ball																				✓	N/A	N/A		
	VP5TQ2G0835L-F9		2G bit	256M×8	DDR3	78ball																				✓				
ISDT	IL2BR20E8H		16Gb/2Channel	256M×32×2Cb	LPDDR2	220ball																		S/A						
YXSC	YX3H2816AB-M9LC		2G bit	128M×16	DDR3L	96ball								S/A											S/A					
	YX3H4816AB-M9LC		4G bit	256M×16	DDR3L	96ball								S/A											S/A					
	YX4H8A16AB-NCMC		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A	N/A	N/A	N/A	N/A		N/A								
	YX4LA816BC-MGPE		16G bit	512M×32	LPDDR4X	200ball				S/A		S/A	S/A																	
KOWIN	KAD3N2M33BNT		4G bit	256M×16	DDR3L	96ball																			S/A					
	KAD4N3M46GUT		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A		N/A								
	KAL3S3C55FN2		8G bit	256M×32	LPDDR3	178ball														S/A										
	KALXX4S43AY2		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			S/A		S/A	S/A	S/A																	
DW MICRO	DWCT536HLC0-OB		16G bit	512M×32	LPDDR4/LPDDR4X	200ball						S/A	S/A																	
	DWCTA36HLC0-OB		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						S/A	S/A					N/A												
	DWCTA36HLC0-OD		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			S/A			S/A																		
	DWCTB36HLC0-OD		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			S/A			S/A																		
GSTO	GSD02GHPB3-E3N3C		2G bit	128M×16	DDR3L	96ball				N/A		N/A	N/A					N/A	N/A											
	GSD04GHPB4-E3N3C		4G bit	256M×16	DDR3L	96ball													N/A	N/A										
	GSD04GHGB5-S3L3C		4G bit	256M×16	DDR4	96ball					S/A		S/A	S/A					S/A	S/A										
	GSD08GHGB6-S3L3C		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A							
Artmem	ATL4X12324M102		12G bit	384M×32	LPDDR4/LPDDR4X	200ball												N/A												
BHE	BH4D4G16M00-DL1		4G bit	256M×16	DDR4	96ball												S/A												
	BH4D4G16M00-DL2		4G bit	256M×16	DDR4	96ball					N/A		N/A	N/A																
	BH4D8G1666-DL1		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A		N/A								
	BH4D8G1666-DL2		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A		N/A								
	BI16G32MD4PDC1-J1		16G bit	512M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A																	
	BI32G32MD4PQC1-J1		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A																	
Rocfour	MC4X1GM32BQ200A-32T		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A																	
	MC4X1GM32BQ200A-42T		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball			S/A			S/A																		
	MC4X2GM32CQ200A-42T		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball			S/A			S/A																		
	MC5D1GM32DQ315B-64T		32G bit	1024M×32	LPDDR5	315ball			S/A			S/A																		
Yangtze Mason	MSP4C0D5I-032G		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						S/A	S/A																	
Baryen	SPMNBQMC-MIXU		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						S/A	S/A																	
JSC	JSL5HC329TKA-03		32G bit	1024M×32	LPDDR5	315ball		S/A			S/A																			
	JSL5HDG32ATKA-03		64G bit	2048M×32	LPDDR5	315ball					S/A																			
TSWC	TEL4XCC32ACY-32G		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						S/A																		

Industrial&Wide Temperature

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK356J	RK3576J	RK3528	RK3562J	RK3588J	RK3568J	RK3566	RV1126K	RV1108K1 RK3308J	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3358J	RK1808K	RK3399PRO		RK3288	RK3368/RK3228A/ RK3228B/RK3229 /PX5	RK2908/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G/ RK3126	RK3066/RK3066A/ PX3/RK3168/ RK3188/PX3	与RK兼容情况		
Micron	MT41K128M16JT-107 IT:K(D9RQN)		2G bit	128M×16	DDR3L	96ball														T/A											
	MT41K256M16TW-107 IT:P(D9SHG)		4G bit	256M×16	DDR3L	96ball											T/A						T/A								
	MT41K512M16VRP-107IT-P(D9ZWN)		8G bit	512M×16	DDR3L	96ball																	T/A								
	MT40A512M16TB-062E IT:R(D8BVB)		8G bit	512M×16	DDR4	96ball					T/A		T/A	T/A																	
	MT40A1G16TD-062E AIT:F (D8CHH)		16G bit	1024M×16	DDR4	96ball					T/A			T/A	T/A										T/A						
	MT40A1G16TB-062E IT:F (D8CJZ)		16G bit	1024M×16	DDR4	96ball					T/A			T/A	T/A																
	MT53E256M32D1KS-046 IT:L (D8FCZ)		8G bit	256M×32	LPDDR4/LPDDR4X	200ball					T/A		T/A	T/A	T/A																
	MT53E384M32D2FW-046 IT:E (D8BXT)		12G bit	384M×32	LPDDR4/LPDDR4X	200ball					T/A		T/A	T/A	T/A	T/A															
	MT53E512M32D1ZW-046 BIT:B (D8FLQ)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball					T/A		T/A	T/A	T/A	T/A															
	MT53E1G32D2FW-046 IT:C (D8DVP)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball					T/A		T/A	T/A	T/A	T/A															
Samsung	K4B4G1646E-BMMA		4G bit	256M×16	DDR3L	96ball											T/A				T/A		T/A								
	K4F6E3S4HM-TP**		16G bit	512M×32	LPDDR4	200ball									S/A ^(B)																
Nanya	NT5CC256M16ER-EK1		4G bit	256M×16	DDR3L	96ball																		T/A							
	NT5AD256M16E4-JR1		4G bit	256M×16	DDR4	96ball					T/A		T/A	T/A																	
	NT5AD512M16C4-JR1		8G bit	512M×16	DDR4	96ball					N/A	N/A	N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A			N/A						
	NT6AN512T32AV-J11		16G bit	512M×32	LPDDR4	200ball					N/A	N/A	N/A	N/A	N/A			N/A		N/A			N/A								
CXMT	CXDQ3BFAM-U-A		8G bit	512M×16	DDR4	96ball				N/A	S/A ^(B)		S/A ^(B)	S/A ^(B)	N/A				N/A	N/A	N/A	S/A ^(B)	N/A		N/A						
GigaDevice	GDP1BFLA-WB		2G bit	128M×16	DDR3L	96ball					T/A		T/A	T/A																	
	GDP2BFLM-WB		4G bit	256M×16	DDR3L	96ball					T/A		T/A	T/A																	
	GDQ2BFAA-WJ		4G bit	256M×16	DDR4	96ball					S/A ^(B)		S/A ^(B)	S/A ^(B)																	
UnitC	SCB13HBG162BF-13K1		8G bit	512M×16	DDR3L	96ball																	T/A								
winbond	W632GU6NB-11K		2G bit	128M×16	DDR3L	96ball																									
	W634GU6NB-11K		4G bit	256M×16	DDR3L	96ball																									
ISSI	IS46DR16320E-25DBLA2		512M bit	32M×16	DDR2	84ball									T/A																
	IS43TR16128DL-125KBL1		2G bit	128M×16	DDR3L	96ball									T/A																
	IS43TR16512BL-107MBL1		8G bit	512M×16	DDR3L	96ball					T/A		T/A	T/A																	
	IS43QR16256B-083RBL1		4G bit	256M×16	DDR4	96ball					N/A	N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A				N/A						
	IS46QR16512A-075VBLA2		8G bit	512M×16	DDR4	96ball					N/A		N/A	N/A																	
	IS43QR16512A-083TBL1		8G bit	512M×16	DDR4	96ball																			N/A						
	IS43LD16128C-18BL1		2Gb bit	128M×16	LPDDR2	134ball																									
	IS43LQ32256A-062BL1		8G bit	256M×32	LPDDR4/LPDDR4X	200ball						S/A ^(B)	S/A ^(B)																		
	IS43LQ32256B-0**BL**		8G bit	256M×32	LPDDR4/LPDDR4X	200ball					N/A	N/A	N/A	N/A			N/A		N/A				N/A								
	Zentel	A3R12E40DBF-8EA		512M bit	32M×16	DDR2	84ball									T/A															
A3T2GF40CBF-HP1			2G bit	128M×16	DDR3	96ball	N/A																								
BIWIN	BWMZAX32H2A-16G-X		16G bit	512M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A	T/A	T/A	T/A																	
	BWMZCX32H2A-32G-X		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		T/A			N/A	T/A	N/A	N/A																	
FORESEE	F60C1A0004-M79W		4G bit	256M×16	DDR3L	96ball					T/A		T/A	T/A																	
Artmem	ATL4X2G32M1D-46 IT		16G bit	512M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																				
	ATL4X4G32M1D-46 IT		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball					T/A		T/A	T/A																	
	ATL4X8G32M2D-46 IT		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball		T/A				T/A																			

Automotive																														
Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK2118	RK3576M			RK3588M	RK3568M				RK3308M														与RK兼容情况
Micron	MT53E256M32D1KS-046 AAT:L (D8FDP)		8G bit	256M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																			
	MT53E512M32D1ZW-046 AAT:B (D8CSG)		16G bit	512M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A	T/A																		
	MT53E768M32D2ZW-046 AIT:C (D8DTX)		24G bit	768M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																			
	MT53E1G32D2FW-046 AAT:B (D8CJB)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A	T/A																		
	MT53E1536M32D4DE-046 AIT:C (D8DCZ)		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A	T/A																		
	MT53E2G32D4DE-046 AAT:C (D8CJB)		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A	T/A																		
	MT53E2G32D4DE-046 AAT:A (D9ZRB)		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																			
	MT53E4G32D8GS-046 AIT:C (D8DHH)		128G bit	4G×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																			
MT53E1G32D2FW-046 AIT:C (D8DWK)		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																				
Samsung	K4F8E3S4HD-GE**		8G bit	256M×32	LPDDR4	200ball		T/A			T/A	T/A																		
	K4F6E3S4HB-KH**		16G bit	512M×32	LPDDR4	200ball		T/A			T/A																			
	K4F8E3S4HA-KH**		24G bit	768M×32	LPDDR4	200ball						N/A																		
	K4FBES3D4HB-KH**		32G bit	1024M×32	LPDDR4	200ball		T/A			T/A	T/A																		
	K4U6E3S4AB-KH**		16G bit	512M×32	LPDDR4X	200ball		T/A			T/A																			
	K4UE3Q4AA-T***		48G bit	1536M×32	LPDDR4X	200ball					N/A	N/A																		
	K4UCE3Q4AB-KH**		64G bit	2048M×32	LPDDR4X	200ball					N/A	T/A																		
Hynix	H54G66BYYVX104		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																			
	H54G46BYYQX085N		16G bit	512M×32	LPDDR4X	200ball		T/A			T/A																			
	H54G56BYYQX089N		32G bit	1024M×32	LPDDR4X	200ball		T/A			T/A																			
	H54G56BYYQX089		32G bit	1024M×32	LPDDR4X	200ball		T/A			T/A																			
Nanya	NT5CC64M16GP-EKH		1G bit	64M×16	DDR3L	96ball													T/A											
	NT5CC256M16ER-EKA		4G bit	256M×16	DDR3L	96ball													T/A											
	NT6AN512T32AC-J2J		16G bit	512M×32	LPDDR4	200ball						N/A	N/A																	
	NT6AN512T32AC-J1H		16G bit	512M×32	LPDDR4	200ball						N/A	N/A																	
CXMT	CXDB4CBAM-EA-M		16G bit	512M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A	T/A																		
	CXDB5CCBM-EA-M		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						N/A																		
	CXDB5CCBM-EA-A		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball					T/A																			
	CXDBCCCDM-EA-M		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																			
	CXDB6CCDM-EA-M		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																			
ISSI	IS46LQ32256B-053BLA1		8G bit	256M×32	LPDDR4	200ball					N/A																			
BIWIN	BWLGYB008GN6ZC		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																			
Artmem	ATL4X4G32M1D-46 AIT		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		T/A			T/A																			