EE1205: Signals and Systems - TA

EE22BTECH11039 - Pandrangi Aditya Sriram

.1 The Z-transform of p(n) is defined as

$$P(z) = \sum_{n = -\infty}^{\infty} p(n)z^{-n}$$
 (.1.1)

.2 If

$$p(n) = p_1(n) * p_2(n), (.2.1)$$

$$P(z) = P_1(z)P_2(z) (.2.2)$$

.3 For a Geometric progression

$$x(n) = x(0) r^n u(n),$$
 (.3.1)

$$\implies X(z) = \sum_{n = -\infty}^{\infty} x(n) z^{-n} = \sum_{n = 0}^{\infty} x(0) r^n z^{-n}$$
 (.3.2)

$$= \sum_{n=0}^{\infty} x(0) \left(rz^{-1}\right)^n \tag{3.3}$$

$$=\frac{x(0)}{1-rz^{-1}}, \quad |z| > |r| \tag{3.4}$$

.4 Substituting r = 1 in (.3.4),

$$u(n)ZU(z) = \frac{1}{1 - z^{-1}}, \quad |z| > 1$$
(.4.1)

.5 From (.1.1) and (.4.1),

$$U(z) = \sum_{n = -\infty}^{\infty} u(n)z^{-n}$$
 (.5.1)

$$\implies \frac{dU(z)}{dz} = -z^{-1} \sum_{n=-\infty}^{\infty} nu(n)z^{-n}$$
 (.5.2)

$$\therefore nu(n)Z\frac{z^{-1}}{(1-z^{-1})^2}, \quad |z| > 1$$
 (.5.3)

.6 For an AP,

$$x(n) = [x(0) + nd] u(n) = x(0)u(n) + dnu(n)$$
(.6.1)

$$\implies X(z) = \frac{x(0)}{1 - z^{-1}} + \frac{dz^{-1}}{(1 - z^{-1})^2}, \quad |z| > 1$$
 (.6.2)

upon substituting from (.4.1) and (.5.3).

.7 From (??), the sum to n terms of a GP can be expressed as

$$y(n) = x(n) * u(n) \tag{.7.1}$$

where x(n) is defined in (.3.1). From (.2.2), (.3.4) and (.4.1),

$$Y(z) = X(z)U(z) \tag{.7.2}$$

$$= \left(\frac{x(0)}{1 - rz^{-1}}\right) \left(\frac{1}{1 - z^{-1}}\right) \quad |z| > |r| \cap |z| > |1| \tag{.7.3}$$

$$= \frac{x(0)}{(1 - rz^{-1})(1 - z^{-1})} \quad |z| > |r| \tag{.7.4}$$

which can be expressed as

$$Y(z) = \frac{x(0)}{r - 1} \left(\frac{r}{1 - rz^{-1}} - \frac{1}{1 - z^{-1}} \right) \tag{.7.5}$$

using partial fractions. Again, from (.3.4) and (.4.1), the inverse of the above can be expressed as

$$y(n) = x(0) \left(\frac{r^{n+1} - 1}{r - 1} \right) u(n)$$
 (.7.6)

.8 For the AP x(n), the sum of first n + 1 terms can be expressed as

$$y(n) = \sum_{k=0}^{n} x(k)$$
 (.8.1)

$$\implies y(n) = \sum_{k=-\infty}^{\infty} x(k)u(n-k) \tag{8.2}$$

$$= x(n) * u(n) \tag{.8.3}$$

Taking the Z-transform on both sides, and substituting (.6.2) and (.4.1) (making use of the convolution property of Z-transform),

$$Y(z) = X(z)U(z) \tag{.8.4}$$

$$\implies Y(z) = \left(\frac{x(0)}{1 - z^{-1}} + \frac{dz^{-1}}{(1 - z^{-1})^2}\right) \frac{1}{1 - z^{-1}} \quad |z| > 1 \tag{8.5}$$

$$= \frac{x(0)}{(1-z^{-1})^2} + \frac{dz^{-1}}{(1-z^{-1})^3}, \quad |z| > 1$$
 (.8.6)

From (.5.3) and (.4.1) we know that:

$$nu(n)Z\frac{z^{-1}}{(1-z^{-1})^2}, \quad |z| > 1$$
 (.8.7)

$$u(n)Z\frac{1}{1-z^{-1}} = \frac{1-z^{-1}}{(1-z^{-1})^2}, \quad |z| > 1$$
 (.8.8)

$$\implies (n+1)u(n)Z\frac{1}{(1-z^{-1})^2} \tag{.8.9}$$

Therefore, using the derivative property and taking the inverse Z-transform of (.8.6),

$$y(n) = x(0) \left[Z^{-1} \left\{ \frac{1}{(1 - z^{-1})^2} \right\} \right] + \frac{d}{2} \left[n Z^{-1} \left\{ \frac{1}{(1 - z^{-1})^2} \right\} \right]$$
 (.8.10)

$$= x(0) \left[(n+1)u(n) \right] + \frac{nd}{2} \left[(n+1)u(n) \right]$$
 (.8.11)

$$= \frac{n+1}{2} (2x(0) + nd) u(n)$$
 (.8.12)