1910.147 the control of hazardous energy (lockout/tagout) checklist

Use while observing a servicing job under lockout or tagout and when reviewing the program records.

OSHA 29 CFR 1910.147

DATE	SHIFT
INSPECTOR	AREA / EQUIPMENT ID

Before you start

1. Mark every item OK, Defect or N/A.
2. Record each Defect with the corrective action and who owns it; do not let servicing continue while a Defect leaves anyone exposed.
3. The equipment manufacturer's instructions and your site rules may add checks.

Legal basis: 29 CFR 1910.147: The control of hazardous energy (lockout/tagout) Source: eCFR, Title 29, Part 1910 Subpart J (text as of 2026-11-09)
Online version and sources: https://safetyindex.blog/us/standards/1910-147-control-hazardous-energy-lockout-tagout

SECTION A | Program and written procedures

No.	Check item	What to look for	OK	Defect	N/A	Notes
1	Energy control program Ref. 1910.147(c)(1)	A program combining procedures, training and periodic inspections is in place and covers this equipment.	☐	☐	☐	
2	Machine-specific procedure Ref. 1910.147(c)(4)(i)	A documented procedure exists for this machine, or every one of the eight exception conditions applies to it.	☐	☐	☐	
3	Shutdown and isolation steps Ref. 1910.147(c)(4)(ii)(B)	The procedure lists specific steps to shut down, isolate, block and secure this machine.	☐	☐	☐	
4	Device placement and transfer Ref. 1910.147(c)(4)(ii)(C)	The procedure states how locks or tags are placed, removed and transferred and who is responsible.	☐	☐	☐	
5	Verification testing Ref. 1910.147(c)(4)(ii)(D)	The procedure states how to test the machine to confirm the energy controls work.	☐	☐	☐	
6	Lock used where possible Ref. 1910.147(c)(2)(ii)	Lockable isolators are locked, or the employer can show tagout gives full employee protection under (c)(3).	☐	☐	☐	
7	New or modified equipment Ref. 1910.147(c)(2)(iii)	Isolators on equipment installed, replaced, majorly repaired, renovated or modified after January 2, 1990 accept a lockout device.	☐	☐	☐	

SECTION B | Locks, tags and tag placement

No.	Check item	What to look for	OK	Defect	N/A	Notes
8	Hardware supplied Ref. 1910.147(c)(5)(i)	Locks, tags, chains, wedges, key blocks, adapter pins or self-locking fasteners needed for the job are provided by the employer.	☐	☐	☐	

General guidance only, not legal advice. Check the current regulation and your employer's procedures.

SECTION B | Locks, tags and tag placement						
No.	**Check item**	**What to look for**	**OK**	**Defect**	**N/A**	**Notes**
9	Dedicated devices Ref. 1910.147(c)(5)(ii)	Energy control locks and tags are singularly identified and not used for anything else.	☐	☐	☐	
10	Standardized Ref. 1910.147(c)(5)(ii)(B)	Devices match the facility standard for color, shape or size; tag print and format match too.	☐	☐	☐	
11	User identified Ref. 1910.147(c)(5)(ii)(D)	Every lock and tag shows the identity of the person who put it on.	☐	☐	☐	
12	Tag legend Ref. 1910.147(c)(5)(iii)	Tags carry a warning such as Do Not Start, Do Not Energize or Do Not Operate.	☐	☐	☐	
13	Tag attachment Ref. 1910.147(c)(5)(ii)(C)(2)	Tags are fixed with a non-reusable, self-locking, hand-attachable tie with an unlocking strength of no less than 50 pounds.	☐	☐	☐	
14	Device durability Ref. 1910.147(c)(5)(ii)(A)(1)	Locks and tags are intact and suited to the environment they are left in for the job.	☐	☐	☐	
15	Tag legibility Ref. 1910.147(c)(5)(ii)(A)(2)	Tags in outdoor, wet or damp locations are intact with a legible message.	☐	☐	☐	
16	Tag position on lockable isolator Ref. 1910.147(d)(4)(iii)(A)	A tag on a lockable isolator is fastened at the point where the lock would go.	☐	☐	☐	
17	Tag not directly attachable Ref. 1910.147(d)(4)(iii)(B)	A tag that cannot be fixed to the isolating device is as close as safely possible to it, where anyone trying to operate the device would see it immediately.	☐	☐	☐	

SECTION C | Applying controls on the job						
No.	**Check item**	**What to look for**	**OK**	**Defect**	**N/A**	**Notes**
18	Who applies Ref. 1910.147(c)(8)	Locks or tags are applied by the authorized employees doing the servicing.	☐	☐	☐	
19	Notice before application Ref. 1910.147(c)(9)	Affected employees were told before controls were applied.	☐	☐	☐	
20	Knowledge before shutdown Ref. 1910.147(d)(1)	The authorized employee can state the energy types and magnitudes, their hazards and how to control them.	☐	☐	☐	
21	Orderly shutdown Ref. 1910.147(d)(2)	The machine was shut down using its established procedure, in an orderly way that added no hazard from the stoppage.	☐	☐	☐	
22	All isolators operated Ref. 1910.147(d)(3)	Every isolating device needed for this machine has been located and operated.	☐	☐	☐	
23	Device on each isolator Ref. 1910.147(d)(4)(i)	A lock or tag is on every isolating device.	☐	☐	☐	
24	Lock position Ref. 1910.147(d)(4)(ii)	Each lock holds its isolating device in the safe or off position.	☐	☐	☐	
25	Stored energy Ref. 1910.147(d)(5)(i)	Residual energy in springs, pressure systems, raised parts and similar sources has been relieved, restrained or made safe.	☐	☐	☐	

General guidance only, not legal advice. Check the current regulation and your employer's procedures.

SECTION C | Applying controls on the job

No.	Check item	What to look for	OK	Defect	N/A	Notes
26	Continued verification Ref. 1910.147(d)(5)(ii)	Where stored energy could reaccumulate to a hazardous level, isolation is re-verified until the work is complete or that possibility no longer exists.	☐	☐	☐	
27	Isolation verified Ref. 1910.147(d)(6)	The authorized employee verified isolation and deenergization before starting work.	☐	☐	☐	

SECTION D | Release, testing, group work and handover

No.	Check item	What to look for	OK	Defect	N/A	Notes
28	Work area inspected Ref. 1910.147(e)(1)	Nonessential items are gone and machine components are operationally intact before devices come off.	☐	☐	☐	
29	Employees clear Ref. 1910.147(e)(2)(i)	All employees are safely positioned or out of the area.	☐	☐	☐	
30	Notice after removal Ref. 1910.147(e)(2)(ii)	Affected employees are told the devices are off before the machine starts.	☐	☐	☐	
31	Removed by applier Ref. 1910.147(e)(3)	Each device is taken off by whoever put it on, or under the employer's documented removal procedure when that person is not at the facility.	☐	☐	☐	
32	Testing or positioning Ref. 1910.147(f)(1)	When devices come off to test or position, the (f)(1) sequence is followed and controls go back on before servicing resumes.	☐	☐	☐	
33	Group lockbox Ref. 1910.147(f)(3)(ii)(D)	On crew jobs, each authorized employee has a personal lock or tag on the group device or lockbox.	☐	☐	☐	
34	Shift change Ref. 1910.147(f)(4)	Protection is transferred in an orderly way between off-going and oncoming employees.	☐	☐	☐	
35	Contractors Ref. 1910.147(f)(2)(i)	Where outside servicing personnel are on site, both employers have exchanged their procedures.	☐	☐	☐	

SECTION E | Inspection and training records

No.	Check item	What to look for	OK	Defect	N/A	Notes
36	Annual periodic inspection Ref. 1910.147(c)(6)(i)	An inspection of this procedure was done within the last year.	☐	☐	☐	
37	Independent inspector Ref. 1910.147(c)(6)(i)(A)	The inspector was an authorized employee not using the procedure being inspected.	☐	☐	☐	
38	Inspection certification Ref. 1910.147(c)(6)(ii)	The certification names the machine, date, employees included and inspector.	☐	☐	☐	
39	Authorized employee training Ref. 1910.147(c)(7)(i)(A)	Authorized employees were trained in hazardous energy recognition, energy type and magnitude, and isolation methods.	☐	☐	☐	
40	Affected employee instruction Ref. 1910.147(c)(7)(i)(B)	Affected employees were instructed in the purpose and use of the procedure.	☐	☐	☐	

General guidance only, not legal advice. Check the current regulation and your employer's procedures.

SECTION E | Inspection and training records

No.	Check item	What to look for	OK	Defect	N/A	Notes
41	Tag limitations training Ref. 1910.147(c)(7)(ii)	Where tags are used, training covered the limitations listed in (c)(7)(ii).	☐	☐	☐	
42	Retraining Ref. 1910.147(c)(7)(iii)(A)	Retraining was given after any job assignment change, a machine or process change presenting a new hazard, or a procedure change.	☐	☐	☐	
43	Training certification Ref. 1910.147(c)(7)(iv)	Training records show each employee's name and training dates and are current.	☐	☐	☐	

DEFECTS FOUND AND ACTION TAKEN

Item no.	Defect description	Reported to	Action taken / date closed

SIGN-OFF

SAFE TO OPERATE?	☐ Yes ☐ No: tagged out of service	
INSPECTOR SIGNATURE		DATE / TIME
SUPERVISOR REVIEW		DATE / TIME

General guidance only, not legal advice. Check the current regulation and your employer's procedures.