Lockout/Tagout Program Check (OSHA 29 CFR 1910.147)

Check a US general-industry energy control program and one live lockout against OSHA's lockout/tagout standard.

OSHA 29 CFR 1910.147, The control of hazardous energy (lockout/tagout)

DATE	SHIFT
INSPECTOR	AREA / EQUIPMENT ID

Before you start

1. Work through each item at the machine or with the program documents in hand. Record what you see, not what the procedure says should happen.
2. This checklist covers federal OSHA general industry only. Construction, maritime, electrical work and state-plan states may have extra or different rules.

Legal basis: OSHA 29 CFR 1910.147, The control of hazardous energy (lockout/tagout) OSHA 29 CFR 1910.147 Appendix A, Typical minimal lockout procedures (non-mandatory) OSHA Directive STD 01-05-019, Inspection Procedures and Interpretive Guidance

Online version and sources: https://safetyindex.blog/blog/lockout-and-tagout-procedures

SECTION A | Program and written procedures

No.	Check item	What to look for	OK	Defect	N/A	Notes
1	The energy control program has procedures, employee training and periodic inspections Ref. 29 CFR 1910.147	All three parts exist and are current for the machines in use	☐	☐	☐	
2	A documented procedure exists for each machine, or all eight exception conditions are met Ref. 29 CFR 1910.147(c)(4)(i)	Written procedure on file, or all eight conditions in the note exist for that machine	☐	☐	☐	
3	Procedures state scope, purpose, authorization, rules, techniques and the means to enforce compliance Ref. 29 CFR 1910.147	Each element appears in the written procedure	☐	☐	☐	
4	Procedures include specific requirements for testing to verify that energy controls are effective Ref. 29 CFR 1910.147	A named verification method for each machine	☐	☐	☐	
5	Any common procedure identifies the equipment it covers	Equipment listed at least by type and location	☐	☐	☐	

General guidance only, not legal advice. Check the current regulation and your employer's procedures.

SECTION B | Locks, tags and isolating devices

No.	Check item	What to look for	OK	Defect	N/A	Notes
6	Lockout is used wherever the energy isolating device can be locked out Ref. 29 CFR 1910.147	Lockable devices carry locks. Where tags are used instead, the employer's demonstration of full employee protection is on file	☐	☐	☐	
7	Tags used on lockable devices go where the lock would have gone and are backed by extra measures Ref. 29 CFR 1910.147(c)(3)(ii)	Tag at the lock location, plus a measure such as a removed valve handle, an opened extra disconnect or a blocked controlling switch	☐	☐	☐	
8	Lockout devices use a positive means to hold the isolating device in a safe position Ref. 29 CFR 1910.147(b)	Key or combination locks, blank flanges or bolted slip blinds	☐	☐	☐	
9	Tags are legible and understandable to everyone in the area Ref. 29 CFR 1910.147	Readable wording that all authorized, affected and other employees in the area can understand	☐	☐	☐	
10	No push button or selector switch is being relied on as the isolation point Ref. 29 CFR 1910.147(b)	Isolation at breakers, disconnects, line valves or blocks, not at control circuit devices	☐	☐	☐	

SECTION C | Applying controls (observe a live lockout)

No.	Check item	What to look for	OK	Defect	N/A	Notes
11	Affected employees are notified before controls are applied Ref. 29 CFR 1910.147	Notice given by the employer or the authorized employee before shutdown	☐	☐	☐	
12	Only the authorized employees doing the work apply locks or tags Ref. 29 CFR 1910.147	Each worker applies their own device. Nobody affixes another person's	☐	☐	☐	
13	Every energy isolating device needed is located and operated Ref. 29 CFR 1910.147	All sources isolated, not only the main disconnect	☐	☐	☐	
14	Stored or residual energy is dissipated or restrained	Springs, capacitors, raised parts, flywheels and pressurized lines grounded, blocked, repositioned or bled down	☐	☐	☐	
15	Isolation is verified before work starts and controls are returned to off	No personnel exposed, a start attempt or test made, controls back in the neutral or off position	☐	☐	☐	

SECTION D | Release and special situations						
No.	**Check item**	**What to look for**	**OK**	**Defect**	**N/A**	**Notes**
16	Each lock or tag is removed by the employee who applied it Ref. 29 CFR 1910.147(e)(3)	If someone else removed it, a documented and trained removal procedure was followed under the employer's direction	☐	☐	☐	
17	Affected employees are told after devices are removed and before restart Ref. 29 CFR 1910.147	Notification recorded or observed before startup	☐	☐	☐	
18	Temporary re-energization for testing or positioning is limited to that task Ref. 29 CFR 1910.147(f)(1)	Equipment deenergized and locked or tagged out again straight afterwards	☐	☐	☐	
19	Group lockouts give every authorized employee a personal device on the group lockbox Ref. 29 CFR 1910.147	Personal locks or tags applied at the start of each person's work and removed when that person stops	☐	☐	☐	
20	Shift changes and outside contractors are covered Ref. 29 CFR 1910.147	Written transfer method between shifts, and an exchange of procedures with each contractor	☐	☐	☐	

SECTION E | Inspection and training						
No.	**Check item**	**What to look for**	**OK**	**Defect**	**N/A**	**Notes**
21	Each energy control procedure was inspected within the last year Ref. 29 CFR 1910.147(c)(6)(i)	Done by an authorized employee other than those using the procedure, with a demonstration	☐	☐	☐	
22	The inspection certification is complete Ref. 29 CFR 1910.147	Machine or equipment, date, employees included and the person who inspected	☐	☐	☐	
23	Authorized employees are trained in energy recognition and isolation methods Ref. 29 CFR 1910.147(c)(7)(i)	Training covers energy sources, type and magnitude, and the means of isolation and control	☐	☐	☐	
24	Retraining follows changes in job, equipment, process or procedure Ref. 29 CFR 1910.147	Retraining records dated after each change	☐	☐	☐	

General guidance only, not legal advice. Check the current regulation and your employer's procedures.

DEFECTS FOUND AND ACTION TAKEN

Item no.	Defect description	Reported to	Action taken / date closed

SIGN-OFF

SAFE TO OPERATE?	☐ Yes ☐ No: tagged out of service	
INSPECTOR SIGNATURE		DATE / TIME
SUPERVISOR REVIEW		DATE / TIME