Course Introduction

Digital Manufacturing



Paolo Bosetti

Updated: 22/10/2026

Table of contents

1 Digital Manufacturing 2

2 Evolution of manufacturing 3

3 Industry 4.0 4

4 Previous industrial revolutions 5

5 Industry 4.0 8

6 Industry 4.0 9

7 Industry 4.0 9

8 Industry 4.0 9

9 Industry 4.0 10

10 Digital Manufacturing 10

11 Digital Manufacturing 10

12 OSI Networking Model 11

13 Digital Manufacturing 11

14 REST vs Message Queuing 12

15 HTTP overhead 12

16 HTTP overhead 13

17 How to reduce overhead 14

18 REST vs Message Queuing 15

19 REST vs Message Queuing 16

20 Digital Manufacturing 16

21 Course Matter 17

22 Tools 19

23 Teaching Material 19

24 Exam rules 20
24.1 Normal exam 20
24.2 Alternative: personal project 21

```
options(width = 60)
set.seed(0)
```

1 Digital Manufacturing

- DM is the evolution of manufacturing, where an integrated approach is centered around a computer system
- Evolution: purely mechanical machinery CNC machines systems of computer-controlled machines
- DM goes within the framework of Industry 4.0
- Industry 4.0 is the 4th industrial revolution

2 Evolution of manufacturing




Figure 1: Milling machine




Figure 2: CNC milling center




Figure 3: 1st NC machine tool (MIT, 1952)





Figure 4: DM plant

3 Industry 4.0

The term is a **marketing slogan** for the 4th industrial revolution, which is the **digitalization of manufacturing**. It was coined in Germany in 2011, and it is now a worldwide concept.

- **Motivation** — reaction from EU and USA to 2008 economical crisis
- **Name origin** — 2011 Hannover Messe (Angela Merkel)

- Hannover Messe 2013 — presentation of **final report** of the *Industrie 4.0* committee, **tasked by German government** in 2011:
  - Design principles
  - Challenges
  - Impacts



4 Previous industrial revolutions

First Industrial Revolution




Figure 5: Mechanical loom, E. Cartwright, **1784**

Second Industrial Revolution



Figure 6: Conveyor belt, Cincinnati Slaughterhouse, **1870**




Figure 7: Conveyor belt, Ford Motor Company, **1913**

Third Industrial Revolution




Figure 8: PLC, Modicon 084, **1969**

5 Industry 4.0

Objectives:

- Re-shoring of added value in western countries
- Sustain salaries of working- and middle-class
- Sustain e-commerce
- Mass customization (added value shifts from manufacturing to design)
- Time compression (life cycle of a car from 5 to 2 years)

6 Industry 4.0

Design principles:

- Interoperability (IoT, IIoT, IoP)
- Cyber-Physical Systems (CPS)
- Information transparency: public, open protocols; digital twins
- Self-support and in-line help to operators
- Decision de-centralization: autonomy, stratification, prioritization

7 Industry 4.0

Table 1: Akin to the *Yardstick of Automation* (Amber & Amber, 1962)

Order	Human attribute	Example
0	None	Manual tools
1	Energy	Powered machines and tools
2	Dexterity	Single-cycle automatics (*dexterity = self-feeding*)
3	Diligence	Repeats cycle; open-loop control
4	Judgment	Closed loop; numerical control; self-measuring
5	Evaluation	Computer control; model of process required for automation
6	Learning	Limited self-programming; some artificial intelligence
7	Reasoning	Inductive reasoning (cause-effects)
8	Creativity	Performs (original) design unaided
9	Dominance	Machine is master (HAL 9000)

8 Industry 4.0

Challenges:

- Cybersecurity
- Reliability and resiliency of M2M communication (bandwidth and latency)
- Drop-in, plug-in approach on existing processes
- Intellectual property (IP) protection
- Reluctancy to change, operators re-training
- Corporate IT
- Initial loss of labor

9 Industry 4.0

Impacts:

- Servitization (from selling goods to selling services)
- Productivity, and its resilience
- Safety
- Integrated design of product/process
- Cost structure
- Socio-economical factors
- Big Data analytics

10 Digital Manufacturing

A set of core, **enabling technologies** are grounding I4.0 and DM:

- **Cyber-Physical Systems** (M2M connectivity): in short, they are mechatronic systems, i.e., mechanisms, whose actuators are controlled by a computer system based on output from sensors and logics provided by algorithms
- CPSs provide the plant controller with information on its own status
- **IIoT** (connectivity layer): *Industrial Internet of Things*
- Additive Manufacturing (dematerialization of design): paradigm of **fully digital manufacturing process**
- **Machine Learning** and AI: strategy to further enhance the level of automation and enable autonomous decisions

11 Digital Manufacturing

- **Industrial Internet of Things (IIoT):** has to support communications among CPSs (M2M communication)
- Every **device** is on the network: we have tens of billions of devices globally connected, and the number is growing fast
- **Problem**: IP protocol: IPv4 has $2^{32} \simeq 4.3 \times 10^9$ addresses
- **Solutions**:
  - IPv6 has $2^{128} \simeq 3.4 \times 10^{39}$ addresses, but IPv6 adoption is slow because of the added costs and complexities
  - **NAT** (*Network Address Translation*) keeps IPv4 and addresses exhaustion problem by allowing multiple devices to share a single public IP address behind a gateway

12 OSI Networking Model

- Networking stack: according to the Internet model, networking happens over a stack of 4 layers

- **Link layer** (L0): physical carrier (Ethernet Cable, WiFi, etc) and its protocol (MAC, 802.11, ARP, etc)
- **Internet (or network) layer** (L1): IPv4, IPv6, ICMP
- **Transport layer** (L2): TCP, UDP
- **Application layer** (L3): HTTP, FTP, IMAP, LDAP, …




Figure 9: OSI layers


13 Digital Manufacturing

Industrial Internet of Things (IIoT): has to support communications among CPSs (M2M communication)

- **Level 0 protocols:** as fast as possible; currently introducing 5G (wireless yet extra-low latency!)
- **IP protocol (L1):** beside address space, IPv6 has other advantages (complex multi-casting, autoconfiguration, IPsec). Its adoption is still slow, though
- **Level 3 protocols:** moving from REST (HTTPS) to more lightweight **message queuing protocols** (MQTT, ZeroMQ, AMQP, OPC-UA)

14 REST vs Message Queuing

- **RE**presentational **S**tate **T**ransfer: it is an IoT extension of HTTP
- It is not ideal:
  - Verbose: large overhead
  - Complex: `PUT/GET/POST/DELETE` verbs that make sense for IoP, but not for IoT
  - Polling-based, event-based actions difficult to implement
  - Point-to-point: n clients to 1 server; routing a message between clients is difficult and not efficient



15 HTTP overhead

Let's see a HTTP/TCP request/reply message exchange by capturing the whole traffic with Wireshark

- Request phrase: `GET / HTTP/1.1` (14×2 bytes)
- The HTTP frame takes 153 bytes total
- The full request stack takes 437 bytes for the **minimum request**




Figure 10: Wireshark capture

16 HTTP overhead

- Response phrase: 77 bytes + HTML
- The whole HTTP frame takes 937 bytes (including 819 bytes of HTML)
- The full response stack takes 1201 bytes, 382 bytes for a **blank page**

> **Overhead**
>
> This is a **huge overhead** for a simple request/reply message exchange, and it is not acceptable for IoT communications, because it adds both bandwidth **and** latency




Figure 11: Wireshark capture

17 How to reduce overhead


- Reliability and robustness are very important for **IoP** communications: variety of web servers, web browsers and document formats, and the web must "just work"
- They are also important in **IoT** (because *things* must do their tasks) but we can enforce standards and minimize possible sources of unexpected conditions

Overhead can be reduced by:


- Simpler transport layer (L2) protocol: UDP has no SYN/ACK/FIN frames (but no confirmation of delivery!)
- Simpler application layer (L3) protocols, where the data frame is as naked as possible
- Trading reliability and robustness for bandwidth and latency

18 REST vs Message Queuing

- IoT messages are typically smaller but much more frequent than IoP messages, and **may need to follow routes more complex than n-to-1** (client**s**–server)
  - Need to minimize overhead
  - Need to support flexible topologies
- Message Queuing protocols (like MQTT and ZeroMQ)



19 REST vs Message Queuing



20 Digital Manufacturing

It is the effort of moving all information flow from the design phase to the manufacturing phase into a digital (paperless) workflow, with the final goal of minimizing human effort and intervention (automation)

- **Conventional machining:** Designer Drawings/models CAM operator part-program CNC machine tool
- **Additive Manufacturing:** Designer Machine tool (like a printer)
- Entirely digital workflow, minimal human intervention
- Support for **Machine Learning** and Artificial Intelligence:
  - Classification of operating conditions
  - Autonomous and de-centralized decision making
  - Level 7 automation on Amber & Amber's scale

21 Course Matter

1. Overview of manufacturing processes, machine architectures, control algorithms
2. Development of a CNC kernel (motion planner and controller)
3. Interfacing the CNC kernel with a digital twin (Simulink model) and a 3D viewer, using an IoT framework




Figure 12: C++ development and testing




Figure 13: CPS simulation (Digital Twin)



Figure 14: 3D printer/3D viewer

22 Tools

- **Programming in C++**: high performance, general purpose language, suitable for real-time systems (controllers), more complex to learn than C (bigger) but more abstract (does not need understanding of hardware)
- **GNU-Unix toolchain** (much more common than Windows in automation)
  - Linux exposed via WSL in Windows (MacOS is UNIX already)
  - And/or custom machine simulator (faster)
- Code will be developed in class and made available on https://github.com/pbosetti/cncpp
- Reference **IoT framework** is MADS

23 Teaching Material

- All teaching materials are provided via Moodle
- Software will be made available on GitHub platform
- Reference textbook is *Manufacturing Automation*, by Y. Altintas (2000), available @BUM (2 copies)




Figure 15: Reference book

24 Exam rules

24.1 Normal exam

- Each Session is made up by a mandatory written exam and an optional oral exam
  - **Written exam:** on Moodle platform, max 26/30
  - **Oral exam:** optional, max 30L/30, must be given in the same session
- **Final mark:** starting from written mark, oral exam can improve or degrade it

24.2 Alternative: personal project

- The students extend the CNC kernel developed in class to implement a selection of new features, and demonstrate it on a simulated machine
- The project is evaluated by the teacher and the final mark is given as a single oral exam (max 30L/30)
- Personal projects begin **after the course end**