Precious Fikile Mkhize

0210210785080

DESCRIBE AND INSTALL A FASCIMILE MACHINE

US 14952



A **facsimile (fax) machine** is an office device that scans physical documents, converts the image into electronic audio signals or binary data, and transmits them over a telephone line or network to another fax machine, which prints out a duplicate copy. [1, 2]

How It Works (Description)

- **Scanning:** An internal sensor or charge-coupled device reads the dark and light areas of the paper.
- **Encoding & Modulation:** The machine translates the visual data into an audio stream via an internal modem.
- **Transmission:** The signals travel across an active analog or digital telephone/landline network.
- **Printing:** The receiving machine decodes the signal and reproduces the document onto paper using thermal, inkjet, or laser technology. [1, 2, 3, 4]

How to Install a Facsimile Machine

1. **Pre-Installation Checks:**
    - Choose a flat, stable, and dry surface near an active electrical outlet and a working telephone landline jack. (Note: standard analog faxes require a copper landline, not a standard internet/VoIP router line unless properly adapted).
    - Check the telephone cable, power supply, and make sure there is no moisture nearby. [2, 5, 6]
2. **Unpacking and Assembling:**
    - Unbox the machine and remove all protective plastic wrap, tape, and shipping locks.
    - Attach the paper feed tray, output extensions, and any modular components per the manufacturer's manual. [5]
3. **Loading Consumables**

- Install the toner cartridge, ink ribbon, or thermal/plain paper roll/sheets into the designated compartments. [6, 7]

4. **Connecting Power and Phone Line:**
   - Plug the power cord into the machine and connect it to a wall outlet or surge protector (keep the machine powered *off* during initial cabling).
   - Locate the port labeled **LINE** (or **TEL LINE**) on the back of the device.
   - Plug one end of an RJ-11 telephone cable into the **LINE** port and the other end into the active wall phone jack.
   - *(Optional)* If sharing the line with a telephone handset, plug that phone into the port labeled **EXT** or **TEL**. [7, 8, 9]
5. **Power On and Test:**
   - Turn on the power switch.
   - Pick up an attached handset or test the line to confirm a clean **dial tone**.
   - Run a test fax or print a self-test/configuration report from the device's control panel menu to verify the setup. [6, 7, 10, 11]