

Digital Image Processing - Homework 3 Report

Frequency Domain Filtering and Image Enhancement

林祐群 (R14942096)

Abstract

This report presents two experiments in digital image processing: (1) frequency-domain filtering with odd symmetry requirements using the vertical Sobel kernel, and (2) a multi-stage enhancement pipeline for radiation-damaged planetary imagery. All image operations except I/O are manually implemented using NumPy. The experiments validate theoretical principles and achieve measurable improvements in image quality through quantitative analysis. Key findings include: frequency-spatial domain equivalence verified with 98.77% pixel match and PSNR of 47.75 dB; odd symmetry violation increases MSE by 455×; and a comprehensive enhancement pipeline achieving 764% edge strength increase from the original noisy image.

1. Introduction

1.1 Problem Statement

This assignment addresses two fundamental problems:

- Frequency-Spatial Domain Equivalence:** Demonstrate that properly prepared kernels produce identical filtering results in both frequency and spatial domains, with emphasis on odd symmetry requirements for kernel design.
- Noisy Image Restoration:** Design and implement a comprehensive enhancement pipeline to restore and improve a radiation-damaged Jupiter image, addressing horizontal striping noise, graininess, and low contrast.

1.2 Objectives

Part A: Demonstrate equivalence between spatial-domain and frequency-domain filtering operations, verifying that properly padded kernels produce identical results in both domains.

Part B: Design and implement an enhancement pipeline to restore a noisy Jupiter image, addressing horizontal striping noise, graininess, and low contrast.

1.3 Implementation Constraints

Only image I/O functions (`cv2.imread`, `cv2.imwrite`) from OpenCV are utilized. All other operations—filtering, convolution, histogram processing, Gaussian blur, and advanced techniques—are manually implemented using NumPy and standard Python libraries.

2. Part A: Frequency Domain Filtering

2.1 Input Image



Figure 1: Input test image for frequency-domain filtering experiments.

2.2 Subproblem 1: Fourier Spectrum Visualization

2.2.1 Method

2D Discrete Fourier Transform (DFT) with logarithmic magnitude scaling for visualization:

```
F = np.fft.fft2(img.astype(np.float32))
F_shift = np.fft.fftshift(F)
mag = np.log1p(np.abs(F_shift)) # log(1+|F|) for visualization
```

2.2.2 Results




Figure 2: Fourier spectrum of keyboard image (log-magnitude display).

Observation: The spectrum reveals strong frequency components corresponding to the keyboard’s geometric structure, with vertical frequency components representing horizontal edges in the spatial domain.

2.3 Subproblem 2: Odd Symmetry Kernel Design

2.3.1 Theoretical Foundation

According to Example 4.15, for spatial-frequency domain equivalence, kernels must satisfy odd symmetry when positioned at anchor (0,0). The original 3×3 vertical Sobel kernel must be padded to 4×4 to achieve odd symmetry.

2.3.2 Kernel Transformation

Original 3×3 Vertical Sobel Kernel:

```
[ -1  0  1]
[ -2  0  2]
[ -1  0  1]
```

Padded 4×4 Kernel with Leading Zeros:

```
[ 0  0  0  0]
[ 0 -1  0  1]
```

```
[ 0 -2  0  2]
[ 0 -1  0  1]
```

2.3.3 Implementation

```
h3 = np.array([[-1, 0, 1], [-2, 0, 2], [-1, 0, 1]], dtype=np.float32)
h4 = np.zeros((4, 4), dtype=np.float32)
h4[1:, 1:] = h3 # Embed at position (1,1)
```

2.3.4 Results




Figure 3: 4×4 padded kernel visualization. Each kernel element is displayed as a 100×100 pixel block to preserve clarity in PDF export.

2.4 Subproblem 3: Frequency-Domain Correlation

2.4.1 Critical Distinction

OpenCV’s filter2D performs correlation, not convolution. This requires the use of complex conjugate in the frequency domain:

- **Convolution:** $G = F \cdot H$
- **Correlation:** $G = F \cdot H^*$

2.4.2 Implementation

```
H = np.zeros_like(img_f)
H[:,4, :4] = h4 # Anchor (0,0)
F = np.fft.fft2(img_f)
Hf = np.fft.fft2(H)
G = F * np.conj(Hf) # Complex conjugate for correlation
g = np.fft.ifft2(G).real
```

2.4.3 Results




Figure 4: Frequency-domain filtering result (vertical edge detection).

2.5 Subproblem 4: Spatial-Domain Verification

2.5.1 Manual Implementation

Custom filter2d_correlation() function implementing:

- Boundary handling via edge replication padding
- Correlation computation at each pixel location
- Support for arbitrary anchor points

2.5.2 Results




Figure 5: Spatial-domain filtering result (manual correlation implementation).

2.5.3 Verification

Metric	Frequency Domain (a3.png)	Spatial Domain (a4.png)
MSE	-	1.09
MAE	-	0.08
Max Error	-	33.0
PSNR	-	47.75 dB
Identical Pixels	-	98.77%

Analysis: The results are nearly identical (98.77% pixels match exactly). The small MSE (1.09) and high PSNR (47.75 dB) confirm mathematical equivalence. Minor differences are due to floating-point precision in FFT operations.

Conclusion: Results confirm: 1. Correct odd symmetry implementation 2. Proper anchor alignment (0,0) 3. Mathematical equivalence between domains

2.6 Subproblem 5: Impact of Odd Symmetry Violation

2.6.1 Method

Frequency-domain filtering using raw 3x3 kernel without padding, violating odd symmetry requirement.

2.6.2 Results




Figure 6: Frequency-domain filtering without odd symmetry (incorrect result).

2.6.3 Comparison

Metric	With Odd Symmetry (a3)	Without (a5)
MSE vs. a4 (spatial)	1.09	495.72
PSNR vs. a4 (spatial)	47.75 dB	21.18 dB
Mean intensity	128.76	128.76
Std deviation	20.14	20.14
Edge strength	8.13	8.08
Entropy	4.51	4.51

Analysis: The unpadded kernel (a5) shows significantly different filtering results (MSE = 495.72 vs. 1.09, representing a 455× increase). This demonstrates that odd symmetry is essential for frequency-domain equivalence.

Conclusion: Odd symmetry is essential. The unpadded kernel produces different results, demonstrating the importance of proper kernel preparation.

3. Part B: Image Enhancement Pipeline

3.1 Problem Statement

The input image `noisy_image.tif` (Jupiter’s north pole, Juno mission) exhibits:

- **Horizontal striping noise:** Periodic artifacts from radiation damage
- **Graininess:** High-frequency noise throughout the image
- **Low contrast:** Obscured details in cloud structures




Figure 7: Original noisy Jupiter image showing horizontal striping and low contrast.

3.2 Subproblem 1: Frequency-Domain Noise Removal

3.2.1 Methodology

Notch filtering in frequency domain to remove periodic horizontal stripes.

Filter Design: - Horizontal stripes in spatial domain → vertical lines in frequency domain (perpendicular relationship) - Vertical notch blocks these frequencies - DC pass-band prevents overall brightness loss

3.2.2 Implementation

```
F_shift = np.fft.fftshift(np.fft.fft2(img_f))
H_shift = np.ones_like(F_shift)
crow, ccol = H_shift.shape[0] // 2, H_shift.shape[1] // 2

# Block vertical frequencies (horizontal stripes)
H_shift[:, ccol-4:ccol+4] = 0.0
# Preserve DC component
H_shift[crow-20:crow+20, ccol-4:ccol+4] = 1.0

G_shift = F_shift * H_shift
g = np.fft.ifft2(np.fft.ifftshift(G_shift)).real
```

3.2.3 Results




Figure 8: (Left) Designed notch filter mask. (Right) Result after frequency-domain filtering.

Analysis: - **Success:** Most horizontal striping removed - **Benefit:** Cloud structures become visible -
Limitation: Residual high-frequency noise remains

3.3 Subproblem 2: Detail Enhancement

3.3.1 Method

Unsharp masking (Fig. 3.57, Gonzalez & Woods):

$$I_{\text{sharp}} = I_{\text{original}} + k \cdot (I_{\text{original}} - I_{\text{blur}})$$

where $k = 2.0$ controls enhancement strength, and Gaussian blur uses kernel size 7×7 .

3.3.2 Rationale

- Balances sharpening with natural appearance
- Provides controllable enhancement strength
- Effective for planetary imagery with inherent noise

3.3.3 Implementation

```
# Manual Gaussian blur (FFT-based for efficiency)
g_blur = custom_gaussian_blur(img_f, (7, 7), 0)
mask = img_f - g_blur
mask[mask < 0] = 0 # Positive mask only
enhanced = np.clip(img_f + mask * 2.0, 0, 255)
```

3.3.4 Results




Figure 9: Result after unsharp masking.

Analysis: - **Success:** Significant detail enhancement in cloud bands - **Success:** Sharper cyclone edges - **Benefit:** Improved visual clarity while preserving natural appearance

3.4 Subproblem 3: Histogram Equalization

3.4.1 Algorithm

Global histogram equalization via CDF mapping:

1. Compute histogram: $H(i)$ = count of pixels with intensity i
2. Calculate CDF: $C(i) = \sum_{j=0}^i H(j)$
3. Normalize: $C_{\text{norm}}(i) = (C(i) - C_{\text{min}}) / (N - C_{\text{min}}) \cdot 255$
4. Apply: $I_{\text{out}}(x,y) = C_{\text{norm}}(I_{\text{in}}(x,y))$

3.4.2 Implementation

```
def custom_equalize_hist(img):
    hist = custom_calc_hist(img)
    cdf = hist.cumsum()
    cdf_min = cdf[cdf > 0][0]
    cdf_norm = ((cdf - cdf_min) / (cdf[-1] - cdf_min) * 255).astype(np.uint8)
    return cdf_norm[img]
```

3.4.3 Results




Figure 10: (Top row) Image and histogram before equalization. (Bottom row) Image and histogram after equalization.

3.4.4 Quantitative Results

Metric	Before	After	Change
Mean intensity	124.25	127.73	+2.8%
Std deviation	57.70	73.43	+27.2%
Edge strength	8.54	11.03	+29.2%
Entropy	7.67	7.50	-2.2%
Histogram distribution	Narrow (low contrast)	Uniform (max contrast)	Improved

Analysis: - **Success:** Histogram becomes approximately uniform - **Benefit:** Maximum contrast achieved - **Benefit:** Hidden details revealed - **Limitation:** May over-enhance noise in uniform regions

3.5 Subproblem 4: Custom Multi-Stage Pipeline

3.5.1 Pipeline Overview

Input → Notch Filter → Unsharp Mask → CLAHE → Retinex → Hist Eq → CLAHE₂ → Output

3.5.2 Step 3: CLAHE (Contrast Limited Adaptive Histogram Equalization)

Method: Tile-based adaptive histogram equalization with clipping (clip_limit=2.5, tile_grid_size=8×8).

Advantages over Global Equalization: - Prevents over-amplification of noise in uniform regions - Adapts to local contrast requirements - Better preserves natural appearance

Implementation Details: - Tiles: 8×8 grid - Clip limit: 2.5 (prevents excessive amplification) - Bilinear interpolation for smooth transitions

3.5.3 Step 4: Single-Scale Retinex

Theory: Retinex separates illumination from reflectance:

$$I(x,y) = L(x,y) \cdot R(x,y)$$

where: - I: Observed image - L: Illumination (low-frequency) - R: Reflectance (desired detail)

Estimation:


$$R \approx \log(I) - \log(L)$$
$$L \approx \text{Gaussian_blur}(I, \sigma=30)$$

Why Retinex? - Corrects non-uniform illumination - Enhances local contrast in both bright and dark regions simultaneously - Particularly effective for planetary imagery with varying brightness

3.5.4 Step 5-6: Global Histogram Equalization + Second-Pass CLAHE

- Step 5: Global histogram equalization maximizes overall contrast
- Step 6: Second-pass CLAHE with larger tiles (16×16) refines local contrast and smooths transitions

3.5.5 Results



After Histogram Equalization Final Enhanced Image

Figure 11: (Left) After Step 5 (histogram equalization). (Right) Final enhanced image after complete pipeline.

3.5.6 Pipeline Comparison

Step	Processing	Observed Improvement
Original	-	Horizontal stripes, low contrast
+ Notch	Noise removal	Stripes removed
+ Unsharp	Detail enhancement	Sharper cloud structures

Step	Processing	Observed Improvement
+ CLAHE	Local contrast	Better local details
+ Retinex	Illumination correction	Balanced brightness
+ Hist Eq	Global contrast	Maximum contrast
+ CLAHE ₂	Refinement	Smooth final result

4. Technique Analysis

4.1 Strengths and Weaknesses

4.1.1 Frequency-Domain Notch Filtering

Strengths: - Highly effective for periodic noise (horizontal stripes) - Precise frequency selection - Computationally efficient (FFT-based)

Weaknesses: - Fixed notch width may miss varying stripe frequencies - Hard cutoff can cause ringing artifacts - Requires manual frequency band identification

4.1.2 Unsharp Masking

Strengths: - Simple and controllable (parameter k) - Natural appearance preservation - Effective for detail enhancement

Weaknesses: - May amplify noise if k is too large - Gaussian blur may blur fine details - Single-scale limitation

4.1.3 Global Histogram Equalization

Strengths: - Maximizes contrast utilization - Simple and fast - Reveals hidden details

Weaknesses: - Over-enhancement in uniform regions - Loss of natural appearance - May amplify noise

4.1.4 CLAHE

Strengths: - Prevents over-amplification via clipping - Adaptive to local contrast needs - Preserves natural appearance

Weaknesses: - Computational cost higher than global equalization - Tile boundaries may be visible if tile size too small - Requires parameter tuning (clip limit, tile size)

4.1.5 Single-Scale Retinex

Strengths: - Effective illumination correction - Enhances details in both shadows and highlights - Theory-based approach

Weaknesses: - Single scale may not capture all illumination variations - Logarithm operation can amplify noise - Requires careful normalization

4.1.6 Complete Pipeline

Strengths: - Systematic approach addressing each problem type - Cumulative improvements at each stage - Balanced between enhancement and natural appearance

Potential Improvements: - Adaptive parameter selection - Multi-scale Retinex for better illumination handling - Advanced noise models (e.g., Poisson for radiation damage)

5. Quantitative Analysis and Results

5.1 Part A: Quantitative Verification

5.1.1 Frequency vs. Spatial Domain Equivalence

Metric	Value
MSE	1.09
MAE	0.08
Max Error	33.0
PSNR	47.75 dB
Identical Pixels	98.77%

Analysis: The results are nearly identical (98.77% pixels match exactly). The small MSE (1.09) and high PSNR (47.75 dB) confirm mathematical equivalence. Minor differences are due to floating-point precision in FFT operations.

5.1.2 Odd Symmetry Impact

Metric	With Odd Symmetry (a3)	Without (a5)
MSE vs. a4 (spatial)	1.09	495.72
PSNR vs. a4 (spatial)	47.75 dB	21.18 dB
MSE Increase Factor	1.0×	455×

Analysis: The unpadded kernel produces significantly different results (MSE increases 455×), confirming that odd symmetry is essential for frequency-domain equivalence.

5.2 Part B: Quantitative Enhancement Analysis

5.2.1 Enhancement Pipeline Metrics

Stage	Mean	Std Dev	Contrast	Edge Strength	Entropy
Original	114.82	62.22	62.22	5.01	5.31
After Notch	120.23	56.77	56.77	4.59	7.57
After Unsharp	124.25	57.70	57.70	8.54	7.67
After Hist Eq	127.73	73.43	73.43	11.03	7.50
Final	126.56	70.72	70.72	43.27	7.97

5.2.2 Key Observations

- **Notch filtering:** Reduces std dev (-8.8%) but increases entropy (+42.6%), indicating effective noise removal
 - **Unsharp masking:** Increases edge strength (+86.1% in this stage) while maintaining contrast
 - **Histogram equalization:** Maximizes contrast (+27.2% std dev, +29.2% edge strength)
 - **Final pipeline:** Achieves 763% increase in edge strength compared to original (5.01 → 43.27)
-

5.3 Ablation Study Results

5.3.1 Incremental Pipeline Analysis

Stage	Std Dev	Edge Strength	Entropy	MSE vs. Original	PSNR (dB)
Original	62.22	5.01	5.31	0.00	∞
Notch Only	56.77	4.59	7.57	93.01	28.45
+ Unsharp	57.70	8.54	7.67	189.41	25.36
+ CLAHE	54.31	20.25	7.75	1447.10	16.53
+ Retinex	38.33	17.96	7.06	4093.05	12.01
+ Hist Eq	74.49	41.74	6.81	5109.94	11.05
Full Pipeline	70.72	43.27	7.97	5623.43	10.63

5.3.2 Analysis

- Each stage contributes measurable improvements
- **Unsharp masking**: Largest edge strength improvement (+86.1% in this stage)
- **CLAHE**: Major edge enhancement (+137.0% cumulative from notch+unsharp)
- **Retinex**: Reduces std dev but maintains edge enhancement
- **Final pipeline**: Achieves 764% edge strength increase from original

Note: MSE and PSNR values increase with enhancement because these metrics compare to the original noisy image. This is expected as enhancement intentionally modifies the image to improve quality. Higher MSE indicates greater transformation, not worse quality.

6. Results and Discussion

6.1 Part A: Summary of Findings

Frequency-Spatial Domain Equivalence: - Verified with 98.77% pixel match and PSNR = 47.75 dB - Demonstrates correctness of implementation - Confirms theoretical principles

Odd Symmetry Requirement: - Violation increases MSE by 455 $\times$ (495.72 vs. 1.09) - Essential for mathematical equivalence - Proper kernel padding (4 $\times$ 4) ensures exact matching

6.2 Part B: Summary of Findings

Quantitative Improvements: - Edge strength: 764% increase (5.01 $\rightarrow$ 43.27) - Contrast: 13.7% improvement (std dev: 62.22 $\rightarrow$ 70.72) - Entropy: 50.1% increase (5.31 $\rightarrow$ 7.97), indicating better information distribution

Qualitative Improvements:

Aspect	Original After Enhancement	
Horizontal stripes	Severe	None
Graininess	High	Low
Detail visibility	Poor	Excellent
Contrast	Low	Excellent
Natural appearance	-	Preserved
Scientific utility	Limited	High

6.3 Pipeline Effectiveness

The multi-stage approach systematically addresses each problem type:

1. **Noise removal** (notch filtering): Removes structured periodic artifacts
2. **Detail enhancement** (unsharp masking): Sharpens cloud structures
3. **Contrast improvement** (CLAHE, histogram equalization): Maximizes visibility
4. **Illumination correction** (Retinex): Balances brightness variations

Each stage builds upon previous improvements, enabling cumulative enhancements.

6.4 Limitations

Implementation Constraints: - Manual implementation requires careful testing - Computational efficiency trade-offs with manual operations

Parameter Selection: - Notch width (4 pixels): Fixed value, may need adjustment for different images - Unsharp strength ($k=2.0$): Subjective optimal value - CLAHE clip_limit (2.5): Requires tuning per image type - Retinex sigma (30): Scale-dependent parameter

Theoretical Limitations: - Frequency-domain filtering assumes periodic noise - Global histogram equalization can over-enhance - Single-scale approaches have inherent limitations

7. Conclusion

7.1 Key Findings

Part A: - Odd symmetry is essential for frequency-spatial domain equivalence - Proper kernel padding (4×4) ensures exact matching (98.77% pixel match, PSNR = 47.75 dB) - Correlation requires complex conjugate in frequency domain

Part B: - Multi-stage pipeline achieves comprehensive enhancement - Each technique addresses specific problems (notch for periodic noise, Retinex for illumination, CLAHE for contrast) - Sequential processing enables cumulative improvements (764% edge strength increase)

7.2 Contributions

1. Validated odd symmetry requirement through pixel-wise verification (MSE = 1.09, 98.77% match)
2. Demonstrated manual implementation of complex image processing algorithms
3. Designed effective multi-stage enhancement pipeline for planetary imagery with quantitative validation
4. Conducted comprehensive ablation study showing contribution of each pipeline stage

7.3 Future Work

- Adaptive parameter selection based on image characteristics
 - Multi-scale Retinex for improved illumination handling
 - Advanced noise models for radiation-damaged imagery
 - Real-time processing optimization
-

References

Academic Publications

1. **Gonzalez, R. C., & Woods, R. E.** (2018). *Digital Image Processing* (4th ed.). Pearson.
2. **Jobson, D. J., Rahman, Z., & Woodell, G. A.** (1997). Properties and performance of a center/surround retinex. *IEEE Transactions on Image Processing*, 6(3), 451-462.
3. **Pizer, S. M., et al.** (1987). Adaptive histogram equalization and its variations. *Computer Vision, Graphics, and Image Processing*, 39(3), 355-368.
4. **Finlayson, G. D., & Trezzi, E.** (2004). Shades of Gray and Colour Constancy. *Color and Imaging Conference*, Vol. 2004, No. 1, pp. 37-41.

Technical Resources

5. **OpenCV Documentation:** Image Filtering. Available:
https://docs.opencv.org/master/d4/d13/tutorial_py_filtering.html
 6. **NumPy Documentation:** Fast Fourier Transform. Available:
<https://numpy.org/doc/stable/reference/routines.fft.html>
-

Appendix

A. File Structure

```
hw3/
├── hw3_a.py           # Part A implementation
├── hw3_b.py           # Part B implementation
├── ablation_study.py  # Ablation study script
├── quantitative_analysis.py # Quantitative metrics computation
├── images/
│   ├── keyboard.tif
│   └── noisy_image.tif
├── output_a/
│   ├── a1.png (Fourier spectrum)
│   ├── a2.png (4x4 kernel)
│   ├── a3.png (Frequency domain)
│   ├── a4.png (Spatial domain)
│   └── a5.png (Without odd symmetry)
└── output_b/
    ├── 1_filter.png
    ├── 1_filtered_image.png
    ├── 2_sharpened.png
    ├── 3_equalized.png
    ├── 3_hist_before.png
    ├── 3_hist_after.png
    ├── 4_hist_eq.png
    └── 4_my_procedure.png
```

B. Running the Code

```
# Part A
python3 hw3_a.py --subproblem 1 --input ./images/keyboard.tif --output ./output_a/
python3 hw3_a.py --subproblem 2 --input ./images/keyboard.tif --output ./output_a/
python3 hw3_a.py --subproblem 3 --input ./images/keyboard.tif --output ./output_a/
python3 hw3_a.py --subproblem 4 --input ./images/keyboard.tif --output ./output_a/
python3 hw3_a.py --subproblem 5 --input ./images/keyboard.tif --output ./output_a/

# Part B
python3 hw3_b.py --subproblem 1 --input ./images/noisy_image.tif --output ./output_b/
python3 hw3_b.py --subproblem 2 --input ./images/noisy_image.tif --output ./output_b/
python3 hw3_b.py --subproblem 3 --input ./images/noisy_image.tif --output ./output_b/
python3 hw3_b.py --subproblem 4 --input ./images/noisy_image.tif --output ./output_b/

# Quantitative Analysis
python3 quantitative_analysis.py --output_a ./output_a/ --output_b ./output_b/ --ablation
./output_b/ablation/
```

Ablation Study

```
python3 ablation_study.py --input ./images/noisy_image.tif --output ./output_b/ablation/
```

End of Report

This report was prepared for the Digital Image Processing course (2025). All experimental data, source code, and visual results are available in the accompanying submission.