GRUNDFOS DATA SHEET

VFS 5-100 QT

Vortex Flowsensor Standard, 5-100 I/min



Fig. 1 VFS 5-100 sensor

Technical overview

VFS is a series of combined flow and temperature sensors (two-in-one) based on the principle of vortex shedding behind a bluff body. The VFS sensors are designed for high-volume production and are fully compatible with wet, aggressive media. The VFS sensor utilises MEMS sensing technology in combination with a novel packaging concept using corrosion-resistant coating on the MEMS sensing element. This makes the VFS sensor very robust and ideal for high-volume OEM applications. QT ™ is a special version of the VFS sensors, where a composite insert creates a compact and cost-effective flow and temperature measuring system which can be integrated closely into the customer's own pipework.

Applications

- · thermal management in solar heating systems
- cooling and temperature control (e.g. manifold systems within machine tools)
- · floor heating/radiant and valve systems
- · monitoring of pumps, valves and filters
- flow rate detection for pump controls
- · industrial process flow control
- · burner control in domestic gas boilers
- heat metering (solar thermal / heat pumps etc.).

Features

- flow range: 5-100 l/min in 42 % glycol mixtures at 30 °C
- designed for harsh environments
- based on vortex shedding
- voltage output (ratiometric, ideal for use with microprocessor and PLC)
- compact and well-proven design
- MEMS sensing technology
- approved for potable water: WRAS, KTW, W270, ACS
- NPSM and BSPP threads.

Benefits

- no moving parts
- flow and temperature sensor in one package (twoin-one sensor)
- quick temperature response (direct media contact)
- · compatible with wet, aggressive media
- cost-effective and robust construction.

Specifications

5 to 100 l/min
3 to 100 ///////
±1.5 % FS
< 1 s
0.5 l/min
0.3 ///////
0 to 100 °C
±1 °C
±1 C
±2 °C
< 1 s
0.5 °C
0.5 C
The sensor is compatible with liquids
(kinematic viscosity $\leq 2 \text{ mm}^2/\text{s}$)
0 to 100 °C
-25 to 120 °C, non-freezing
–25 to 60 °C
−55 to 90 °C
0 - 95 % (relative), non-condensing
> 16 bar
5 V DC (±5 %). Grounding of the sensor supply is required (PELV)
Ratiometric
0.5 - 3.5 V (Zero at 0.35 V)
0.5 - 3.5 V
< 50 mW
> 10 kΩ
-
Silicon-based MEMS sensor
EPDM rubber
1.4408
PPA 40-GF
Corrosion-resistant coating, EPDM,
PPS, PPA 40-GF
IP44 (Non overmoulded IP20)
IEC 68-2-14
20 - 2000 Hz, 10G, 4h
EN 61326-1
EN 61326-1
EN 61326-1 47 x 40 x 20 mm, see drawing

If the equipment is used in a manner not specified by the manufacturer, the protection provided by the equipment may be impaired.

Dimensions (in mm)





Fig. 2 Dimensional sketches of VFS QT



Fig. 3 VFS 5-100 QT sensor components

Type key

The sensor is labelled with a type designation.



For more information, see http://www.grundfos.com/directsensors.

Electrical connections




Fig. 4 Electrical connections

Pin	configuration	Colour
1	Temperature signal (0.5 to 3.5 V relative to pin 3)	Yellow
2	Flow signal (0.5 to 3.5 V relative to pin 3)	White
3	GND (0 V)	Green
4	Power supply (+ 5 VDC), PELV	Brown

Power supply requirements

- 5 VDC
- separated from hazardous live circuitry by double or reinforced insulation
- power limitation:150 VA; current limitation: 8 A.

Sensor output signals




Fig. 5 Flow response




Fig. 6 Temperature response

97648723 0610 Repl. 97648723 0210

Subject to alterations.

TM03 8217 0807

TM03 8149 0607

