



Dual Holiday Countdown Display

Firmware Update Instructions

Before You Begin

Firmware updates are provided through the [HomeHackery GitHub](#) project.

You will need:

- A phone, tablet, or computer connected to the same Wi-Fi network as the display
- The latest firmware .ino.bin file
- The firmware update username and password

Important: Only use the .ino.bin firmware file provided with the release. Do not select an .ino file or any other file.

1. Download the Latest Firmware

Go to the [Dual Holiday Countdown Display GitHub project](#) and select Releases. Open the release marked Latest.

Under Assets, download the file named similar to:

DualHolidayCountdown_v1_0_15.ino.bin

The version number will change with future releases. You only need the **.ino.bin** file.

2. Open the Display Control Page

Make sure your phone, tablet, or computer is connected to the same Wi-Fi network as the display.

Open a web browser and go to:

<http://dualholiday.local>

3. Open Firmware Update

On the display's control page, select Firmware Update. You will be asked for a username and password.

Username: admin

Password: HomeHackery

4. Select the Firmware File

Select the .ino.bin file you downloaded from the GitHub release.

For example: DualHolidayCountdown_v1_0_15.ino.bin

Then select Update Firmware.

5. Wait for the Update to Complete

Do not unplug the display or disconnect power while the firmware is being updated.

The display will restart automatically when the update is complete.

After it restarts, allow the display a few moments to reconnect to Wi-Fi and synchronize its time. The countdown will then appear.

If the Update Does Not Work

If the update is rejected:

1. Make sure you downloaded the firmware from the Latest GitHub release.
2. Make sure you selected the .ino.bin file.
3. Make sure the username and password were entered correctly.
4. Make sure the display and your device are connected to the same Wi-Fi network.

The current firmware will remain installed if an invalid file or incorrect credentials are entered.

For additional information or the latest updates, check the HomeHackery GitHub project.