Christopher D. Supino
Managing Senior Corporate Counsel
Direct Dial: 317-517-2963
Email: csupino@misoenergy.org

October 2, 2026

VIA ELECTRONIC FILING

The Honorable Debbie-Anne Reese
Secretary
Federal Energy Regulatory Commission
888 First Street, NE
Washington, DC 20426

Re: Midcontinent Independent System Operator, Inc.'s
Large Load Addition Resource Study Process
Docket No. ER27-___-000

Dear Secretary Reese:

The Midcontinent Independent System Operator, Inc. ("MISO"), through this filing,[1] submits proposed revisions to its Open Access Transmission, Energy and Operating Reserve Markets Tariff ("Tariff"),[2] to establish a Large Load Addition Resource Study ("LARS") process,[3] associated application and operational requirements to enable load and generation to be studied together leveraging existing MISO processes to facilitate the timely availability of the tool to customers.[4] The LARS proposal will help streamline the MISO generator and load interconnection process by providing expedited review of the addition of 200 MW or greater loads together with new generation resources that are electrically proximate to those loads. Through this coordinated study framework, LARS is designed to facilitate the timely and reliable interconnection of Large Loads and new generation onto the MISO system.

---

1 This filing is made pursuant to section 205 of the Federal Power Act ("FPA"), 16 U.S.C. § 824d, and Part 35 of the regulations of the Federal Energy Regulatory Commission ("FERC" or "Commission"), 18 C.F.R. § 35.1, *et seq*.

2 Unless otherwise indicated by the text or context of this transmittal letter, all terms used herein have the definitions set forth in Module A of the Tariff.

3 For the purposes of this filing, references to "LARS" may refer to the Large Load Addition Resource Study or may be used as a general reference to the processes and operational requirements that are part of the proposal submitted herein.

4 MISO uses the uncapitalized term "large load" in this transmittal letter and associated testimony rather than the "Large Load" term proposed in MISO's pending Large Load Interconnection Reliability filing. This is done to avoid confusion because that definition remains pending before the Commission and because, given the 200 MW threshold for entry into LARS, not all "Large Loads" will be eligible to be a "LARS Associated Load."

MISO requests that the Tariff revisions submitted herewith be made effective December 2, 2026, which is not less than sixty (60) days nor more than one-hundred and twenty (120) days from the date of this filing. MISO requests that the Commission issue an order by this date in order to allow MISO to commence the first LARS Study Period in Q1 of 2027. As discussed below and in the supporting testimony of Christina Drake,[5] action is needed in the near term to enhance the available tools to address the reliability impacts associated with the impending interconnection of Load, including the anticipated interconnection of significant large loads.

I. EXECUTIVE SUMMARY

LARS responds to rapidly evolving reliability and resource adequacy needs in the MISO region. MISO is proposing LARS to facilitate the cost effective, timely and reliable integration of new large loads into the system. LARS supports the Commission's call to action to meet these new challenges in short order. LARS will provide a path for the interconnection of both large loads and supporting generation pairs in a parallel 120-day study process. The proposal leverages the existing success in the MISO's Expedited Project Review ("EPR") process on the load side and lessons learned from Expedited Resource Additions Study ("ERAS") process on the generation side.

MISO is experiencing significant growth in electricity demand at the same time that additional resources are needed to reliably serve that demand. MISO projects annual load growth of approximately 1% to 3% through 2044, driven in part by energy-intensive loads such as data centers and manufacturing expansion, and has identified the need to accelerate new resource additions as demand grows.[6]

The need to accelerate the infrastructure necessary to reliably serve growing electricity demand is also reflected in the Department of Energy's ("DOE") Speed to Power initiative, which seeks to accelerate development timelines for large-scale transmission and generation projects to meet rising electricity demand.[7] LARS advances that objective within the MISO region by providing a process through which significant new large loads and generation intended to support that load can be studied on an accelerated and coordinated basis.

---

[5] Prepared Direct Testimony of Christina Drake, Director—Generation Interconnection, attached hereto as Tab C ("Drake Testimony").

[6] MISO, 2026 Reliability Imperative Report at 4 (Feb. 2026) (projecting annual load growth of approximately 1% to 2% through 2044 and identifying data centers, manufacturing expansion, and electrification as drivers of sustained, concentrated load growth); *see also*, MISO, 2026 Planning Resource Auction Results at 2 (May 22, 2026) (stating that faster resource additions are needed to support large-load growth and ensure resource adequacy).

[7] DOE, *Speed to Power Initiative* (Sept. 18, 2025) (describing the initiative as a federal effort to accelerate development timelines for large-scale transmission and generation projects and ensure sufficient power to meet rising electricity demand).

LARS is also responsive to the Commission's June 18, 2026, Order Instituting Proceeding Under Section 206 of the Federal Power Act in Docket No. EL26-70-000 ("Show Cause Order"). The Commission preliminarily found, among other things, that MISO's existing Tariff may be unjust and unreasonable because it does not provide generator interconnection study procedures and services that account for the operational dynamics of serving electrically proximate large loads.[8] The Commission specifically addressed the potential for a new generating facility and an electrically proximate large load to be studied in a manner that accounts for their combined transmission system impacts.[9] LARS provides a mechanism for MISO to study a large load and the generation that will serve it at the same time such that their combined transmission system impacts may be considered together.

In addition, the Commission requested a detailed informational report on any proposals under consideration to address the issue of resource adequacy to serve new large loads, strongly encouraging new proposals to the extent necessary to address these concerns.[10] The LARS process responds to this concern and serves to provide a critical tool that allows the timely integration of resources associated with these new loads supporting regional resource adequacy. While MISO's existing processes have been sufficient to ensure resource adequacy in the short term, the unique commercial and operational characteristics of new large loads and the speed with which they need to come online have prompted MISO to develop LARS as an additional tool to further support resource adequacy as new large loads are integrated into the MISO region in the future.

This proposal is deliberately tailored to significant new large loads. MISO initially proposed a minimum eligibility threshold of 250 MW and expressly sought stakeholder input regarding whether that threshold appropriately captured high-impact loads without unnecessarily expanding the scope of the process.[11] MISO set the initial threshold at 250 MW as recent EPR results showed that large loads of 250 MW and greater created meaningful grid impacts, with upgrades becoming increasingly likely between 300–500 MW and consistently necessary at 1,200 MW and above with multi-element upgrades. Stakeholders proposed alternative thresholds, including 200 MW, which MISO proposes herein as it expands the LARS proposal beyond hyperscale load to apply to other kinds of large loads including industrial loads.[12]

---

8 *Midcontinent Independent System Operator, Inc.,* Order Instituting Proceeding Under Section 206 of the Federal Power Act, 195 FERC ¶ 61,212 at P 113 (2026) ("Show Cause Order" or "SCO").

9 *Id.*

10 *Id.* at P 122.

11 MISO, Large Load Working Group ("LLWG"), *Generation and Large Load Alignment*, LLWG-2026-6, Stakeholder Feedback (July 30–31, 2026) (soliciting stakeholder feedback on whether 250 MW was the appropriate minimum threshold and what alternative threshold would capture high-impact loads without diluting the intent of the proposed process), *available at* https://www.misoenergy.org/engage/stakeholder-feedback/2026/llwg-large-load-addition-resource-study-llwg-2026-6-20260827/.

12 *Id.*

Importantly, LARS is designed to work in concert with other MISO large load initiatives, such as MISO's proposed Zero Injection Generator Interconnection Agreement ("ZGIA")[13] and Interconnection Reliability Requirement ("IRR")[14] frameworks currently pending before the Commission and maintains protections for generation already progressing through MISO's generator interconnection queue or more commonly known as the Definitive Planning Phase ("DPP") process. LARS provides a different tool for large load interconnection arrangements involving paired generation that do not fit within the ZGIA framework.

Taken LARS provides MISO with a targeted tool to address the intersection of significant large load additions, optimized Network Upgrades with generation and load, generation development, and supports resource adequacy. The proposal allows MISO to study qualifying load and associated generation on a coordinated basis, responds to issues identified in the Commission's Show Cause Order, and is designed to preserve the integrity of MISO's existing generator interconnection processes. LARS is needed now to facilitate the cost-effective and reliable interconnection of impending new large loads and generation additions on an accelerated timeline.

II. OVERVIEW OF THE LARS PROCESS

A. BACKGROUND

The MISO region is experiencing a significant change in both the magnitude and pace of anticipated electricity demand. MISO's 2026 Reliability Imperative explains that, following a period in which electricity demand grew at an average annual rate of approximately 0.5% between 2009 and 2024, MISO now projects annual load growth of approximately 1% to 3% through 2044.[15] MISO identifies energy-intensive loads, including data centers and manufacturing expansion, among the sources of this sustained and concentrated growth.[16]

This growth has corresponding implications for the resources necessary to maintain operational reliability and resource adequacy. MISO has stated that, as demand grows rapidly, maintaining existing resources and accelerating new resource additions are critical.[17] MISO's 2026 Planning Resource Auction results likewise recognize that, although the region has sufficient resources to satisfy resource adequacy requirements for the 2026-2027 Planning Year, faster

---

[13] *Midcontinent Indep. Sys. Operator, Inc*, Docket No. ER26-3552 (Aug. 18, 2026) ("ZGIA Filing").

[14] *Midcontinent Indep. Sys. Operator, Inc*, Docket No. ER26-3650 (Aug. 28, 2026) ("IRR Filing").

[15] MISO, *2026 Reliability Imperative Report* at 4 (Feb. 2026) (contrasting historical load growth of approximately 0.5% annually from 2009 through 2024 with projected annual growth of approximately 1% to 2% through 2044).

[16] *Id.*

[17] *Id.*

resource additions remain necessary to support large-load growth and ensure resource adequacy.[18] MISO has, therefore, identified rapid load growth as a core component of its broader Reliability Imperative. MISO's Transmission Evolution work specifically identifies the need to "speed up timelines for new generation and transmission projects" while managing large-load growth without compromising reliability.[19]

Against this backdrop, the challenge presented by new large load growth is not limited to connecting the load itself. Significant new demand must be accompanied by sufficient resources to maintain reliability and resource adequacy. MISO's Large Load Working Group ("LLWG") was established to address this broader relationship, with a mission encompassing markets, reliable operations, planning, and resource adequacy associated with the integration and enablement of large loads.[20] LARS is intended to address one aspect of that challenge by establishing a process through which qualifying Large Load additions and associated new generation can be studied on a coordinated basis. Studying qualifying load and generation together, with aligned study timeline, provides a mechanism for MISO to consider significant new demand and the resources associated resulting in optimized network upgrades. In this manner, LARS is designed to facilitate the reliable integration of significant new load and generation on an accelerated timeline.

B. STRUCTURE OF LARS AND PARTIES

LARS provides a parallel study process for a proposed large load and generation pair.[21] As MISO explained in its motion for abeyance, "LARS will assess the transmission infrastructure needed to meet new large loads and new generation in an efficient process that can be executed on a shorter timeline, further supplementing the opportunities available for members to facilitate new large spot loads effectively."[22] The generation and load studies will be completed at the same time and will finish within approximately 120 days. To allow this to happen, LARS brings the requirements that are needed for both the generation and load studies under a common application,

---

[18] MISO, 2026 Planning Resource Auction Results at 2 (May 22, 2026) (finding sufficient resources for the 2026-2027 Planning Year while stating that faster resource additions are needed to support large-load growth and ensure resource adequacy).

[19] MISO, *Reliability Imperative 2026* (identifying rapid load growth and a changing generation mix as transmission challenges and identifying accelerated generation and transmission development as part of MISO's response).

[20] MISO, *Large Load Working Group Charter* at 1 (Apr. 20, 2026) (establishing the LLWG to provide input and policy guidance concerning markets, reliable operations, planning, and resource adequacy associated with large-load integration), ("LLWG Charter"), available at: https://cdn.misoenergy.org/20260420%20LLWG%20Item%2001c%202026%20LLWG%20Charter_Draft750858.pdf.

[21] Attachment X defines Large Load Addition Resource Study (LARS) as "the procedure as set forth in Section 3.12 of this GIP for studying an Interconnection Customer's proposed Generating Facility in parallel with the study of a LARS Associated Load Customer's proposed load." *See* Section 1 of Attachment X.

[22] Motion of the Midcontinent Independent System Operator, Inc. and the MISO Transmission Owners to Hold Proceeding in Abeyance and Request for Shortened Comment Period and Expedited Treatment, Docket No. EL26-70-000 (Aug. 3, 2026) ("Abeyance Motion").

the LARS Application and provides a framework for participation by the entities involved in the existing MISO processes that LARS builds upon.

There are four primary types of entities involved in implementing LARS aside from MISO. These are the LARS Associated Transmission Customer, the Interconnection Customer(s) who will own or operate the Generating Facility, the applicable Transmission Owner, and the owner/controller of the ultimate load (called the "LARS Associated Load"). To understand how LARS will work, a brief explanation of each of these parties' roles in the process is provided below.

The first of these parties is the LARS Associated Transmission Customer.[23] This is the entity that procures Transmission Service for load and has a direct relationship with the load. This is often a Load Serving Entity ("LSE"). Because only the Transmission Customer can procure Transmission Service under established Tariff processes, LARS requires the LARS Associated Transmission Customer to be the party that initiates the LARS Application and obtains the resulting Transmission Service.[24] Ultimately, the LARS Associated Transmission Customer acts as a coordinator between the other entities involved in the LARS process.

Second, there is the Interconnection Customer. This is the entity that will complete the section of the LARS Application that supports the generation portion of the LARS study, will be responsible for meeting the requirements of Attachment X pertaining to the generation study, and will receive Interconnection Service under an LLGIA. The Interconnection Customer can be any entity (including an Independent Power Producer ("IPP")) whose Generating Facility will provide Energy for the LARS Associated Load provided it is permitted by applicable laws and regulations to do so.[25] The Interconnection Customer has the contractual relationships required by LARS to show that the Generating Facility is in fact paired with the LARS Associated Load.[26]

Third, the Transmission Owner owns the facilities the LARS Associated Load will connect to the Transmission System. The Transmission Owner works with the other parties to establish the Point of Interconnection ("POI") for the Generating Facility(ies) and the Point of Withdrawal

---

[23] In GIP Section 1 of Attachment X, a LARS Associated Transmission Customer is defined as "the entity that is responsible for submitting the LARS Application and procures Transmission Service in order to serve LARS Associated Load and designates such load as formally paired with an Interconnection Customer's LARS Interconnection Request."

[24] *See* GIP Section 3.12.1.

[25] Interconnection Customer is defined as "any entity, including Transmission Provider, Transmission Owner or any of the Affiliates or subsidiaries of either, that proposes to interconnect its Generating Facility with the Transmission System. For the purposes of Large Load Addition Resource Study (LARS), Interconnection Customer shall refer to the entity developing the Generating Facility that will execute the LLGIA, which may be a different entity from the LARS Associated Transmission Customer that submitted the LARS Application." *See* GIP Section 1 of Attachment X.

[26] *See* GIP Section 3.12.2(i).

for the LARS Associated Load and has the responsibility to construct Network Upgrades (subject to applicable Tariff rules that are not changed by this filing).[27]

The fourth key participant is the entity that owns or controls the LARS Associated Load, which for purpose of LARS must be a large load of at least 200 MW.[28] While MISO usually will not have a direct relationship with this entity and does not purport through this filing to impose obligations directly on them, this entity will have a crucial role in establishing relationships between the parties directly involved in LARS, in supplying information necessary to complete the LARS Application, and study process, and in enabling the other parties to meet their obligations under LARS.

As noted above, the roles of these parties and their specific responsibilities reflect existing Tariff requirements and practices. LARS does not seek to fundamentally change the established roles of the entities participating in the load and generation studies but rather seeks to coordinate them. LARS thus provides for faster and more transparent interconnection arrangements for large loads with paired generation, while offering customers speed-to-power, optimized transmission solutions, and greater certainty to support siting, and financing of large load projects. The outcome of the LARS process is MTEP approval of transmission required to reliably facilitate the withdrawal of the load and corresponding injection rights for the proposed generation. The component parts of the process are discussed in greater detail below.

C. THE LARS APPLICATION

MISO is establishing a single application process for the participants in the LARS process. The LARS Application will be a single submission consisting of materials required by Attachment FF for the load and Attachment X for the generation.[29] Because LARS involves two separate study processes being completed concurrently and in parallel, all the relevant parties to the load and generation pairing must apply together.[30] While the LARS Application process may only be initiated by the LARS Associated Transmission Customer, the Interconnection Customer, the Transmission Owner, and the LARS Associated Load customer must all complete the required information as part of the application before it will be reviewed by MISO. Independent Power Producers and other kinds of Interconnection Customers are not prohibited from participating in

---

[27] *See* GIP Section 3.12.1.

[28] The LARS Associated Load is defined as the "source of electrical load that is at least 200 MW and that is formally paired with one or more Interconnection Customer(s) that have submitted an Interconnection Request to LARS proposing one or more new Generating Facility(ies) to provide energy to such load." *See* GIP Section 1 of Attachment X.

[29] The LARS Application is defined as "a single submission consisting of the materials required for LARS processing as required by Section I.D.1.b.ii of Attachment FF to the Tariff as well as the information required for studying the Generating Facilities under this Attachment X (in the form of Appendix 1) to these generator interconnection procedures. For purposes of this GIP, a LARS Application shall be a form of Interconnection Request."

[30] *See* Drake Testimony at 17-18.

the LARS process.[31] The LARS Application will also serve as a repository for all information required by the load and generation study processes. A non-refundable fee of $250,000 must accompany the LARS Application and be paid by the LARS Associated Transmission Customer.[32]

Notably, MISO is establishing a "pre-submission coordination process" that LARS applicants must participate in prior to submitting a LARS Application.[33] This coordination process requires the potential LARS Interconnection Customer and the Transmission Owner to meet and agree on a definitive Point of Interconnection for the proposed LARS Generating Facility. Forty-five days prior to a LARS Application deadline, a potential LARS Interconnection Customer must notify the Transmission Owner to whose Transmission Facilities the potential LARS Interconnection Customer proposes to Interconnect of its plans to participate in LARS. After receiving a request to meet from any potential LARS Interconnection Customer, the Transmission Owner must meet with them and any other impacted parties necessary to determine a definitive POI within ten business days after receiving a request for the meeting. The parties must jointly agree on a feasible POI no later than ten business days prior to the next LARS Application deadline as published on MISO's website. An attestation from the Transmission Owner stating that it has an agreed POI with the LARS Interconnection Customer(s) must be included in the LARS Application.[34]

MISO is proposing these pre-submission coordination activities for several reasons. First, while the LARS Associated Transmission Customer is the only party that may submit the LARS Application, MISO is requiring that they actively participate in the LARS process with the potential LARS Interconnection Customers prior to LARS Application deadline. Second, requiring pre-submission coordination activities will increase the efficiency of reviewing the LARS Application with all the relevant parties identified, the agreed upon POI identified, and other necessary details have already been determined by the time the LARS Application is submitted to MISO. Having the LARS Application parties agree on many of these necessary details in advance of submission will also help avoid future disagreements or changes, which can lead to unnecessary or late withdrawals from the study process. MISO has heard from stakeholders and learned from experience that an accelerated study process requires that the relevant participants have coordinated and agreed upon key details (such as the location of the POI) up front and not after they have submitted their application. Third, requiring coordination meetings between these parties will assist them with identifying any other relevant parties who may need to participate in the LARS process. Ms. Drake explains that to effectively facilitate the speed of the LARS study process, MISO needs all relevant parties to the load and generation pair to not only be identified at the outset but committed to working together.[35]

---

31 *Id.* at 18-19.

32 *See* GIP Section 3.3.1 ("A LARS Application for the Large Load Addition Resource Study shall be accompanied by a Non-Refundable Deposit 1 (D1) of $250,000 submitted by the LARS Associated Transmission Customer.").

33 *See* GIP Section 3.12.1 and Section I.D.1.b.ii(a) of Attachment FF.

34 *See* Drake Testimony at 20; GIP Section 3.12.1.

35 Drake Testimony at 19-20.

MISO will accept LARS Applications on a rolling basis, and the applications will be queued on a serial, time-stamped basis based on time of submission to the LARS process. There will be three LARS study periods each year and each study period will be completed in approximately 120 days, as explained by Ms. Drake.[36] MISO will accept ten LARS Applications per study period and the LARS Applications will be assigned to study periods in order of submission. Customers interested in joining the next LARS study period must submit their LARS Application to MISO no later than 20 business days prior to the scheduled kick-off of the LARS study period as published on the MISO public website. MISO will keep an open queue of LARS Applications and will replace any LARS Application that withdraw prior to study kick off with the next submitted generation/load pair not included in the current study period. Once the LARS study process has kicked off for a specific LARS generation/load pair, then that spot is lost for the LARS study period it is part of even if the pair later withdraws during the study process.[37]

An Interconnection Request included in a LARS Application must be accompanied by an executed agreement between the Interconnection Customer and either the LARS Associated Tranmission Customer or the entity that owns or controls the LARS Associated Load. The agreement must demonstrate that the output of the LARS Generating Facility will serve the LARS Associated Load. The agreement must be legally binding and must state a minimum term of five years so that if any transmission solutions need to be developed, there is sufficient time to work through the processes for development. As described in Section 3.12.2(i) of Attachment X, the agreement must be in the form of a power purchase agreement ("PPA") or similar off-take agreement, a Build-Own-Transfer Agreement, or any other kind of agreement used by Load Serving Entities including a special contract, a large load tariff agreement, or a retail service agreement. Ms. Drake explains that in response to stakeholder feedback, MISO revised the Tariff redlines to explicitly state the agreement can be executed between the generator and large load. [38] This does not supersede the role of the LARS Associated Transmission Customer to determine whether to submit a LARS Application but does allow flexibility for different types of agreements that are consistent with state law and supported by the parties.[39] MISO also added the third agreement option to incorporate specific utility arrangements with large loads that are not traditional PPAs to link the generation and load.[40]

---

36 *See id.* at 13.

37 For example, if MISO holds the LARS study kick-off calls for all ten generation/load pairs and one of the pairs withdraws the following week, MISO will not move up another pair into that study cycle since the study process had already commenced. If the generation/load pair withdraws shortly before the LARS study kick-off call, then MISO would move the next LARS generation/load pair into that study cycle.

38 MISO, Large Load Working Group ("LLWG"), *Generation and Large Load Alignment*, LLWG-2026-6, MISO Response to Feedback at 8, (Sep. 28, 2026), available at: https://cdn.misoenergy.org/LLWG%20Large%20Load%20Addition%20Resource%20Study%20Response%20(LLWG-2026-6)%20(20260827)784877.pdf

39 Drake Testimony at 31-32.

40 *See id.*

Other requirements of the LARS Application include limiting the Interconnection Requests to NRIS, limiting the amount of requested Interconnection Service to no more than 150% of the peak demand of the LARS Associated Load, and demonstration of 100% site control for the POI including a one-line diagram demonstrating the Generating Facilities and any associated electrical equipment required.[41] Based on stakeholder feedback MISO established the 150% of Interconnection Service limitation to ensure the generation is required to reliably serve the load within the same LRZ. As Ms. Drake states, MISO sought to establish a closer connection between what is needed by the LARS Associated Load and what is being proposed by the LARS Interconnection Customer.[42] Thus, MISO implemented this requirement to directly connect the Generating Facility with the LARS Associated Load and to allow for different generator fuel types and accreditation. Ms. Drake explains that "this requirement establishes a clear connection between the output of the Generating Facility and the load without being overly prescriptive on generation fuel type, dispatch requirements, or other operational considerations."[43]

Another important condition of the LARS process is the requirement that the load and generation pair be located in the same Local Resource Zone ("LRZ").[44] The Point of Interconnection(s) specified in a LARS Application must be located in the same LRZ as the Point of Withdrawal ("POW") of the LARS Associated Load. As discussed by Ms. Drake, the intent of the LARS process is to identify an optimized Network Upgrade solution for both the load and generation, and MISO retains that flexibility in the LRZ because it aligns with MISO's Resource Adequacy construct.[45] Specifically, MISO does not have a requirement that loads bring generation, but through the proposed LARS process, by restricting the Point of Interconnection(s) specified in a LARS Application to be located in the same LRZ as the Point of Withdrawal, MISO providing an incentive for Load to bring Generation in a manner that maximizes the positive impact this Generation has on Resource Adequacy. MISO recognizes there are other ways it could have limited the pairing such as requiring the generation and LARS Associated Load to be located in the same Local Balancing Authority area or through requiring that the location of the Generating Facilities be within a specific number of substations of the LARS Associated Load. However, limiting the pairing of Generating Facilities and LARS Associated Load to the same LRZ strikes an appropriate balance between accommodating large, landlocked LARS Associated Loads that may need additional POIs to propose sufficient Generating Facilities needed to serve that load. Limiting the proximity of the Generating Facilities and LARS Associated Load provides a solution

---

41 *See* GIP Section 3.12.2.

42 *See* Drake Testimony at 29.

43 *Id.*

44 Attachment X defines Local Resource Zone (LRZ) as the "geographic area within the Transmission Provider Region that is prescribed by the Transmission Provider, based upon the criteria in Section 68A.3, to address congestion that limits Planning Resource deliverability." An LRZ is the smallest geographic area defined by MISO for planning and market purposes and it is used to allocate resource adequacy requirements, capacity benefits, and reliability needs based on transmission constraints, electrical boundaries, and local reliability requirements. LRZs are used in the Planning Resource Auction ("PRA") as well as for allocating the Planning Reserve Margin ("PRM") requirement.

45 *See* Drake Testimony at 40.

that is not overly restrictive and is consistent with MISO's resource adequacy construct by ensuring deliverability of the Generating Facilities to LARS Associated Load within the same LRZ.

MISO is proposing to increase flexibility in the LARS process by allowing a LARS Associated Load to be served by multiple Generating Facilities under specific circumstances. First, all Generating Facilities serving a LARS Associated Load must be included and identified in the same LARS Application and must request a minimum of 200 MW of Generator Interconnection Service in aggregate. Second, a LARS Associated Load may be served by more than one group of Generating Facilities located at different POIs, but a separate LARS Application must be submitted for each POI group of Generating Facilities. Stated differently, each group of aggregated LARS Generating Facilities at a single POI must submit a separate LARS Application. Each LARS Application must identify the total amount of load requested by the LARS Associated Load and must identify every Generating Facility providing power to that load.[46] While MISO is allowing aggregation for LARS Generating Facilities, MISO is not allowing aggregated load to participate in LARS. As explained earlier, MISO developed LARS in the context of dramatic large load growth and created the LARS process to help address that growth. Ms. Drake explains that limiting LARS load participants to at least 200 MW at one POW ensures that the load coming online is sufficiently large to warrant inclusion in LARS and is not a large group of small loads banded together.[47]

While the LARS Application requirements are expected to reduce the number of speculative projects submitting applications, they provide enough flexibility to enable these large loads to connect to the system. As Ms. Drake explains in her testimony, ensuring that only commercially viable and shovel ready projects enter LARS is a necessary prerequisite to running these extremely fast serial studies because each LARS study must be able to rely on the Network Upgrades resulting from previously completed LARS study actually being developed.[48] Thus, the strict entry requirements for LARS both support its intended benefits while also underscoring that LARS is not, and should not be, a replacement for the DPP.[49] Rather, it is intended to be a narrowly scoped but powerful process.

D. THE LARS STUDY PROCESS

The requirements of the LARS generator interconnection study process are outlined in Section 3.12.2 of Attachment X. Based on principles established in ERAS, the LARS generation-side study will provide a Large Load Generator Interconnection Agreement ("LLGIA") in approximately 120 days and will be a permanent MISO study process. Similarly, the load process will start the approval process after a 90-day study process. While the LARS generation and load studies are completed separately and in parallel, they both start with the same overall base

---

46 *See id.* at 23, 30.

47 *See id.* at 24-25.

48 *See id.* at 9-11.

49 *See id.* at 12.

configuration system including both MTEP and GIA projects in their models.[50] On top of that common base model, MISO then adds the LARS generation, load, and the proposed transmission solutions to study all three components together. Ms. Drake explains how this allows for both the generation and load studies to have a fuller picture of system impacts than would be possible if each was studied in isolation, enabling greater efficiency in Network Upgrade identification.[51] The load and generation studies will be completed at approximately the same time.[52] MISO designed the LARS process to ensure the proposed load and generation pair is evaluated to the same standards as those submitted separately through MISO's other existing processes (*i.e.*, MTEP/EPR and ERAS).

1. THE GENERATION STUDY

For each LARS study period, the individual generation/load pairs will be studied in one model, and MISO will have ten models that represent those ten generation/load pairs. MISO will complete these studies individually and in a serial fashion based on their submission date. This allows MISO to look at any generation or load violations individually and together with the results from the load side study as explained by Ms. Drake.[53] Then any common violations that show up in the generation and load studies are assigned to BRP and Other project types. Only the violations but for the generator are assigned GIP project types.[54]

As MISO explained to stakeholders in the LLWG, all studies begin with the MTEP models as a base to contain consistent topology, generation, and load assumptions.[55] The LARS model build will include all Existing Generating Facilities, including those from completed DPP cycles, the ERAS process, and the latest MTEP base case with all approved MTEP projects as well as any recently approved EPR projects. This is the same process utilized for the DPP process except the DPP models include all higher queued Interconnection Requests from earlier cycles and all Interconnection Requests within that DPP cycle. As Ms. Drake explained, "LARS studies will not include Interconnection Requests currently in the generator interconnection queue that do not have an executed GIA."[56] MISO has designed the LARS study this way to reduce the number of speculative projects in the modeling process. Thus, on the generation study side, MISO is analyzing whether there are enough pathways and requested Network Service to allow the generator to integrate into the system. On the load study side, MISO is analyzing the cumulative

---

50 *Id.* at 13-14.

51 *Id.* at 14-15.

52 *Id.* at 26.

53 *Id.* at 14-16.

54 *See id.* at 15-16.

55 *See* MISO, LLWG, *Generation and Large Load Alignment*, LLWG-2026-6, Large Load Addition Resource Study (LARS) presentation at 5 (Sep. 23, 2026), available at: https://cdn.misoenergy.org/20260923%20LLWG%20Item%2006%20Large%20Load%20Addition%20Resource%20Study%20(LLWG-2026-6)782864.pdf.

56 Drake Testimony at 29.

impacts of adding the large loads to the system and identifying common issues solutions. Notably, MISO will not limit the study process to the specific LRZ the generation/load pair will be located in – this requirement is solely for the pairing of the load and generation.[57] MISO will look at the full impacts of the generation/load pair on MISO's Transmission System using the same study criteria and processes applicable to NRIS evaluations of other Interconnection Requests.

As a result of the way MISO's study models are structured, LARS projects will not impact existing projects in the DPP process.[58] LARS Interconnection Requests will not be included in ongoing DPP studies and therefore will not utilize any available transmission capacity in those studies. Any Network Upgrades approved through the LARS process will be reflected in later cycles and may mitigate constraints that would otherwise be identified there. Thus, LARS cannot impact ongoing DPP cycles and, to the extent that LARS projects could impact future cycles, such impacts would only be positive.[59] In the event that overallocation does occur, any constraints that are identified as needing mitigation in the MTEP process will be formalized in a future MTEP project.[60] The cost of the MTEP project will be allocated based on existing Tariff rules, which is likely to be the load within the transmission pricing zone where the transmission upgrade is required. This cost shift is consistent with MISO's existing processes. The Interconnection Customer will be responsible for all Network Upgrades identified in the LLGIA as GIP project types even if it later withdraws from LARS.[61] Ms. Drake explains that this is necessary both to ensure commitment from those entering the LARS process and provide certainty to the other processes (including later LARS and DPP studies) that will include facilities identified through LARS in their starting models.[62]

At the end of the LARS process, the generator will receive a LLGIA to generate up to 150% of identified MW need of the LARS Associated Load.

2. THE LOAD STUDY

The requirements of the LARS load interconnection study process are outlined in Section I.D.1.b.ii of Attachment FF. For each LARS study period, all ten generation/load pairs will be represented in one model, and MISO will complete ten separate studies in that one model.[63] The LARS load study process is built upon MISO's existing EPR process and requires similar

---

[57] *Id.* at 4 ("Completing the generation and load studies in parallel allows MISO to see the full impacts on the system with each different configuration, which enables MISO to identify solutions for both the generation and load sides.").

[58] *See* Drake Testimony at 32-33.

[59] *Id.* at 33.

[60] *Id.*

[61] *Id.* at 37-38.

[62] *Id.* at 15-16.

[63] *Id.* at 14 ("All ten generation/load pairs will be represented in one model, and MISO will complete ten separate studies in that one model.").

information. MISO's load study process focuses on accounting for cumulative impacts of the proposed loads and the coordination with affected systems. The transmission reliability studies will employ a format including all other submitted EPRs and LARS projects to ensure the cumulative impacts of the load and transmission are observed. The Transmission Owner's initial set of transmission solutions are identified and submitted to MTEP. This allows MISO to view and analyze the full spectrum of contingencies across timeframes and processes.[64]

First, MISO will complete a load model build with the proposed LARS generators. Then MISO will review the proposed LARS projects with reliability assumptions and determine if any constraints are identified. This process includes reviewing the outage of the generator in the study. After completing a load and generation constraint review, MISO will determine whether there are any common issues solutions. A planning level solution is established at the end of the load study process. While completing the study, MISO is looking to determine whether the available generation and transmission pathways can reliably serve the LARS Associated Load without negatively impacting the rest of the transmission system. As Ms. Drake explains, MISO is looking at different scenarios and conditions within the load model to ensure that the load can be reliably served under a variety of circumstances.[65] By including every load for that LARS study period in one model, MISO is able to look at the cumulative impacts and reduce the risk that multiple transmission projects will need to be developed. Any cost impacts from the study outcomes will be assigned to Baseline Reliability Projects and Other type projects.[66] In addition, a *pro forma* cost shifting agreement will need to be executed and any new terms in transmission services agreements will need to be met. MISO notes that it is continuing to work with stakeholders through the LLWG to develop the *pro forma* cost shifting agreement and any necessary terms for transmission service for large loads, all of which will be submitted to the Commission in a FPA section 205 filing by November 16, 2026.

The proposed Attachment FF updates reinforce the core requirement of generator commitment to LARS, other MISO processes require that a GIA must be executed before a resource can be included in the load study models as it provides the necessary certainty for the load planning process. In the LARS study process, MISO includes the paired generator in the LARS load study even though it will not have an executed GIA at the time of study. This pairing of load and generation for a parallel process supports or facilitates identification of a more efficient and potentially more cost-effective set of Network Upgrades than would be possible if the generation and load were studied in isolation and acknowledges the increasing number of projects that require coordinated evaluation. In addition, the cost allocation hierarchy—transitioning from GIP to BRP when appropriate—supports procedural alignment and simplifies outcomes when common constraints lead either to BRP designation or another path.

---

64 *Id.* at 14-15, 25.

65 *Id.* at 25.

66 *Id.* at 27-28. MISO's proposed Tariff language is sufficient to categorize these costs as BRPs or Other project types, with cost responsibility flowing from such designation under existing rules. The LARS structure is compatible with these agreements and MISO will incorporate them into LARS once they are accepted. However, LARS can be implemented based on the Tariff revisions filed herein and need not await these future filings.

E. COORDINATED LARS STUDY PROCESS

The LARS process builds off the existing EPR and ERAS processes but improves upon them by integrating planned load with the generation, which enables the identification of more optimal Network Upgrades. If MISO knows a large load is coming, which it will in the LARS process, then MISO can study the load's impacts with greater certainty and reduce the risk of speculative generation or load. By running the generation and load studies in parallel, MISO is able to review constraints identified on both the load and generation sides and can see the impacts to the system with each different configuration. This information can then inform the transmission network upgrades that are solutions for the transmission needs identified in the load and generation studies. MISO can also bring Sugar-developed solutions to the Transmission Owner and Interconnection Customer for coordination.[67]

The goal of LARS is not necessarily to find the lowest cost solution for either the load or generation but to identify the solution that best fits *both* the generation and load needs at the lowest cost. MISO expects LARS to produce more cost-effective solutions that are more efficient for the grid overall.[68] This allows MISO to combine solutions between the load and generation side for more optimal, efficient, and effective responses. MISO can then come up with more effective solutions to help integrate load and generation into the system, which maximizes the benefits of both study processes and reduces integration costs. Thus, as Ms. Drake explains, the LARS process enables MISO to optimize solutions for the transmission grid to reduce costs overall while also maintaining reliability.[69]

The LARS Application must identify a Commercial Operation Date for the Generating Facility and a Load In-Service Date for the LARS Associated Load that is no later than three (3) years from the date the LARS Application is submitted.[70] The load can start receiving service for less than the full amount of transmission service requested (start receiving service in phases), but must commence service for the full amount of transmission service requested in LARS Application no later than the Generating Facility's COD. While the load is operating at less than the full amount of service, the Generating Facility must remain subject to the Annual ERIS ("AERIS") and the Quarterly Operating Limit ("QOL"). Thus, once the LLGIA is executed, some amount of the LARS Associated Load must be in-service before the Generator can come online. The Generator may not come online prior to the LARS Associated Load coming in service.

---

67 MISO uses an integrated modeling software Suite of Unified Grid Analyses with Renewables ("SUGAR"), for Phase 1 and Phase 2 DPP studies with plans to integrate it in Phase 3. The SUGAR software leverages powerful circuit simulation methods developed to study billion-transistor electronic systems. SUGAR reduced DPP phase 1 cycle time significantly from the status quo as evidenced in the DPP 2022, 2023 and 2025 cycles.

68 *See* Drake Testimony at 4.

69 *Id.* at 10-12.

70 *See* GIP Section 3.12.9.

To encourage certainty and facilitate optimized transmission solutions, MISO is requiring that the generation and load commit to remain contractually paired for a minimum of five years at application, which coincides with MISO's planning horizon.[71] This requirement thus enables MISO to rely on the pairing of the Generating Facility and LARS Associated Load in conducting its planning. This application and study processing requirement is separate from the obligation to remain paired for a fifteen-year period. As described below, LARS requires that the generation and load remain paired for a minimum of fifteen years. However, MISO acknowledges that it may be difficult to obtain a commercial agreement for such a period at time of LARS Application submission. Requiring that the commercial agreement specify at least a 5-year term at application allows some flexibility to renew the contract between the paired load and generation during the operational life of the generation and load while still ensuring a significant, upfront commitment to even be studied in the LARS process.

If either the load or generation portion withdraws after the LARS study is completed, the LLGIA is void and non-refundable deposits are forfeited. There will be no restudy with the LARS process. Notably, if either of the parties terminate a LLGIA, withdraw the load after MTEP approval, cease use of the Transmission Service granted through LARS, or terminate their commercial agreement after notice to proceed, the parties will be responsible for all assigned Network Upgrades costs. The Interconnection Customer remains responsible for any identified GIP Network Upgrades and the LARS Associated Transmission Customer remains responsible for any identified BRPs or Other assigned Network Upgrades. Moreover, the LARS Associated Load would then need to be studied through the applicable MTEP process to maintain service.[72]

If the LARS Associated Load is withdrawn, ceases use of the Transmission Service granted through LARS, or the commercial agreement between the generation and the load terminates during the first fifteen years after the date that the LARS Associated load commences use of the Transmission Service granted through LARS, then MISO will terminate the LLGIA after a limited operations transition period and Interconnection Customer would need to obtain new Interconnection Service through the DPP to continue making injections onto the MISO Transmission System.[73] Both the 15-year commitment period and the limited operations transition process are important design features that warrant further discussion.

With respect to the requirement to remain paired and in service for fifteen years, MISO determined that requiring both the Generating Facility and LARS Associated Load to remain in service and retain their relationship provided important safeguards. This requirement ensures that the LARS study process accurately reflects the expected impacts of the Generating Facility and LARS Associated Load on the Transmission System for a significant period of time. It also serves to prevent customers from gaming or otherwise misusing the LARS process to obtain Interconnection Service not intended for long-term service to a specific large load. Along with

---

71 *See* Drake Testimony at 35.

72 *Id.* at 36-37.

73 *Id.*

these considerations, MISO also weighed stakeholders' legitimate concerns that Generating Facilities submitted to LARS in good faith and which in fact served LARS Associated Loads for long periods of time could should not be forced to go offline or undergo a second study process with potentially significant new costs if the LARS Associated Load unexpectedly ceased operations more than a decade into the relationship. Several stakeholders also expressed concerns that a permanent pairing requirement would strand a Generating Facility that had a remaining useful service life even if such Generating Facility could be used—or was needed—to address resource adequacy needs following the departure of the LARS Associated Load. These discussions convinced MISO that that a permanent pairing requirement would not only create significant long-term commercial risk to the LARS Interconnection Customer but that such a risk could create challenges to funding LARS projects that would otherwise be beneficial.

Based on these discussions, MISO considered the implications of several potential time durations for the pairing requirement before determining that a fifteen-year pairing requirement for the generation and load struck the best balance between ensuring LARS was used as intended and enabling long term commercial certainty for Interconnection Customers. MISO reached this conclusion for several reasons. First, fifteen years is a standard duration for large load contracts and thus a fifteen-year commitment aligns with contracting timeframes. Second, fifteen years is a sufficiently extensive period to deter entities from invoking the needs of a specific large load as a pretext to bypass the DPP queue and receive unrestricted Interconnection Service on an accelerated timeline. This positions the DPP as the more flexible and lower risk option for Generating Facilities with all but the firmest long-term relationships with a large load. Finally, the fifteen-year period provides an outer limit on Interconnection Service risk that increases the commercial viability of LARS and avoids the potentially negative resource adequacy implications of imposing a permanent limitation with effects that would become known only beyond the reasonable commercial and planning horizon visible at the time LARS commercial arrangements are made.

With respect to the transition period, MISO will provide the Generating Facility up to one year after the LARS Associated Load withdraws to continue to operate under the LLGIA in order to provide time for the Interconnection Customer to enter the DPP and obtain new NR Interconnection Service.[74] MISO further proposes that this period would be extended for the duration of a DPP cycle if the Interconnection Customer submits an Interconnection Request for DPP processing and remains in such DPP cycle through to GIA. Operations during this transition period would be subject to MISO's Quarterly Operating Limits ("QOL") and Annual ERIS ("AERIS") processes to ensure reliability.[75] MISO developed this transition period to mitigate the impacts to a Generating Facility whose LLGIA must be terminated within the first fifteen Calendar Years after the LARS Associated Load commences use of the Transmission Service granted through LARS. The limited transition period also prevents adverse reliability impacts from operating the Generating Facility without the LARS Associated Load online and is consistent with

[74] *Id.*

[75] *Id.*

the requirement to obtain new Interconnection Service because it provides only a temporary bridge to avoid immediately taking the Generating Facility offline. While MISO fully expects that future DPP cycles will be completed within one year, MISO added the automatic extension as a safeguard against DPP delays. Because the automatic extension only lasts for as long as the Interconnection Customer maintains its Interconnection Request in the DPP and meets the progressively increasing commitments required by that process, this extension would not provide a useful stalling mechanism for Interconnection Customers that is not actively seeking new Interconnection Service.

After 15 years, it is reasonable to allow the Interconnection Service granted through the LLGIA to remain even if the LARS Associated Load subsequently leaves service. This allowance addresses the need for commercial certainty for the Generating Facilities participating in LARS and helps reduce any reliability impacts that may be associated with immediately terminating the LLGIA if the load were to go offline. This also reflects the purpose of LARS as providing a process for formally paired generation and load to be studied together and connect to MISO's Transmission System efficiently and effectively. Ultimately, the outcome of the LARS process is MTEP-approved transmission for reliable load integration into the system, the allocation of LLGIA generation interconnection service, a more optimized set of Network Upgrades within approximately 120-days, and generation/load pair that has agreed to remain paired within same LRZ for a minimum of fifteen years.

III. THE PROPOSED REVISIONS ARE JUST AND REASONABLE

The LARS proposal and its corresponding Tariff changes are just and reasonable. LARS provides a valuable tool to enable the study of LARS Associated Loads that are brought to MISO with a paired generation solution. LARS meets the urgent need for an accelerated evaluation process that accounts for both load and generation, responds to concerns identified in the Show Cause order regarding proximity between large loads and their associated generation, and does not disturb existing DPP processes. The LARS process is not unduly discriminatory to any potential market participant and respects existing roles and responsibilities. LARS brings together several independent MISO processes needed to integrate a new large load. Through the LARS Application, MISO has established a framework that allows different stakeholders to proactively coordinate the addition of these generation/load pairs onto the system. The result is an accelerated process that allows for the integration of generation/load pairs and optimized transmission solutions.

A. LARS COMPLEMENTS OTHER COMPONENTS OF MISO'S LARGE LOAD FRAMEWORK

The need to accelerate reliable power infrastructure is reflected in the DOE's Speed to Power initiative. DOE launched Speed to Power in September 2025 as an effort to accelerate development timelines for large-scale transmission and generation projects and ensure sufficient

power to meet rising electricity demand.[76] On June 18, 2026, the Commission issued the Show Cause Order addressing MISO's Tariff provisions governing the interconnection of large loads.[77] The Commission preliminarily found that aspects of MISO's existing Tariff may be unjust and unreasonable and identified potential reforms concerning the integration of large loads and associated generation.[78] Of particular relevance to LARS, the Commission addressed the absence of generator interconnection procedures and services designed to facilitate the interconnection of generation brought onto the transmission system to serve electrically proximate large loads.[79] The Commission also addressed the electrical relationship between a large load and generation intended to serve that load.[80]

LARS is responsive to the Commission's focus on the coordinated consideration of significant new load and generation. At the July 16, 2026 LLWG meeting, MISO first introduced a new proposal designed to align the study processes for new large loads and generation intended to serve those loads.[81] Certain stakeholders described MISO's proposal as allowing load and generation to be studied in parallel using consistent assumptions, thereby addressing timing mismatches between existing study processes.[82] MISO subsequently developed that concept into LARS and has included it within its broader large load framework. While LARS is an independent, standalone process and does not need the other parts of the framework to proceed as explained by Ms. Drake, it is complementary to other proposals in MISO's large load framework.[83] While the ZGIA process addresses the generator interconnection service and study framework for generation serving co-located load, LARS will address the distinct study issues presented by new generation and large load that are electrically proximate but are not eligible for ZG Interconnection Service.

LARS is intended to work in concert with MISO's broad large load framework by facilitating the coordinated study of qualifying large load additions and associated generation while

---

76 DOE, *Speed to Power Initiative* (Sept. 18, 2025) (describing Speed to Power as an initiative to accelerate development timelines for large-scale transmission and generation projects to meet rising demand for reliable and secure energy).

77 *Midcontinent Indep. Sys. Operator, Inc.*, 195 FERC ¶ 61,212 (2026) ("Show Cause Order").

78 *Id.*

79 *Id*. at P 117 (expressing concern that the absence of such procedures and services could result in MISO's generator interconnection process failing to keep pace with new large loads seeking to integrate onto the MISO transmission system).

80 *Id.* at P 113-119.

81 *See* MISO, LLWG, *Generation and Large Load Alignment*, LLWG-2026-6 (Jul. 16, 2026), available at: https://cdn.misoenergy.org/20260716%20LLWG%20Item%2006b%20Generation%20and%20Load%20Alignment%20Presentation768740.pdf.

82 *See* MISO, LLWG, *Generation and Large Load Alignment*, LLWG-2026-6, Stakeholder Feedback (July 30–31, 2026) (including stakeholder feedback supporting an integrated process for studying load and generation in parallel and addressing timing mismatches between existing processes), available at: https://www.misoenergy.org/engage/stakeholder-feedback/2026/llwg-generation-and-large-load-alignment-llwg-2026-6-20260716/.

83 *See* Drake Testimony at 8.

maintaining appropriate limitations on the rights available to generation that has not completed MISO's ordinary Generator Interconnection Queue process.[84] The preservation and protection of the DPP process was an express consideration in the LARS stakeholder process. Stakeholders have raised questions regarding how LARS generation will interact with generation already progressing through the ordinary Generator Interconnection Queue and the protections necessary to avoid adversely affecting existing Interconnection Customers.[85] The transmission capacity headroom available at the beginning of the DPP cycle is still available the end of the cycle and is not impacted by the LARS Applications.[86] Similarly, the transmission capacity headroom for the LARS models are separate and distinct as they start with different MTEP base models and the LARS models are not inclusive of generation without executed GIAs. The models from LARS and the DPP process will be reconciled through MTEP.[87]

In addition to ZGIA and LARS, MISO is working with stakeholders through the LLWG on additional initiatives that will address the other concerns raised by the Show Cause Order. MISO has introduced several of these initiatives at the LLWG meetings and many have specific details that are still being worked out with stakeholders. These additional initiatives and proposals will be evaluated through the LLWG through the fall and will ultimately be presented to the Commission in separate FPA section 205 filings by November 16, 2026.

B. ADDRESSING FERC'S SHOW CAUSE ORDER: ELECTRICALLY PROXIMATE REQUIREMENT

MISO continues to advance a coordinated set of solutions designed to balance speed to power, fairness, and, most importantly, reliability. In particular, MISO has developed solutions that are responsive to the Commission's concerns noted in the Show Cause Order surrounding the interconnection and study processes for co-location arrangements, large load reliability requirements, and now is addressing the need for service of proximate large loads. MISO has developed LARS against this backdrop of its broader efforts to address the reliable integration of large loads and associated generation. MISO developed the ZGIA process through the LLWG with express consideration of resource adequacy, markets, and reliable operations.[88] The LARS offers more flexibility in the siting of the load/generation pair to maximize the effectiveness of any transmission solutions developed. Thus, the ZGIA process will be utilized to meet the co-located

---

84 *See id.* at 7-8.

85 *See* MISO, LLWG, *Large Load Addition Resource Study*, LLWG-2026-6, Stakeholder Feedback (Sept. 9, 2026) (reflecting stakeholder comments concerning the relationship between LARS and the existing Generator Interconnection Queue).

86 *See* Drake Testimony at 32-33.

87 *See id.*

88 ZGIA Filing at 5-6.

portion of the Order and LARS will address the electrically proximate large load portion of the Order, by pairing generation with large load in the same LRZ.

In its Show Cause Order, the Commission found that MISO's Tariff "appears to be unjust and unreasonable" because it did not contain provisions allowing an interconnection customer to serve "an electrically proximate large load."[89] The Commission defined electrically proximate large load to mean a large load "that is sufficiently electrically close to the interconnection customer's requested point of interconnection, such that the impact on the transmission system of the combination of the generating facility and the load, with the exception of the transmission facilities between the two, will be effectively the same as if they were located at the same substation (e.g., large load that is located no more than two substations away from the generating facility)."[90] The Commission then stated that it would consider proposed revisions to this definition to "ensure it is appropriately tailored to MISO's transmission system."[91] Per this invitation, MISO is now proposing revisions that address the Commission's concerns related electrically proximate generation and load pairs as part of a broader regionally-tailored framework.

LARS establishes the Tariff structures necessary to enable an Interconnection Customer to serve an electrically proximate load under study processes that reflect the interaction between generation and load. In MISO, anchoring the proximate requirement with the LRZ is more efficient and effective because it aligns with MISO's existing resource adequacy construct and enables more generation to serve a single load across a broader area but in a manner that still addresses resource adequacy and reliability of the system. MISO did not want to limit the pairing of generation with associated load to a specific number of substations because that is likely too geographically narrow and could limit how MISO may optimize common transmission solutions. Moreover, allowing Generating Facilities participating in LARS to interconnect at multiple POIs provides a "proximate plus" solution for the pairing of load with generation. This provides Interconnection Customers with the necessary flexibility to serve extremely large loads and in way that MISO can optimize any necessary transmission solutions. As Ms. Drake explained in her testimony, "[u]ltimately, limiting the generation and LARS Associated Load to locations within the same LRZ ensures deliverability of the generation to the LARS Associated Load because it avoids potential capacity import / capacity export limitations for the individual LRZ and also avoids price separation between the paired generation and LARS Associated Load."[92] This structure also reflects stakeholder feedback regarding the need to accommodate the interconnection of large, landlocked loads that may need additional POIs.

The LARS process was designed to produce optimized load-and-generation Network Upgrades, which aligns with the intent of the Show Cause Order and the proximate generation requirement. Requiring the load and the generation to be located in the same LRZ provides the necessary proximity while also providing sufficient flexibility to enable LARS to be a successful

---

89 Show Cause Order at P 113.

90 *Id.* at P 112.

91 *Id.*

92 Drake Testimony at 40-41.

process.[93] MISO is confident that LARS is a beneficial addition to its large load framework, differentiated from the co-location requirements of the ZGIA process, and provides another just and reasonable way for large loads to connect to the grid. Accordingly, LARS intends to provide a resource solution associated with significant new demand without establishing an unrestricted alternative to MISO's ordinary generator interconnection process. Together with the ZGIA framework, LARS provides MISO with an additional mechanism to facilitate the development of resources needed to support significant new load growth while maintaining reliability and appropriate protections for existing Interconnection Customers.

IV. DESCRIPTION OF PROPOSED TARIFF REVISIONS

To implement the LARS process proposed herein, MISO is requesting approval of new Tariff provisions, as well as revisions to several existing provisions.[94]

A. Attachment X (Generator Interconnection Procedures).

The proposed Tariff revisions implement the LARS process and are necessary to distinguish the key differences in how the LARS study process and the resulting LLGIA will operate in comparison to MISO's standard three-phase generator interconnection queue. For convenience, MISO discusses the revisions to the GIP by section, below.

1. Section 1: Definitions

Section 1 contains definitions that are used throughout the GIP and its supporting attachments. MISO is proposing both to add several new terms and definitions to Attachment X, as well as to revise the definition of several existing terms. The proposed new definitions are necessary to implement the LARS process and to provide clarity and consistency throughout the GIP. MISO proposes the following revisions to existing definitions in Attachment X:

> **Interconnection Customer** shall mean any entity, including Transmission Provider, Transmission Owner or any of the Affiliates or subsidiaries of either, that proposes to interconnect its Generating Facility with the Transmission System. For the purposes of Large Load Addition Resource Study (LARS), Interconnection Customer shall refer to the entity developing the Generating Facility that will execute the LLGIA, which may be a different entity from the LARS Associated Transmission Customer that submitted the LARS Application.
>
> **Interconnection Request** shall mean (1) an Interconnection Customer's request, in the form of Appendix 1 to the Generator Interconnection Procedures, to interconnect a new

[93] *Id.* at 39-40.

[94] This transmittal letter frequently quotes proposed Tariff revisions to facilitate its explanation. In the event of a conflict between the Tariff language as discussed in this letter and that reflected in the attached Tariff sheets, MISO intends that the language in the attached Tariff sheets control.

Generating Facility, or a request for the Expedited Resource Addition Study for a new generation capacity, or a request for the processing of a proposed Generating Facility as part of a Large Load Addition Resource Study, or to increase the capacity of, or make a Material Modification to the operating characteristics of, an Existing Generating Facility that is interconnected with the Transmission System, or to interconnect an Existing Generating Facility that is external to the Transmission System, or to change Energy Resource Interconnection Service to Network Resource Interconnection Service for an Existing Generating Facility; or (2) an MHVDC Connection Customer's request, in the form of Appendix 1 to the Generator Interconnection Procedures, to obtain Injection Rights.

Party or Parties shall mean Transmission Provider, Transmission Owner, Interconnection Customer, LARS Associated Transmission Customer, or any combination of the above.

These changes are necessary to properly document that LARS projects will be studied separately from MISO's generator interconnection queue and will require a separate election in Appendix 1 to the GIP ("Interconnection Request for a Generating Facility") to be studied as a LARS project. MISO proposes these revisions to ensure that the LARS process is included in the Interconnection Request procedures and to clarify that the Interconnection Customer in the LARS process may not be the same entity that is the Transmission Customer or Transmission Owner.

MISO also proposes the following new definitions for addition to the GIP (and LLGIA):

Large Load Addition Resource Study (LARS) shall mean the procedure as set forth in Section 3.12 of this GIP for studying a Interconnection Customer's proposed Generating Facility in parallel with the study of a LARS Associated Load Customer's proposed load.

Large Load Addition Resource Study (LARS) Period shall mean the period of time in which Interconnection Requests for proposed Generating Facility are studied in parallel with the study of a LARS Associated Load Customer's proposed load. There are three LARS study periods in one year and each study period will run for approximately 120 days. All Interconnection Customers requesting to join the next Large Load Addition Resource Study (LARS) shall submit their Interconnection Request to the Transmission Provider no later than the LARS application deadline as published on the MISO public website, which shall be at least twenty (20) Business Days prior to the scheduled kick-off of the LARS cycle published on the MISO public website.

These definitions are necessary to describe the study that MISO will conduct for a generation/load pair in the same process. These definitions also establish that LARS will be conducted three times per year and provides the timing requirements of when the LARS Applications must be submitted to MISO to be included in the LARS process.

Large Load Generator Interconnection Agreement (LLGIA) shall mean the form of interconnection agreement governing the terms and conditions of Large Load Interconnection Service, set forth in Appendix 6 to the GIP. This agreement shall follow

> the form of the Transmission Provider's *pro forma* Generator Interconnection Agreement with modifications to reflect the Large Load Addition Resource Study process. Unless otherwise provided in the GIP, all requirements applicable to the *pro forma* Generator Interconnection Agreement shall apply to the LLGIA. A LLGIA is a form of GIA and, where used in the Tariff, references to Generator Interconnection Agreements or GIAs encompasses LLGIAs.

MISO proposes the above definition for the *pro forma* agreement that would be tendered to an Interconnection Customer at the conclusion of the LARS process. MISO notes that the LLGIA is closely based on the MISO's *pro forma* GIA in Tariff Attachment X, Appendix 6 with modifications as described below. MISO includes the last sentence of this definition to avoid any confusion and clarify that the numerous references in other sections of the Tariff to GIAs include LLGIAs by default.[95]

> **LARS Application** shall be a single submission consisting of the materials required for LARS processing as required by Section I.D.1.b.ii of Attachment FF to the Tariff as well as the information required for studying the Generating Facilities under this Attachment X (in the form of Appendix 1) to these generator interconnection procedures. For purposes of this GIP, a LARS Application shall be a form of Interconnection Request.

MISO is adding this defined term to the Tariff provides the vocabulary needed for discussing all of the pieces of information that must be supplied to MISO in a single submission prior to participating in the LARS process.

> **LARS Associated Load** shall mean a source of electrical load that is at least 200 MW and that is formally paired with one or more Interconnection Customer(s) that have submitted an Interconnection Request to LARS proposing one or more new Generating Facility(ies) to provide energy to such load.

> **LARS Associated Transmission Customer** shall mean the entity that is responsible for submitting the LARS Application and procures Transmission Service in order to serve LARS Associated Load and designates such load as formally paired with an Interconnection Customer's LARS Interconnection Request.

Adding these defined terms to the Tariff provides the vocabulary needed for discussing the specific load that a Generating Facility with a LLGIA is limited to serving and to identify the entity responsible for submitting the LARS Application.

---

[95] MISO has built its LLGIA Tariff sheets using the latest effective version of Appendix 6 to Attachment X of the Tariff. This does not include the ZGIA revisions currently housed in Appendix 19, which are pending before the Commission in Docket No. ER26-3552-000 or MISO's revisions submitted in compliance with Order No. 2023, which remains pending before the Commission in Docket No. ER24-2046-003. MISO has used this approach for version control and administrative reasons. MISO commits to reconcile these versions as appropriate once they are accepted.

2. Section 2.1—Application of Generator Interconnection Procedures

MISO proposes to add a subsection k to GIP Section 2.1 that governs the application of interconnection procedures. This subsection explains that a request for LARS should be evaluated according to the procedure in GIP Section 3.12, which is a new Section MISO proposes to add for the implementation of the LARS process. This addition is necessary to distinguish the process for evaluating requests for LARS from other projects entering MISO's generator interconnection queue.

3. Section 3.3.1—Valid Interconnection Request

MISO proposes to revise Section 3.3.1, which encompasses the procedures for submitting an Interconnection Request. The revisions include clarifying language surrounding the timeline for submitting LARS Applications to MISO and where the application timeline will be posted on the MISO website. MISO also proposes to increase the Non-Refundable Deposit 1 (D1) to $250,000 for LARS projects and to require an entry milestone (M2) of $30,000 per Megawatt for new Interconnection Service requested to ensure only projects that are "shovel ready" and commercially viable apply to LARS.

To further demonstrate that a project is "shovel ready," all documentation, milestone payments, deposits and any necessary data is required at the time of LARS Application submission. These up-front requirements will allow MISO to complete the study process within its estimated 120-day timeframe. MISO also proposes to require that LARS projects have a Commercial Operation Date within three calendar years from the date of the Interconnection Request and the LARS Associated Load will have an identical anticipated Service Commencement Date. All LARS projects are eligible to use the grace period of up to three years as documented in GIA Article 2.3.1.

4. Section 3.5.1.1—Inclusion in a JTIQ Screening Group, JTIQ Participation Group, and JTIQ Commitment Group

MISO proposes to revise GIP Section 3.5.1.1 subsection (1) to clarify that LARS projects shall be included in a JTIQ Screening Group, along with projects in the generator interconnection queue. As discussed in prior stakeholder meetings, MISO intends to consider LARS projects for JTIQ. This revision is necessary to ensure that LARS projects are properly included in JTIQ Screening Groups along with projects from MISO's DPP interconnection queue.

5. Section 3.5.4—Affected Systems Coordination Procedures to Interconnection Requests Included in a Large Load Addition Resource Study

MISO proposes new Section 3.5.4 governing coordination with affected systems in the evaluation of Interconnection Requests participating in LARS. Proposed Section 3.5.4 closely follows the affected systems coordination procedure accepted for ERAS Interconnection Requests. Specifically, proposed Section 3.5.4 provides that MISO will apply the same coordination

procedures and screening criteria as that used for Interconnection Requests in the DPP. MISO submits that these rules are appropriate because they provide a structure for processing Interconnection Requests for LARS rapidly and in a manner that recognizes the serial nature of such studies. Requiring LARS Interconnection Customers to execute LLGIAs where affected systems information has not yet been provided is necessary to maintain the accelerated speed of the LARS process and to provide certainty to LARS Interconnection Requests in subsequent LARS study periods whose models will be built from the prior completed study. MISO will work with its AFS partners to accelerate the AFS study process of any projects participating in LARS.

6. Section 3.12—Large Load Addition Resource Study

MISO proposes to add new GIP Section 3.12 to encompass the necessary processes and implementation details for the LARS process. LARS provides a single application and study process that produces an optimized set of Network Upgrades in 120 days for any large load and generation pair that meet the requirements set out in this section.

7. Section 3.12.1 – Pre-Submission Coordination Process

Proposed Section 3.12.1 explains the pre-coordination procedures required for parties to a LARS Application. The purpose of this new section is to build in a coordination and collaboration process into the LARS timeline. Since a LARS Application requires information from a wide variety of parties, a viable application requires that the parties have met and agreed on key details before submitting the required materials to the LARS process. These agreements will ensure that all the parties agree on the POI for the Generating Facility(ies), avoiding post-submission withdrawals and enabling MISO to complete the LARS studies on an accelerated basis.

First, the revisions state that the LARS Associated Transmission Customer initiates and submits the LARS Applications with support from the Interconnection Customer on the generation side and the Transmission Owner on the load side.

Second, the proposed language explains the timeline for when Interconnection Customers looking to participate in LARS must contact the Transmission Owner to request a meeting to determine the POI for the Generating Facility. Interconnection Customers must request this meeting at least 45 calendar days prior to a LARS Application deadline. The Transmission Owner is then required to meet with the Interconnection Customer and any other impacted parties within 10 business days. Following the meeting to discuss an agreed-upon POI for the Generating Facility, the Tranmission Owner will have at least 15 business days to provide an attestation for the LARS Application, which will state that the parties have agreed upon a definitive POI. This last provision is needed to avoid leaving the Transmission Owner with too little time to make the attestation.

8. Section 3.12.2

MISO proposes to add new GIP Section 3.12.2 to explain the requirements for participating in the LARS process.

First, MISO proposes to require the LARS Associated Transmission Customer and the potential LARS Interconnection Customer to provide an executed agreement evidencing that the output of the Generating Facility for which LARS processing is sought is intended to be used to provide energy to the LARS Associated Load. The proposed language is as follows:

> A LARS Application for processing through the Large Load Addition Resource Study must meet the requirements listed in Section 3.3.1 above, plus the following requirements:
>
> i. The Interconnection Request shall be accompanied by an agreement executed by the Interconnection Customer and either the LARS Associated Transmission Customer or the entity that owns or controls the LARS Associated Load evidencing that the output of the Generating Facility for which LARS processing is sought shall be used to provide energy to the LARS Associated Load. Such agreement shall take one of the following forms and state a minimum term of at least five (5) years to align with MISO's transmission planning horizon as described in Section I.D.1.b.ii of Attachment FF to the Tariff:
>
> a. A power purchase agreement (PPA) or similar off-take agreement between the Interconnection Customer submitting the Interconnection Request for LARS processing and the entity with the LARS Associated Load to be served (including, but not limited to, an Alternative Retail Electric Supplier or its Load Serving Entity); or
> b. An agreement that calls for the Interconnection Customer to develop the Generating Facility described in the Interconnection Request and subsequently transfer ownership or control of such Generating Facility (Build-Own-Transfer Agreement) to the entity with the LARS Associated Load to be served (including, but not limited to, an Alternative Retail Electric Supplier or its Load Serving Entity); or
> c. For Load Serving Entities (or an Alternative Retail Electric Supplier or equivalent in a retail choice state), evidence of other types of agreements that provide that the generation is intended to serve the LARS Associated Load customer. These agreements include, but are not limited to, a special contract, a large load tariff agreement, or retail service agreement.

This requirement is necessary both to prevent speculative Interconnection Requests, and to verify that the LARS Associated Load intends to use the output of the Generating Facility. The agreement may take several forms, as documented in Section 3.12.2, depending on the type of project and associated parties. This language is intended to limit LARS projects to those that have been formally paired together, while also ensuring that certain business models and agreements are not excluded from participating in LARS.

Second, MISO proposes to require any Interconnection Request submitted as part of a LARS Application include documentation demonstrating that the Electromagnetic transient ("EMT") modeling requirements have been met for inverter-based resource ("IBR") generation as specified in MISO's BPM. Including the specific technical data needed in the BPM is consistent with requirements for other types of Interconnection Requests and provides needed flexibility to update specific technical details as MISO and its stakeholders gain experience with new kinds of Interconnection Service Requests.

Third, MISO proposes to require that any Interconnection Request submitted as part of a LARS Application Demonstrate 100% site control including 100% generator and Interconnection Customer Interconnection Facility ("ICIF") site control. This is to ensure that truly "shovel-ready" projects apply to participate in LARS and reduces the risk of withdrawals later in the process.

Fourth, MISO proposes to require that any Interconnection Request submitted as part of a LARS Application include a one-line diagram showing the Generating Facility and associated electrical equipment. MISO also proposes to require a detailed power flow model for the proposed Generating Facility that includes the POI and any proposed system protection facilities. Because LARS Generating Facilities are restricted to serving a specified load, the LARS Associated Load, submission of detailed and accurate one line diagrams and power flow models showing both the Generating Facility, the LARS Associated Load, protection facilities, and their configuration with respect to the Transmission System is critical to accurately studying how a proposed LARS Generating Facility will interact with the Transmission System and to ensuring limited impacts. In addition, it is essential to document this configuration in the resulting LLGIA because the results of the LARS study will depend on the proposed configuration remaining as proposed.

Sixth, MISO proposes to require that any Interconnection Request submitted as part of a LARS Application request NRIS in an amount that is at least 200 MW (the minimum threshold for a LARS Associated Load) and in an amount that is not more than 150% of the peak Demand of the LARS Associated Load. The LARS Application must include the LARS Associated Load's expected peak demand over any one-hour period. This will allow MISO to know what the total amount of MW demand is expected from this load and ensure that the total amount of requested Interconnection Service by the Generating Facilities does not exceed 150% of that peak demand amount. These requirements strengthen the connection between the Generating Facility and the LARS Associated Load in such a manner as to consider them formally paired. Allowing a Generating Facility to serve up to 150% of the load's peak demand also allows for more flexibility in the kinds of generation that may participate in LARS.

MISO also proposes to require that the LARS Associated Load and any paired Generating Facilities be located in the same LRZ. In order to address the Commission's desire for large loads to have the option to be located electrically proximate to generation, MISO is proposing to expand the concept of "electrically proximate" to the LRZ and not limit it to a pre-determined number of substations. This serves two purposes. First, this allows load and generation to site near each other in a flexible way that will also optimize any common transmission solutions. Second, placing the electrically proximate requirement within the LRZ construct aligns LARS with MISO's existing resource adequacy construct.

Seventh, MISO is establishing three-year deadline for a Generating Facility's Commercial Operation date and requiring that the LARS Associated Load reach its full-service amount in the same amount of time. This provision provides the flexibility needed to enable both the generation and load to come online at roughly the same time while also providing a deadline by which they both must be fully operating on MISO's system. The Commercial Operation Date provisions follow those applicable under MISO's standard process. The requirement to specify an analogous date for the LARS Associated Load preserves and reinforces the linkage between the Generating Facility and the LARS Associated Load that underpins the LARS study.

Eighth, MISO is proposing to include a provision that would allow Interconnection Customers participating in LARS to elect the option to build. Notably, MISO is requiring that the Interconnection Customer include that election at the time of submission of the LARS Application and MISO will not accept future elections for the option to build after the LARS Application is submitted. This is to ensure certainty for MISO study processes and so that the proper internal administrative timelines can be established upon the submission of the LARS Application.

Ninth, MISO proposes to add provisions to allow a LARS Associated Load to be served by multiple Generating Facilities. The proposed revisions are as follows:

> A LARS Associated Load may be served by multiple Generating Facilities provided that:
> 1. All Generating Facilities serving a LARS Associated Load behind the same Point of Interconnection must be identified in the LARS Application for the specific LARS Associated Load and must request a minimum of 200 MW of Interconnection Service in the aggregate; or,
> 2. Multiple Generating Facilities serving a LARS Associated Load may be located behind different Points of Interconnection provided that they:
>   a. Be located in the same LRZ as the LARS Associated Load,
>   b. Request a minimum of 200 MW of Interconnection Service for all Generating Facility(ies) behind a separate Point of Interconnection; and,
>   c. Be submitted as a separate LARS Application for the amount of demand of the LARS Associated Load it will serve through that Point of Interconnection.

MISO made this change in response to stakeholder requests to allow multiple POIs for generation located within the same LRZ as the LARS Associated Load. This revision allows multiple generators to aggregate behind a single POI to serve one LARS Associated Load. Due to the size of some of the large loads that are looking to connect to the system, allowing Generating Facilities to aggregate to supply for the large load is efficient. Adding the requirement that the Generating Facilities contained in a single LARS Application be sited behind a single POI enable MISO to adequately study the load with the requested generation. The requested minimum of requested Interconnection Service by the Generating Facilities must be at least 200 MW at each POI and generators can aggregate to reach that minimum. A LARS Associated Load may be served by several different groups of Generating Facilities at multiple POIs. To assist MISO with keeping track of the LARS Associated Load and its paired Generating Facilities, a LARS Application must

be submitted for each POI group of Generating Facilities. Thus, a LARS Associated Load should have a LARS Application for each POI where generators are serving it.

Tenth, MISO proposes to add language stating that no changes shall be made to the LARS Application, including any underlying Interconnect Requests, after submission. The proposed revisions are as follows:

> No changes shall be made to the LARS Application after submission and prior to the execution or the unexecuted filing of the LLGIA and MTEP approval for the LARS Associated Load except that a LARS Application that is deferred to the next available LARS Study Period will be allowed to extend its In-Service Date or Commercial Operation Date to be no more than three calendar years from the kickoff of the LARS Study Period in which its LARS Application is studied.

Because the timeline from submission to an executed LLGIA is 120 days, this proposed language is necessary to ensure that LARS projects are studied expeditiously and can be online as soon as possible to meet the stated resource adequacy and/or reliability need. To make this timeframe workable and avoid delays that would impact other Interconnection Customers, it is necessary to require that these Interconnection Services be well-considered and provide certainty with respect to the details to be studied at the time they are submitted. This readiness requirement is mitigated by the fact that MISO will complete the LARS study process three times per year. Therefore, an Interconnection Customer that is not certain of the details to be included in its Interconnection Request for the LARS Application would only need to wait until the following LARS study period for another opportunity to participate. Moreover, MISO has included language that will allow LARS applicants to change their COD or In-Service Date if their LARS Application is pushed to a later LARS study period.

Eleventh, MISO proposes a paragraph to allay concerns expressed during the stakeholder process that LARS could be read as conflicting with state and local laws by allowing the owner of a generator that is not a Load Serving Entity to serve load when not authorized to do so by state law. The inclusion of this language neither imposes, nor is intended to impose, any independent restrictions on an Interconnection Customer.

Finally, MISO proposes to limit the period of review to identify deficiencies in LARS Applications to a single period for MISO and to limit the period for curing the identified deficiencies to a single period for the LARS applicants. This will ensure that the study process remains on track and timely as it avoids multiple review and cure periods for MISO and the LARS participants. If the LARS Application is not cured within the one allotted cure time period, then it will be automatically withdrawn from LARS with any associated penalties.

9. Section 3.12.3 – Evaluation Process for Large Load Addition Resource Study Interconnection Request

MISO proposes to add GIP Section 3.12.3 to facilitate the evaluation process of projects seeking to use LARS and limits the number of generation/load pairs to be studied to ten per LARS

study cycle. The proposed language explains that projects will be evaluated in the order in which they are submitted. Proposed language also clarifies that if the project is found to be ineligible for LARS, the project will lose its Non-Refundable Deposit D1. The risk of losing a large deposit if determined to be ineligible for LARS will encourage parties to only submit projects that they are certain will meet the strict LARS requirements. This requirement addresses MISO's need for certainty on transmission needs and their associated costs.

Proposed Section 3.12.3 also documents the process for projects currently in the DPP process to transfer to LARS for evaluation. In the situation where a project in the generator interconnection queue is eligible to participate in LARS, proposed language clarifies that the project will forfeit its Non-Refundable Deposit D1 and will be subject to withdrawal penalties per Sections 7.6.2.1.1 and 7.8. This proposed addition is necessary to ensure that projects dropping out of the generator interconnection queue do not harm remaining projects in their respective cycles. Similarly, proposed language in Section 3.12.3 limits projects from leaving the generator interconnection queue to LARS to only those that have not reached Decision Point II. This language is required to ensure that projects remaining in the generator interconnection queue are not harmed by restudies that occur after projects drop out after Decision Point II.

10. Section 3.12.4 – The Study

MISO proposes to add a new GIP Section 3.12.4 to describe the studies that will take place for LARS generation projects. The proposed revisions are as follows:

> The Interconnection Study for LARS will follow the same manner of NR Interconnection Study as noted in Sections 3.2.1.2 and 3.2.2.2 needed to integrate the Generating Facility in the same manner as for any Generating Facility being designated as a Network Resource. Transmission Provider will use Reasonable Efforts to study LARS Interconnection Requests from all Interconnection Customers regardless of Generating Facility within sixty (60) Calendar Days after the kickoff date for such study. The study will be performed for each Interconnection Request, including the LARS Associated Load, individually in a serial fashion based on their submission date per LARS Study Period. The LARS interconnection study will result in a Final LARS System Impact Study and any associated LARS Interconnection Facilities Studies.
>
> Transmission Provider shall include in the final study any Affected System Study results and information regarding Network Upgrades from Affected Systems provided the Affected System Study Reports are available. If Affected Systems analysis is not available for inclusion in the final LARS study, the Transmission Provider shall provide such analysis separately when received from the applicable Affected System.
>
> Mitigations developed to address violations observed in only the transmission studies shall be assigned Baseline Reliability Projects (BRP) or Other project types. Mitigations developed to address common violations observed in both the

> transmission study and the generation study shall be assigned Baseline Reliability Projects (BRP) or Other project types. Mitigations developed to address violations observed only in the generation study shall be assigned to the LARS Interconnection Customer under the Generator Interconnection Project (GIP) project type.

This proposed section implements the alignment of the load and generation study process and describes the generation study side of LARS. The transmission and generation studies remain separate but run in parallel and conclude at approximately the same time. This language is necessary for LARS Applications to be evaluated on a rolling basis during each LARS study period. The studies will be performed serially, based on submission date. Serial studies are ideal for LARS projects since there will be a considerably smaller number of proposed LARS generation/load pairs per year. On the generation side of the LARS study process, each generation/load pair will be studied individually in a serial fashion in their own model.

Proposed language in this section also explains that any Affected System Study results, if available, will be included at the time of the final LARS study. If the Affected System Study results are unavailable at the time of the final study, those results will be provided separately when received from the applicable Affected System.

Finally, the proposed language at the end of Section 3.12.4 addresses how mitigations developed to address violations will be assigned depending on where they were observed. If they were only observed in the load side study of LARS, then they will be assigned BRPs and Other project types. If mitigations were developed to address violations observed in both the generation and load studies, then they will be assigned BRPs and Other project types. And finally, any mitigations developed to address violations observed that were caused *only* in the generation study will be assigned to the Interconnection Customer under the Generator Interconnection Project ("GIP") project type.

11. Section 3.12.5 – Notice to Proceed to LLGIA

MISO proposes to add the following Section 3.12.5, which is titled Notice to Proceed to LLGIA. This proposed language is necessary to distinguish between the shorter timeline for LARS and the general timeline for providing a notice to proceed for a DPP interconnection project. The shortened five Business Day timeline is necessary to allow Customers to execute their LLGIA within approximately 120 days from kickoff of the LARS study period.

12. Section 3.12.6 – GIA for Large Load Addition Resource Study Projects (LLGIA)

Proposed GIP Section 3.12.6 governs the timeline and necessary requirements regarding tender of the draft *pro forma* LLGIA and JTIQ applicability, and also points to Sections 11.1 through 11.4 of the GIP governing procedures such as MISO's tender of the draft LLGIA, negotiations, and execution of the LLGIA. This proposed Section provides a five Business Day

timeline for MISO to tender a draft *pro forma* LLGIA after receiving notification of the Interconnection Customer's intent to proceed to LLGIA.

Due to the varied nature of MISO's and SPP's processes related to JTIQ Service Agreements, proposed revisions provide a path forward for JTIQ eligible LARS projects if SPP's JTIQ Service Agreement has not been provided to the Interconnection Customer prior to the tender of the draft LLGIA. If the SPP JTIQ Service Agreement has not been received at the time of MISO's tender of the LLGIA, proposed language requires JTIQ eligible LARS projects to include a milestone in GIA Appendix B requiring the parties to execute or request the unexecuted filing of an SPP JTIQ Service Agreement within 15 Calendar Days after such agreement has been tendered to the Interconnection Customer. Proposed language also states that LARS Interconnection Requests included in a JTIQ Participation Group shall adhere to all JTIQ procedures and execute JTIQ Service Agreements as applicable.

13. Section 3.12.7 – Large Load Addition Resource Study Refunds

Proposed GIP Section 3.12.7 and its subparts document the process for obtaining refunds of study deposits and milestone payments in the LARS process.

Proposed GIP Section 3.12.7.1 governs applicable refunds of the Study Deposit (D2). As with generator interconnection requests, LARS D2 study deposit amounts are based on Megawatt amount of new Interconnection Service of the LARS project as stated in GIP Section 3.3.1. The Interconnection Customer will be charged the actual amount of the Large Load Addition Resource Study and will be required to pay any additional costs or will be refunded any overages as applicable.

Proposed GIP Section 3.12.7.2 details the process for receiving a refund of the LARS milestone payment M2. LARS projects are eligible to receive a 100% refund of M2 upon withdrawal prior to execution of the LLGIA. If a LARS project withdraws after execution of the LLGIA, the project is only eligible to receive a refund of any remaining M2 milestone after meeting the Initial Milestone Payment and/or Network Upgrade costs memorialized in the LLGIA.

Should a project withdraw after execution of the LLGIA, the proposed Section 3.12.7.3 documents the process for providing the initial payment to the Transmission Owner, which will occur within forty-five Calendar Days from the effective date of the LLGIA. If the M2 provided by the Interconnection Customer exceeds the initial payment amount, MISO will provide a refund of any remaining M2 within 45 Calendar Days of the effective date of the LLGIA. If the Interconnection Customer's M2 is less than the initial payment, the proposed language of 3.12.7.3 requires the Interconnection Customer to provide the remaining portion of the initial payment to the Transmission Owner.

The proposed language in Section 3.12.7.4 describes what happens when the LLGIA is terminated or the large load is withdrawn from the LARS process before or after the minimum fifteen-year pairing period has passed. The proposed language in the first paragraph is as follows:

> In the event that the Interconnection Customer's LLGIA is terminated after execution by all parties or after LLGIA is filed unexecuted, the Interconnection Customer will be responsible for the costs of the Network Upgrades that are classified as GIPs and documented in the LLGIA and/or corresponding FCAs or MPFCAs, including those GIP Network Upgrades arising from the Affected System Study process. The Interconnection Customer will be responsible for Network Upgrades resulting from a LARS Study that are classified as GIPs under Attachment X. To the extent the generator fails to commence operation or retires, the load may go through MTEP and during that transition may be subject to similar limitations if the load's Service Commencement Date is prior to the date LARS Generating Facility commences commercial operation.

The purpose of this language is to clearly establish that the Interconnection Customer is responsible for all assigned Network Upgrades that are classified as GIPs identified in the LLGIA. MISO is proposing this language to ensure that whether or not the LLGIA is ultimately terminated or filed unexecuted, the Interconnection Customer is on the hook for the costs associated with its proposed project. This is necessary to clearly assign responsibility to the Interconnection Customer and to protect other market parties from paying for those costs. The language also clarifies what will happen to the LARS Associated Load if the Generating Facility fails to commence operations or retires completely.

The next paragraph of Section 3.12.7.4 addresses these permutations in the following language:

> In the event that the LARS Associated Load is withdrawn from LARS or ceases use of the Transmission Service granted through LARS within the first fifteen (15) Calendar Years after the LARS Associated Load commences use of the Transmission Service granted through LARS, then operations of the Generating Facility shall be subject to the Annual ERIS ("AERIS") and the Quarterly Operating Limit ("QOL") for a one year period until termination as set forth in Article 2.3.1 of the Attachment X Appendix 6. An Interconnection Customer that desires to continue injections shall be required to obtain Interconnection Service through the DPP as described in Attachment X. The LLGIA will be terminated after the period specified in Article 2.3.1. Following the first fifteen (15) Calendar Years after a LARS Associated Load ceases use of its Transmission Service or if the agreement required by GIP Section 3.12.2.i is terminated or otherwise ceases to be in effect, then Transmission Provider shall not terminate the Generating Facility's Interconnection Service.

Since the successful operation of LARS is dependent on the formal pairing of both the generation and load for fifteen years, MISO has proposed Tariff language to address different permutations of what happens if the generation were to stop operating or the load were to stop accepting Transmission Service within the first fifteen years.

If the LARS Associated Load ceases service within the first fifteen years, then the Generating Facility will have up to one year to acquire new Interconnection Service. MISO added this provision in response to stakeholder concerns that the termination of the relationship between the LARS Associated Load and the Generating Facility (either through termination of their agreement or the LARS Associated Load discontinuing operations) could leave an otherwise useful Generating Facility suddenly without Interconnection Service and unable to serve other Load needs. If the LARS Associated Load withdraws from LARS in the first fifteen years, then its paired Generating Facility will be subject to AERIS and the QOL processes and will have up to one year to obtain Interconnection Service through the MISO DPP process. If the Generating Facility is unable to obtain new Interconnection Service within one year, then the LLGIA will be terminated. This is necessary to avoid any resource adequacy concerns that might be implicated by immediately terminating the LLGIA and provides flexibility for the Generating Facility to continue operating until it can be utilized in a different MISO process.

If the LARS Associated Load ceases service *after* the first fifteen years of being formally paired, then it is reasonable to allow the Generating Facility to continue to utilize the Interconnection Service granted through the LLGIA. Several stakeholders expressed concern that a permanent pairing requirement would strand a Generating Facility that had a remaining useful service life even if such Generating Facility could be used—or was needed—to address resource adequacy needs following the departure of the LARS Associated Load. MISO added this language in response to these stakeholders' legitimate concerns that Generating Facilities submitted to LARS in good faith and that had served LARS Associated Loads for long periods of time should not be forced to go offline or undergo a second study process with potentially significant new costs if the LARS Associated Load unexpectedly ceased operations.

Thus, MISO is requiring the generation and load to remain paired for fifteen years because it provides important safeguards that prevent customers from misusing the LARS process to obtain Interconnection Service and only serve the LARS Associated Load for a short period of time. Fifteen years is also a reasonable time period as reflected in many standard large load contracts and sufficient to deter entities from invoking the needs of a specific large load as a pretext to bypass the DPP queue and receive immediate and unrestricted service. This language clearly allows the Generating Facility to continue operating under the terms of the LLGIA after fifteen years have passed even if the LARS Associated Load ceases use of its Transmission Service. This provides the Generating Facilities with certainty after the fifteen-year period has passed and allows for these facilities to continue assisting with any resource adequacy needs that may be occurring at that time.

The final paragraph of Section 3.12.7.4 addresses what costs the LARS Associated Transmission Customer is required to pay for its participation in LARS. The proposed language is as follows:

> Once MTEP approval occurs for the LARS Associated Load, the LARS Associated Transmission Customer remains responsible for the identified BRPs and Other assigned projects even if such LARS Associated Load does not commence service. In addition, if the LLGIA for a LARS Associated Load is terminated, the

> LARS Associated Transmission Customer remain responsible for the costs thereof. If the load portion of the MTEP Project for the LARS Associated Load is withdrawn, then the Network Upgrade costs assigned as BRP or Other projects for the LARS Associated Load remains the responsibility of the LARS Associated Transmission Customer. If the load portion of the MTEP Project for the LARS Associated Load is withdrawn, the load may go through the applicable MTEP study process.

The language clearly explains in what instances the LARS Associated Transmission Customer is required to pay for any assigned Network Upgrades. Once MTEP approval occurs for the LARS Associated Load, then the LARS Associated Transmission Customer is on the hook for any of the Network Upgrade costs assigned to the load's portion of the project. This language is necessary to ensure that Network Upgrades are built as anticipated, even after a Generating Facility can no longer operate. In this instance, the LARS Associated Load may go through the MTEP process.

This section clearly identifies which party is responsible for what mitigation costs. Once the LARS Associated Load receives MTEP approval, then the LARS Associated Transmission Customer remains responsible for the identified BRPs and Other type projects assigned even if the load does not commence service. Similarly, if the LLGIA is terminated, then the LARS Associated Transmission Customer remains responsible for any associated costs identified in the LLGIA. If the LARS Associated Load commences service and then later withdraws the load portion of the MTEP Project, then the Network Upgrade costs assigned as BRP or Other projects remain the responsibility of the LARS Associated Transmission Customer. These provisions are necessary to ensure that the proper party pays for the associated costs of their portion of the LARS project even if they never commence service or later withdraw from LARS. These provisions can be implemented now and will be compatible with the large load study process reforms MISO is developing.

14. Section 3.12.8 – Transfer of Ownership of Large Load Addition Resource Study Interconnection Request

The proposed language in Section 3.12.8 is necessary to prevent transfers of ownership prior to LLGIA execution that might slow down the timeline for studying a LARS project and ultimately delay the ability for MISO to move LARS projects to LLGIA execution within 120 days from kickoff. Prohibiting any changes to a LARS Application prior to LLGIA execution will allow MISO to maintain its proposed LARS timeline and enable large loads to connect the system faster.

15. Section 3.12.9 – Modifications of Large Load Addition Resource Study Request

The proposed Section 3.12.9 is necessary to ensure that no details of a LARS Application are changed during the study process. The proposed revisions are as follows:

> After submission of the LARS Application, no modification to the Interconnection Request or any of its parameters, including any information provided by the Transmission Owner such as the agreed-upon Point of Interconnection, is permitted under Section 4.4 or otherwise prior to the execution or unexecuted filing of the final LLGIA. Any modification made by the Interconnection Customer, LARS Associated Transmission Customer, or Transmission Owner prior to the execution or unexecuted filing of the final LLGIA shall cause the LARS Interconnection Request to be deemed withdrawn.
>
> After entering the Large Load Addition Resource Study as defined in Section 3.12.4, no changes to the In-Service Date or Commercial Operation Date of the Generating Facility is permitted via section 4.4.4 except that a LARS Application that is deferred to the next available LARS Study Period will be allowed to extend its In-Service Date or Commercial Operation Date to be no more than three calendar years from the kickoff of the LARS Study Period in which its LARS Application is studied. At the completion of the Large Load Addition Resource Study, the Commercial Operation Date and Service Commencement Date for the LARS Associated Load shall be set forth in the LLGIA.
>
> Consistent with Article 2.3.1 of the LLGIA, once that LLGIA is executed or filed unexecuted, if the Generating Facility fails to reach Commercial Operation by the specified Commercial Operation Date set forth in the LLGIA, such specified Commercial Operation Date as set forth in the LLGIA may be extended by Interconnection Customer for a period up to three (3) consecutive years, after which Transmission Provider shall terminate the LLGIA if the Generating Facility has still failed to reach Commercial Operation.

The proposed language is necessary to ensure that LARS Applications are able to be studied on both the load and generation side within the timeframe required by LARS. MISO has to have certainty to complete these studies in parallel and in 120 days. Thus, it is not allowing any modifications to the information provided in the LARS Application and any modification made will result in the withdrawal of the LARS Application. Similarly, the proposed LARS COD requirements set forth in GIP Section 3.3.1 are specifically for generation needed to meet load intended to come online while LARS is in place. Disallowing changes to the In-Service Date or COD after entering LARS again provides the certainty necessary to ensure that these projects will remain paired during the process and will prevent projects with uncertain timelines from entering LARS.

16. Section 11 – Generator Interconnection Agreement (GIA), Facilities Construction Agreement (FCA), and Multi-Party Facilities Construction Agreement (MPFCA)

Proposed revisions to Section 11.1 include the distinction that LARS projects will not complete restudies and that the tender of the draft LLGIA will occur after the Interconnection Facilities Study is initiated through LARS. MISO also proposes to revise this Section to clarify that LARS Interconnection Requests tender of the LLGIA will occur on a different timeline than DPP projects, which timeline for tender is memorialized in new GIP Section 3.12.6. These edits are necessary to properly document the shortened timeline for tender of LARS projects and the differences in timing between LARS projects with one study and DPP projects with multiple studies.

MISO proposes to revise Section 11.2 to clarify that LARS projects will have a shorter, 10 Business Day timeline to return comments on the draft LLGIA. MISO also proposes to revise this Section to clarify that MISO shall tender a revised draft LLGIA after 5 Business Days of receiving the comments. For LARS projects, negotiations of LLGIAS shall be no more than 20 Business Days from the notice to proceed in Section 3.9.4. Revisions to 11.2.1 clarify that LARS projects are unable to postpone the start of the LLGIA negotiation period. These edits are needed to shorten the negotiations timeframe to keep the LARS process to approximately 120 days from kickoff to LLGIA execution. This shortened timeframe will ensure that LARS projects are able to execute the LLGIA quickly and come online within the timeframe allotted to serve the project's identified need.

MISO proposes to revise Section 11.3 to provide that for LARS projects the Transmission Provider shall provide the Interconnection Customer and Transmission Owner a final LLGIA within 15 Business Days after completion of the negotiation period in accordance with Section 11.2. These revisions also provide that the parties must execute the LLGIA or request to file unexecuted within 15 Business Days of tender of the final LLGIA, otherwise the project will be deemed to have withdrawn its Interconnection Request. These revisions are required to properly document the shorter timeline for LARS projects as compared to the timeline for DPP GIA execution as memorialized in this Section.

The proposed revisions of Section 11.4 simply expand the requirements related to the commencement of interconnection activities to LLGIAs.

B. <u>Attachment X – Appendix 1 (Interconnection Request for a Generating Facility)</u>

MISO is proposing to revise this Appendix to integrate the LARS framework into the interconnection request form. These revisions include adding new options for interconnection requests and interconnection service to accommodate LARS, confirm that the amount of Interconnection Service cannot exceed 150% of the total amount of its LARS Associated Load, to describe the requirements for LARS Associated Load and facilities to connect to the Transmission System, along with System Protection Facilities or operating procedures to prevent injections onto

the Transmission System beyond the substation and voltage level where the Resource is located, and to describe requirements for the disclosure of additional information for MISO to evaluate the request. The specific changes are:

- Section 1: MISO has added a new section requiring information for the LARS Application.

- Section 2: MISO has added a new check box for a Generating Facility to indicate the Interconnection Request is for processing through the Large Load Addition Resource Study process.

- Section 4: MISO has added a new address or location section for the LARS Associated Load to fill out.

MISO has also added a new row for NRIS Service requested for processing through LARS to the table of required information by type of service requested. This row requires the Interconnection Customer to indicate the MW/MVAR of the request and states that the amount of NRIS shall not be less than 200 MW and not exceed 150% of the LARS Associated Load's peak demand expected over any one-hour period, including the load MW amount and the percentage.

MISO added a new sub-section (e) for LARS Interconnection Requests anticipated Service Commencement for the LARS Associated Load by day, month, and year. A new contact section was added for the LARS Associated Transmission Customer and the LARS Associated Load contact.

MISO added a new sub-section (h) requiring an agreement executed by the Interconnection Customer and the entity that owns or controls the LARS Associated Load meeting the requirements of Section 3.12.2 of the Generator Interconnection Procedures.

In sub-section (i), MISO added new information requirements including the POI MTEP substation bus number, the LRZ of the POI, and the attestation required by Section 3.12.1 of the Generator Interconnection Procedures.

MISO added a new sub-section (t), requiring the identification of the LARS Associated Large Load POW, the LRZ the POW is located in, and amount of Transmission Service Requested for the LARS Associated Load.

- Attachment A-5: MISO has added a new paragraph below the dynamic modelling information required for other types of Interconnection Requests to require to require Interconnection Customers participating LARS to provide a detailed power flow model that includes the LARS Associated Load, its Point of Withdrawal, and the POI for the Interconnection Request, as well as system protection facilities. This provides necessary information for MISO to study the Interconnection Request.

- Attachment A-6: MISO has added a paragraph requiring that all inverter-based generators must comply with all modeling requirements specified in BPM-015 and that all LARS inverter-based generators must comply with the modeling requirements specified in BPM-015 Appendix I.

MISO submits that these requirements are just, reasonable, and necessary to the performance of LARS process given the formal pairing of the Generating Facility and LARS Associated Load to this new type of study process.

D. Attachment X – Appendix 6 (Generator Interconnection Agreement)

MISO is proposing to revise this Attachment to require contractual commitments associated with the LARS Associated Load.

1. Revisions to Recitals

MISO proposes a new fifth recital for use in the LLGIA that explains that the output of the Generating Facility will be used to serve the LARS Associated Load. Including this recital provides clarity about what the LLGIA does at the front of the document.[96]

2. Revisions to Article 1—Definitions

MISO proposes to include the same new and revised definitions in the LLGIA that are proposed for inclusion in the GIP. The proposed terms and definition language are identical to those described above for GIP revisions except for non-substantive edits needed to reflect the location of the definition in the LLGIA rather than the GIP.[97] MISO refers to its discussion above and asks that the Commission accept the definition changes as just and reasonable for the reasons explained in the discussion of these changes.

MISO also added the following definition for the LARS study process to indicate the point in the system where the LARS Associated Load is connected:

> **Point(s) of Withdrawal (POW)** shall mean the point(s) where a non-transmission facility that is used to withdraw Energy from the Transmission System to serve Load connects to the Transmission System.[98]

MISO proposes this definition in order create a load equivalent to the existing defined term, Point of Interconnection, which is used to describe the point at which the Interconnection Facilities

---

[96] When merged with Appendix 6, MISO would include this recital in brackets indicating it is to be used only for LLGIAs.

[97] These changes consists of revising "these GIP" to "the GIP" in Appendix 19 in order to avoid confusion. The change is not intended to be substantive.

[98] MISO proposed this defined term as part of its ZGIA filing. While the definition remains pending, MISO proposes it again here because LARS utilizes this concept and is being built from Attachment X, Appendix 6 rather than Appendix 19 where the pending definition is included.

connect to the Transmission System. Because the relative location and configuration of Load with respect to the Generating Facility and to the Transmission System is a critical component LARS, vocabulary is needed to discuss the point where the LARS Associated Load connects to the Transmission System in reference to the Point of Interconnection. The term "Point(s) of Withdrawal" provides a delineation between the two points that facilitates clearer Tariff rules.

3. Revisions to Article 2.3—Termination Procedures

MISO proposes revising Article 2.3.1 describing the conditions under which a LLGIA will be terminated by the Transmission Provider. The proposed revisions are as follows:

> This LLGIA shall be terminated by Transmission Provider after giving Interconnection Customer ninety (90) Calendar Days advance written notice if:
>
> (1) the LARS Associated Load or a portion of the LARS Associated Load fails to achieve a Service Commencement Date for Transmission Service by the Commercial Operation Date for this Generating Facility, including any extension provided thereunder; or
> (2) within the first fifteen (15) Calendar Years after the LARS Associated Load commences use of the Transmission Service granted through LARS, the LARS Associated Load or a portion of the LARS Associated Load has ceased use of Transmission Service granted through LARS for a period of one year beginning with the last date of use of such Transmission Service; or
> (3) within the first fifteen (15) Calendar Years after the LARS Associated Load commences use of the Transmission Service granted through LARS the agreement required by GIP Section 3.12.2.i is terminated or otherwise ceases to be in effect except that a replacement agreement that satisfies the requirements of GIP Section 3.12.2.i involving the same Generating Facility and LARS Associated Load.
>
> In the event that the LARS Associated Load ceases use of its Transmission Service or the agreement required by Section 3.12.2.i terminates within the first fifteen (15) Calendar Years after the LARS Associated Load commences use of the Transmission Service granted through LARS, this Agreement shall be terminated one year after the date of such occurrence. During such one year period the Generating Facility shall be allowed to operate subject to the Annual ERIS ("AERIS") and the Quarterly Operating Limit ("QOL") processes as specified in BPM-015 Section 6.6 in order to allow the Interconnection Customer to obtain new Interconnection Service pursuant to the GIP. If the DPP processing is delayed beyond one year due to factors beyond the Interconnection Customer's control, then this LLGIA shall be extended until the relevant DPP studies are completed provided Interconnection Customer' Interconnection Request is not withdrawn.
>
> Where: (1) the LARS Associated Load fails to commence service for the full amount of Transmission Service requested in the LARS Application by the

> Commercial Operation Date for this Generating Facility, including any extension provided thereunder; (2) ceases use of such full output within the first fifteen (15) Calendar Years after the LARS Associated Load commences use of the Transmission Service granted through LARS for a period of one year beginning with the last date of use of such Transmission Service; or (3) the parties to the agreement required by Section 3.12.2.i reduce the MW output from the Generating Facility that the LARS Associated Load intends to utilize within the first fifteen (15) Calendar Years after the LARS Associated Load commences use of the Transmission Service granted through LARS, Transmission Provider shall only terminate the portion of the Interconnection Service granted under this LLGIA that exceeds 150% of the reduced peak Demand being utilized by the LARS Associated Load.
>
> Following the first fifteen (15) Calendar Years after a LARS Associated Load ceases use of its Transmission Service or if the agreement required by GIP Section 3.12.2.i is terminated or otherwise ceases to be in effect, then Transmission Provider shall not terminate the Generating Facility's Interconnection Service.

This proposed section lays out the instances where a LLGIA will be terminated, which includes when the LARS Associated Load (or some portion thereof) fails to achieve a service commence date by the COD of the Generating Facility, when LARS Associated Load has ceased use of the transmission service granted through LARS for a period of one year, or when the required executed agreement under GIP Section 3.12.2.i is terminated.

The second paragraph goes into additional detail regarding what happens when the LARS Associated Load no longer operates. The Generating Facility's LLGIA is not immediately terminated but it is granted up to one year to acquire new Interconnection Service. During that year, the Generating Facility must operate subject to MISO's AERIS and QOL processes as specified in the BPM.

MISO refers the Commission to its discussion of parallel language in GIP Section 3.12.7.4 as described in this transmittal letter, for additional explanation of why this language is just and reasonable.[99]

The third paragraph addresses the situation where the LARS Associated Load changes its amount of Transmission Service to a lower amount than was originally requested in the LARS Application. In that circumstance, MISO will only terminate (or amend) the portion of the Interconnection Service granted by the LLGIA that exceeds 150% of reduced peak demand being utilized by the LARS Associated Load. This will ensure that the generation remains paired with the load and results in an amended LLGIA for the Generating Facility.

---

[99] *See* discussion regarding Attachment X, Section 3.12.7.4, *supra* at pp. 34-36.

MISO is also revising Article 2.3.3 to state that LARS projects must provide all security required in Section 2.4 prior to any termination request for a LARS project becoming effective. The proposed language is as follows:

> For LLGIAs, all security as required by Section 2.4 shall be provided prior to termination.
>
> For LLGIAs, any termination or withdrawal of the LARS Application from LARS or any cessation of operations or discontinuation of Transmission Service by the LARS Associated Load shall be an event of default pursuant to Article 17 of this LLGIA.

This language is necessary to ensure that projects are held liable for any Network Upgrades that would be memorialized in an LLGIA or related agreement and to prevent harm to other projects due to the withdrawal.

MISO is proposing to revise Article 2.4 to specify that should a LARS project terminate, it will be liable for any Network Upgrade costs identified in the LLGIA or that would be memorialized in an FCA, MPFCA, or JTIQ Service Agreement. The proposed language is as follows:

> In the event that this LLGIA is terminated by Interconnection Customer, Interconnection Customer is responsible for the full cost of all Network Upgrades that are designated as GIP projects and are identified in this LLGIA as well as any GIP Network Upgrades identified during the LARS process that are to be memorialized in an agreement other than this LLGIA, including any applicable FCA, MPFCA, or JTIQ Service Agreements. If the Network Upgrade costs for Network Upgrades subject to an FCA, MPFCA, or JTIQ Service Agreement have not been finalized or the Interconnection Customer has not made the payment under such agreement as of the date that termination of this LLGIA is sought, Interconnection Customer shall provide the payment or security for such Network Upgrades in the amount required by the applicable agreement. If such agreement has not been executed and final costs are not available as of a date that termination is sought, Interconnection Customer shall provide such payment or security in an amount corresponding to the most recent estimate provided by the Transmission Provider during the LARS process. Interconnection Customer shall pay or Transmission Provider shall refund, as applicable, to Interconnection Customer the difference between the amount of any estimated payment or security made pursuant to this Article and the final cost of such Network Upgrade within ninety (90) Calendar Days after such final costs are invoiced to the Interconnection Customer.

These additions are necessary to establish that if the final costs have not been determined, the Customer must provide security according to the most recent estimate. Additionally, the Transmission Provider will provide any applicable refunds of payments or security within 90 Calendar Days of providing the final invoice of NUs to the Customer. As stated above, the

proposed language is necessary to ensure that only "shovel ready" projects submit to LARS, knowing those projects will assume the risk of paying for any Network Upgrades identified in an LLGIA or that would be memorialized in an FCA, MPFCA, or JTIQ Service Agreement. This language will ensure that no other projects are affected by the termination.

4. Revisions to Article 4.1—Interconnection Product Options

MISO also proposes adding a check box in Article 4.1 to indicate whether the LLGIA has been processed through the LARS Study Process. The option indicates that ER and NR are the only options.

5. Revisions to Article 9.7.4.7—Operations under an LLGIA prior to Service Commencement Date

MISO proposes to add new article 9.7.4.7 establishing the obligation of a Generating Facility with an LLIGA prior to service commencement date. The proposed revisions are as follows:

> If this GIA is an LLGIA, Interconnection Customer shall not commence Commercial Operation or otherwise inject electricity onto the Transmission System prior to the Service Commencement Date of the LARS Associated Load except for injections associated with testing otherwise allowed by this LLGIA. In the event that the LARS Associated Load commences service for an amount of Transmission Service less than the amount requested in the LARS Application, Interconnection Customer's injections shall be subject to the Annual ERIS Evaluation Study and Quarterly Operating Limits processes as described in Section 6.6 of the Generator Interconnection Business Practices Manual and may be limited to the current Demand of the LARS Associated Load until such time as the LARS Associated Load has commenced service.

These provisions allow the Generating Facility to operate even when the LARS Associated Load has commenced service for lower than the total amount identified in the LARS Application. This situation will likely occur when the LARS Associated Load is being phased in over time. These provisions will allow the Generating Facility to begin providing service to the load but subject to the Annual ERIS Evaluation Study and Quarterly Operating Limits processes as described in Section 6.6 of the Generator Interconnection Business Practices Manual. The provisions also explain that the Generating Facility's output may be limited to the current Demand of the LARS Associated Load until such time as the LARS Associated Load has fully commenced service. These revisions are a just and reasonable approach to addressing timing mismatches that can occur in practice between when the Generating Facility and LARS Associated Load enter service, which may occur where the LARS Associated Load is delayed or comes online in phases.

6. Revisions to Appendices

MISO proposes several revisions to Appendix A in order to implement the LARS process.

First, MISO proposes to include a new Section 2 that includes a description of the LARS Associated Load, identifying the MW, Point(s) of Withdrawal and need by date of the ZG Associated Load. This section requires a single line diagram illustrating the connections between the Generating Facility, ZG Associated Load, and the Transmission System and the identification of the equipment and configurations that prevent injections outside of the Transient Tolerance Window.

This section reflects the technical requirements applicable to a LARS Associated Load participating in LARS and makes the studied equipment and configuration a part of the LLGIA that can be enforced. This requirement works with MISO's material modification rules in the same way that section 1 operates to ensure that changes to the configuration of the AG Associated Load that could affect the impacts of the ZG Interconnection Service as studied are subject to the same modification rules applicable to the Generating Facility under Section 1 of Appendix A. This is necessary and appropriate given the importance of these configuration details to the completion of the LARS process.

MISO also proposes revisions to Appendix B, the revisions are made to milestone 1f to include LARS in the agreement requirement for an Affected System study process pursuant to GIP Section 3.5.4.

E. <u>Attachment FF (Transmission Expansion Planning Protocol)</u>

MISO is proposing to add a new sub-section (ii) to Section I.D.1.b of Attachment FF to implement the requirements of the LARS process reflected in Attachment X but for the LARS Associated Transmission Customer. MISO included relevant explanations of the Interconnection Customer's responsibilities in this new proposed section to ensure alignment with new revisions to Attachment X to implement LARS.

The reasoning for the new provisions proposed in Section I.D.1.b.ii.(a) for the LARS Pre-Submission Coordination Process are the same as the previously described Sections 3.12.1 of Attachment X.

MISO added a new section to address the LARS Application Timing and Deposits for the load study. The proposed revisions are as follows:

> <u>The LARS Associated Transmission Customer is responsible for submitting the LARS Application. Both the Transmission Owner supporting the LARS Application and requesting to join LARS shall submit the required Large Load information to the MTEP Portal and an Interconnection Customer supporting the LARS Application and requesting to join LARS shall submit their Interconnection Request with the LARS Associated Transmission Customer to the Transmission</u>

> Provider no later than the LARS Application deadline as published on the MISO public website, at least twenty (20) Business Days prior to the scheduled kick-off of the LARS study period published on the MISO public website and as described in Section 3.12 of Attachment X. A valid LARS Interconnection Request shall be included in the next available LARS study period that commences after such request is submitted.
>
> A LARS Application shall be accompanied by a Non-Refundable Deposit 1 (D1) of $250,000 submitted by the LARS Associated Transmission Customer. Additional LARS Study Deposits such as D2 as described in Section 3.3.1 of Attachment X apply to the LARS Application and shall be submitted by the Interconnection Customer. All applicable deposits, milestone payments and data required to enter the Large Load Addition Resource Study must be received at the time the LARS Application is submitted.

The purpose of this section is to align the timing of the LARS generation study with the load study. The second paragraph also identifies which parties are responsible to pay which deposits.

Section I.D.1.b.ii.(c) includes the proposed LARS Application requirements for the load study and identifies what information must be provided to MISO. This section closely aligns with the existing information requirements of the EPR process. Otherwise, the remaining proposed requirements match those included in Section 3.12.2 of Attachment X and were previously explained in the Attachment X section.

The new provisions of Sections I.D.1.b.ii.(d) describe and implement the same evaluation process for LARS Applicants as those previously described in Sections 3.12.3 of Attachment X.

The new provisions of Sections I.D.1.b.ii.(e) describe and implement the LARS cure and deficiency periods as described in Section 3.3.3 of Attachment X. The proposed revisions to Attachment FF are as follows:

> A LARS Application will not be considered valid until all items in Section 3.12 of Attachment X and Section I.D.1.b.ii of Attachment FF, have been received by Transmission Provider. If the LARS Application fails to meet the requirements, Transmission Provider shall notify the Transmission Customer within fifteen (15) Business Days of receipt of the LARS Application either that the Transmission Provider has accepted the Application as valid or has determined that the Application is not valid due to one or more deficiencies. In the event Transmission Provider determines that the Application does not meet all the requirements and thus is not valid, Transmission Provider shall also provide an explanation of the reasons for such determination. The Transmission Customer shall have ten (10) Business Days from the date that the Transmission Provider identifies the Application as deficient to provide the additional requested information needed to constitute a valid request. The requirements of Section 3.3.3 of Attachment X apply to LARS Applications. The Transmission Provider will have one period of review

> to identify deficiencies and the entities identified in the LARS Application shall have one cure period to address deficiencies.

This section was necessary to add to Attachment FF because the LARS Application must contain the information required by Section I.D.1.b.ii.(c). MISO clarified in both Attachment X and in Attachment FF that it will have one single review period to identify any deficiencies in the LARS Application and the applicants will have one single cure period to address those deficiencies. That is necessary to ensure that LARS process only lasts approximately 120 days. MISO cannot be delayed by numerous deficiency and cure periods.

The new provisions of Sections I.D.1.b.ii.(f) describe and implement the refund process for the LARS study. Any difference between the study deposit and the actual cost of the study will be paid by or refunded to the Interconnection Customer.

The new provisions of Sections I.D.1.b.ii.(g)-(i) first describe and implement the responsibilities of the Interconnection Customer or the LARS Associated Transmission Customer depending on whether the load or the generation withdraws from LARS after the LLGIA is executed. The section states that the parties will remain responsible for the costs identified in the LLGIA if the project is withdrawn depending on which party caused the withdrawal. The new provisions in sub-section (h) clearly state that no modifications of the LARS Application are permitted following its submission. This is to ensure that MISO may complete the necessary studies in order to provide MTEP approval and a LLGIA on the approximate 120-day timeline required by LARS. Finally, the new provisions in sub-section (i) assign the costs of any necessary mitigations developed to address violations observed in the following instances: 1) violations observed only in the transmission studies to study the impact of the load; 2) violations observed in both the load and generation studies; and 3) violations observed in only the generation study. Mitigation costs are then assigned to either the Interconnection Customer or the LARS Associated Transmission Customer depending on which instance applies.

The new provisions of Section I.D.1.b.ii.(j) addresses consideration of including generating facilities in the LARS study process. The proposed revisions are as follows:

> In accordance with the LARS definitions, Section 3.3.1, and Section 3.12 of Attachment X, and notwithstanding the requirements of Section I.D.1.b.ii, a generating solution that does not yet have generator interconnection agreement filed with the Commission pursuant to Attachment X of this Tariff may be considered as an alternative transmission solution if: (1) a valid Interconnection Request for such Generating Facility has been submitted for processing under the LARS process specified by Attachment X to the Tariff; and (2) the Transmission Provider has received an executed agreement between the LARS Interconnection Customer, the entity(ies) with the LARS Associated Load with a minimum of 200 MW, and the LARS Associated Transmission Customer that satisfies the requirements of Attachment X, Section 3.12.2(i) with a minimum term of at least five years to align with MISO's transmission planning horizon to ensure the ability to provide adequate lead time for an alternative transmission solution should the

> agreements terminate. The study will be performed for each LARS Associated Load, including the Interconnection Request, capturing the cumulative impact based on their submission date per LARS Study Period. The outcome of the LARS Associated Load study is MTEP approval of the load and associated optimized network upgrades.
>
> In the event that the Load In-Service Date is prior to the date on which the proposed LARS Resource achieves Commercial Operations, the Transmission Provider may either; (1) require the applicable Load Serving Entity to delay the in-service date of the LARS Associated Load until such time as an alternative solution can be placed in service or the Generating Facilities achieve(s) Commercial Operation in accordance with Section I.D.1.b.ii of this Attachment; or (2) impose operational limitations on the LARS Associated Load that the Transmission Provider determines are reasonably necessary to maintain the reliability of the Transmission System until such time as the Generating Facility achieves Commercial Operation or an alternative solution is placed into service.
>
> There will be no restudies if a load withdraws from the LARS process.

These provisions describe situations where a generating solution does not yet have a GIA on file with the Commission and indicates that it may be considered as an alternative transmission solution in the LARS load study if: (1) a valid Interconnection Request for such Generating Facility has been submitted for processing under the LARS process specified by Attachment X to the Tariff; and (2) the Transmission Provider has received an executed agreement between the LARS Interconnection Customer, the entity(ies) with the LARS Associated Load with a minimum of 200 MW, and the LARS Associated Transmission Customer that satisfies the requirements of Attachment X, Section 3.12.2(i). The provisions also explain that if the LARS Associated Load's in-service date is prior to the COD of the Generating Facility, then MISO can: 1) require the LSE to delay the in-service date of the LARS Associated Load until such time as an alternative solution can be placed in service or the Generating Facilities achieve(s) COD in accordance with Section I.D.1.b.ii of this Attachment; or (2) impose operational limitations on the LARS Associated Load that MISO deems are reasonably necessary to maintain the reliability of the Transmission System until such time as the Generating Facility achieves Commercial Operation or an alternative solution is placed into service.

Finally, the new provisions added in Section I.D.1.b.ii.(j) state that MISO will not complete any restudies if a LARS Associated Load withdraws from the LARS process. This is to ensure that the integrity and swiftness of the LARS process is maintained.

V. THE LARS STAKEHOLDER PROCESS

MISO developed LARS through an iterative stakeholder process focused on the relationship between significant new load, associated generation, and the need to maintain system reliability. The LLWG itself is charged with addressing large-load issues across markets, reliable operations, planning, and resource adequacy.[100] Stakeholders first raised the need to coordinate large load and generator interconnection studies through MISO's issue process.[101] In early January 2026, MISO convened a Large Load Additions Workshop where it presented its forecast of large load additions, which showed large load additions escalating sharply over the next several years, driven primarily by data centers, and noted that federal policy supporting artificial intelligence was accelerating near-term growth.[102]

Large loads continued to be a significant topic of conversation in all of MISO's stakeholder meetings. To provide a dedicated forum for large load matters, MISO's Steering Committee approved a charter for the Large Load Working Group.[103] The LLWG reports to MISO's Advisory Committee and is chartered to provide input and policy guidance to MISO Management and the Advisory Committee on market, reliability, planning, and resource adequacy matters related to the integration of large loads within the MISO footprint. The LLWG held its first meeting on April 20, 2026.[104] In its first several meetings, the LLWG took up the large load interconnection reliability requirements (LLWG-2026 3), reserve product enhancements for large load (LLWG-2026-2), Firm Service Step Up for large load interconnections (LLWG-2026-1), and the ZGIA (PAC-2024-4B), each of which forms part of the broader large load framework within which LARS was developed.[105]

On June 18, 2026, the Commission issued an order directing MISO to show cause why its Tariff remains just and reasonable without provisions tailored to large loads, or to propose Tariff

---

[100] MISO, LLWG Charter at 1, *supra* note 20.

[101] On January 29, 2025, Clean Grid Alliance ("CGA") presented Issue PAC-2024-7, Sharing and Coordinating MTEP and DPP to Accommodate Large Load, to the PSC. Coordinating Large Load and Generator Interconnection (PAC-2024-7), PLANNING SUBCOMMITTEE (Jan. 29, 2025), available at: https://cdn.misoenergy.org/20250129%20PSC%20Item%2007%20Sharing%20and%20Coordinating%20MTEP%20and%20DPP%20to%20Accomodate%20Large%20Load%20(PAC-2024-7)674624.pdf.

[102] Large Load Additions Workshop, MIDCONTINENT INDEP. SYS. OPERATOR (Jan. 30, 2026), available at: https://cdn.misoenergy.org/20260130%20Large%20Load%20Workshop%20Presentation 738349.pdf.

[103] *See* LLWG Charter, *supra* note 20.

[104] *See* MISO, LLWG (Apr. 20, 2026available at: https://www.misoenergy.org/events/2026/large-load-working group-llwg---april-20-2026/; Large Load Working Group (LLWG), MIDCONTINENT INDEP. SYS. OPERATOR, available at: https://www.misoenergy.org/engage/committees/large-load-working-group/.

[105] Minutes, LARGE LOAD WORKING GROUP (June 10, 2026), available at: https://cdn.misoenergy.org/20260629%20LLWG%20Item%2001c%20Minutes%202026 0610764681.pdf ("LLWG June 10 Minutes"); see also Liaison Report, LARGE LOAD WORKING GROUP at 3-10 (Sept. 9,

revisions.[106] MISO held a special Steering Committee meeting on July 7, 2026, where it determined that the LLWG would be the forum for continued discussion of the large load issues that had been proceeding at the PAC, including the ZGIA and the Large Load Definition.[107] In its liaison report at the July 16, 2026 LLWG meeting, MISO described the three core objectives of its large load framework: to "[c]onnect within 120 days with all studies completed and GIAs signed," to "[t]ransition and scale with flexible options consistent with timing of network upgrade buildouts," and to "[s]ustain reliable operations with ability to withdraw or inject energy based on conditions and signals."[108]

At the July 16, 2026, LLWG meeting, MISO first introduced the LARS proposal as a new issue and titled it the Generation and Large Load Alignment proposal. MISO sought stakeholder input concerning the eligibility and design of a process for studying new large loads and their associated generation.[109] MISO specifically asked stakeholders whether a minimum threshold of 250 MW appropriately captured high-impact loads and, if not, what alternative threshold would better capture those loads without diluting the purpose of the process.[110] MISO asked for written feedback by July 30, 2026, asking stakeholders in particular whether 250 MW was the right threshold, what readiness and securitization rules should apply to prevent speculative requests, and what other improvements were needed, and outlined its next steps as review of draft Tariff language at the August 27, 2026 LLWG meeting and a Tariff filing in September 2026.[111]

MISO continued to refine the proposal following that feedback. At the August 27, 2026 LLWG meeting, MISO formally presented LARS as a process for concurrently studying Large Loads and associated generation and circulated draft Tariff language for stakeholder review.[112] MISO summarized the outcomes of the process as an allocation of Interconnection Service to the generator, transmission service for reliable withdrawal by the load, and optimized Network

---

2026), available at: https://cdn.misoenergy.org/20260909%20LLWG%20Item%2003%20Liaison%20Report 779834.pdf.

[106] Show Cause Order at P 122 (directing MISO to submit, within 30 days, an informational report on proposals under consideration in its stakeholder process to address resource adequacy for new large loads, with a schedule of key milestones and anticipated filing dates).

[107] Liaison Report, LARGE LOAD WORKING GROUP at 8 (July 16, 2026), available at: https://cdn.misoenergy.org/20260716%20LLWG%20Item%2004%20Liaison%20Report 768708.pdf ("LLWG July 2026 Liaison Report"); Minutes, LARGE LOAD WORKING GROUP at 4 (July 16, 2026), available at: https://cdn.misoenergy.org/20260812%20LLWG%20Item%2001c%20Minutes%202026 0716771087.pdf.

[108] LLWG July 2026 Liaison Report at 4.

[109] MISO, LLWG, *Generation and Large Load Alignment*, LLWG-2026-6 (July 16, 2026).

[110] MISO, LLWG, *Generation and Large Load Alignment*, LLWG-2026-6, Stakeholder Feedback (July 30–31, 2026) (requesting feedback on whether "≥250 MW" was the appropriate minimum and what alternative threshold would capture high-impact loads without diluting the proposal's intent).

[111] Generation and Large Load Alignment (LLWG-2026-6), LARGE LOAD WORKING GROUP (July 16, 2026), available at: https://cdn.misoenergy.org/20260716%20LLWG%20Item%2006b%20Generation%20and%20Load%20Alignment%20Presentation768740.pdf ("LLWG July 2026 Presentation").

[112] MISO, LLWG, *Large Load Addition Resource Study*, LLWG-2026-6 (Aug. 27, 2026).

Upgrades, and stated that the study process and GIA would together be completed in 120 calendar days.[113] MISO also posted draft Tariff language implementing LARS and requested that stakeholders provide feedback on the proposed Tariff redlines and identify any additional process clarifications needed through the Stakeholder Feedback Tool by September 10, 2026.[114]

As a result of stakeholder feedback, MISO changed the LARS process minimum Large Load value to be 200 MW instead of 250 MW. Stakeholders proposed a range of approaches to the threshold. The July LLWG stakeholder record includes a recommendation to reduce the minimum threshold from 250 MW to 200 MW to capture projects sufficiently large to warrant coordinated load-generation evaluation while maintaining the proposal's focus on projects with significant system impacts.[115] Other stakeholders supported retaining a minimum-MW mechanism to limit the process to high-impact large loads.[116] MISO made this change based on significant stakeholder feedback that many emerging data center and large industrial projects in the 200-250 MW range can have significant system impacts and would benefit from the coordinated study process. Lowering the threshold also allows access to the LARS framework while maintaining its focus on large, impactful load additions. The 200 MW minimum threshold strikes the right balance between different kinds of large load and hyperscalers.

At the September 23, 2026, LLWG meeting, MISO presented the final proposed LARS process and updated tariff language for Attachement FF, Attachment X and associated Appendices in response to the September 10th feedback. MISO explained that it had changed the minimum threshold LARS Associated Load size to 200 MW (from the proposed 250 MW), allowed multiple Generating Facilities to group at different POIs for one LARS Associated Load, and added a new contract agreement option for LSEs. MISO also clarified several of the requirements of the LARS process including addressing the concerns on representation of the LARS generator/load pair within the parallel study processes.[117]

The stakeholder process also addressed the relationship between the load and generation, project-readiness requirements, study assumptions, and the interaction between LARS and the existing Generator Interconnection Queue.[118] The resulting LARS proposal reflects MISO's effort

---

[113] Large Load Addition Resource Study (LLWG-2026-6), LARGE LOAD WORKING GROUP at 7-10 (Aug. 27, 2026), available at: https://cdn.misoenergy.org/20260827%20LLWG%20Item%2007%20Load%20Addition%20Resource%20Study%20(LLWG-2026-6)777236.pdf ("LARS August 2026 Presentation").

[114] LARS August 2026 Presentation at 16.

[115] *Id.*

[116] *Id.* (including OMS Work Groups feedback supporting a minimum-MW mechanism that limits the proposal to high-impact large loads).

[117] *See* MISO, LLWG, Large Load Addition Resource Study (LLWG-2026-6), (Sep. 23, 2026), available at: https://cdn.misoenergy.org/20260923%20LLWG%20Item%2006%20Large%20Load%20Addition%20Resource%20Study%20(LLWG-2026-6)782864.pdf.

[118] MISO, LLWG, *Large Load Addition Resource Study*, LLWG-2026-6, Stakeholder Feedback (Sept. 2026) (reflecting stakeholder comments concerning project readiness, the relationship between associated load and generation, study models, and the interaction between LARS and the existing Generator Interconnection Queue).

to establish a targeted process for significant new load additions while coordinating the study of associated generation. The 200 MW threshold maintains LARS's focus on substantial load additions while broadening eligibility beyond hyperscale projects exceeding 250 MW to include projects involving larger manufacturing and industrial processes. MISO worked closely with stakeholders to ensure that it considered and incorporated certain elements of feedback.

MISO submits that the Tariff revisions proposed in this filing establish a just, reasonable, and not unduly discriminatory mechanism for rapidly integrated large loads with paired generation. The Tariff revisions are limited in scope and in impact but offer significant benefits in terms of improving the coordination between load and generation studies to reflect the joint impact of both the generation and the load it will serve, and avoiding negative impacts to other MISO processes and the stakeholders who participate in them. As proposed, LARS is both a powerful tool for responding to urgent industry needs as well as a tailored solution with safeguards sufficient to guard against overuse of the process. The benefits of LARS are not free. Both the Interconnection Customer and LARS Associated Transmission Customer are required to undertake commitments that exceed those imposed on Interconnection Customers in the DPP. These additional commitments and risk are necessary to provide the certainty that allows LARS to move at an expedited pace without negative impacts to other processes. The LARS process is open to all Interconnection Customers that meet the Tariff's requirements and that are willing to accept the greater commitments and limitations imposed by LARS.

VI. DOCUMENTS SUBMITTED IN THIS FILING

In addition to this Transmittal Letter, this submission includes:

Tab A – Redline Tariff;[119]

Tab B – Clean Tariff; and

Tab C – Prepared Direct Testimony of Christina Drake.

[119] Language currently pending before the Commission in the following docket and is highlighted in yellow: ER24-2046-003, ER26-3552-000, ER26-3777-000 and ER26-3813-000. MISO requests that the Commission treat such highlighted language as subject to the outcome of this pending proceeding. MISO commits to file any revisions to this highlighted language as necessary to comply with any Commission orders in this proceeding. MISO has removed language that has a future effective date of 6/1/2029 and is pending in Docket No. ER22-1640-006. MISO has removed language that has a future effective date of 6/1/2028 and is pending in Docket No. ER26-2825-000. MISO has removed language from Attachment X, Appendix 6 – Generator Interconnection Agreement that has an effective date of 7/28/2025 and is pending in Docket No. ER24-2046-003. MISO commits to make a subsequent filing with the Commission to reflect the most up-to-date versions of the then-current Tariff provisions prior to the effective date of the language accepted in Docket Nos. ER26-2825-000, ER24-2046-003, ER22-1640-006.

VII. EFFECTIVE DATE

MISO requests an effective date of December 2, 2026 for the Tariff revisions submitted herein, which is not less than 60 days nor more than 120 days, after the filing date. MISO intends to open the first LARS Study Period in the first quarter of 2027. Acceptance of LARS by the requested effective date is necessary to allow LARS to begin on this timeframe because the proposed rules require pre-submission coordination and for MISO to develop software to support the LARS Application prior to opening the first LARS Study Period. This effective date will allow the revisions proposed herein to be effective in time for MISO and stakeholders to prepare for studies with certainty regarding the applicable rule set.

VIII. COMMUNICATIONS

MISO respectfully requests waiver of Rule 203(b)(3) of the Commission's Rules of Practice and Procedure, 18 C.F.R. § 385.203(b)(3) (2026), to the extent necessary to permit the designation of more than two persons for service on behalf of MISO in this proceeding and requests all communications related to this filing be directed to:

Christopher D. Supino*
Managing Senior Corporate Counsel
Michael Kessler
Managing Assistant General Counsel
Midcontinent Independent System Operator, Inc.
720 City Center Drive
Carmel, Indiana 46032
Telephone: (317) 249-5400
csupino@misoenergy.org
mkessler@misoenergy.org

James C. Holsclaw*
Calfee, Halter & Griswold LLP
3900 Salesforce Tower
111 Monument Circle
Indianapolis, Indiana 46204
Telephone: (317) 308-4266
jholsclaw@calfee.com

IX. NOTICE AND SERVICE

MISO has served a copy of this filing electronically upon all parties listed on the Commission's eService list, and upon all Tariff customers, MISO Members, Member representatives of Transmission Owners and non-Transmission Owners, as well as all state commissions within the MISO Region and the Organization of MISO States. The filing has been posted electronically on MISO's website at https://www.misoenergy.org/legal/ferc-filings/ for other interested parties in this matter.

X. CONCLUSION

For all of the foregoing reasons, MISO respectfully requests that the Commission accept this filing and grant waiver of any Commission regulations the Commission deems applicable, but not specifically addressed above in order for the Commission to accept it as proposed.

Respectfully submitted,

/s/ Christopher D. Supino
Christopher D. Supino
Managing Senior Corporate Counsel
Michael Kessler
Managing Assistant General Counsel
Midcontinent Independent System Operator, Inc.
720 City Center Drive
Carmel, Indiana 46032
Telephone: (317) 249-5400
csupino@misoenergy.org
mkessler@misoenergy.org

James C. Holsclaw
Calfee, Halter & Griswold LLP
3900 Salesforce Tower
111 Monument Circle
Indianapolis, Indiana 46204
Telephone: (317) 308-4266
jholsclaw@calfee.com

Attorneys for the Midcontinent Independent System Operator, Inc.