

Comptia A+ Assignment

[A+ - Peripherals and Power Supply]

Peripheral Troubleshooting Theory.

Common issues and solutions for peripherals. Troubleshoot a non-working printer.

Task

❖ **1. List 5 common issues users face with USB keyboards or mice on laptops, and write one possible solution for each.**

➤ Common Issues with USB Keyboards or Mice on Laptops and Their Solutions given Below.

Common Issue	Possible Solution
Keyboard or Mouse is Not Detected	Disconnect the USB device and reconnect it to another USB port. Restart the laptop if the device is still not detected.
USB Port is Not Working	Test the keyboard or mouse on another USB port. If the problem continues, check the USB drivers in Device Manager and update or reinstall them.

Keyboard Keys or Mouse Buttons Are Not Responding	Clean the keyboard or mouse to remove dust and dirt. If the issue persists, test the device on another computer to determine whether it is faulty.
Cursor Freezes or Mouse Moves Slowly	Clean the optical sensor on the mouse and use it on a smooth surface. Adjust the mouse sensitivity in the operating system settings if necessary.
Device Driver Problem	Open <u>Device Manager</u> , update or reinstall the keyboard or mouse driver, and restart the computer to apply the changes.

❖ **2. Simulate a troubleshooting flow: Your Bluetooth headphones are not connecting to your phone. Write the exact step-by-step actions you would take to diagnose and fix the issue, mentioning any settings or indicators you would check.**

➤ Troubleshooting Bluetooth Headphones Not Connecting to a Phone their step given below.

1) Check the Battery Level:

- First, I would make sure that the Bluetooth headphones have enough battery power. If the battery is low, I would charge the headphones before trying to connect them again.

- Why:
- Low battery can prevent Bluetooth devices from entering pairing mode or maintaining a stable connection.

2) Turn Bluetooth on:

- I would open the phone's Settings → Bluetooth and ensure that Bluetooth is turned ON.
- Indicator Checked:
- The Bluetooth icon should appear in the phone's status bar.

3) Enable Pairing Mode:

- I would press and hold the Bluetooth button or power button on the headphones until the LED indicator starts flashing (usually blue or blue/red).
- Indicator Checked:
- A flashing LED light indicates that the headphones are in pairing mode.

4) Search for Available Devices:

- On the phone, I would tap Scan or Pair New Device and wait for the headphones to appear in the list of available Bluetooth devices.
- Indicator Checked:
- The headphones' name should appear in the Bluetooth device list.

5) Connect the Headphones:

- I would select the headphones from the list and wait for the pairing process to complete.
- Indicator Checked:
- The phone should display Connected, and the LED on the headphones usually changes from flashing to a steady light.

6) Forget and Re-Pair the Device:

- If the headphones still do not connect, I would select Forget Device in the Bluetooth settings and repeat the pairing process.
- Why:
- Removing the old pairing information often resolves connection problems.

7) Restart Both Devices:

- I would restart both the smartphone and the Bluetooth headphones, then try connecting them again.
- Why:
- Restarting clears temporary software issues that may prevent Bluetooth connections.

8) Check the Distance:

- I would keep the headphones within 1–2 meters of the phone and remove any obstacles that could interfere with the Bluetooth signal.
- Why:
- Bluetooth works best over short distances without interference.

9) Update Software:

- I would check if the smartphone has any pending system updates and installs them if available.
- Why:
- Software updates often fix Bluetooth compatibility and connectivity issues.

10) Test with Another Device:

- Finally, I would connect the headphones to another smartphone or laptop.
- Why:
- If the headphones work with another device, the issue is likely with the original phone. If they do not work anywhere, the headphones may have a hardware problem.

❖ **3. A user reports that their external webcam is not detected during a Zoom call on Windows 10. Write a checklist of 6 things to check or try to resolve the problem. Consider device manager, privacy settings, and app permissions.**

➤ Checklist to Resolve an External Webcam Not Detected During a Zoom Call (Windows 10).

Checklist	Why It Is Important
Check the USB Connection	Ensure the webcam is securely connected to the USB port. If it is not detected, try a different USB port to rule out a faulty connection.
Check Device Manager	Open <u>Device Manager</u> and verify that the webcam appears under <u>Cameras or Imaging Devices</u> . If a warning icon is shown, update or reinstall the webcam driver.
Check Windows Privacy Settings	Go to <u>Settings</u> → <u>Privacy</u> → <u>Camera</u> and make sure <u>Camera access</u> is enabled for the device and for desktop applications.
Allow Camera Permission for Zoom	Open Zoom settings and ensure the correct webcam is selected. Also verify that Zoom has permission to access the camera in Windows.
Close Other Applications Using the Camera	Exit applications such as Microsoft Teams, Skype, or the Camera app, as only one application may be able to use the webcam at a time.
Restart and Update the System	Restart the computer and check for Windows or webcam driver updates. Updates often fix hardware compatibility and camera detection issues.

❖ 4. You are helping a friend whose printer is showing 'offline' status on their PC. Describe how you would use the Windows Troubleshooter tool to try to fix the issue, and explain what information the tool provides during the process.

➤ Using Windows Troubleshooter to Fix a Printer Showing "Offline" Status you try below steps.

1) Open Windows Settings:

- Click the Start button and open Settings.
- Purpose:
- This allows access to Windows troubleshooting and printer settings.

2) Open Troubleshoot Settings:

- Settings → Update & Security → Troubleshoot → Additional Troubleshooters
- Then select Printer and click Run the Troubleshooter.
- Purpose:
- This starts the built-in Windows Printer Troubleshooter.

3) Select the Printer:

- Choose the printer that is showing the Offline status from the list of installed printers.
- Purpose:

- The troubleshooter will examine the selected printer for configuration or connection problems.

4) Allow Windows to Scan:

- Wait while Windows automatically checks the printer.
- The troubleshooter examines:
 - Printer connection (USB or Wi-Fi)
 - Printer driver
 - Print Spooler service
 - Default printer settings
 - Printer status (Online/Offline)
 - Communication between the PC and the printer
- Purpose:
 - Windows searches for the most common causes of printer problems.

5) Apply the Recommended Fix:

- If Windows detects a problem, click Apply this Fix when prompted.
- Examples of automatic fixes include:
 - Restarting the Print Spooler service
 - Setting the printer as the default printer
 - Clearing stuck print jobs
 - Bringing the printer back online
- Purpose:
 - Windows automatically repairs common printer issues whenever possible.

6) Test the Printer:

- After the troubleshooting process is complete, print a test page to verify that the printer is working correctly.
- Purpose:
- This confirms that the printer is now online and ready for use.