Roast sheet: Costa Rica La Rosa (washed)

Roast 2026-11-10-01 | CBR-120POT | First roast: find first crack, aim for light-medium (city+)

PROGRAM	GREEN BEANS	TIMER	EXPECT 1ST CRACK
P01	**90 g**	**14 min**	**~8:30**

Before

- Read the rating label on the base (write below).
- Range hood or open window. 30 cm clear all round.
- No kettle or microwave on the same circuit.
- Chaff bin empty. Intake screen clean.
- Weigh the whole bag, then weigh out 90.0 g. Remove stones and broken beans.
- Beans below MAX line. Lid, bin and chamber locked.
- Stopwatch ready (count up).

Start

1. Hold Power 3 s.
2. Knob to **P01**, press Power.
3. Knob to **14**, press Power. **Start the stopwatch on this press.**
4. Stay with the roaster the whole time.

Press Power to cool when:

- **30 s after first crack ends**
- or 2:00 after first crack starts, if the end is unclear
- or **at once** on second crack (fast, quiet crackle)
- or at **13:00** (display 1:00), whatever has happened

Write the stopwatch time of each event

EVENT	HOW TO RECOGNIZE IT	TIME (MM:SS)
Color change	Green turns yellow or tan. Smell goes from grass to hay or bread.	
First crack start	Several popcorn-like cracks within a few seconds. One stray pop does not count. Expect 7:00–10:00.	
First crack rolling	Cracks are continuous.	
First crack end	No cracks for about 10 s. Count 30 s, then press Power.	
Smoke noticeable	Visible smoke from the outlet.	
Second crack	Should not happen. If it does, press Power at once.	
Power pressed (cool)	End of heating.	
Cooling ends	Unit returns to standby. Unload only now.	

Measurements

Rating label: V = Hz = W =

Room temperature (°C):

Whole bag before roast (g):

Location and outlet:

Green weight loaded (g):

Roasted weight, no chaff (g):

Error code (E1 / E2 / E3):

Roast date, if not 2026-11-10:

After (circle one in each row)

Bean movement	good / sluggish / stalled	**Chaff**	light / moderate / heavy
Color evenness	even / slightly uneven / uneven	**Defects**	none / dark patches / dark tips / chips

If the stopwatch fails: elapsed time = 14:00 minus the display. | Afterwards: empty the chaff bin, store the beans airtight, rest 3–5 days before tasting. | Expected weight loss 12–15 % (about 76–79 g roasted).