Roast sheet: Costa Rica La Rosa (washed)

Roast 2026-11-11-01 | CBR-120POT | Roast 2: two minutes longer than roast 1, aim for light-medium (city+)

PROGRAM	GREEN BEANS	TIMER	TARGET ROASTED WEIGHT
P01	**90 g**	**16 min**	**78–79 g**

Before

- Same place and outlet as roast 1. Roaster cold.
- Range hood or open window. 30 cm clear all round.
- No kettle or microwave on the same circuit.
- Chaff bin empty. Intake screen clean.
- Weigh out 90.0 g. Remove stones and broken beans.
- Beans below MAX line. Lid, bin and chamber locked.
- Stopwatch ready (count up).

Start

1. Hold Power 3 s.
2. Knob to **P01**, press Power.
3. Knob to **16**, press Power. **Start the stopwatch on this press.**
4. Stay with the roaster the whole time.

Let the timer run out (16:00).
Press Power early only on:

- **second crack** (fast, quiet crackle, like rice cereal in milk)
- or **heavy smoke**

Write the stopwatch time of each event

EVENT	HOW TO RECOGNIZE IT	TIME (MM:SS)
Color change	Green turns yellow or tan. Smell goes from grass to hay or bread.	
First crack start	Several popcorn-like cracks within a few seconds. Not heard in roast 1. Stand close and listen from 10:00 to 14:00.	
First crack rolling	Cracks are continuous.	
First crack end	No cracks for about 10 s.	
Smoke noticeable	Visible smoke from the outlet.	
Second crack	Should not happen. If it does, press Power at once.	
Heating ends	16:00 if the timer ran out. Otherwise the time Power was pressed.	
Cooling ends	Unit returns to standby. Unload only now.	

Measurements

Smell at the end (hay / bread / caramel / smoke): _____

Room temperature (°C): _____

Whole bag after weighing out (g): _____

Location and outlet: _____

Green weight loaded (g): _____

Roasted weight, no chaff (g): _____

Error code (E1 / E2 / E3): _____

Roast date, if not 2026-11-11: _____

After (circle one in each row)

Bean movement	good / sluggish / stalled	**Chaff**	light / moderate / heavy
Color evenness	even / slightly uneven / uneven	**Defects**	none / dark patches / dark tips / chips

If the stopwatch fails: elapsed time = 16:00 minus the display. | Afterwards: empty the chaff bin, photograph the beans beside roast 1, store airtight with the lid closed. | Roast 1 was 80.8 g (10.2 % loss). Expected now: 12–13.5 % loss.