Printed 6 mm balls

30 balls for the Pie Caddy bearing test: 27 go in, 3 are spares.

1 Print them



- **printed_bbs_fine_0.12mm.gcode.3mf: already sliced, send it straight to the printer.**
- 0.12 mm layers, no supports, a 3 mm brim round each ball. About 29 min and 4.2 g.
- Each ball stands on a small flat (3 mm across) so its first layers don't sag.
- Snap each ball off its brim ring: there's a 0.1 mm gap, so it breaks clean.

2 Tidy them (optional, 2 minutes)



- **Each ball has a seam up one side, where every layer starts. It's the main bump.**
- Roll them between two sheets of fine sandpaper, or shake them in a jar with a strip of it.

Design-review renders and a toolpath render of the real slice, not photos.

Printed 6 mm balls: in the bearing test

Design-review renders, not photos.

3 Put 27 in the bearing test



- **Drop them into the channel, then set the top on. Flat side any way up.**
- Put a mug on top and give it a flick.

Good

- It spins with a flick and coasts for a turn or more.
- No wobble, and no balls climbing out of the channel.

Tell me

- spins and coasts, rough or rumbly, or stops dead;
- if any ball stuck flat-side down and slid instead of rolling;
- if you try airsoft BBs too, which one turned better.

Design-review renders and a toolpath render of the real slice, not photos.