



# INSTALLATION INSTRUCTIONS FOR ATLASGS30H

**WARNING:** Read the following carefully before attempting to install or service this unit! Failure to do so may result in bodily injury, property and/or fixture damage. Retain this sheet for future reference.

## GENERAL DESCRIPTION:

This luminaire is designed for indoor and outdoor ceiling mounted application areas and is suitable for use in wet locations. It should not be installed in locations with limited ventilation or within enclosures with high ambient temperatures.

## CAUTION:

Please be sure to follow local electrical codes. Luminaires should only be installed by a qualified electrician.

## ELECTRICAL CONNECTIONS:

Luminaires are factory wired for specific voltages. Make sure the supply voltage is compatible with the luminaire. Universal voltage luminaires may be used with any voltage between 120V and 277V.

## WIRING GUIDE:

HOT = Black

NEUTRAL = White

GROUND = Green or Green w/ Yellow Stripe

## Mounting Instructions

1. Align the  $\frac{3}{4}$ " NPT pendant mount with the  $\frac{3}{4}$ " NPT threaded hole. Rotate the luminaire to secure it onto the pendant mount. Tighten set screw
2. Slide  $\frac{1}{2}$ " NPT wet location rated cord connector over power cord. Screw cord connector into plate.
3. Unscrew plate.
4. Make wiring connections, and secure using supplied wire nuts. Screw plate back onto luminaire.
5. Make sure cord connector and screws are tightly fastened to ensure a water tight seal.

