

QUEST TRACKER

Quick Start Guide

A chore tracking & allowance system for families.
Set up quests, track progress, and pay allowances
-- all from your kiosk.

Version 1.0 | February 2026

What You Need

- Raspberry Pi (3B or 4B) with power supply
- Touchscreen LCD (7" or similar, connected to Pi)
- MicroSD card with the Quest Tracker image pre-installed
- Wi-Fi network (the Pi connects over your home Wi-Fi)

First Boot

Step 1 -- Power On

1. Plug in the power supply.
2. The Pi will boot and the Quest Tracker kiosk appears automatically (30-60 seconds).

Step 2 -- Connect to Wi-Fi (if needed)

1. Tap SYSTEM CONFIG (bottom-right of home screen).
2. Enter the parent PIN (default: 1234).
3. Tap WI-FI, select your network, and enter the password.
4. Wait for connection, then return to home screen.

CHANGE YOUR PIN! The default parent PIN is 1234. Change it immediately under System Config > Configure System > Update Parent PIN.

Adding Your Kids (Crew Members)

Step 3 -- Open Crew Management

1. Tap SYSTEM CONFIG > enter your PIN.
2. Tap MANAGE CREW.
3. Tap + NEW RECORD.

Step 4 -- Create Each Kid's Profile

1. Enter their name.
2. Enter their weekly allowance amount (e.g., 10.00 for \$10/week).
3. Tap CREATE RECORD.
4. Repeat for each child (supports up to 10).

Avatars: After creating a kid, tap their card on the home screen to open their dashboard. From there you can pick a fun sci-fi avatar (robot, rocket, shield, and more).

Creating Quests (Chores)

Quests are the chores your kids need to complete to earn their allowance.

Step 5 -- Open Quest Manager

1. Tap SYSTEM CONFIG > enter your PIN.
2. Tap MANAGE QUESTS.
3. Tap + NEW QUEST.

Step 6 -- Set Up a Quest

1. Assign to: Pick which kid this quest is for.
2. Name: Give it a clear name (e.g., "Dishes", "Clean Room").
3. Description: Optional details about what's expected.
4. Frequency: Daily (every day) or Weekly (once a week on a set day).
5. Tap SAVE QUEST.

Rotation Quests (Shared Chores)

For chores that kids take turns doing (like taking out the trash):

Step 7 -- Create a Rotation

1. In Quest Manager, tap NEW ROTATION.
2. Enter the quest name and description.
3. Choose a rotation type (see table below).
4. Select which kids participate.
5. Tap SAVE QUEST.

Type	How It Works
Alternating Daily	Due every day -- kids take turns (A today, B tomorrow, A again...)
Every Other Day	Due every other day -- kids rotate on active days. Off days = nobody does it.
Biweekly	Due every 2 weeks on the same day of the week as the start date.

Daily Use -- How It Works

For Kids

- Tap your card on the home screen to open your dashboard.
- Tap COMPLETE next to the chore you finished.
- Wait for approval -- the quest shows as pending until a parent reviews it.

Home screen cards show: name & avatar, current balance, today's progress (e.g., 2/3), and a weekly progress bar.

For Parents -- Approving Quests

- Tap PARENT ZONE (bottom-left of home screen).
- Enter your PIN.
- Review pending quests -- tap APPROVE or REJECT for each one.

Tip: Only approved quests count toward the weekly allowance. Rejected quests don't count but the chore can be re-submitted.

Allowance & Payouts

Quest Tracker automatically calculates allowances each week based on quest completion. There are two payout modes:

Mode	How It Works	Best For
All-or-Nothing	Must hit threshold (default 80%) for full allowance. Below threshold = \$0.	Strong motivation
Proportional	60% of quests done = 60% of allowance earned.	Gradual rewards

Configure payout mode:
SYSTEM CONFIG > PIN >
CONFIGURE SYSTEM.

Payouts happen automatically every Sunday at midnight. The earned amount is added to each kid's balance.

Managing Balances

- Go to SYSTEM CONFIG > LEDGER.
- Select a crew member.
- PAYOUT ALL -- resets balance to \$0 (when you hand them cash).
- ADJUST (+/-) -- add a bonus or subtract a penalty.

Web Admin Portal (Remote Access)

Manage everything from your phone or computer -- no need to walk to the kiosk!

Step 8 -- Access the Web Portal

1. Make sure your device is on the same Wi-Fi as the kiosk.
2. Open a browser and go to: `http://<kiosk-ip>:8000/admin`
3. Find the IP: SYSTEM CONFIG > shown on the settings screen.

The web portal has full feature parity -- manage crew, quests, rotations, approvals, ledger, and settings.

Bookmark it! Save the admin URL on your phone's home screen for quick access.

Updating the Kiosk

- Tap SYSTEM CONFIG > enter your PIN.
- Tap CHECK FOR UPDATES.
- If an update is available, it downloads and installs automatically.
- The kiosk will reboot when complete.

Updates preserve all your data (kids, quests, balances, history).

Troubleshooting

Problem	Solution
Shows "CONNECTING..."	Backend is starting. Wait 30 seconds. If it persists, check Wi-Fi or reboot the Pi.
Progress shows 0	Quests must be approved by a parent to count toward progress.
Forgot parent PIN	Need SSH access to the Pi to reset. Contact your admin.
Touch not responding	Reboot the Pi by unplugging and re-plugging the power supply.
Update button fails	Check that the kiosk has an active internet connection (Wi-Fi settings).
Kid not on home screen	Verify the profile was created under Manage Crew and is active.