

GLOBAL

; up · . down · , / left/right · **ENTER** select · ` /DEL back · { } page · **b** screenshot · **h** help

HOME

ENTER opens item; menu scrolls: Satellites, Next Passes, Passes, Track, World Map, Sun/Moon, Space Wx, Weather, QRZ Lookup, Location, Update, Settings, Log, Messages, About

SATELLITES

f favorite · **v** favs-only · **n** new GP sat · **x** del manual sat · **e** EQX table · **k** OSCARLOCATOR · **3** 3D globe · **2** sat-to-sat · **o** orbital · **s** sim · **t** transponders · **d** 10-day · **i** illum · **ENTER** passes · right edge: dot = AMSAT heard, square = telemetry, ring = not heard

SAT-TO-SAT (Sats → 2)

Windows when selected sat + a 2nd fav are BOTH above your horizon (start, dur, peak el each). **n** next sat · **r** recompute · ` back

LIVE GPS POS (Location → v)

DMS lat/lon (max precision) + decimal, alt, grid, speed, course. Rovers/portable. ` back

3D GLOBE (Sats → 3)

Wireframe Earth, auto-follows selected sat. Graticule, coastline, day/night terminator, QTH, favs, selected sat + footprint + ground-track trail. **g** DX 2nd location (grid) + footprint · **G** clear · **arrows** turn · **ENTER** re-follow · ` back

EQX TABLE (Sats → e)

Equator-crossing UTC + longitude (W-positive) for OSCARLOCATOR, next 3 days. ;/. scroll · **d** asc/desc node · **r** recompute · ` back

OSCARLOCATOR (Sats → k)

Live azimuthal-equidistant plot: sub-point, footprint, QTH range ring + full ground track (AOS/LOS). **m** toggle polar (default, auto N/S, flips at equator) / QTH-centred · ` back

DX DOPPLER TABLE (Mutual → d)

RX/TX dial freqs for BOTH stations every 30s across a mutual window. Two lines/step: me (green) + DX (cyan). **t** cycle transponder · **m** mode: true rule / fixed DL / fixed UL · **a** anchor dial (me/DX RX/TX) · ;/ in fixed mode step anchored dial to

round 1 kHz (else passband 1 kHz) · header shows pb +/- from center · ;/. scroll · ` back

NEXT PASSES (favs)

ENTER track · **m** world map · **r** refresh · **z** deep-sleep until AOS

PASSES (sel)

;/. select · **d** detail · **t/ENTER** track · **n** add TX · **r** recompute · **x** mutual-DX · **v** 10-day · **i** illum · **g** grids · **w** US states · **e** DXCC

TRACK (sel)

m TUNE/CAL · **d** tune mode (FULL/DL/UL/hold) · **t** next TX · **n** jump to beacon · **c** CTCSS · **k** CW both legs (linear) · **r** radio · **o** rotator · **p** polar · **z** big readout · **y** tilt on/off (ADV) · **f** Manual · **l** log QSO · **v** voice memo (SD) · **g** grids · **w** states · **e** DXCC now · **ENTER** save cal

BIG READOUT (z from Track)

Big RX/TX + az/el + tune mode (follows Track). Radio+rotator keep tracking · ;/ tune · **s/x** step/ctr · **m/d** mode · **t** TX · **n** beacon · **k** CW (linear) · **r** radio · **o** rot · **y** tilt · **l** log · **z** back

MANUAL (no radio)

Fix one leg, read Doppler freq to tune the other by hand. **u** toggle HOLD/TUNE leg · ;/ passband (linear) · **m** CAL · **t** next TX · **z** big view · **l** log · **p** polar · **g** grids · **w** states · **e** DXCC · ;/f Track

MANUAL BIG (z from Manual)

HOLD/TUNE legs in big digits · **u** swap leg · ;/ tune · **s/x** · **m** CAL · **t** TX · **z** back

TRACK · TUNE

;/ tune · ;/+ · **s** step 100/1k/5k · **x** recenter · tilt to tune if enabled (ADV)

TRACK · CAL

;/ downlink · ;/. uplink · **s** step 10/100/1k · **x** zero

WORKABLE GRIDS / STATES / DXCC

Footprint coverage (per-pass union or live now), count on a cyan line: **g** 4-char grids · **w** US states+DC · **e** DXCC (all 340, hybrid polygons+points). ;/. & {/} scroll · ` back

POLAR / PASS DETAIL

Pass detail: **p** polar of this pass. Polar: **l** log QSO · **p/ENTER** back

SUN / MOON

Graphic sky-dome (Sun/Moon glyphs by az/el) · **g** graphic/list · **/**. pick Sun/Moon · **o** rotor track on/off · **s** sky sources · **x** stop · **`** back

SKY SOURCES (Sun/Moon → s)

Planets (cyan dots) + strong radio sources (orange +): Cas A, Cyg A, galactic centre, Crab, Virgo A, on a sky dome. Antenna-pointing / RF reference. **/**. select · **`** back

SPACE WX (menu)

Solar 10.7cm flux + planetary Kp, labelled & colour-coded, with HF/sat operating outlook & data age · **r** refresh (WiFi) · **`** back

WEATHER (menu)

Current conditions + multi-day forecast for your site (Open-Meteo). Refreshes on entry (WiFi) & with Update. Units in Settings · **r** refresh · cached offline · **`** back

QRZ LOOKUP (menu)

Callsign lookup via QRZ.com XML (needs QRZ XML subscription + user/pass in Settings → Network). **ENTER** type call → name/addr/grid/class. WiFi req'd · **`** back

TRANSPONDER DB (Sats → t)

Sat's transponder/beacon entries: **D** downlink+mode, **U** uplink+tone/inv · **/**. select (* = manual) · **x** del manual (2x) · **`** back

ORBITAL ANALYSIS

/ 9 pages: Info / Live / Next pass / Ground track / Doppler / Nodal / Sun-Beta / Pass outlook / Orbit position · **r** recompute · Doppler **f** sets beacon freq

SIMULATION

/ step time · **/**. step size · **m** world-map view (sub-point + footprint) · **x** reset to now · **`** back

LOCATION

e/o/a lat/lon/alt · **g** grid · **p** GPS on/off · **s** GPS source · **c** set clock · **v** live position (DMS) · **ENTER** GPS sky plot

GPS SKY PLOT

Live GNSS by az/el, coloured by signal (green=strong, grey=weak) · **`** back

WORLD MAP

All footprints · **f** highlight favorite · **c** recenter on QTH/0° · yellow=sunlit cyan=eclipse · **`** back

SCHEDULES

10-day: **/**. scroll +/- 1 day (fills full days), **r** recompute · Illum: **/** scroll +/- 60 days · Mutual: **/**. scroll

LOG

Menu: **ENTER** new QSO / browse / export ADIF / voice memos · List: **/**. scroll, **ENTER** edit · Entry: **/**. field, **ENTER** edit, **s** save, **x** x2 delete

VOICE MEMOS (Log → Voice Memos)

Browse newest-first (date/time/sat/len). **ENTER** play · **n** new · **d** del · **r** refresh · record via **v** on Track. SD req'd

LORA MESSAGES (Home → Messages)

CardSat-to-CardSat broadcast chat (Cap LoRa). Same freq/SF/BW = same group. Set **region** (US 33cm / EU 70cm / JP 430) in Settings for a legal default freq. **n** write/send · **/**. scroll · **r** retry · **`** back. **Rx always on**: new msgs show an envelope+count badge in the header on any screen, plus a banner (opt-in beep) — set **Msg notify** (off/banner/banner+beep) in Settings. Needs RadioLib build. Untested HW

UPDATE

k/ENTER GP+clock+AMSAT+space-wx+weather · **f** fast (GP+AMSAT+favs' TX) · **a** cache all TX (auto-reboots) · **w** WiFi only

SETTINGS

/ change · **ENTER** edit/toggle · **s** scan WiFi · opt. 2nd WiFi (field fallback) · reset = ERASE

GP SOURCE

AMSAT / **CelesTrak** JSON-PP category / **Custom URL** · **/**. move · **ENTER** select

ROTATOR (manual)

/ az · **/**. el · **s** step · **x** stop · **`** back

NETWORK SERVERS

rigctl PC drives rig (VFOA=DL/B=UL) · **rotctl** PC drives GS-232 · **rigctl** drives remote rig · **Web** opt-in mobile page (no auth, trusted LAN)

EDIT

type · **DEL** backspace · **ENTER** ok · **`** cancel

ABOUT

Build/version, IP, free heap and diagnostics (read-only).