

Concept Review

LCD Touch Displays

Why Use Touchscreen Displays?

Touchscreens are ubiquitous in modern technology that span across multiple engineering disciplines, from smartphones and tablets to industrial control panels and automotive systems. Engineers routinely specify displays for applications ranging from consumer electronics to industrial equipment, making knowledge of touchscreen operating principles and selection criteria a valuable engineering skill.

Introduction

A touchscreen, also known as a touch panel or touch monitor, is an electronic visual display that combines the functions of both a display and an input device, allowing users to interact directly with content using their fingers or a stylus. These devices enable people to operate computers and digital systems through direct touch, replacing the need for traditional keyboards or mice with a more intuitive interface.

The major differences between touchscreen technologies lie in how the touch is detected. Some measure physical pressure, others detect changes in electrostatic fields, while others use sound waves or light beams. All technologies require sophisticated signal processing circuits to ensure precise and fast interface response.

Operating Principle

The fundamental operation of any touchscreen involves detecting a touch point and translating it into X-Y coordinates. At their core, touchscreens use internal sensors to detect a user's touch, which is then translated into an instructional command that results in visible system response. The key element in any touchscreen is the detection layer, which translates a simple finger touch into coordinates and signals the system can understand and act upon.

Types of Touchscreen Technologies

While several touchscreen technologies exist (including infrared, surface acoustic wave, and optical imaging), this document focuses on the two most common types: **resistive** and **capacitive** touchscreens. Understanding the differences between capacitive and resistive technologies enables engineers to make informed decisions when specifying displays. The choice involves carefully balancing sensitivity, durability, cost, environmental conditions, and user requirements to select the optimal technology for each application.




Figure 1: Both resistive and capacitive touchscreens make use of a transparent conducting material, typically indium tin oxide (ITO), to detect touch inputs.

Capacitive Touchscreens

Capacitive touch screens detect changes in capacitance, the ability of an object to store energy in the form of an electric charge. The screen surface maintains a small uniform electrical charge within a transparent conductive layer. When a conductive object (such as a human finger) approaches the surface, it alters the electric field. Sensors, usually placed at the screen's corners, measure the change in capacitance and calculate the precise touch location.

Resistive Touchscreens

Resistive touchscreens represent an older but still relevant technology, consisting of two flexible conductive layers separated by a tiny air gap and spacer dots. The system applies voltage to the layers alternately. When pressure is applied to the screen surface, the top layer flexes and contacts the bottom layer, closing an electrical connection. This creates a voltage divider, and by measuring the voltage at the point of contact, the controller calculates the X and Y coordinates of the touch.

Comparison of Touchscreen Types

Each touchscreen type has its own benefits and drawbacks. Capacitive touchscreens offer faster, more precise responses than resistive touchscreens. For a lower cost, a resistive touchscreen offers less precision and requires more force since it operates using pressure-based detection. At the same time, this property enables resistive touchscreens to be operated with gloves or a stylus, making it more suitable for applications such as industrial controls, medical equipment, and point-of-sale systems. Capacitive touchscreens support multiple touch inputs and a higher display clarity, so they are often found in consumer devices such as smartphones, household appliances, and tablets.

Advantages and Limitations of Touchscreens

While the specific advantages and disadvantages of capacitive and resistive technologies are critical for selection, touchscreens in general offer several benefits. They provide intuitive, direct interaction with content that reduces learning curves and simplifies input through natural gestures like tapping and swiping. Touchscreens enable space-saving, compact designs by eliminating physical keyboards and mice, and modern capacitive screens support multi-touch capabilities for rich interactions. The flexibility of touch interfaces allows for dynamic, context-sensitive controls that adapt to user needs.

However, touchscreens also present some general limitations. They can be less precise than traditional input devices for detailed work, and accumulate fingerprints requiring regular cleaning. Extended typing on touchscreen keyboards is generally less efficient than physical keyboards, and larger screens can be susceptible to accidental inputs.

Datasheet and Selection Considerations

When selecting an appropriate touchscreen technology for a specific application, consider requirements for both the touch input and display screen:

Input complexity: Applications requiring multi-touch gestures, such as pinch-to-zoom or two-finger scroll, will require capacitive technology while resistive touchscreens are better suited for simple, single-touch inputs.

Sensitivity and input methods: Will users interact with bare fingers, gloved hands, or styluses? Environments requiring gloved operation, such as manufacturing, may call for resistive touchscreens.

Size and display capabilities: Consider the physical screen size (measured in inches) and resolution (total pixels). Also determine whether the display will actively show content or simply record input, such as a signature capture device or drawing tablet that does not require integrated display functionality.

Controller requirements: Does the display include an integrated controller or requires an external controller module? Consider the communication interface (USB, I²C, SPI) and driver support for your target operating system or microcontroller platform.

Durability and environmental conditions: Consider resistance to scratches, impacts, liquid spills, temperature extremes, or chemically resistant coatings. Capacitive touchscreens offer the best scratch-resistance due to their glass surface but can still be shattered by impacts. Resistive touchscreens are less susceptible to input errors caused by dust or dirt on the screen.

Optical performance and lighting conditions: Evaluate lighting conditions in the intended installation location to ensure that the display has adequate readability given the amount of glare, reflection, and sunlight in the environment. Other factors that impact readability of the display are its brightness, clarity, and viewing angle. Capacitive screens offer superior optical performance, while resistive screens have reduced clarity due to multiple layers.

Lifespan and maintenance: Resistive screens may wear over time from repeated pressing, while capacitive screens typically offer longer operational life.

Sources: <https://www.iqsdirectory.com/articles/membrane-switch/capacitive-touch-screens.html>
<https://butlertechnologies.com/blog/capacitive-touch-screen-types-benefits>
<https://www.hp.com/us-en/shop/tech-takes/how-do-touch-screens-work>

© Quanser Inc., All rights reserved.



Solutions for teaching and research. Made in Canada.