TELECOMMUNICATIONS TECHNOLOGY SOLUTIONS INCORPORATED (TELTECH)

NATIONWIDE 5G STANDALONE (SA) FIXED WIRELESS ACCESS (FWA) NETWORK

RFP REFERENCE: RFP-TELTECH-FWA-2026-001

BID BULLETIN NO. 1

TO ALL PROSPECTIVE BIDDERS: All Qualified Bidders, System Integrators, and Authorized Equipment Suppliers
FROM: Oliver Tungol, Lead Technical Architect & Tender Secretariat
DATE OF ISSUANCE: October 21, 2026
SUBJECT: Official Clarifications, Technical Baseline Amendments, and Response Matrix to Bidder Inquiries

1. EXECUTIVE SUMMARY & PURPOSE

This **Bid Bulletin No. 1** is issued pursuant to Section 1.5 (*Clarification and Amendment of Bidding Documents*) of the Master RFP Document. It provides binding official responses to technical, commercial, civil, and operational inquiries submitted by prospective bidders between October 19 and October 21, 2026.

All amendments, specifications, and clarifications contained herein are hereby incorporated into the Tender Documents and shall form an integral part of the final contract for the **Turnkey 5G SA FWA Rollout (1,000 Phase 1 Macro Sites)**.

2. KEY ARCHITECTURAL & CONTROLLING CLARIFICATIONS

2.1 Spectrum Physics, Band n50 Operating Bandwidth & Regional Boundaries

1. **Metro Manila (NCR) & Meralco Franchise Footprint:**
2. Operating Band: **1457 – 1517 MHz (60 MHz continuous channel bandwidth TDD)**.
3. Resource Blocks: **162 RBs** at 30 kHz Subcarrier Spacing (SCS).
4. Boundary Condition: In Metro Manila (NCR) and non-NCR municipalities within the Meralco electric distribution franchise (parts of Bulacan, Cavite, Rizal, Laguna, Batangas, Quezon, and Pampanga) where the 1437–1457 MHz sub-band is assigned to the utility corporation, the 1437–1457 MHz block is excluded from Operator transmissions. RRU transceivers implement sharp digital filtering with Digital Pre-Distortion (DPD) to guarantee adjacent-channel isolation.
5. **Rest of the Country (Provincial / Regional / Non-Meralco Footprint):**
6. Operating Band: **1437 – 1517 MHz (up to 80 MHz continuous channel bandwidth TDD — Desired Baseline)**.
7. Resource Blocks: **217 RBs** at 30 kHz SCS (+34% capacity gain, unlocking 650–720 Mbps aggregate sector downlink throughput).
8. **Hardware Tuning Capability:**
9. All proposed Baseband Units (BBU) and Remote Radio Units (RRU) / Active Antenna Units (AAU) must natively support the full 3GPP Band n50 range (**1432 – 1517 MHz**) in hardware.
10. Operating bandwidth must be software-configurable to 40 MHz, 50 MHz, 60 MHz, or 80 MHz without requiring tower-climbing or hardware replacement.
11. **Out-of-Band Rejection & Satellite Protection:**
12. High End (1517 MHz): Must comply with **ITU-R M.2159-0 / WRC-15 Resolution 223** to protect adjacent Maritime Mobile Satellite Service (MSS, 1518 – 1525 MHz). Transceiver unwanted emissions in the 1518–1525 MHz band must not exceed -30 dBm/MHz at the antenna port. Standard 3GPP TS 38.104 Category B filtering is compliant.
13. Low End (1437 / 1457 MHz): Must comply with 3GPP Category B Operating Band Unwanted Emissions (OBUE). Digital Pre-Distortion (DPD) within the RRU ensures sharp rolloff at the assigned carrier boundary.

2.2 Power Architecture & Rectifier Sizing Methodology (Lot 2)

1. **Installed Capacity:** Sized at **>= 12.0 kW total installed capacity** using **4 × 3.0 kW (or 4 × 4.0 kW) modular hot-swappable switchmode rectifier modules in an N+1 architecture**.
2. **Operational Load under N+1:** With a single module failure (3 operational modules), the system provides **9.0 kW continuous DC output**, which comfortably accommodates the maximum site DC load of **7.28 kW** (3.0 kW BTS RAN load + 4.28 kW fast battery recharging at 0.2C for a 400 Ah / 20 kWh lithium bank).
3. **Mounting:** Weather-resistant (IP55) integrated outdoor ground-mounted power/battery cabinets on an elevated concrete pad represent the baseline design. Pole-mounted or wall-mounted power units are approved for rooftop/space-constrained co-location sites.

2.3 Transmission, Backhaul Architecture & KPI Tiering

1. **Media-Tiered Latency SLAs (Document 04 / Appendix C Amendment):**
   - **Phase 1 Terrestrial Fiber-Connected Sites (100% of Phase 1):** Ping Round-Trip Time (RTT) ≤ 18 ms target (≤ 30 ms maximum). Following executive fiber-priority rollout alignment, all 1,000 Phase 1 sites are assigned to terrestrial fiber backhaul (962 sites ≤ 1.0 km from existing fiber/nodes, and 38 sites > 1.0 km planned for lateral drops under Comclark optical rollout), eliminating satellite backhaul from Phase 1 scope.
   - **Starlink Satellite-Fed Sites (Phase 2 / Expansion Batches):** For remote/island candidates in subsequent rollout batches where terrestrial fiber is unviable, the LEO satellite latency threshold is relaxed to **≤ 60 ms target (≤ 80 ms maximum)** during SSV and cluster acceptance to reflect satellite orbital physics.
2. **Backhaul Outage Exclusions:**
   - Downtime, packet loss, or latency degradation caused by third-party fiber cuts, upstream IP transit failures, or satellite constellation outages outside the site compound are strictly excluded from supplier RAN availability SLA penalties.

2.4 TowerCo, Civil Works & Site Siting

1. **Phase 1 Siting Quantities & Commercial Allocation Baseline:** The contractual commercial evaluated baseline across all RFP documents (Master Tender Section 2.1, BoQ Table 6, and Appendix D) is formally confirmed at **897 Co-location Sites (89.7%) and 103 Greenfield Monopole Sites (10.3%)**. In Document 07, spatial proximity screening against the audited master database classifies 885 Co-location Candidates within ≤ 2.0 km and 115 Greenfield Candidates at Class T4 (> 2.0 km) nationwide. While tender evaluation and contract award remain strictly anchored on the 897 / 103 commercial baseline, actual site implementation counts will be determined during Milestone 1 TSSR approvals: if a screened greenfield site identifies an unmapped operational tower within the search ring, it converts to Tier 1 co-location; conversely, if an audited tower fails structural load verification, it converts to Tier 2 B2S or Tier 3 greenfield substitution.
2. **Commercial Valuation & Siting True-Up Mechanism:** While tender evaluation and contract award are based on the lump-sum pricing of the 897 Co-Location / 103 Greenfield baseline, actual contractor compensation will be trued up at Milestone 1 (TSSR Approval). If an evaluated co-location site converts to Tier 2 B2S or Tier 3 Greenfield (or vice-versa), contract value adjustments shall be calculated strictly using Document 06 Table 5B (Siting Conversion & Milestone 1 True-Up Rate Schedule) via an administrative contract variation order:
   - **Tier 1 Co-Location Baseline (`LOT5-COLO`):** Rate = Item CIV-SVC-03 ($0.00 variation differential).
   - **Tier 2 TowerCo Build-to-Suit (`LOT5-B2S`):** Under the Operator MLA, the TowerCo finances, permits, and constructs the tower and compound turnkey; Operator civil scope is identical to co-location (`CIV-SVC-03`). Rate = `LOT5-B2S` = `CIV-SVC-03` . Variation differential vs. Co-Location = **$0.00 / site** (`LOT5-B2S - LOT5-COLO = $0.00`).
   - **Tier 3 Greenfield 30m Monopole (`LOT5-GF30`):** Compound foundation, 8x8m fence/gravel, grounding grid, 30m monopole, and SAQ permits (`CIV-SVC-02 + CIV-SVC-04 + CIV-SVC-05 + CIV-SVC-06`). Net contractual addition per converted co-location site: **`ACost = LOT5-GF30 - LOT5-COLO = (CIV-SVC-02 + CIV-SVC-04 + CIV-SVC-05 + CIV-SVC-06) - CIV-SVC-03`** . Reverse conversion from GF30 to Co-Lo issues an equivalent credit.
   - **Tier 3 Greenfield 40m Monopole (`LOT5-GF40`):** Compound foundation, 8x8m fence/gravel, grounding grid, 40m monopole, and SAQ permits (`CIV-SVC-02 + CIV-SVC-04 + CIV-SVC-05 + CIV-SVC-07`). Net contractual addition per converted co-location site: **`ACost = LOT5-GF40 - LOT5-COLO = (CIV-SVC-02 + CIV-SVC-04 + CIV-SVC-05 + CIV-SVC-07) - CIV-SVC-03`** . Reverse conversion from GF40 to Co-Lo issues an equivalent credit.
3. **Division of Structural Responsibilities (Audit vs. Analysis):**
   - **Contractor Scope (Structural Audit):** The turnkey contractor's scope is strictly on-site physical auditing—recording tower member dimensions, mounting elevations, existing antenna counts, azimuths, and compiling the total proposed equipment loading profile (weights, surface areas, wind drag).
   - **TowerCo / Operator Scope (Structural Analysis & Certification):** Formal structural loading analysis, wind stress modeling, foundation capacity verification, and structural PE sign-off are performed by the TowerCo under the Operator's Master Lease Agreement (MLA). Required tower retrofits/reinforcements are executed by the TowerCo under the MLA.
4. **Site Hunting & Excluded Sites:** Delays caused by local government (LGU) moratoria, right-of-way disputes, or utility connection delays exceeding 45 days permit the Operator and supplier to substitute the blocked candidate with a pre-approved site from the 4,000-candidate reserve pool

without schedule penalty.

5. **Variation Orders (VOs):** Abnormal site construction conditions (hard rock excavation requiring pneumatic equipment, manual material hauling > 500 meters across unpaved/mountainous terrain, and engineered retaining walls) are eligible for established unit-rate Variation Orders under Lot 5.
6. **Mandatory 3-Tier Infrastructure Sourcing Hierarchy (TowerCo-First Mandate):** Siting must strictly follow:
   - **Tier 1 (Mandatory Baseline):** Co-location on existing operational towers across the Operator's audited master database of **13,810 nationwide TowerCo registry records (representing 13,746 deduplicated operational physical tower candidate locations across all licensed Philippine Independent TowerCos; 13,799 unique Universal Tower IDs)**. Reduces Ready-for-Installation (RFI) to 15–30 days.
   - **Tier 2 (Secondary):** TowerCo Build-to-Suit (B2S) under TelTech MLA if structural loading exceeds EPA limits on existing towers.
   - **Tier 3 (Restricted Exception):** Operator own-build greenfield monopoles are strictly restricted to search rings where no feasible or available TowerCo infrastructure exists after documented technical and field checks. Qualification operates strictly under two mutually exclusive pathways:
     - **Pathway A (Zero Infrastructure / Siting Void):** Confirmed total absence of operational towers within the primary search ring (500m urban / 1,000m rural) and within 2.0 km line-of-sight. Substantiation: Certified Absence of Tower Infrastructure in the approved joint TSSR, verified against the audited master database and 360° drone/visual survey.
     - **Pathway B (Technical / Structural Exhaustion of Existing Infrastructure):** Where operational towers exist within the search ring or within 2.0 km, but co-location is physically or structurally unfeasible due to: (i) structural over-utilization / EPA overload where the TowerCo confirms the tower cannot support additional 3x 8T8R AAU mounts and foundation reinforcement is unviable; (ii) physical compound/aperture exhaustion (zero ground space for outdoor DC power pad or no vertical mounting aperture at required AGL); or (iii) unresolvable terrain/foliage clutter blocking optical Fresnel zone line-of-sight into the target settlement cluster. Substantiation: Formal written **Structural Denial / Space Unavailability Letter(s)** issued by the operating TowerCo(s) under the MLA framework (a single denial letter if only 1 TowerCo operates in the ring; minimum 2 letters if multiple TowerCos operate within the ring), accompanied by TSSR RF simulation proving coverage blockage.
   - **Survey Exception Candidates:** Sited co-location candidate references located between 1.0 km and 2.0 km from the demand centroid (including 174 Phase 1 candidate references) are designated Survey Exception Candidates: during Milestone 1 TSSR, field teams evaluate whether clear line-of-sight and link budget (RSRP ≥ -105 dBm) can be achieved from the out-of-ring tower; if confirmed, the candidate is confirmed as Tier 1 Co-Location; if obstructed or unfeasible, the candidate converts under Pathway A or B to Tier 2 B2S or Tier 3 Greenfield at the nominal demand centroid.
7. **Search Ring Sizing & Mandatory 3-Candidate Rule (A, B, C):**
   - **Search Rings:** Strictly 500 meters radius for Urban/Suburban; 1,000 meters radius for Rural/Remote centered on the nominal demand centroid. Search rings define site hunting limits and are completely distinct from RF cell coverage radii (2.5–3.2 km rural, 1.0–1.5 km urban).
   - **3-Candidate Presentation:** Field teams must present Candidate A (BEST — Primary Target), Candidate B (BETTER — Secondary Backup), and Candidate C (GOOD — Fallback). Where fewer than three viable structures exist in remote rural rings, documented justification in the TSSR is permitted.
   - **Commercial Authority:** All commercial lease negotiations, space reservations, and MLA Service Orders with TowerCos are strictly the exclusive responsibility of the Operator (TelTech/Comclark). The contractor's scope is technical identification, structural audit data gathering, and TSSR submission.
   - **14-Day Technical Escalation Protocol:** If Candidate A fails structural loading verification or if Operator-TowerCo commercial SAA processing encounters an impasse exceeding 14 calendar days, the Operator shall instruct the contractor to immediately activate Candidate B to prevent project delay.
8. **Structural Wind Load Standards & Deflection Limits (NSCP 2015 7th Ed. / TIA-222-H):**
   - **Governing Design Standard:** National Structural Code of the Philippines (NSCP 2015 7th Edition, Section 207 Wind Loads) and ANSI/TIA-222-H. Structure classification: Essential Communications Facility / Risk Category IV (Importance Factor $I_w = 1.15$).
   - **Nominal Basic Design Wind Speed (ASD):** Minimum basic design wind speed is **250 km/h (ASD nominal fastest-mile / 10-minute mean equivalent per NSCP 2015 Category IV)** for structural strength and foundation stability calculations.
   - **Ultimate / Survivable Wind Speed (V_{ult} / LRFD 3-second gust):** Conforms strictly to **NSCP 2015 Wind Zones**:
     - **Zone 1 (V_{ult} = 315 km/h / 87.5 m/s):** High-typhoon eastern seaboard (Batanes, Cagayan, Isabela, Aurora, eastern Quezon coast/Polillo, Bicol Region, Samar, Leyte, Dinagat Islands, Surigao del Norte/Sur, Davao Oriental).
     - **Zone 2 (V_{ult} = 270 km/h / 75.0 m/s):** Central and Western Luzon (NCR, Bulacan, Pampanga, Tarlac, Bataan, Zambales, Nueva Ecija), CALABARZON (western Quezon, Laguna, Batangas, Cavite, Rizal), MIMAROPA (Occidental/Oriental Mindoro, Marinduque, Romblon), and Western/Central Visayas (Iloilo, Cebu, Bohol, Negros).
     - **Zone 3 (V_{ult} = 250 km/h / 69.4 m/s Minimum Project Floor):** Low-risk regions (Palawan, Zamboanga Peninsula, and southern inland Mindanao). While NSCP maps Zone 3 at 200 km/h, the Project enforces 250 km/h minimum ultimate survivability nationwide as a mandatory contractual quality floor.
   - **Operational Wind Speed:** 140 – 160 km/h (Serviceability Limit State per TIA-222-H).
   - **Allowable Twist:** ≤ ±0.5° for MW, ≤ ±1.0° for macro sector; **Allowable Sway:** ≤ ±1.0°; **Verticality (Plumbness):** ≤ 1:500 (0.20% of height H = 60 mm for 30m tower). Details codified in revised Appendix D.

9. **Panoramic Drone Survey & Permitting Waiver:** High-resolution 360° panoramic video and cardinal-point photos at antenna centerline. *Conditional Waiver:* Where drone flight is prohibited/restricted by CAAP or military airspace regulations, OR where local municipal/flight permits cannot be secured within fourteen (14) calendar days, high-magnification telephoto mast photography from multiple ground vantage points combined with verified TowerCo structural drawings is acceptable upon Operator approval.

2.5 Digital OSS/BSS & 5G Core Architecture

1. **Turnkey BSS Scope:** Real-time Prepaid Convergent Charging System (CCS/CHF via 3GPP Nchf/Diameter Ro) for the 4 consumer FWA tiers (₱599, ₱799, ₱999, ₱1,299). Complex cyclic enterprise invoicing is handled via integration with Comclark/TelTech's existing enterprise billing platform.
2. **SIM-IMEI & Cell-ID Location Locking:** The BSS/PCF must enforce strict hardware-network binding to ensure FWA service cannot be operated outside the authorized installation address.
3. **Core Network Functions (NEF & SEPP):** In Phase 1, NEF (Network Exposure) and SEPP (Security Edge Protection Proxy) are optional/phased roadmap functions.
4. **Compute Platform:** Dual-socket carrier-grade x86 (Intel/AMD) or equivalent enterprise ARM-based architecture running certified carrier-grade Linux / Kubernetes is fully acceptable.

2.6 Customer Premises Equipment (CPE - Lot 7)

1. **Operating Band:** Native Band n50 (1432 – 1517 MHz, 60 MHz TDD) in 5G SA mode is mandatory.
2. **Indoor CPE Antenna Gain:** Integrated antenna array gain of **5.0 – 6.0 dBi across Band n50** is accepted as compliant (leveraging the superior propagation of 1.5 GHz compared to 3.5 GHz). Outdoor CPE requires >= 12.0 dBi.
3. **SIM Form Factor:** Physical Nano-SIM (4FF) with anti-theft locking cover is mandatory. eSIM (MFF2) is an acceptable optional enhancement.

---

3. CONSOLIDATED RESPONSE MATRIX (PART 1: RAN, POWER & TRANSMISSION)

NO.	DOMAIN	REFERENCE SECTION	PROSPECTIVE BIDDER CLARIFICATION REQUEST	COMCLARK / TELTECH OFFICIAL RESPONSE
1	RAN	2.1 Spectrum Physics: Band n50 Advantage	Since the 1437–1457 MHz band has been assigned to another corporation in the NCR, kindly please confirm the following spectrum deployment plan: Metro Manila (NCR): 1457–1517 MHz (60 MHz) Rest of the country: 1437–1517 MHz (80 MHz)	CONFIRMED. The baseline spectrum deployment plan is formally confirmed as follows: 1. Metro Manila (NCR): 1457 – 1517 MHz (60 MHz continuous TD bandwidth), fully compliant with the Operator's statutory authori NTC demonstration permit. 2. Rest of the Country (Provincial / Regional): 1437 – 1517 MHz (MHz IBW/OBW capability). Bidders' 5G NR Baseband Units (BBU) and Remote Radio Units (Active Antenna Units (AAU) must natively support the full 3GPP tuning range (1432 – 1517 MHz) in hardware, with carrier bandwi software-configurable to 40 MHz, 50 MHz, 60 MHz, or up to 80 assigned.
2	RAN	2.1 Spectrum Physics: Band n50 Advantage	Further clarification is required regarding the bandwidth that needs to be supported. Are there any special	CONFIRMED & DETAILED: Point 1 (NCR Carrier: 1457–1517 MHz): Supplier equipment must with 3GPP TS 38.104 Category B Operating Band Unwanted Emi (OBUE) and standard NTC Type Approval spurious emission mas low end (1457 MHz), the RRU digital filtering and DPD must ensu attenuation to protect adjacent users below 1457 MHz. At the hig (1517 MHz), equipment must implement appropriate filtering to p the adjacent Maritime Mobile Satellite Service (MSS, 1518–1525

NO.	DOMAIN	REFERENCE SECTION	PROSPECTIVE BIDDER CLARIFICATION REQUEST	COMCLARK / TELTECH OFFICIAL RESPONSE
			customization requirements for the filter's out-of-band rejection and emissions? Point 1: If the 1437–1457 MHz band is occupied by another operator, are there any specific spurious emission requirements that supplier's equipment must comply with for the low end and high end(1457M and 1517M)? Point 2: If the 1437–1457 MHz band is available for use outside the NCR areas, does the NTC impose any spurious emission requirements for the low and high end(1437M and 1517M)?	ITU-R M.2159-0), with unwanted emissions not exceeding -30 d Point 2 (Outside NCR: 1437–1517 MHz): Standard 3GPP Band n5 38.104 Category B emission masks apply at the 1437 MHz lower 1517 MHz upper edge. No non-standard or proprietary hardware customization is required beyond compliant 3GPP Release 16/17 radio hardware.
3	RF Planning	07_RFP_5G_FWA_Candidate_Site_List_and_Rollout_Schedule.xlsx	To support the above planning activities, bidder kindly requests Comclark/TelTech to share the following information for the nearest tower(s): location (longitude / latitude) and tower height.	CONFIRMED & PROVIDED VIA DEDICATED INVENTORY. 1. Candidate site nominal demand centroids (Latitude / Longitud WGS84) for all 1,000 Phase 1 candidate sites are fully provided i Document 07 ('07_RFP_5G_FWA_Candidate_Site_List_and_Rollout_Schedule. 2. The audited master inventory of **13,810 operational co-locat towers**—including TowerCo IDs, Operator MNO IDs, precise geo coordinates (WGS84 Lat/Long), structure types, and tower heigh Ground Level (m AGL) across PTCI/MIDC, EdgePoint, LDIC, FTAP and FTAP Smart—is classified as Proprietary Commercial Informa is released exclusively to accredited bidders as companion work **`09_Towerco_Master_Asset_Inventory.xlsx`** upon execution formal Project Non-Disclosure Agreement (NDA) via the RFP Sec (rfp-5g@teltech.ph).
4	Transmission	2.3 Transmission & Backhaul Topology	Bidder proposes that Comclark/TelTech clarify the defination of "fiber segments" and the "optical nodes"	CLARIFICATION OF DEFINITIONS: - 'Optical Node': An audited, active Comclark/TelTech point-of-interconnect—specifically an Optical Distribution Frame (ODF), F Distribution Terminal (FDT), or Primary Fiber Hub equipped with optical splice/splitter capacity to serve as the backhaul transmis handover point. - 'Fiber Segment': An audited physical fiber optic cable route (fe distribution, or lateral FOC) spanning between the optical node/c office and the customer/tower drop point, as verified in Comclark/TelTech's audited GIS distribution plant.
5	Transmission	2.3 Transmission & Backhaul Topology	Bidder proposes that Comclark/TelTech	CLARIFICATION OF DEFINITION: 'Class C: Line-tap splice closure <= 0.5 km' designates a candid tower location where an existing aerial or underground Comclark

NO.	DOMAIN	REFERENCE SECTION	PROSPECTIVE BIDDER CLARIFICATION REQUEST	COMCLARK / TELTECH OFFICIAL RESPONSE
			clarify the defination of " C: Line-tap splice closure <= 0.5 km"	trunk/distribution fiber optic cable passes within 500 meters of t compound, and interconnection will be achieved by cutting into at an existing or newly inserted inline splice closure (FOSC / Don Enclosure) rather than routing back to a centralized ODF/node.
6	Transmission	2.4 Backhaul Transmission Path Survey	Does the "distance to the nearest node" refer to the distance to the 5G base station ? Bidder proposes that Comclark/TelTech clarify the defination of " distance to line-tap closure"	CLARIFICATION OF DEFINITIONS: - 'Distance to Nearest Node': Refers to the estimated terrestrial cable route distance from the proposed 5G Macro Tower compo nearest confirmed Comclark/TelTech Optical Node (Class A <= 0 Class B <= 1.0 km). - 'Distance to Line-Tap Closure': Refers to the linear cable distar the 5G Base Station to the designated trunk cable splice closure <= 0.5 km).
7	Transmission	2.3 Transmission & Backhaul Topology	Bidder respectfully proposes that Comclark/TelTech confirm whether the Microwave solution for Class D is to be considered within the Supplier's scope of supply, or whether it will be provided by Comclark/TelTech directly.	CONFIRMED: SUPPLIER SCOPE OF SUPPLY / PRICING. Class D sites (~1.7% of Phase 1 sites, plus microwave backup lin island sites) require a turnkey high-capacity microwave backhau GHz / 18 GHz / 23 GHz or E-Band 80 GHz, minimum 1.0 Gbps ful throughput). Bidders must quote the microwave split-mount hard (IDU, ODU, antenna, IF cabling) and installation services in Appe (Commercial BoQ) under Lot 1 / Lot 3 options. Comclark/TelTech the right to provide direct fiber drops prior to NTP where feasible
8	Power	PWR-01	Kindly confirm whether the 12 kW rating refers to the total installed rectifier capacity (4 × 3 kW modules, including one N+1 redundant module) rather than the output that must be maintained after a single module failure. For reference, a typical load — 3 kW BTS with a 400 Ah battery charged at 0.2C — requires a total DC demand of 7.28 kW (4.28 kW charging + 3 kW BTS load). This demand is fully served by three 3 kW modules, with a fourth module providing N+1	CONFIRMED ACCEPTABLE. The required sizing methodology is confirmed as follows: - Total Installed Rectifier Capacity: >= 12.0 kW composed of 4 × (or 4 × 4.0 kW) modular hot-swappable switchmode rectifier mo an N+1 architecture. - Active Operational Capacity under N+1: With a single module fa operational modules), the system provides 9.0 kW continuous D which comfortably exceeds the peak site DC demand of 7.28 kW BTS RAN load + 4.28 kW fast battery recharging at 0.2C for 400 kWh lithium bank). Supplier's proposed load-based N+1 configuration is fully compl

NO.	DOMAIN	REFERENCE SECTION	PROSPECTIVE BIDDER CLARIFICATION REQUEST	COMCLARK / TELTECH OFFICIAL RESPONSE
			redundancy (12 kW installed; 9 kW available under N+1). Supplier appreciates your confirmation that this load-based N+1 sizing methodology is acceptable, including functionally equivalent configurations.	
9	Power	PWR-01 / PWR-04	Please clarify whether pole-mounted installation is mandatory or an integrated ground-mounted outdoor cabinet is acceptable for power HW and RAN HW ?	CLARIFICATION OF INSTALLATION STANDARD: Both configurations are acceptable depending on site compound archetype: 1. Co-location / Rooftop Sites with Space Constraints: Integrated pole-mounted or wall-mounted power/RAN solutions are accepta where ground compound footprint is restricted by the TowerCo. 2. Greenfield / Ground Compound Sites (Standard): An integrate weather-resistant (IP55) ground-mounted outdoor power & batt cabinet installed on an elevated equipment concrete pad is the p baseline design.
10	Project	LOT 5: SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS	Who is the responsible for transmission and last mile ?	DIVISION OF RESPONSIBILITY: - Comclark / TelTech Scope: Core IP/MPLS network, backbone tr optical node infrastructure, upstream bandwidth, fiber drop cabl provisioning up to the tower demarcation/ODF, and Starlink satel terminals. - Supplier Scope: Turnkey supply of optical transceivers (10G/25 eCPRI and 10G/25G SFP+ backhaul optics), armored optical patc terminal fiber interconnect from tower demarcation box to Baseb (BBU), and end-to-end backhaul circuit acceptance testing durir
11	Project	LOT 2: POWER SYSTEMS & PASSIVE INFRASTRUCTURE	There are no engineering services items about Rectifier, Battery, Tap-Off Box & Submeter, Getset, pls confirm engineering services isn't supplier's scope.	CLARIFICATION OF SERVICES SCOPE: Installation, wiring, and commissioning of the rectifier, lithium ba bank, AC tap-off box, submeter, and optional genset are include turnkey rollout scope under Lot 1 Services (Table 2: RAN Turnkey Services, Item RAN-SVC-02) and Lot 5 (Civil Works & Power Inte Turnkey implementation includes all physical mounting, DC cabli breaker terminations, grounding, and commissioning of the powe subsystem.
12	Project	LOT 5: SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS	Please provide detailed site design for each civil work item, such as: Equipment Pad Foundation & Cable Gantry, Greenfield Compound Civil Works & Foundation, Grounding Grid & Lightning Protection System,	CLARIFICATION & GUIDELINES: Typical engineering guidelines, governing wind loading specifica (250 km/h ASD basic design wind speed with 270–315 km/h ultir survivability conforming to NSCP 2015 Category IV / TIA-222-H) bearing criteria, and grounding grid requirements (<= 5 Ohms) a detailed in Document 05 ('05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidel Detailed structural fabrication and foundation construction draw established during the Joint Technical Site Survey (TSSR) stage Milestone 1) based on site-specific geotechnical soil test results actual compound boundaries. Bidders are invited to submit their type-approved civil drawings and monopole designs in their tech proposal for committee evaluation.

NO.	DOMAIN	REFERENCE SECTION	PROSPECTIVE BIDDER CLARIFICATION REQUEST	COMCLARK / TELTECH OFFICIAL RESPONSE
			30m/40m Galvanized Steel Monopole Tower.	
13	Project	LOT 5: SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS	There are no engineering services items about Commercial Power Access, pls confirm engineering services isn't supplier's scope.	COORDINATED SCOPE: - TelTech / Operator Scope: Payment of official electric cooperat Meralco / DU) application fees, transformer capital contributions deposits, and power supply contracts. - Supplier Scope: Turnkey on-site civil and electrical works from property line / service drop demarcation pole to the equipment p including service entrance conduit/riser, utility revenue class kW base/enclosure, main service disconnect switch, AC panel (ACPI surge protective device (Type 1+2 SPD).

4. CONSOLIDATED RESPONSE MATRIX (PART 2: DETAILED BIDDER INQUIRIES)

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
1	Other Business Matters	01_RFP_5G_FWA_Master_Tender_Document (5. TENDER SUBMISSION STRUCTURE & COMPLIANCE REQUIREMENTS)	Kindly provide this Form A.	CONFIRMED & PROVIDED. The official Form A templa Letter & Consortium Structure) is provided as Attachm No. 1 and is available for download directly in the onlir (Document Library Tab 1).
2	OSS & BSS Integration	01_RFP_5G_FWA_Master_Tender_Document (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Is billing considered in scope?	CLARIFICATION OF BILLING SCOPE: In Phase 1, real-time Convergent Charging (CCS/CHF Nchf/Diameter Ro) for prepaid FWA balance managem and quota tracking is the mandatory turnkey scope. C cyclic invoice generation and accounts receivable (A/F Comclark/TelTech's enterprise billing system via stanc export, or may be proposed as an optional modular ac
3	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Bidder inquiry: System supports various tariff structures but requests clarification on specific offering rules. Such as: 1. These offerings need group management (such as family package) or not? 2. These offerings need rollover feature (such as unused data rollove to next cycle) or not? 3. These offerings should support auto upgrade (such as 599 not enough of this cycle automatical upgrade to 700 for next cycle) or not?	CLARIFICATION OF PRODUCT OFFERINGS: 1. Group Management: Optional roadmap feature; sing is baseline for Phase 1. 2. Rollover Feature: Supported in product catalog con high-speed data quota rolls over into the subsequent cycle upon prompt re-subscription). 3. Auto-Upgrade: Speed-cap throttling (e.g. throttle t quota exhaustion with option for customer to purchas on) is the required policy, rather than forced tariff upg

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
4	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Bidder inquiry: System supports standard 3GPP protocols and real-time balance rating and charging. some concerns: 1. We assume BSS will support 5G SA network only. 2. Smart quota, dynamic granted quota feature should enable or not?	CLARIFICATION OF CHARGING REQUIREMENTS: 1. Network Architecture: Confirmed 5G Standalone (SA 2. Quota Management: Standard 3GPP dynamic grant threshold notification alerts (at 80% and 100% quota SMS / self-care push notification) must be enabled.
5	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Bidder inquiry: System exposes standard REST APIs for digital payment gateways, with specific operational queries: 1. Should support Voucher recharge or not(3rd party send voucher no and PIN as example)? 2. Should consider Recharge tax or not(When feedback the message to 3rd party or notification to end-subscribers)? 3. Should consider Recharge promotion or not(When feedback the message to 3rd party or notification to end-subscribers)?	CLARIFICATION OF DIGITAL PAYMENT RECHARGE: 1. Voucher Recharge: Omnichannel digital recharge via QR Ph is primary. Third-party electronic voucher PIN r supported as an optional secondary channel. 2. Taxation: BSS catalog must support Philippine 12% (VAT) calculation and display on payment confirmation 3. Promotions: The charging system must natively sup promotional rules (e.g., bonus data allowances, referra promotional validity extensions).
6	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	What's the FWA service scenario shall be supported by the BSS? For example: New Registration, SIM Location Locking, Address Change, Transfer Owership, Contract Lifecycle Management, CPE/WIFI Router Installment	MANDATORY FWA SERVICE SCENARIOS: The turnkey BSS/OSS must support: 1. New Customer Digital Registration & KYC. 2. Strict SIM-IMEI & Cell-ID Location Locking (binding the authorized installation address to prevent nomadic unauthorized usage). 3. Relocation / Address Change workflow (manual or a unbinding upon authorized relocation request). 4. Transfer of Ownership & Account Termination. 5. Contract / Subscription Lifecycle Management. 6. CPE Inventory Assignment and Remote FOTA Mana
7	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	What's the payment mode shall be supported by the BSS? Prepaid, Postpaid, Hybrid? If need postpaid, and hybrid, does it meant the supplier need to provide the billing, invoice relevant components?	PAYMENT MODE ARCHITECTURE: The primary business model for Phase 1 is 100% Prep recurring subscription validity. Postpaid hybrid invoici integration with Comclark/TelTech's enterprise billing bidders/suppliers are only required to provide the real CHF/CCS engine and payment gateway connectors.
8	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Beside the listed systems, shall the new BSS integrate with ERP Finance system,	ENTERPRISE INTEGRATIONS: The BSS must support standard daily accounting jour to Comclark/TelTech's SAP ERP and daily CDR/event e

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
			DWH/BI? Is there data streaming requirement for real-time data synchronization?	enterprise Data Warehouse (DWH). Real-time Kafka-b streaming is preferred for operational analytics.
9	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Beside the self-care channels, shall the supplier provide the retail portal which can be used by the in-shop agent or call center agent?	RETAIL & AGENT PORTAL SCOPE: CONFIRMED. Supplier must provide a secure, web-ba Service Representative (CSR) and Authorized Dealer F agents, partner distribution dealers, and call center ho customer onboarding, balance lookups, and troublesh
10	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Beside the CPE inventory management, shall the new BSS/OSS system manage the MSISDN and SIM card resource?	RESOURCE MANAGEMENT SCOPE: CONFIRMED. The turnkey BSS must incorporate a uni inventory management module for SIM cards (ICCID), hardware serial numbers (IMEI / MAC).
11	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Does the exisiting network have PCF (Policy Control Function)? Does the BSS need to integrate with this?	POLICY CONTROL (PCF) INTEGRATION: Under Lot 3 (5G Core Network), the supplier is deliver SA Core, which includes the Policy Control Function (P integrate directly with the supplier's supplied PCF via N28 interfaces.
11	Wireless and Delivery	05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines.pdf (3. RF PROPAGATION & CELL DIMENSIONING GUIDELINES)	The coverage radius is too large. It is recommended that the coverage radius be 1 km in suburban areas and 1.5 km in rural areas.	CLARIFICATION OF SITE SEARCH RINGS VS. RF CELL 1. Candidate Site Search Rings (Hunting Radii): Siting are strictly governed by Section 1.2 of Appendix D and Bulletin at 500 meters (Urban/Suburban) and 1,000 m centered on the nominal demand centroid. 2. RF Cell Coverage Radius & Link Budget: The recom conservative RF cell coverage radius of 1.0 km (Subur and 1.5 – 2.0 km (Rural/Open terrain) is endorsed as a vendor engineering benchmark for dimensioning link b guaranteeing >= -95 dBm RSRP coverage over popula zones. This does not alter the controlling 500m / 1,000 search rings.
12	Wireless and Delivery	04_Appendix_C_SLAs_KPIs_Liquidated_Damages.pdf (3.1 Core Radio KPIs (Calculated 24/7/365 Nationwide))	In the case of multiple users, the environment is complex and the attenuation is large. It is recommended that the average cell traffic be controlled within 40 Mbps/10 MHz.	CONFIRMED ACCEPTABLE. The recommended engine baseline of 40 Mbps average cell throughput per 10 M (yielding ~240 Mbps average cell throughput on a 60 carrier with 4:1 DL:UL frame structure) is endorsed as design criteria for multi-user FWA deployment.
13	Site, civil work, and managed services	05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines (2.2 Tower Structure & Loading Audit (Co-Location Sites))	For TowerCo tower, the tower structural Loading verification usually under TowerCo Scope (Operator provide the equipment list and loading info to TowerCo, TowerCo to provide result). 1. Please kindly suggest if we need to provide structural loading verification service or not. Or we quote this service in a	STRUCTURAL LOADING RESPONSIBILITY: 1. For the 897 TowerCo co-location sites, Tower Struc Verification is the responsibility of the Operator and th the executed Master Lease Agreement (MLA). The sup equipment weights, dimensions, wind load surface are routing details. 2. If loading verification fails, the TowerCo is obligated perform structural retrofitting, or the Operator will rea candidate tower from the pre-approved pool.

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
			seperate item. 2. If Loading Verification fail, Please suggest the next step (build new tower, or request towerco retrofit tower) Suggest: TowerCo do the structural loading verification.	
14	Site, civil work, and managed services	04_Appendix_C_SLAs_KPIs_Liquidated_Damages ()	Whats the acceptance standard and procedure for Tower, Civil and Power part? Suggest: Bidder / Supplier may propose standard QA/QC templates if needed.	ACCEPTANCE STANDARDS: Acceptance standards and checklists for Civil, Tower, detailed in Document 05 ('05_Appendix_D_Site_Survey_RF_Planning_Civil_Pow and Document 04 (Appendix C). Supplier's standard C and handover templates are acceptable subject to Joi Committee approval.
15	Site, civil work, and managed services			
16	Site, civil work, and managed services			
17	Site, civil work, and managed services	03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 6: LOT 5 — SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS)	1. For the TowerCo site, Is it Comclark/TelTech scope to rent and negotiate with TowerCo? Suggest: For towerco site, should be Comclark/TelTech's responsibility for site renting and negotiating with TowerCo. 2. If the site hunting fail, whats the next step? (Comclark/TelTech to provide another site for hunting to swap the failed site? or cancel the site). Suggest: Contractor will hunt each site with up to 3 candidate parcels; if site acquisition fails due to zoning/legal defects, Operator provides alternative candidate without penalty.	SITE ACQUISITION & TOWERCO LEASE NEGOTIATION 1. For the 897 Co-location sites, lease agreements, sp and commercial negotiations with TowerCos (PhilTowe EDOTCO, Unity) are strictly the Operator's responsibil Lease Agreements (MLA). 2. For the 103 Greenfield sites, the supplier performs with up to 3 candidate parcels. If site hunting fails due title defects, the Operator will provide a replacement c without bidder penalty.

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
18	Site, civil work, and managed services	03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 3: LOT 2 — POWER SYSTEMS & PASSIVE INFRASTRUCTURE)	Bidder suggestion: Install outdoor soundproof canopy genset directly on an elevated concrete equipment pad without building an enclosed shelter structure.	GENSET INSTALLATION STANDARD: CONFIRMED ACCEPTABLE. Outdoor soundproof weat gensets installed directly on an elevated concrete equ (without an enclosed brick/steel shelter building) are f
19	Site, civil work, and managed services	03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 6: LOT 5 — SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS)	Is fiber backhaul drop cable installation Operator scope or Bidder / Supplier scope?	FIBER BACKHAUL RESPONSIBILITY: Comclark/TelTech provides the core optical distributio terrestrial fiber drop cable up to the site boundary/OD satellite terminals. The supplier is responsible for opti patchcords, and joint I&C testing from the demarcatio
20	Site, civil work, and managed services	03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 6: LOT 5 — SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS)	For the non-standard and special construction reuqirment, such as manul hauling, retaining wall and others, Can the bidder / supplier claim abnormal civil conditions separately as a Variation Order (VO)?	VARIATION ORDER (VO) ELIGIBILITY: CONFIRMED. Non-standard civil construction conditio rock excavation requiring pneumatic breakers/blasting hauling exceeding 500 meters across unpaved/mount engineered retaining walls) are recognized as eligible based on pre-agreed unit rates in Appendix B (Lot 5 B
21	Site, civil work, and managed services	03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 3: LOT 2 — POWER SYSTEMS & PASSIVE INFRASTRUCTURE)	For TowerCo Power part, Usually Towerco will provide AC and DC, Please clarify if the bidder / supplier needs to supply the submeter and electrical tap materials when connecting to TowerCo power.	TOWERCO POWER EQUIPMENT: Where TowerCo supplies regulated -48V DC power di needs only connect to the designated DC distribution TowerCo provides raw AC utility power, supplier suppl ACPDB, and surge suppression.
22	Testing / KPI	05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines.pdf; 04_Appendix_C_SLAs_KPIs_Liquidated_Damages.pdf (Section 5 SSV — Ping RTT acceptance; KPI-RAN-07 Radio Round-Trip Latency)	For the 17 Starlink backhaul sites, should the RTT KPI threshold be adjusted (e.g., relaxed to <= 50 ms maximum) given the inherent LEO satellite latency? Or are these sites exempt from KPI-RAN-07? Please confirm whether a separate KPI schedule applies to satellite backhaul sites.	STARLINK SATELLITE RTT LATENCY KPI: CONFIRMED & ADOPTED. For the 17 remote/island ca backhauled via Starlink LEO satellite, the Ping RTT SL 60 ms target (<= 80 ms maximum) during SSV and clu reflecting satellite orbital propagation latency.
23	Wireless and Delivery	01_RFP_5G_FWA_Master_Tender_Document (2.3 Transmission & Backhaul Topology / App.C 3.1 KPI-RAN-07)	1. Please provide the verified per-site fiber node/segment list (optical node ID, connection class A-D, committed bandwidth) after on-ground verification — the site list shows all Starlink-fed sites have dist-to-node > 20 km.	BACKHAUL RESOURCES & SLA EXCLUSIONS: 1. Candidate site list in Document 07 provides audited classes (Class A <= 0.5km to Class D). 2. Confirmed: Backhaul transport facilities (Comclark/ FOC and Starlink links) are Operator-provided. 3. Media-tiered RTT KPIs are formally confirmed: Fibe maximum; Satellite sites <= 80 ms maximum. 4. Confirmed: Downtime caused by upstream third-pa outages or fiber cuts outside the site compound is exc supplier RAN availability penalty assessments.

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
			2. Please confirm that backhaul resources (Comclark/TelTech fiber SLA, Starlink links) are Operator/third-party provided, and the Operator is responsible for their availability, bandwidth and latency. 3. Do you accept media-tiered RTT KPIs: fiber-fed sites bound by <= 30ms, while satellite-fed sites follow their link physics (e.g. <= 100ms)? 4. Please confirm backhaul outage time is excluded from KPI assessment (RAN availability, end-to-end availability, packet loss). Expected: written confirmation + per-site backhaul list.	
24	Site, civil work, and managed services	01_RFP_5G_FWA_Master_Tender_Document (2.2 Site Infrastructure & Tower Strategy)	1. Please provide TowerCo lease confirmations / ownership proofs for all co-location sites before NTP. 2. Please provide a tower-readiness schedule per site (lease signed, structural audit, access) feeding the 1,000-sites/365-day plan. 3. Do you agree to back-to-back liability — delays caused by TowerCo approval, access or structural defects are excluded from the contractor's schedule liability with automatic day-for-day time extension? Expected: written commitment + schedule.	TOWERCO LEASE READINESS & SCHEDULE COMMIT 1. Operator will provide TowerCo Site Access Authoriz Notice to Proceed (NTP) for each site batch. 2. Confirmed: Schedule milestones commence upon f Handover with approved TowerCo access. Delays cau TowerCo structural retrofit or access permit delays wi day time extensions without liquidated damages.

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
25	Site, civil work, and managed services	01_RFP_5G_FWA_Master_Tender_Document (2.2 Deployment Typology / App.C 2.1 Milestones M1-M4)	1. Please confirm an 'Excluded Sites' mechanism — sites blocked by permits (LGU/Barangay/CAAP), land, power connection, TowerCo or coverage issues are deducted from milestone counts. 2. May Milestone-1 TSSR be submitted in phasing (first 200 sites in 45 days, then 300 sites every 30 days), given typical permitting and TowerCo access cycles in the Philippines? 3. Do you accept the 365-day milestone counted in net working days (or auto-extended by the same number of days of Operator/third-party delays)? 4. Please confirm permit fees and utility connection application costs are pass-through (CCP). Expected: written confirmation + revised milestone wording.	MILESTONES & PERMITTING CLAUSES: 1. Blocked Sites Mechanism: Sites blocked by LGU mo way disputes, or power utility delays beyond 45 days with approved reserve sites without schedule penalty. 2. Phased TSSR Submissions: Submitting TSSRs in pr batches (e.g. 150–200 sites per month) is fully accept 3. Project schedule will account for approved force ma Operator/third-party delay extensions. 4. Official LGU building permit statutory fees and utilit fees are pass-through to Operator.
25	Site, civil work, and managed services	01_RFP_5G_FWA_Master_Tender_Document (LOT 5: RF PLANNING, SITE SURVEY & CLUSTER OPTIMIZATION)	Can you accept not requiring a drone, as long as the photos can reflect the 360° surrounding environment, and AGL refer to TowerCo provided height for FWA project?	DRONE SURVEY WAIVER: CONFIRMED ACCEPTABLE. Where drone flight permit secured from CAAP or local authorities within 14 days, 360-degree panoramic telephoto ground photography verified TowerCo structural engineering drawings is ac approval.
25	Power system and delivery	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 2: POWER SYSTEMS & PASSIVE SITE INFRASTRUCTURE)	1. Do they have Blade requirement ? 2. Can we request room layout or site pictures if available for Lithium Battery Approval? 3. Is there existing rectifier cabinet in existing sites? 4. If SAT requirement is one per equipment or the whole quantity? 5. What is the Total actual DC power for single rectifier requipment?	POWER SYSTEM & BATTERY SPECIFICATIONS: 1. Standard 19" rack-mount modular switchmode recti mount 48V 100Ah LiFePO4 battery modules are requi 2. Typical site DC load is ~2.8 to 3.2 kW continuous. S 12.0 kW installed capacity (4 × 3 kW modules, N+1 re 3. Site layout and equipment pad drawings are provide
25	Wireless and Delivery	01_RFP_5G_FWA_Master_Tender_Document.pdf (2.1 Spectrum Physics: Band n50 Advantage)	1. According to ITU-R M.2159-0, the 1518–	SPECTRUM PHYSICS & FILTERING (1457–1517 MHz): 1. Standard 3GPP Band n50 Category B filtering guara

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
			1525 MHz frequency band is used for maritime communications satellites. If the frequency range of the RRU includes 1512–1517 MHz, it cannot ensure a -30 dB suppression within the 1518–1523 MHz band. Therefore, please confirm whether the NTC allows the use of the 1512–1517 MHz spectrum. 2. We understand that the 1427–1457 MHz frequency band will be allocated by the NTC as spectrum for enterprises. Please consider whether Comclark/TelTech intends to use the 1457–1467 MHz band. It is recommended to refer to the NTC's spectrum usage regulations to determine whether a guard band is required. Therefore, please confirm whether the NTC allows the use of the 1457–1467 MHz spectrum.	suppression (-30 dBm/MHz) into the adjacent 1518–15 (maritime satellite). Use of the 1457–1517 MHz band is authorized under NTC demonstration permit. 2. In NCR, operation is continuous 60 MHz (1457–151 filtering within the RRU prevents out-of-band emissio
25	Wireless and Delivery	05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines.pdf (overall)	Besides interference analysis with maritime communication satellites, suggest to carry out frequency clearance scan before commercial network deployment.	FREQUENCY CLEARANCE TEST: CONFIRMED & AGREED. Supplier and Operator RF tea joint baseline spectrum clearance sweeps prior to site to identify and resolve any legacy co-channel or adjac
31	Wireless and Delivery	05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines.pdf (5.. SINGLE SITE VERIFICATION (SSV) & CLUSTER ACCEPTANCE CRITERIA)	Is there Dl &UL speed requirement at near, Mid, and Far/Edge?	SSV SPEED TARGETS PER DISTANCE ZONE: - Near Zone (< 500m): DL >= 200 Mbps / UL >= 30 M - Mid Zone (1.0 – 1.5 km): DL >= 100 Mbps / UL >= 20 - Far / Cell Edge (>= 2.0 km): DL >= 25 Mbps / UL >= SLA threshold).
25	CPE	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7))	Currently, only n50 is planned for FWA development, and NSA networks should not be involved	CONFIRMED. Phase 1 deployment is strictly 5G NR Sta Band n50. NSA operation is not required.
25	CPE	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7))	Currently, only the n50 band is planned for FWA development. Is it mandatory for other sub-6 GHz frequency bands?	CONFIRMED. Native Band n50 (1432 – 1517 MHz, 60 I mandatory. Fallback sub-6 GHz bands (n1, n3, n78) ar Philippine market.

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
25	CPE	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7))	The N50 low-frequency system does not need to rely on extremely high antenna gain to compensate for spatial attenuation as high-frequency systems do. Whether 5-6 dBi is sufficient?	CONFIRMED ACCEPTABLE. For Indoor CPE, an integra gain of 5.0 – 6.0 dBi across Band n50 is accepted as c favorable propagation characteristics of 1.5 GHz L-Ba GHz. For Outdoor CPE, >= 12.0 dBi remains mandator
25	CPE	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7))	The network port is seldom used and is mainly used for network configuration and commissioning. Can only one network port be reserved for the product?	CPE ETHERNET INTERFACES: - Outdoor CPE: 1x 2.5GE PoE input port + companion router is standard. - Indoor CPE: At least 1x 2.5GE or 1x 1GE LAN port + ir acceptable for consumer FWA tiers; multi-port is prefe
25	CPE	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7))	Can it only support the eSIM MFF2 solution?	CONFIRMED. Physical Nano-SIM (4FF) with anti-theft mandatory for mass-market deployment. eSIM (MFF2) optional enhancement.
25	Wireless and Delivery	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 1: RADIO ACCESS NETWORK (RAN) TECHNICAL SPECIFICATIONS)	PIM is an indicator that is mainly concerned in FDD mode and does not need to be concerned in TDD mode. Is it necessary to change it to an OBUE (Operating Band Unwanted Emissions)indicator?	CONFIRMED. For synchronized TDD systems, Operati Emissions (OBUE) per 3GPP TS 38.104 is the primary benchmark. Passive Intermodulation (PIM <= -150 dB external RF components (antennas, jumpers, connecto receiver desensitization.
25	Wireless and Delivery	07_RFP_5G_FWA_Candidate_Site_List_and_Rollout_Schedule.xlsx (Phase 1 (First 1,000 Sites))	We note that the distance from the planned site to the nearest tower ranges from 0.16 km to 1.94 km. Could the specific tower locations be provided for simulation calculations?	CONFIRMED & PROVIDED. Candidate site demand cer Longitude in WGS84) are provided in Document 07. C operational tower locations (precise WGS84 coordinat types, and tower heights (m AGL) across all 13,810 no records are classified as Proprietary Commercial Infor released exclusively to accredited bidders in compani 09_Towerco_Master_Asset_Inventory.xlsx upon execu Project Non-Disclosure Agreement (NDA) via the RFP 5g@teltech.ph).
25	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Will a separate monitoring platform be deployed, or can it be integrated with the existing AUTIN platform?	OSS INTEGRATION: Supplier must deliver EMS/NMS for domain element m equipped with open northbound interfaces (REST APIs for integration into Comclark/TelTech's enterprise mon (AUTIN).
25	Core network & IT infrastructure and delivery	01_RFP_5G_FWA_Master_Tender_Document.pdf (SECTION 3: 5G CORE NETWORK (5GC SA) & DATACENTER INFRASTRUCTURE)	The NEF is responsible for network capability exposure, and there are currently no commercial use cases. The SEPP is responsible for signaling security protection and topology hiding across PLMNs. Based	CONFIRMED. In Phase 1, NEF (Network Exposure) and Edge Protection Proxy) are treated as optional roadma can be licensed in Phase 2 when enterprise API expos international roaming are activated.

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
			on the experience of other projects, this function is also not mandatory. Therefore, it is recommended that the NEF and SEPP functions be treated as optional requirements or removed from the current RFP.	
25	Core network & IT infrastructure and delivery	01_RFP_5G_FWA_Master_Tender_Document.pdf (SECTION 3: 5G CORE NETWORK (5GC SA) & DATACENTER INFRASTRUCTURE)	Please Clarify whether the UPF needs to be deployed at the edge or co-deployed with the 5G Core at the central site. If the UPF needs to be deployed at the edge, specify the number of edge UPFs. It is recommended that the UPF form be not limited.Either 2U/4U/8U is ok	UPF DEPLOYMENT ARCHITECTURE: In Phase 1, 5G Core control plane and central UPF are Tier-3 primary datacenter (Clark/Metro Manila). Edge optional for future ultra-low-latency enterprise zones. or 8U server form factors are acceptable.
25	Core network & IT infrastructure and delivery	01_RFP_5G_FWA_Master_Tender_Document.pdf (SECTION 3: 5G CORE NETWORK (5GC SA) & DATACENTER INFRASTRUCTURE)	or hardware with the same capabilities such as Kunpeng server （E9000H-4/8）	CONFIRMED ACCEPTABLE. Carrier-grade server hard equivalent compute and throughput capabilities (inclu carrier-grade ARM architecture running certified Linux fully acceptable for 5GC NFV infrastructure.

5. ATTACHMENT 1: FORM A — BID SUBMISSION LETTER & CONSORTIUM STRUCTURE

(Prospective bidders must reproduce this letter on corporate letterhead, signed by an authorized corporate signatory, and submit within Envelope 1 / Administrative Envelope).

```
[BIDDER CORPORATE LETTERHEAD]

Date: _____
Reference: RFP-TELTECH-FWA-2026-001

To:
TELECOMMUNICATIONS TECHNOLOGY SOLUTIONS INCORPORATED (TELTECH)
Comclark Network & Technology Corp. / TelTech
Reliance IT Center, Pasig City / Clark Freeport Zone, Pampanga, Philippines
Attention: Oliver Tungol, Lead Technical Architect & Tender Secretariat
Email: oliver.tungol@comclark.com.ph

SUBJECT: FORM A – FORMAL BID SUBMISSION LETTER & CONSORTIUM DECLARATION

Gentlemen:

1. Having examined the RFP Bidding Documents, including the Master Tender Specification (01_RFP_5G_FWA_Master_Tender_Document), Technical Specifications

   "NATIONWIDE 5G STANDALONE (SA) FIXED WIRELESS ACCESS (FWA) NETWORK (PHASE 1: 1,000 MACRO SITES)"

   in full conformity with the stated requirements, specifications, and commercial terms.

2. We confirm that our proposal represents a turnkey, single-point-of-responsibility solution covering all lots bid, executed in full compliance with th

3. BIDDER & CONSORTIUM INFORMATION:
```

```
   - Primary Bidder / Lead OEM Entity: _____
   - Country of Incorporation: _____
   - Principal Business Address: _____
   - Authorized Representative / Corporate Signatory: _____
   - Official Corporate Email & Contact Phone: _____
   - Consortium / Delivery Partners (if applicable):
     * Partner 1 (Civil Works / Rollout Services): _____
     * Partner 2 (Power Systems / Logistics): _____

4. We confirm that our sealed proposal is submitted in three (3) distinct envelopes (Envelope 1: Administrative & Eligibility; Envelope 2: Technical Com

5. We acknowledge that our proposal shall remain valid and binding for a period of one hundred twenty (120) calendar days from the submission deadline o

Respectfully submitted,


_____
(Signature over Printed Name of Authorized Signatory)

Title / Designation: _____
Corporate Seal: [SEAL]
Date: _____
```

END OF BID BULLETIN NO. 1

Issued by the TelTech 5G FWA Tender Committee & Secretariat.