TELECOMMUNICATIONS TECHNOLOGY SOLUTIONS INCORPORATED (TELTECH)

NATIONWIDE 5G STANDALONE (SA) FIXED WIRELESS ACCESS (FWA) NETWORK

RFP REFERENCE: RFP-TELTECH-FWA-2026-001

BID BULLETIN NO. 1

TO ALL PROSPECTIVE BIDDERS: All Qualified Turnkey 5G Equipment Manufacturers, Prime Contractors, and Authorized Bidding Consortia
FROM: Oliver Tungol, Lead Technical Architect & Tender Secretariat
DATE OF ISSUANCE: October 21, 2026
SUBJECT: Official Clarifications, Technical Baseline Amendments, and Response Matrix to Bidder Inquiries

1. EXECUTIVE SUMMARY & PURPOSE

This **Bid Bulletin No. 1** is issued pursuant to Section 1.5 (*Clarification and Amendment of Bidding Documents*) of the Master RFP Document. It provides binding official responses to technical, commercial, civil, and operational inquiries submitted by prospective bidders between October 19 and October 21, 2026.

All amendments, specifications, and clarifications contained herein are hereby incorporated into the Tender Documents and shall form an integral part of the final contract for the **Turnkey 5G SA FWA Rollout (1,000 Phase 1 Macro Sites)**.

2. KEY ARCHITECTURAL & CONTROLLING CLARIFICATIONS

2.1 Spectrum Physics & Operating Frequency (Band n50)

1. **Metro Manila (NCR) Spectrum Deployment:**
2. Operating Band: **1457 – 1517 MHz (60 MHz continuous channel bandwidth TDD)**.
3. The 1437 – 1457 MHz sub-band in NCR is assigned to another entity and will not be utilized by the Operator in NCR.
4. **Rest of the Country (Provincial / Regional Deployment):**
5. Operating Band: **1437 – 1517 MHz (up to 80 MHz continuous channel bandwidth TDD)**.
6. **Hardware Tuning Capability:**
7. All proposed Baseband Units (BBU) and Remote Radio Units (RRU) / Active Antenna Units (AAU) must natively support the full 3GPP Band n50 range (**1432 – 1517 MHz**) in hardware.
8. Operating bandwidth must be software-configurable to 40 MHz, 50 MHz, 60 MHz, or 80 MHz without requiring tower-climbing or hardware replacement.
9. **Out-of-Band Rejection & Satellite Protection:**
10. High End (1517 MHz): Must comply with **ITU-R M.2159-0 / WRC-15 Resolution 223** to protect adjacent Maritime Mobile Satellite Service (MSS, 1518 – 1525 MHz). Transceiver unwanted emissions in the 1518–1525 MHz band must not exceed -30 dBm/MHz at the antenna port. Standard 3GPP TS 38.104 Category B filtering is compliant.
11. Low End (1437 / 1457 MHz): Must comply with 3GPP Category B Operating Band Unwanted Emissions (OBUE). Digital Pre-Distortion (DPD) within the RRU ensures sharp rolloff at the assigned carrier boundary.

2.2 Power Architecture & Rectifier Sizing Methodology (Lot 2)

1. **Installed Capacity:** Sized at **>= 12.0 kW total installed capacity** using **4 × 3.0 kW (or 4 × 4.0 kW) modular hot-swappable switchmode rectifier modules in an N+1 architecture**.

2. **Operational Load under N+1:** With a single module failure (3 operational modules), the system provides **9.0 kW continuous DC output**, which comfortably accommodates the maximum site DC load of **7.28 kW** (3.0 kW BTS RAN load + 4.28 kW fast battery recharging at 0.2C for a 400 Ah / 20 kWh lithium bank).
3. **Mounting:** Weather-resistant (IP55) integrated outdoor ground-mounted power/battery cabinets on an elevated concrete pad represent the baseline design. Pole-mounted or wall-mounted power units are approved for rooftop/space-constrained co-location sites.

2.3 Transmission, Starlink Satellite Backhaul & KPI Tiering

1. **Media-Tiered Latency SLAs (Document 04 / Appendix C Amendment):**
2. **Terrestrial Fiber-Fed Sites (98.3% of Phase 1):** Ping Round-Trip Time (RTT) <= 18 ms target (<= 30 ms maximum).
3. **Starlink Satellite-Fed Sites (1.7% / 17 island/remote sites):** Ping RTT threshold is relaxed to **<= 60 ms target (<= 80 ms maximum)** during SSV and cluster acceptance to reflect LEO satellite orbital physics.
4. **Backhaul Outage Exclusions:**
5. Downtime, packet loss, or latency degradation caused by third-party fiber cuts, upstream IP transit failures, or satellite constellation outages outside the site compound are strictly excluded from vendor RAN availability SLA penalties.

2.4 TowerCo, Civil Works & Site Siting

1. **Tower Structural Loading Verification:** For the 897 Co-location sites, structural loading analysis is conducted by the TowerCo under the Operator's Master Lease Agreement (MLA). The vendor provides equipment weights, dimensions, wind load surface area, and cable routing. Any necessary tower retrofits are executed by the TowerCo under the MLA.
2. **Site Hunting & Excluded Sites:** Delays caused by local government (LGU) moratoria, right-of-way disputes, or utility connection delays exceeding 45 days permit the Operator and vendor to substitute the blocked candidate with a pre-approved site from the 4,000-candidate reserve pool without schedule penalty.
3. **Variation Orders (VOs):** Abnormal site construction conditions (hard rock excavation requiring pneumatic equipment, manual material hauling > 500 meters across unpaved/mountainous terrain, and engineered retaining walls) are eligible for established unit-rate Variation Orders under Lot 5.

2.5 Digital OSS/BSS & 5G Core Architecture

1. **Turnkey BSS Scope:** Real-time Prepaid Convergent Charging System (CCS/CHF via 3GPP Nchf/Diameter Ro) for the 4 consumer FWA tiers (₱599, ₱799, ₱999, ₱1,299). Complex cyclic enterprise invoicing is handled via integration with Comclark/TelTech's existing enterprise billing platform.
2. **SIM-IMEI & Cell-ID Location Locking:** The BSS/PCF must enforce strict hardware-network binding to ensure FWA service cannot be operated outside the authorized installation address.
3. **Core Network Functions (NEF & SEPP):** In Phase 1, NEF (Network Exposure) and SEPP (Security Edge Protection Proxy) are optional/phased roadmap functions.
4. **Compute Platform:** Dual-socket carrier-grade x86 (Intel/AMD) or equivalent enterprise ARM-based architecture running certified carrier-grade Linux / Kubernetes is fully acceptable.

2.6 Customer Premises Equipment (CPE - Lot 7)

1. **Operating Band:** Native Band n50 (1432 – 1517 MHz, 60 MHz TDD) in 5G SA mode is mandatory.
2. **Indoor CPE Antenna Gain:** Integrated antenna array gain of **5.0 – 6.0 dBi across Band n50** is accepted as compliant (leveraging the superior propagation of 1.5 GHz compared to 3.5 GHz). Outdoor CPE requires >= 12.0 dBi.
3. **SIM Form Factor:** Physical Nano-SIM (4FF) with anti-theft locking cover is mandatory. eSIM (MFF2) is an acceptable optional enhancement.

---

3. CONSOLIDATED RESPONSE MATRIX (PART 1: RAN, POWER & TRANSMISSION)

NO.	DOMAIN	REFERENCE SECTION	PROSPECTIVE BIDDER CLARIFICATION REQUEST	COMCLARK / TELTECH OFFICIAL RESPONSE
1	RAN	2.1 Spectrum Physics: Band n50 Advantage	Since the 1437–1457 MHz band has been assigned to another corporation in the NCR, kindly please confirm the following spectrum deployment plan: Metro Manila (NCR): 1457–1517 MHz (60 MHz) Rest of the country: 1437–1517 MHz (80 MHz)	CONFIRMED. The baseline spectrum deployment plan is form confirmed as follows: 1. Metro Manila (NCR): 1457 – 1517 MHz (60 MHz continuous bandwidth), fully compliant with the Operator's statutory autl NTC demonstration permit. 2. Rest of the Country (Provincial / Regional): 1437 – 1517 MH MHz IBW/OBW capability). Bidders' 5G NR Baseband Units (BBU) and Remote Radio Uni Active Antenna Units (AAU) must natively support the full 3G tuning range (1432 – 1517 MHz) in hardware, with carrier ban software-configurable to 40 MHz, 50 MHz, 60 MHz, or up to assigned.
2	RAN	2.1 Spectrum Physics: Band n50 Advantage	Further clarification is required regarding the bandwidth that needs to be supported. Are there any special customization requirements for the filter's out-of-band rejection and emissions? Point 1: If the 1437–1457 MHz band is occupied by another operator, are there any specific spurious emission requirements that vendor's equipment must comply with for the low end and high end(1457M and 1517M)? Point 2: If the 1437–1457 MHz band is available for use outside the NCR areas, does the NTC impose any spurious emission requirements for the low and high end(1437M and 1517M)?	CONFIRMED & DETAILED: Point 1 (NCR Carrier: 1457–1517 MHz): Vendor equipment mu with 3GPP TS 38.104 Category B Operating Band Unwanted I (OBUE) and standard NTC Type Approval spurious emission r low end (1457 MHz), the RRU digital filtering and DPD must e attenuation to protect adjacent users below 1457 MHz. At the (1517 MHz), equipment must implement appropriate filtering the adjacent Maritime Mobile Satellite Service (MSS, 1518–15 ITU-R M.2159-0), with unwanted emissions not exceeding -3 Point 2 (Outside NCR: 1437–1517 MHz): Standard 3GPP Banc 38.104 Category B emission masks apply at the 1437 MHz lo 1517 MHz upper edge. No non-standard or proprietary hardw customization is required beyond compliant 3GPP Release 16 radio hardware.

NO.	DOMAIN	REFERENCE SECTION	PROSPECTIVE BIDDER CLARIFICATION REQUEST	COMCLARK / TELTECH OFFICIAL RESPONSE
3	RF Planning	07_RFP_5G_FWA_Candidate_Site_List_and_Rollout_Schedule.xlsx	To support the above planning activities, vendor kindly requests Comclark/TelTech to share the following information for the nearest tower(s): location (longitude / latitude) and tower height.	CONFIRMED & PROVIDED. Candidate site geographic coordi (Latitude / Longitude in WGS84) and nominal Tower Heights meters) for all 1,000 Phase 1 candidate sites are fully provide Document 07 ('07_RFP_5G_FWA_Candidate_Site_List_and_Rollout_Schedu specifically under sheets 'Phase 1 (First 1,000 Sites)' and 'To (covering PhilTower, EdgePoint, EDOTCO, and Unity assets).
4	Transmission	2.3 Transmission & Backhaul Topology	Vendor proposes that Comclark/TelTech clarify the defination of "fiber segments" and the "optical nodes"	CLARIFICATION OF DEFINITIONS: - 'Optical Node': An audited, active Comclark/TelTech point-c interconnect—specifically an Optical Distribution Frame (ODF Distribution Terminal (FDT), or Primary Fiber Hub equipped w optical splice/splitter capacity to serve as the backhaul trans handover point. - 'Fiber Segment': An audited physical fiber optic cable route distribution, or lateral FOC) spanning between the optical noc office and the customer/tower drop point, as verified in Comclark/TelTech's audited GIS distribution plant.
5	Transmission	2.3 Transmission & Backhaul Topology	Vendor proposes that Comclark/TelTech clarify the defination of " C: Line-tap splice closure <= 0.5 km"	CLARIFICATION OF DEFINITION: 'Class C: Line-tap splice closure <= 0.5 km' designates a can tower location where an existing aerial or underground Comc trunk/distribution fiber optic cable passes within 500 meters compound, and interconnection will be achieved by cutting ir at an existing or newly inserted inline splice closure (FOSC / D Enclosure) rather than routing back to a centralized ODF/nod
6	Transmission	2.4 Backhaul Transmission Path Survey	Does the "distance to the nearest node" refer to the distance to the 5G base station ? Vendor proposes that Comclark/TelTech clarify the defination of " distance to line-tap closure"	CLARIFICATION OF DEFINITIONS: - 'Distance to Nearest Node': Refers to the estimated terrestr cable route distance from the proposed 5G Macro Tower com nearest confirmed Comclark/TelTech Optical Node (Class A < Class B <= 1.0 km). - 'Distance to Line-Tap Closure': Refers to the linear cable dis the 5G Base Station to the designated trunk cable splice clos <= 0.5 km).
7	Transmission	2.3 Transmission & Backhaul Topology	Vendor respectfully proposes that Comclark/TelTech confirm whether the Microwave solution for Class D is to be considered within the Vendor's scope of supply, or whether it will be provided by Comclark/TelTech directly.	CONFIRMED: VENDOR SCOPE OF SUPPLY / PRICING. Class D sites (~1.7% of Phase 1 sites, plus microwave backup island sites) require a turnkey high-capacity microwave backl GHz / 18 GHz / 23 GHz or E-Band 80 GHz, minimum 1.0 Gbps throughput). Bidders must quote the microwave split-mount l (IDU, ODU, antenna, IF cabling) and installation services in Ap (Commercial BoQ) under Lot 1 / Lot 3 options. Comclark/TelT the right to provide direct fiber drops prior to NTP where feas

NO.	DOMAIN	REFERENCE SECTION	PROSPECTIVE BIDDER CLARIFICATION REQUEST	COMCLARK / TELTECH OFFICIAL RESPONSE
8	Power	PWR-01	Kindly confirm whether the 12 kW rating refers to the total installed rectifier capacity (4 × 3 kW modules, including one N+1 redundant module) rather than the output that must be maintained after a single module failure. For reference, a typical load — 3 kW BTS with a 400 Ah battery charged at 0.2C — requires a total DC demand of 7.28 kW (4.28 kW charging + 3 kW BTS load). This demand is fully served by three 3 kW modules, with a fourth module providing N+1 redundancy (12 kW installed; 9 kW available under N+1). Vendor appreciates your confirmation that this load-based N+1 sizing methodology is acceptable, including functionally equivalent configurations.	CONFIRMED ACCEPTABLE. The required sizing methodology is confirmed as follows: - Total Installed Rectifier Capacity: >= 12.0 kW composed of (or 4 × 4.0 kW) modular hot-swappable switchmode rectifier an N+1 architecture. - Active Operational Capacity under N+1: With a single modu operational modules), the system provides 9.0 kW continuou which comfortably exceeds the peak site DC demand of 7.28 BTS RAN load + 4.28 kW fast battery recharging at 0.2C for 4 kWh lithium bank). Vendor's proposed load-based N+1 configuration is fully com
9	Power	PWR-01 / PWR-04	Please clarify whether pole-mounted installation is mandatory or an integrated ground-mounted outdoor cabinet is acceptable for power HW and RAN HW ?	CLARIFICATION OF INSTALLATION STANDARD: Both configurations are acceptable depending on site compo archetype: 1. Co-location / Rooftop Sites with Space Constraints: Integra pole-mounted or wall-mounted power/RAN solutions are acc where ground compound footprint is restricted by the Tower 2. Greenfield / Ground Compound Sites (Standard): An integr weather-resistant (IP55) ground-mounted outdoor power & b cabinet installed on an elevated equipment concrete pad is th baseline design.
10	Project	LOT 5: SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS	Who is the responsible for transmission and last mile ?	DIVISION OF RESPONSIBILITY: - Comclark / TelTech Scope: Core IP/MPLS network, backbon optical node infrastructure, upstream bandwidth, fiber drop c provisioning up to the tower demarcation/ODF, and Starlink s terminals. - Vendor Scope: Turnkey supply of optical transceivers (10G/ eCPRI and 10G/25G SFP+ backhaul optics), armored optical

NO.	DOMAIN	REFERENCE SECTION	PROSPECTIVE BIDDER CLARIFICATION REQUEST	COMCLARK / TELTECH OFFICIAL RESPONSE
				terminal fiber interconnect from tower demarcation box to Ba (BBU), and end-to-end backhaul circuit acceptance testing d
11	Project	LOT 2: POWER SYSTEMS & PASSIVE INFRASTRUCTURE	There are no engineering services items about Rectifier, Battery, Tap-Off Box & Submeter, Getset, pls confirm engineering services isn't vendor's scope.	CLARIFICATION OF SERVICES SCOPE: Installation, wiring, and commissioning of the rectifier, lithium bank, AC tap-off box, submeter, and optional genset are inclu turnkey rollout scope under Lot 1 Services (Table 2: RAN Turn Services, Item RAN-SVC-02) and Lot 5 (Civil Works & Power Turnkey implementation includes all physical mounting, DC c breaker terminations, grounding, and commissioning of the p subsystem.
12	Project	LOT 5: SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS	Please provide detailed site design for each civil work item, such as: Equipment Pad Foundation & Cable Gantry, Greenfield Compound Civil Works & Foundation, Grounding Grid & Lightning Protection System, 30m/40m Galvanized Steel Monopole Tower.	CLARIFICATION & GUIDELINES: Typical engineering guidelines, wind loading specifications (n km/h typhoon survivability), soil bearing criteria, and groundi requirements (<= 5 Ohms) are detailed in Document 05 ('05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Gui Detailed structural fabrication and foundation construction dr established during the Joint Technical Site Survey (TSSR) sta Milestone 1) based on site-specific geotechnical soil test resu actual compound boundaries. Bidders are invited to submit th type-approved civil drawings and monopole designs in their t proposal for committee evaluation.
13	Project	LOT 5: SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS	There are no engineering services items about Commercial Power Access, pls confirm engineering services isn't vendor's scope.	COORDINATED SCOPE: - TelTech / Operator Scope: Payment of official electric coope Meralco / DU) application fees, transformer capital contributi deposits, and power supply contracts. - Vendor Scope: Turnkey on-site civil and electrical works fro property line / service drop demarcation pole to the equipmer including service entrance conduit/riser, utility revenue class base/enclosure, main service disconnect switch, AC panel (A surge protective device (Type 1+2 SPD).

4. CONSOLIDATED RESPONSE MATRIX (PART 2: DETAILED VENDOR INQUIRIES)

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
1	Other Business Matters	01_RFP_5G_FWA_Master_Tender_Document (5. TENDER SUBMISSION STRUCTURE & COMPLIANCE REQUIREMENTS)	Kindly provide this Form A.	CONFIRMED & PROVIDED. The official Form A template (Bic Letter & Consortium Structure) is provided as Attachment 1 No. 1 and is available for download directly in the online RFP (Document Library Tab 1).
2	OSS & BSS Integration	01_RFP_5G_FWA_Master_Tender_Document (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Is billing considered in scope?	CLARIFICATION OF BILLING SCOPE: In Phase 1, real-time Convergent Charging (CCS/CHF via 3G Nchf/Diameter Ro) for prepaid FWA balance management, s and quota tracking is the mandatory turnkey scope. Comple cyclic invoice generation and accounts receivable (A/R) are

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
				Comclark/TelTech's enterprise billing system via standard C export, or may be proposed as an optional modular add-on.
3	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Bidder inquiry: System supports various tariff structures but requests clarification on specific offering rules. Such as: 1. These offerings need group management (such as family package) or not? 2. These offerings need rollover feature (such as unused data rollove to next cycle) or not? 3. These offerings should support auto upgrade (such as 599 not enough of this cycle automatical upgrade to 700 for next cycle) or not?	CLARIFICATION OF PRODUCT OFFERINGS: 1. Group Management: Optional roadmap feature; single-ac is baseline for Phase 1. 2. Rollover Feature: Supported in product catalog configura high-speed data quota rolls over into the subsequent 30-da cycle upon prompt re-subscription). 3. Auto-Upgrade: Speed-cap throttling (e.g. throttle to 1 Mb quota exhaustion with option for customer to purchase spee on) is the required policy, rather than forced tariff upgrade.
4	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Bidder inquiry: System supports standard 3GPP protocols and real-time balance rating and charging. some concerns: 1. We assume BSS will support 5G SA network only. 2. Smart quota, dynamic granted quota feature should enable or not?	CLARIFICATION OF CHARGING REQUIREMENTS: 1. Network Architecture: Confirmed 5G Standalone (SA) onl 2. Quota Management: Standard 3GPP dynamic granted qu threshold notification alerts (at 80% and 100% quota consu SMS / self-care push notification) must be enabled.
5	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Bidder inquiry: System exposes standard REST APIs for digital payment gateways, with specific operational queries: 1. Should support Voucher recharge or not(3rd party send voucher no	CLARIFICATION OF DIGITAL PAYMENT RECHARGE: 1. Voucher Recharge: Omnichannel digital recharge via GCa QR Ph is primary. Third-party electronic voucher PIN rechar supported as an optional secondary channel. 2. Taxation: BSS catalog must support Philippine 12% Value (VAT) calculation and display on payment confirmations and 3. Promotions: The charging system must natively support r promotional rules (e.g., bonus data allowances, referral rec promotional validity extensions).

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
			and PIN as example)? 2. Should consider Recharge tax or not(When feedback the message to 3rd party or notification to end-subscribers)? 3. Should consider Recharge promotion or not(When feedback the message to 3rd party or notification to end-subscribers)?	
6	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	What's the FWA service scenario shall be supported by the BSS? For example: New Registration, SIM Location Locking, Address Change, Transfer Owership, Contract Lifecycle Management, CPE/WIFI Router Installment	MANDATORY FWA SERVICE SCENARIOS: The turnkey BSS/OSS must support: 1. New Customer Digital Registration & KYC. 2. Strict SIM-IMEI & Cell-ID Location Locking (binding the FW the authorized installation address to prevent nomadic/mob unauthorized usage). 3. Relocation / Address Change workflow (manual or automa unbinding upon authorized relocation request). 4. Transfer of Ownership & Account Termination. 5. Contract / Subscription Lifecycle Management. 6. CPE Inventory Assignment and Remote FOTA Managemer
7	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	What's the payment mode shall be supported by the BSS? Prepaid, Postpaid, Hybrid? If need postpaid, and hybrid, does it meant the vendor need to provide the billing, invoice relevant components?	PAYMENT MODE ARCHITECTURE: The primary business model for Phase 1 is 100% Prepaid wit recurring subscription validity. Postpaid hybrid invoicing is h integration with Comclark/TelTech's enterprise billing platfo are only required to provide the real-time prepaid CHF/CCS payment gateway connectors.
8	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Beside the listed systems, shall the new BSS integrate with ERP Finance system, DWH/BI? Is there data	ENTERPRISE INTEGRATIONS: The BSS must support standard daily accounting journal exp to Comclark/TelTech's SAP ERP and daily CDR/event extract enterprise Data Warehouse (DWH). Real-time Kafka-based streaming is preferred for operational analytics.

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
			streaming requirement for real-time data synchronization?	
9	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Beside the self-care channels, shall the vendor provide the retail portal which can be used by the in-shop agent or call center agent?	RETAIL & AGENT PORTAL SCOPE: CONFIRMED. Vendor must provide a secure, web-based Cu Service Representative (CSR) and Authorized Dealer Portal agents, partner distribution dealers, and call center hotlines customer onboarding, balance lookups, and troubleshooting
10	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Beside the CPE inventory management, shall the new BSS/OSS system manage the MSISDN and SIM card resource?	RESOURCE MANAGEMENT SCOPE: CONFIRMED. The turnkey BSS must incorporate a unified re inventory management module for SIM cards (ICCID), MSISD hardware serial numbers (IMEI / MAC).
11	OSS & BSS Integration	02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION)	Does the exisiting network have PCF (Policy Control Function)? Does the BSS need to integrate with this?	POLICY CONTROL (PCF) INTEGRATION: Under Lot 3 (5G Core Network), the vendor is delivering the SA Core, which includes the Policy Control Function (PCF). integrate directly with the vendor's supplied PCF via standa N28 interfaces.
11	Wireless and Delivery	05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines.pdf (3. RF PROPAGATION & CELL DIMENSIONING GUIDELINES)	The coverage radius is too large. It is recommended that the coverage radius be 1 km in suburban areas and 1.5 km in rural areas.	CONFIRMED ACCEPTABLE. The revised planning criteria are adopted: - Suburban / Dense Urban: Nominal reliable cell radius of 1.0 - Rural / Semi-Rural: Nominal reliable cell radius of 1.5 – 2.0 These guidelines ensure 95% indoor/outdoor coverage relia Band n50 and will govern the updated link budget benchma Document 05.
12	Wireless and Delivery	04_Appendix_C_SLAs_KPIs_Liquidated_Damages.pdf (3.1 Core Radio KPIs (Calculated 24/7/365 Nationwide))	In the case of multiple users, the environment is complex and the attenuation is large. It is recommended that the average cell traffic be controlled within 40 Mbps/10 MHz.	CONFIRMED ACCEPTABLE. The recommended engineering baseline of 40 Mbps average cell throughput per 10 MHz of (yielding ~240 Mbps average cell throughput on a 60 MHz E carrier with 4:1 DL:UL frame structure) is endorsed as realis design criteria for multi-user FWA deployment.
13	Site, civil work, and managed services	05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines (2.2 Tower Structure & Loading Audit (Co-Location Sites))	For TowerCo tower, the tower structural Loading verification usually under TowerCo Scope (Operator provide the	STRUCTURAL LOADING RESPONSIBILITY: 1. For the 897 TowerCo co-location sites, Tower Structural L Verification is the responsibility of the Operator and the Tow the executed Master Lease Agreement (MLA). The vendor p equipment weights, dimensions, wind load surface area, and routing details. 2. If loading verification fails, the TowerCo is obligated unde perform structural retrofitting, or the Operator will reassign candidate tower from the pre-approved pool.

NO.	DOMAIN	RFP DOCUMENT REF	CLARIFICATION QUESTION	COMCLARK / TELTECH OFFICIAL RESPONSE
			equipment list and loading info to TowerCo, TowerCo to provide result). 1. Please kindly suggest if we need to provide structural loading verification service or not. Or we quote this service in a seperate item. 2. If Loading Verification fail, Please suggest the next step (build new tower, or request towerco retrofit tower) Suggest: TowerCo do the structural loading verification.	
14	Site, civil work, and managed services	04_Appendix_C_SLAs_KPIs_Liquidated_Damages ()	Whats the acceptance standard and procedure for Tower, Civil and Power part? Suggest: Turnkey vendor may propose standard QA/QC templates if needed.	ACCEPTANCE STANDARDS: Acceptance standards and checklists for Civil, Tower, and P detailed in Document 05 ('05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_G and Document 04 (Appendix C). Vendor's standard QA/QC and handover templates are acceptable subject to Joint Tec Committee approval.
15	Site, civil work, and managed services	05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines		

03_Appendix_B_Commercial_Proposal_BoQ_Templates (2.3 Power Infrastructure & Utility Audit

TABLE 3: LOT 2 — POWER SYSTEMS & PASSIVE INFRASTRUCTURE) | For New Site, the BOQ not include the commerical power application and installation (From COOP to Site). Do we need to quote this part?
If the commerical power not ready, does the turnkey contractor need to provide temporary generator power to energize the site?

Suggest: Commerical power shall included and temporary power can consider as VO when needed. | COMMERCIAL POWER & TEMPORARY POWER:
1. Official electric cooperative (EC/DU) application fees and power connection contracts are Operator scope.
2. Turnkey on-site civil and electrical installation (service entrance, meter base, disconnect, ACPDB) is Vendor scope.
3. If commercial utility power is delayed by the power utility, the site will be provisionally accepted using temporary generator power where expedited on-air is mutually agreed, with generator runtime costs handled via established Variation Order (VO). | | 16 | Site, civil work, and managed services | 03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 3: LOT 2 — POWER SYSTEMS & PASSIVE INFRASTRUCTURE

TABLE 6: LOT 5 — SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS) | 1. Do you have Type approved brand for Tower, Genset, Aviation light, ACPDB and other power or civil material?

2. Can you provide Typical Design drawing for Tower, Fence and foundation? Or the turnkey contractor to propose the solution.

Suggest: Turnkey vendor may propose standard QA/QC templates if needed. | TYPE-APPROVED BRANDS & CIVIL DESIGNS:
1. Civil and electrical materials must comply with Philippine Electrical Code (PEC), ASTM, and PNS standards (Class A hot-dip galvanized steel, NEMA 3R/4 outdoor enclosures, Schneider/ABB/Eaton breakers).
2. Typical structural and foundation drawings are provided in Document 05. Bidders may propose their type-approved standard foundation, fence, and monopole designs in their technical submission. | | 17 | Site, civil work, and managed services | 03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 6: LOT 5 — SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS) | 1. For the TowerCo site, Is it Comclark/TelTech scope to rent and negotiate with TowerCo?

Suggest: For towerco site, should be Comclark/TelTech's responsibility for site renting and negotiating with TowerCo.

2. If the site hunting fail, whats the next step? (Comclark/TelTech to provide another site for hunting to swap the failed site? or cancel the site).

Suggest: Contractor will hunt each site with up to 3 candidate parcels; if site acquisition fails due to zoning/legal defects, Operator provides alternative candidate without penalty. | SITE ACQUISITION & TOWERCO LEASE NEGOTIATION:
1. For the 897 Co-location sites, lease agreements, space reservation, and commercial negotiations with TowerCos (PhilTower, EdgePoint, EDOTCO, Unity) are strictly the Operator's responsibility under Master Lease Agreements (MLA).
2. For the 103 Greenfield sites, the vendor performs primary site hunting with up to 3 candidate parcels. If site hunting fails due to zoning, legal, or title defects, the Operator will provide a replacement candidate site without vendor penalty. | | 18 | Site, civil work, and managed services | 03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 3: LOT 2 — POWER SYSTEMS & PASSIVE INFRASTRUCTURE) | Bidder suggestion: Install outdoor soundproof canopy genset directly on an elevated concrete equipment pad without building an enclosed shelter structure. | GENSET INSTALLATION STANDARD:
CONFIRMED ACCEPTABLE. Outdoor soundproof weatherproof canopy gensets installed directly on an elevated concrete equipment pad (without an enclosed brick/steel shelter building) are fully acceptable. | | 19 | Site, civil work, and managed services | 03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 6: LOT 5 — SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS) | Is fiber backhaul drop cable installation Operator scope or Turnkey Contractor scope? | FIBER BACKHAUL RESPONSIBILITY:
Comclark/TelTech provides the core optical distribution network, terrestrial fiber drop cable up to the site boundary/ODF, and Starlink satellite terminals. The vendor is responsible for optical transceivers, patchcords, and joint I&C testing from the demarcation box to the BBU. | | 20 | Site, civil work, and managed services | 03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 6: LOT 5 — SITE ACQUISITION, DETAILED SITE SURVEY (TSSR), RF DESIGN & CIVIL WORKS) | For the non-standard and special construction reuqirment, such as manul hauling, retaining wall and others, Can the turnkey contractor claim abnormal civil conditions separately as a Variation Order (VO)? | VARIATION ORDER (VO) ELIGIBILITY:
CONFIRMED. Non-standard civil construction conditions (such as hard rock excavation requiring pneumatic breakers/blasting, manual material hauling exceeding 500 meters across unpaved/mountainous terrain, and engineered retaining walls) are recognized as eligible for Variation Orders based on pre-agreed unit rates in Appendix B (Lot 5 BoQ). | | 21 | Site, civil work, and managed services | 03_Appendix_B_Commercial_Proposal_BoQ_Templates (TABLE 3: LOT 2 — POWER SYSTEMS & PASSIVE INFRASTRUCTURE) | For TowerCo Power part, Usually Towerco will provide AC and DC, Please clarify if the turnkey contractor needs to supply the submeter and electrical tap materials when connecting to TowerCo power. | TOWERCO POWER EQUIPMENT:
Where TowerCo supplies regulated -48V DC power directly, vendor needs only connect to the designated DC distribution breaker. Where TowerCo provides raw AC utility power, vendor supplies the submeter, ACPDB, and surge suppression. | | 22 | Testing / KPI | 05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines.pdf; 04_Appendix_C_SLAs_KPIs_Liquidated_Damages.pdf (Section 5 SSV — Ping RTT acceptance; KPI-RAN-07 Radio Round-Trip Latency) | For the 17 Starlink backhaul sites, should the RTT KPI threshold be adjusted (e.g., relaxed to <= 50 ms maximum) given the inherent LEO satellite latency? Or are these sites exempt from KPI-RAN-07? Please confirm whether a separate KPI schedule applies to satellite backhaul sites. | STARLINK SATELLITE RTT LATENCY KPI:
CONFIRMED & ADOPTED. For the 17 remote/island candidate sites backhauled via Starlink LEO satellite, the Ping RTT SLA is relaxed to <= 60 ms target (<= 80 ms maximum) during SSV and cluster acceptance, reflecting satellite orbital propagation latency. | | 23 | Wireless and Delivery | 01_RFP_5G_FWA_Master_Tender_Document (2.3 Transmission & Backhaul Topology / App.C 3.1 KPI-RAN-07) | 1. Please provide the verified per-site fiber node/segment list (optical node ID, connection class A-D, committed bandwidth) after on-ground verification — the site list shows all Starlink-fed sites have dist-to-node > 20 km.
2. Please confirm that backhaul resources (Comclark/TelTech fiber SLA, Starlink links) are Operator/third-party provided, and the Operator is responsible for their availability, bandwidth and latency.
3. Do you accept media-tiered RTT KPIs: fiber-fed sites bound by <= 30ms, while satellite-fed sites follow their link physics (e.g. <= 100ms)?
4. Please confirm backhaul outage time is excluded from KPI assessment (RAN availability, end-to-end availability, packet loss).
Expected: written confirmation + per-site backhaul list. | BACKHAUL RESOURCES & SLA EXCLUSIONS:

1. Candidate site list in Document 07 provides audited fiber distance classes (Class A <= 0.5km to Class D).
2. Confirmed: Backhaul transport facilities (Comclark/TelTech terrestrial FOC and Starlink links) are Operator-provided.
3. Media-tiered RTT KPIs are formally confirmed: Fiber sites <= 30 ms maximum; Satellite sites <= 80 ms maximum.
4. Confirmed: Downtime caused by upstream third-party transmission outages or fiber cuts outside the site compound is excluded from vendor RAN availability penalty assessments. | | 24 | Site, civil work, and managed services | 01_RFP_5G_FWA_Master_Tender_Document (2.2 Site Infrastructure & Tower Strategy) | 1. Please provide TowerCo lease confirmations / ownership proofs for all co-location sites before NTP.
2. Please provide a tower-readiness schedule per site (lease signed, structural audit, access) feeding the 1,000-sites/365-day plan.
3. Do you agree to back-to-back liability — delays caused by TowerCo approval, access or structural defects are excluded from the contractor's schedule liability with automatic day-for-day time extension?
Expected: written commitment + schedule. | TOWERCO LEASE READINESS & SCHEDULE COMMITMENTS:
1. Operator will provide TowerCo Site Access Authorizations prior to Notice to Proceed (NTP) for each site batch.
2. Confirmed: Schedule milestones commence upon formal Site Handover with approved TowerCo access. Delays caused exclusively by TowerCo structural retrofit or access permit delays will receive day-for-day time extensions without liquidated damages. | | 25 | Site, civil work, and managed services | 01_RFP_5G_FWA_Master_Tender_Document (2.2 Deployment Typology / App.C 2.1 Milestones M1-M4) | 1. Please confirm an 'Excluded Sites' mechanism — sites blocked by permits (LGU/Barangay/CAAP), land, power connection, TowerCo or coverage issues are deducted from milestone counts.
2. May Milestone-1 TSSR be submitted in phasing (first 200 sites in 45 days, then 300 sites every 30 days), given typical permitting and TowerCo access cycles in the Philippines?
3. Do you accept the 365-day milestone counted in net working days (or auto-extended by the same number of days of Operator/third-party delays)?
4. Please confirm permit fees and utility connection application costs are pass-through (CCP).
Expected: written confirmation + revised milestone wording. | MILESTONES & PERMITTING CLAUSES:
1. Blocked Sites Mechanism: Sites blocked by LGU moratorium, right-of-way disputes, or power utility delays beyond 45 days will be swapped with approved reserve sites without schedule penalty.
2. Phased TSSR Submissions: Submitting TSSRs in progressive monthly batches (e.g. 150–200 sites per month) is fully acceptable.
3. Project schedule will account for approved force majeure and Operator/third-party delay extensions.
4. Official LGU building permit statutory fees and utility interconnection fees are pass-through to Operator. | | 25 | Site, civil work, and managed services | 01_RFP_5G_FWA_Master_Tender_Document (LOT 5: RF PLANNING, SITE SURVEY & CLUSTER OPTIMIZATION) | Can you accept not requiring a drone, as long as the photos can reflect the 360° surrounding environment, and AGL refer to TowerCo provided height for FWA project? | DRONE SURVEY WAIVER:
CONFIRMED ACCEPTABLE. Where drone flight permits cannot be secured from CAAP or local authorities within 14 days, high-resolution 360-degree panoramic telephoto ground photography combined with verified TowerCo structural engineering drawings is accepted for TSSR approval. | | 25 | Power system and delivery | 02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 2: POWER SYSTEMS & PASSIVE SITE INFRASTRUCTURE) | 1. Do they have Blade requirement ?
2. Can we request room layout or site pictures if available for Lithium Battery Approval?
3. Is there existing rectifier cabinet in existing sites?
4. If SAT requirement is one per equipment or the whole quantity?
5. What is the Total actual DC power for single rectifier requipment? | POWER SYSTEM & BATTERY SPECIFICATIONS:
1. Standard 19" rack-mount modular switchmode rectifiers and 19" rack-mount 48V 100Ah LiFePO4 battery modules are required.
2. Typical site DC load is ~2.8 to 3.2 kW continuous. Sizing requirement is 12.0 kW installed capacity (4 × 3 kW modules, N+1 redundancy).
3. Site layout and equipment pad drawings are provided in Document 05. | | 25 | Wireless and Delivery | 01_RFP_5G_FWA_Master_Tender_Document.pdf (2.1 Spectrum Physics: Band n50 Advantage) | 1. According to ITU-R M.2159-0, the 1518–1525 MHz frequency band is used for maritime communications satellites. If the frequency range of the RRU includes 1512–1517 MHz, it cannot ensure a -30 dB suppression within the 1518–1523 MHz band. Therefore, please confirm whether the NTC allows the use of the 1512–1517 MHz spectrum.
2. We understand that the 1427–1457 MHz frequency band will be allocated by the NTC as spectrum for enterprises. Please consider whether Comclark/TelTech intends to use the 1457–1467 MHz band. It is recommended to refer to the NTC's spectrum usage regulations to determine whether a guard band is required. Therefore, please confirm whether the NTC allows the use of the 1457–1467 MHz spectrum. | SPECTRUM PHYSICS & FILTERING (1457–1517 MHz):
1. Standard 3GPP Band n50 Category B filtering guarantees required suppression (-30 dBm/MHz) into the adjacent 1518–1525 MHz band (maritime satellite). Use of the 1457–1517 MHz band is formally authorized under NTC demonstration permit.
2. In NCR, operation is continuous 60 MHz (1457–1517 MHz); digital filtering within the RRU prevents out-of-band emissions below 1457 MHz. | | 25 | Wireless and Delivery | 05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines.pdf (overall) | Besides interference analysis with maritime communication satellites, suggest to carry out frequency clearance scan before commercial network deployment. | FREQUENCY CLEARANCE TEST:
CONFIRMED & AGREED. Vendor and Operator RF teams will conduct joint baseline spectrum clearance sweeps prior to site commercial on-air to identify and resolve any legacy co-channel or adjacent interference. | | 31 | Wireless and Delivery | 05_Appendix_D_Site_Survey_RF_Planning_Civil_Power_Guidelines.pdf (5.. SINGLE SITE VERIFICATION (SSV) & CLUSTER ACCEPTANCE CRITERIA)

| Is there Dl &UL speed requirement at near, Mid, and Far/Edge? | SSV SPEED TARGETS PER DISTANCE ZONE:
- Near Zone (< 500m): DL >= 200 Mbps / UL >= 30 Mbps.
- Mid Zone (1.0 – 1.5 km): DL >= 100 Mbps / UL >= 20 Mbps.
- Far / Cell Edge (>= 2.0 km): DL >= 25 Mbps / UL >= 5 Mbps (minimum SLA threshold). | | 25 | CPE | 02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7)) | Currently, only n50 is planned for FWA development, and NSA networks should not be involved | CONFIRMED. Phase 1 deployment is strictly 5G NR Standalone (SA) in Band n50. NSA operation is not required. | | 25 | CPE | 02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7)) | Currently, only the n50 band is planned for FWA development. Is it mandatory for other sub-6 GHz frequency bands? | CONFIRMED. Native Band n50 (1432 – 1517 MHz, 60 MHz TDD) is mandatory. Fallback sub-6 GHz bands (n1, n3, n78) are optional for the Philippine market. | | 25 | CPE | 02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7)) | The N50 low-frequency system does not need to rely on extremely high antenna gain to compensate for spatial attenuation as high-frequency systems do. Whether 5-6 dBi is sufficient? | CONFIRMED ACCEPTABLE. For Indoor CPE, an integrated antenna array gain of 5.0 – 6.0 dBi across Band n50 is accepted as compliant due to favorable propagation characteristics of 1.5 GHz L-Band compared to 3.5 GHz. For Outdoor CPE, >= 12.0 dBi remains mandatory. | | 25 | CPE | 02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7)) | The network port is seldom used and is mainly used for network configuration and commissioning. Can only one network port be reserved for the product? | CPE ETHERNET INTERFACES:
- Outdoor CPE: 1x 2.5GE PoE input port + companion indoor Wi-Fi 6 router is standard.
- Indoor CPE: At least 1x 2.5GE or 1x 1GE LAN port + integrated Wi-Fi 6 is acceptable for consumer FWA tiers; multi-port is preferred for SME tiers. | | 25 | CPE | 02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 7: 5G CUSTOMER PREMISES EQUIPMENT (CPE - LOT 7)) | Can it only support the eSIM MFF2 solution? | CONFIRMED. Physical Nano-SIM (4FF) with anti-theft locking slot is mandatory for mass-market deployment. eSIM (MFF2) is an acceptable optional enhancement. | | 25 | Wireless and Delivery | 02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 1: RADIO ACCESS NETWORK (RAN) TECHNICAL SPECIFICATIONS) | PIM is an indicator that is mainly concerned in FDD mode and does not need to be concerned in TDD mode. Is it necessary to change it to an OBUE (Operating Band Unwanted Emissions)indicator? | CONFIRMED. For synchronized TDD systems, Operating Band Unwanted Emissions (OBUE) per 3GPP TS 38.104 is the primary RF compliance benchmark. Passive Intermodulation (PIM <= -150 dBc) applies to external RF components (antennas, jumpers, connectors) to avoid receiver desensitization. | | 25 | Wireless and Delivery | 07_RFP_5G_FWA_Candidate_Site_List_and_Rollout_Schedule.xlsx (Phase 1 (First 1,000 Sites)) | We note that the distance from the planned site to the nearest tower ranges from 0.16 km to 1.94 km. Could the specific tower locations be provided for simulation calculations? | CONFIRMED. Candidate site coordinates (Lat/Long) and nominal tower heights are provided in Document 07. | | 25 | OSS & BSS Integration | 02_Appendix_A_Technical_Specifications_Compliance_Matrix.xlsx (SECTION 4: CONVERGED DIGITAL OSS/BSS & FIELD FORCE AUTOMATION) | Will a separate monitoring platform be deployed, or can it be integrated with the existing AUTIN platform? | OSS INTEGRATION:
Vendor must deliver EMS/NMS for domain element management, equipped with open northbound interfaces (REST APIs, SNMPv3, Kafka) for integration into Comclark/TelTech's enterprise monitoring umbrella (AUTIN). | | 25 | Core network & IT infrastructure and delivery | 01_RFP_5G_FWA_Master_Tender_Document.pdf (SECTION 3: 5G CORE NETWORK (5GC SA) & DATACENTER INFRASTRUCTURE) | The NEF is responsible for network capability exposure, and there are currently no commercial use cases.
The SEPP is responsible for signaling security protection and topology hiding across PLMNs. Based on the experience of other projects, this function is also not mandatory.
Therefore, it is recommended that the NEF and SEPP functions be treated as optional requirements or removed from the current RFP. | CONFIRMED. In Phase 1, NEF (Network Exposure) and SEPP (Security Edge Protection Proxy) are treated as optional roadmap functions and can be licensed in Phase 2 when enterprise API exposure and international roaming are activated. | | 25 | Core network & IT infrastructure and delivery | 01_RFP_5G_FWA_Master_Tender_Document.pdf (SECTION 3: 5G CORE NETWORK (5GC SA) & DATACENTER INFRASTRUCTURE) | Please Clarify whether the UPF needs to be deployed at the edge or co-deployed with the 5G Core at the central site.

If the UPF needs to be deployed at the edge, specify the number of edge UPFs.

It is recommended that the UPF form be not limited.Either 2U/4U/8U is ok | UPF DEPLOYMENT ARCHITECTURE:
In Phase 1, 5G Core control plane and central UPF are co-deployed at the Tier-3 primary datacenter (Clark/Metro Manila). Edge UPF deployment is optional for future ultra-low-latency enterprise zones. Standard 2U, 4U, or 8U server form factors are acceptable. | | 25 | Core network & IT infrastructure and delivery | 01_RFP_5G_FWA_Master_Tender_Document.pdf (SECTION 3: 5G CORE NETWORK (5GC SA) & DATACENTER INFRASTRUCTURE) | or hardware with the same capabilities such as Kunpeng server（E9000H-4/8） | CONFIRMED ACCEPTABLE. Carrier-grade server hardware with equivalent compute and throughput capabilities (including enterprise carrier-grade ARM architecture running certified Linux / Kubernetes) is fully acceptable for 5GC NFV infrastructure. |

5. ATTACHMENT 1: FORM A — BID SUBMISSION LETTER & CONSORTIUM STRUCTURE

(Prospective bidders must reproduce this letter on corporate letterhead, signed by an authorized corporate signatory, and submit within Envelope 1 / Administrative Envelope).

```
[BIDDER CORPORATE LETTERHEAD]

Date: _____
Reference: RFP-TELTECH-FWA-2026-001

To:
TELECOMMUNICATIONS TECHNOLOGY SOLUTIONS INCORPORATED (TELTECH)
Comclark Network & Technology Corp. / TelTech
Reliance IT Center, Pasig City / Clark Freeport Zone, Pampanga, Philippines
Attention: Oliver Tungol, Lead Technical Architect & Tender Secretariat
Email: oliver.tungol@comclark.com.ph

SUBJECT: FORM A — FORMAL BID SUBMISSION LETTER & CONSORTIUM DECLARATION

Gentlemen:

1. Having examined the RFP Bidding Documents, including the Master Tender Specification (01_RFP_5G_FWA_Master_Tender_Document), Technical Specific

   "NATIONWIDE 5G STANDALONE (SA) FIXED WIRELESS ACCESS (FWA) NETWORK (PHASE 1: 1,000 MACRO SITES)"

   in full conformity with the stated requirements, specifications, and commercial terms.

2. We confirm that our proposal represents a turnkey, single-point-of-responsibility solution covering all lots bid, executed in full compliance w

3. BIDDER & CONSORTIUM INFORMATION:
   - Primary Bidder / Lead OEM Entity: _____
   - Country of Incorporation: _____
   - Principal Business Address: _____
   - Authorized Representative / Corporate Signatory: _____
   - Official Corporate Email & Contact Phone: _____
   - Consortium / Delivery Partners (if applicable):
     * Partner 1 (Civil Works / Rollout Services): _____
     * Partner 2 (Power Systems / Logistics): _____

4. We confirm that our sealed proposal is submitted in three (3) distinct envelopes (Envelope 1: Administrative & Eligibility; Envelope 2: Technic

5. We acknowledge that our proposal shall remain valid and binding for a period of one hundred twenty (120) calendar days from the submission dead

Respectfully submitted,

_____
(Signature over Printed Name of Authorized Signatory)

Title / Designation: _____
Corporate Seal: [SEAL]
Date: _____
```

END OF BID BULLETIN NO. 1

Issued by the TelTech 5G FWA Tender Committee & Secretariat.