

FreshFlow Beverages Pvt. Ltd.

FreshFlow Bottling Plant - Pune Production Facility
FSSAI: 10012022000345 | ISO 22000:2018 / ISO 14001:2015

STANDARD OPERATING PROCEDURE

Shutdown Procedure for Packaging Line 67

Department: Packaging

Document Number: SOP-067
Revision: Rev 4.3
Classification: CONFIDENTIAL - INTERNAL USE ONLY
Prepared by: Engineering / QA Department
Approved by: Plant Manager

Document Control Information

Parameter	Value
SOP Number	SOP-067
Title	Shutdown Procedure for Packaging Line 67
Department	Packaging
Plant	FreshFlow Bottling Plant - Pune Production Facility
Prepared By	Employee 8
Reviewed By	Anita Desai
Approved By	Rajesh Kulkarni - Plant Manager
Issue Date	2023-02-11
Next Review Date	2025-10-14
Revision	Rev 1.2

1. Purpose

Pack finished product into secondary and tertiary packaging to protect product integrity and enable safe storage and distribution.

2. Scope

Packaging department operators and warehouse team.

3. Prerequisites and Requirements

3.1 Training Requirements

- Packaging machinery operation training
- Forklift certification (if applicable)

3.2 Tools and Materials Required

- Calibrated instruments as listed in the plant calibration schedule.
- Appropriate PPE as specified in Section 4.
- Completed permit-to-work (if required for maintenance activities).
- Access to relevant equipment manual and P&ID drawings.
- CMMS access to create and close work orders.

4. Health, Safety and Environmental Requirements

! WARNING

This SOP must not be carried out without appropriate PPE and, where required, a valid Permit to Work (SOP-SAF-006). If in doubt about safety, STOP and consult the Safety Officer (EMP009 / EMP017).

4.1 Identified Hazards

- Shrink tunnel (160-200°C) - severe burn if hands inserted
- Robotic cell - robot arm can move unexpectedly if safeguarding bypassed
- Forklift traffic - pedestrian collision risk in warehouse zone

4.2 Emergency Response

In case of any emergency during this procedure: Press the nearest Emergency Stop, alert personnel in the vicinity, call the Safety Officer and Shift Supervisor. Refer to the Emergency Response Plan (SOP-SAF-004) and site evacuation procedure.

5. Detailed Procedure

5.1 Pre-Task Verification

1. Confirm the relevant equipment is available and no conflicting activities are planned.
2. Check shift handover log for any outstanding issues with this equipment.
3. Verify all required materials, tools, and chemicals are available and correctly labelled.
4. Obtain all required permits (PTW, hot work, confined space as applicable).
5. Brief all involved personnel on this SOP before starting.

5.2 Main Procedure

1. Notify the shift supervisor and next upstream/downstream department of planned shutdown.
2. Reduce production rate to minimum before initiating shutdown.
3. Initiate shutdown sequence from SCADA or local panel as per control configuration.
4. Allow equipment to reach rest before applying isolation.
5. Close all isolation valves (suction, discharge, utility) in the sequence specified in the P&ID.
6. For food-contact equipment: initiate CIP sequence before shutdown if required.
7. Apply LOTO if shutdown is for maintenance purpose - see SOP-SAF-002.
8. Record shutdown time, reason, and condition of equipment in the shift log.

6. Quality and Verification Checks

Verification Check	When	Responsible	Record
All product contact surfaces visually clean	Before production	Operator	Shift Log
CIP conductivity ≤ 20 uS/cm	After each CIP	Operator	CIP Record
CIP pH 6.5-7.5	After each CIP	Operator	CIP Record
Microbiological swab <10 CFU/cm ²	After each CIP	QC Lab	Micro Report
Key process parameters in normal range	At startup	Operator	SCADA Historian
First-off product sample - Brix, pH, CO ₂	After startup	QC Analyst	QC Lab Report

7. Non-Conformance and Escalation

If any check fails or if the procedure cannot be completed as written: STOP the task. Do not force equipment to operate outside specification. Escalate to the Shift Supervisor (Suresh Patil / Ravi Deshpande). Raise a Non-Conformance Report (NCR) in the CMMS system. QC Manager (Anita Desai) must be notified for any product safety impact.

8. Records and Documentation

Record Type	Frequency	Responsible	Storage Location
Shift Log - Packaging	After each shift	Shift Supervisor	Shift Log Book / SCADA
CMMS Work Order	For every maintenance task	Technician	FreshFlow CMMS
CIP Record (FFB-QA-CIP-001)	After every CIP cycle	Operator	QA Filing System
Instrument Calibration Log	After calibration	QC/Maintenance	Calibration Database

A. Supplementary Notes

This SOP should be read in conjunction with the relevant equipment manual and the FreshFlow Beverages Good Manufacturing Practice (GMP) guidelines. Any suggested improvements to this SOP should be submitted to the Engineering Department using the Document Change Request (DCR) form FFB-ENG-DCR-001. This SOP is reviewed annually or whenever a significant process change occurs.

Related SOPs: SOP-SAF-002 (LOTO), SOP-GEN-010 (GMP), SOP-QA-005 (HACCP), SOP-GEN-001 (Shift Handover), SOP-GEN-006 (Plant Startup). For questions on this procedure, contact the Engineering or QA Department.