


Start guide OSCcourier



Track types

-  **markers:** primarily intended for reference timepoints, possibly as magnetic guides. Can be labeled
-  **bang:** points for distinct events. Aka bangs
-  **curve:** linear and-non linear interpolation between points
-  **step:** for discrete changes. Step sequences. Boolean (gate) or variable range (float)
-  **message:** text messages sent at timepoints (e.g., as key for dictionary)

Track header

-  **track handle:** grab to reorder track stack
-  **fold/Unfold track:** to save onscreen space. Fold all tracks with ⌘F
-  **delete track:** remove track
-  **clear track:** erase track content. Hover with ⌘, it becomes  duplicate track
-  **mute track:** inhibit OSC messages from being sent
-  **edit range:** specify min & max amplitude of track (range), possibly vertical quantization
-  **Auto fill:** fill a track with a pattern (see Auto fill below)
-  **Lock** (on top of header) : prevents any modification

Double-click on a track name to rename it.

You cannot remove the markers track nor rename it.

Editing range only applies to curve and step tracks.

Dragging the striped resize handle at the bottom of a curve or step track header allows vertical resizing for easier point positioning and visibility. Double-clicking it resets the track height to default.

Command bar

knurled knob: horizontal zooming (pinch out, ⌘+scroll). Double-click resets zoom to default

play/pause: play or pause (ugh, a tough one!)

stop: stop playing & rewind

cycle: loop playback

duration: set total length

time: ongoing playhead time position. Double-click switches to compact command bar

add tracks: add *bang*, *curve*, *message* or *step* tracks

x,y: display/hide points coordinates

 **grid:** show/hide grid. ⌘ + click to edit offset (Φ) and gridstep (T)

 **clear:** clear all track content

 **OSC messages window:** opens a popup window displaying outgoing OSC messages

 **Point List:** opens the Point List Window, where you can review and edit point properties

Save & Load: save current content of track as a Json file. Load saved file

Playback

Playhead can be dragged for scrubbing (as viewed in the OSC window)

Double-click playhead red triangle ▼ to edit its position. Drag with ⌘ to snap to grid or markers

Click above the ruler to make the playhead jump here

Dragging duration trim handle ◀ at the right end of the tracks, allows you to modify the sequence duration.

Dragging in the ruler draws a yellow Loop Zone. Drag ends to adjust. Double-click to edit. Drag to slide

Editing track content

click & drag: add a point

point dragging: move point position

double-click on a point: edit point position, value and label if available, and comment

shift-click on a point: remove a point

shift-click on a curve segment: remove a segment, or rebuild it

command-drag a point: snap to any gray marker line in the vicinity

option-drag a line segment: add curvature, simple or S-shape (curve tracks only)

Selection, Copy & Paste

To select points with a lasso, ⌘⌘ + click and drag on a track.

- you can then drag (and snap) the whole selection on the current track
- you can delete the selection ⌘
- you can copy the selection ⌘C. With ⌘V (paste) you're entering the paste mode:
 - the cursor takes a cross hair shape  and a **red** color.
 - click (or click and drag + ⌘ to snap) to choose paste location
 - rescaling option might be asked
- you can duplicate the selection (⌘D), which repeats the last paste at the same offset — keep pressing it to stamp out evenly-spaced copies
- you can nudge the selection using arrow keys

Auto fill

The **Auto Fill** function allows you to automatically fill tracks, for example, to create LFOs. The available options depend on the track type:

- for *marker*, *bang* & *message* tracks: you can set the period of the bangs (T, in seconds) and the offset at the start of the track (Φ).
- for *curve* tracks: you can choose a sine wave, with adjustable period (T), phase (Φ) and amplitude, or a triangular wave with an additional skew setting.
- for *step* tracks: Auto Fill generates a rectangular wave, with adjustable period (T), phase (Φ), amplitude, and pulse width.

Settings

The **Settings** window in the *OSCcourier* menu bar offers a few options:

- switch between auto, light or dark UI
- add a prefix to the address of outgoing OSC messages
- specify the port for receiving OSC messages controlling *OSCcourier* transport functions

Accepted messages are:

- **play, pause, and stop**
- **loop** <0 or 1> for loop activation
- **goto** <time (seconds)> or <marker name> to go to position or marker
- **loopzone** <start> <end> to specify start and end of the loop zone
- **mute** <track name> <0 or 1> to mute a track

- set rate of output messages (default 20msg/s.)

Hotkeys

play/pause: Spacebar

stop: Enter

loop: C

reset zoom: Z

reset tracks height: H

OSC message window: M

Point list window: P

See also **Modifier keys** in the **Help** menu to get a list of specific modifier keys

Some specific navigation options are also available through the **Play** menu, using time or markers as reference points for navigation:

Go to (mm:ss)... ⌘T: go to a specific time point

Go to Marker... ⌘⌘T: jump to a marker by its name

Go to Next Marker... ⌘⇨: jump to the next marker after the playhead

Go to Previous Marker ⌘⇩: move back to the previous marker before the playhead